PMF: the front end electronic of the ALFA detector

P. Barrillon ^a, S. Blin ^a, C. Cheikali ^a, D. Cuisy ^a, M. Gaspard ^a, D. Fournier ^a,
M. Heller ^a, W. Iwanski ^b, B. Lavigne ^a, C. De la Taille ^a, P. Puzo ^a, J-L. Socha ^a

^aLaboratoire de l'Accélérateur Linéaire, 91898 Orsay, France

^bCERN, 1211 Geneva 23, Switzerland

[Corresponding author: barrillo@lal.in2p3.fr](mailto:barrillo@lal.in2p3.fr)

Abstract

The front end electronic (PMF) of the future ATLAS luminometer is described here. It is composed by a MAPMT and a compact stack of three PCBs which deliver the high voltage, route and readout the output signals. The third board contains a FPGA and MAROC, a 64 channels ASIC which can correct the non uniformity of the MAPMT channels gain thanks to a variable gain preamplifier. Its main role is to shape and discriminate the input signals at 1/3 photo-electron and produce 64 trigger outputs. Laboratory tests performed on prototype and pre-series PMFs have showed performances in good agreement with the requirements.

I. INTRODUCTION

The PMF (section B) is the front end electronics designed for the ATLAS luminometer (section A). It consists of a 64 channels photomultiplier (MAPMT) and a very compact stack of three different PCBs, mounted directly on the back and in the shadow of the MAPMT. The ASIC MAROC (section C) is used for the signal readout and treatment.

A. ALFA detector

Fig. 1. Schematic view of the Roman Pots location with respect to the LHC beam.

ALFA stands for Absolute Luminosity For ATLAS [1]. This detector is located at 240 m from the interaction point (Fig. 1) and is meant to detect high energy diffused protons from the LHC beam. It is made of 20 staggered U-V scintillating fiber layers (Fig. 2) inserted in Roman Pots (eight in total). Each of these plans is made of 64 fibers which produce light when a particle comes through them. The light is then collected by multi-anode photomultiplier tubes H7546 from Hamamatsu [2], that will run at 800 to 950 V which

corresponds to a gain of $3 \cdot 10^5$ to $2 \cdot 10^6$. These PMTs have an important non-uniformity that can not be corrected by applying a different high voltage to each channel. Therefore one has to amplify the output signal with different factors for each channel.

Fig. 2. Schematic view of location of the scintillating fibers with respect to the beam. The U/V layers are arranged orthogonally to each other.

Figure 3 shows a schematic of a Roman Pot and the front end electronic. The whole readout system of ATLAS luminometer is presented in reference [3].

Fig. 3. Exploded schematic view of a Roman Pot and its front end electronic.

B. PMF

The Photomultiplier Front end (PMF) electronic is represented on the Fig. 4. It is made of a MAPMT and three boards (3 cm × 3 cm) in its shadow:

- The HV board which brings the high voltage to the MAPMT;
- The passive (or intermediate) board which routes the signals to connectors located on the edge;
- The active board which has the read out chip MAROC directly wire-bonded on the PCB on one side and a FPGA (Lattice) on the other side.

2) Tests with a LED

Trigger measurements were performed illuminating one or all channels of the MAPMT with a LED for different settings. The parameters tuned were the threshold, the diode pulse amplitude (V_{diode}) and the high voltage (HV).

Fig. 8. Left: S-curves of 8 channels for a fixed V_{diode} value. Right: S-curves of a single channel for four different V_{diode} values.

Left part of figure 8 represents the trigger efficiency, for fixed V_{diode} and HV, as a function of the threshold applied to the PMF for 8 different channels. As expected the so called s-curves are observed with a trigger efficiency going from a constant (plateau) value to 0.

Increasing the amplitude of the LED increases the level of this plateau as it can be seen on the right side of the figure 8.

A test of the gain equalization was tried by illuminating all channels as uniformly as possible. Figure 9 shows the trigger efficiency as a function of the channel number before and after gain equalization. Dispersion was improved by a factor 3.5 from 13.3 % to 3.8 %.

Fig. 9. Trigger efficiency as a function of channel number before and after gain equalization.

C. Pre-series

Here are presented results of the measurements performed on 28 active boards out of the 32.

1) Pedestals

Fast shaper pedestals were measured and a good homogeneity was found as it can be seen on figure 10 which represents the distribution of the pedestal for all the channels of the 28 active boards (i.e. 1792 channels in total). The dispersion is small and equal to 0.4 %.

Fig. 10. Fast shaper pedestal distribution for pre-series active boards.

2) DAC linearity

Similarly the DAC linearity of the 28 active boards has been measured. It consisted in measuring the amplitude (V_{dac}) obtained for different DAC register values. Top part of figure 11 gives the evolution of V_{dac} as a function of this register for all boards. The nice homogeneity observed is confirmed by the linear fit parameters represented as a function of the PMF number (bottom part of figure 10).

Fig. 11. Top: DAC linearity for the 28 active boards. Bottom left: slope of the DAC linearity fit as a function of PMF number. Bottom right: intercept (V_{dac} at $DAC=0$) of the DAC linearity fit as a function of PMF number.

3) Trigger outputs

The trigger output behaviour was studied by scanning the injected charge for a fixed threshold value and a unity gain applied to all channels.

Figure 12 represents the s-curves obtained for 1785 channels out of 1792. The 7 remaining ones are a bit shifted but nothing that can be corrected by tuning the gain.

Fig. 12. S-curves for the 28 active boards distinguished by different colors.

The good homogeneity observed can be characterized by the distribution of the injected charge needed to get 50 % trigger efficiency represented on figure 13.

Fig. 13. Distribution of the injected charge needed to get 50 % trigger efficiency among all 1792 channels.

III. CONCLUSIONS

The laboratory tests carried out on prototype and pre-series PMFs have showed that they are matching the requirements. The technological challenge consisting in producing a 10 layers PCB with several different vias and an ASIC bonded directly on it seemed to be achieved.

The pre-series batch of active boards showed a really high yield with no board rejected. Only 0.4 % of the channels (7 out of 1792) had an s-curve shifted with respect to the others.

LED tests performed at CERN and DESY proved that the full PMF was also working well.

23 pre-series PMFs were used during beam tests of a complete Roman Pot which took place during August 2008. Results should give the final green light for full production of all three kinds of board.

IV. REFERENCES

- [1] ATLAS Collaboration, *ATLAS Forward Detectors for Measurement of Elastic Scattering and Luminosity Determination*, Technical Design Report, CERN/LHCC/2008-004.
- [2] Hamamatsu web site, PM H7546B datasheet.
- [3] G. Blanchot et al., *System Design of the ATLAS Absolute Luminosity Monitor*, proceedings of TWEPP07 conference.
- [4] P. Barrillon et al., *64-channel Front-End readout chip – MAROC* datasheet.
- [5] P. Barrillon et al., *MAROC: Multi-Anode ReadOut Chip*, proceedings of 2007 TWEPP conference.