CM-P00062755

CERN - EUROPEAN ORGANIZATION FOR NUCLEAR RESEARCH

CERN/EF/BEAM 77-1
25 February 1977SOLID STATE DETECTORS USED IN THE NEUTRINO FLUX MONITORING (NFM)

H.M. Heijne

1. INTRODUCTION

This paper describes the solid state detectors used for the flux-monitoring of muons in the neutrino-filter in the CERN West-Area, their calibration and the way they are mounted in the underground pits. Subsequent papers treat the electronics for the detectors and the data acquisition, which is handled by the NFM-NORD-10 computer.

2. MECHANICAL LAYOUT [1]

The muon-flux inside the iron shielding can be measured in 6 gaps, after respectively 9.21 m, 29.64 m, 49.66 m, 70.09 m, 94.12 m and 118.55 m of iron. Detectors are mounted on a support plate in an arrangement of 6 concentric circles, with radii from 0 to 90 cm, in steps of 15 cm. The detector positions are numbered as is shown in fig. 1. The plate as a whole can be moved perpendicular to the beam in the horizontal x-direction from -72 to +277 mm, and in the vertical y-direction from -75 to +240 mm, in steps of .2 mm. The origin is the geometrical centre of the gap, which coincides with the theoretical centre of the wide-band neutrino beam. A calibration box, moving independently, upstream from the plate can be positioned in every point of the plane $x = (-985 \text{ to } +1235) \text{ mm}$, $y = (-618 \text{ to } +751) \text{ mm}$, again with the origin at the gap centre. In reality, however, the position is indicated as the distance from the garage, which has position $x = 1235 \text{ mm}$, $y = 751 \text{ mm}$. The various coordinate systems are drawn in fig. 2. The minimum step of the calibration box is .3 mm, the precision of the

HMH/mk

alignment with a detector on the plate is probably 1 mm. The command for the movements of the calibration box is simplified, so that radial distance and azimuthal angle related to the centre of the plate, wherever this may be, are the only input needed to move the box in front of a given detector on the plate. This operation is frequently needed to perform the relative calibration of the fixed detectors.

Normally there are 14 or 21 fixed detectors on the plate, one radius and one or two complete circles, and 5 detectors in the calibration box, which cover the full range of the flux.

3. DETECTORS

Solid state detectors of three types are used for the flux measurement, all silicon diodes but the junction is made either by diffusion or by ion-implantation or it is a Schottky surface barrier.

Compared to liquid or gaseous ionization chambers Si-detectors have the advantage of a small and stable volume, high signal, low bias-voltage and the ease of manipulation. Disadvantages are the susceptibility to radiation damage and the rather high price.

The operating principle of these detectors is the separation by an electric field (about 2000 V/cm) of the electron-hole pairs generated by the ionizing particle in the charge-depleted region of the diode.

The depleted thickness W is a function of the applied reverse bias voltage V_{BIAS} and the resistivity ρ of the silicon; V_0 is the built-in junction potential, about .5 V

$$W = .56 \sqrt{\rho \sqrt{V_0 + V_{\text{BIAS}}}} \quad (\mu\text{m}).$$

In fig. 3(c) is shown a surface barrier detector with no external bias, with partially depleting bias and with fully depleting bias voltage. In the last case, which is the preferred situation for our flux-measurement, the full wafer thickness, well-known by measurement, is charge depleted,

and thus sensitive to ionizing particles. In the non-depleted part of a detector electron-hole pairs are still formed by ionizing particles, but many of them recombine with the already existing free charge, before collection is possible. Charge collection from the depleted region is normally 100% because the effective lifetime of the carriers is much longer ($10\ \mu\text{s}$ - $5\ \text{ms}$) than the transit time to reach the contact ($10\text{-}50\ \text{ns}$). However, if the silicon contains many impurities or is much radiation-damaged (short carrier lifetime) the collection efficiency goes down. To some extent this can be overcome by a higher collecting field.

The difference between partial and full depletion is illustrated in fig. 4. First note that the single bunches from the PS, of which there were 18 in FE 74 at that time, can be easily distinguished. The bunch length is $10\ \text{ns}$, with $100\ \text{ns}$ between bunches. When the bias-voltage is less than the full depletion V_{FULL} , as in figs 4(b) and 4(c), the next bunch covers the tail of the charge collection of the preceding, but in 4(d), where some overbias $V_{\text{BIAS}} > V_{\text{FULL}}$ is applied, the flat zone after $\sim 70\ \text{ns}$ indicates complete charge collection.

Silicon detectors are mostly used for measuring the energy loss of single particles, in our case however, single particle counting is impossible in the fast ejection mode ($2.1\ \mu\text{s}$ at the PS, $20\ \mu\text{s}$ at the SPS) and only practical in low flux in the fast-slow ejection mode which is foreseen at the SPS. So charge integration is used, with a correction applied for the leakage current of the detector. This "leakage" ("reverse" or "dark") current is the sum of several components: the diode saturation current, the diode generation current, surface or edge leakage currents, depending on the design of the detector and the manufacturing. Generally, all components are temperature-dependent and increase with time due to irradiation damage.

The current is measured between pulses, and stepwise the exact compensation is established, and stored in digital form. A compensation current is then generated, based on this digital value. Updating of the compensation is done every 15 minutes. Details are described in the following paper.

The choice of type, size and manufacturer of the detectors was made after an extensive test of prototypes. The size is imposed by the requirement that the signal at the lowest possible flux must be comparable to the leakage current, which is less than proportional to the volume. But big detectors are expensive. Given the wide-band beam muon flux distribution in the shield, 5 different sizes were adopted as given in table I. The testing of 20 prototype detectors from 5 manufacturers according to our specifications [2] showed some weaknesses [3]. In general surface barrier detectors are less stable under a high irradiation dose, so for size A and B the ion-implanted or diffused detectors are preferred. The latter however, present often a high leakage current.

Radiation damage is caused by the removal of atoms from their lattice position and the subsequent association in a stable defect structure. It is reported to deteriorate the spectroscopic quality of Si-detectors after e.g. 10^{11} alpha's/cm², 10^{12} neutrons/cm², etc. The limiting factor in this case is the HF noise which degrades the energy resolution. In the charge integration mode and with the relatively high signals we obtain (e.g. 10^3 muons/cm² in a 100 μ m thick Si-detector generate a charge of 1.77 pC, equivalent to 40 MeV energy loss); we are rather unsensitive to this noise, but noise at low frequencies is dangerous for both the signal and the leakage current compensation. Associated to the noise is the increase of the leakage current, due to the creation of generation-recombination centres. The prototypes were tested in a ⁶⁰Co gamma-cell up to 2.4×10^7 rad. The big detectors, made of high resistivity Si (25'000 Ω cm) were more affected as the smaller ones. For some detectors we observed an initial decrease of the current, corresponding to reversal of the n-type to p-type Si caused by acceptor type defects. The collection efficiency was not changed by this irradiation. Afterwards the same detectors were exposed to 10^{12} - 10^{13} neutrons/cm². The currents increased dramatically, and even reduced collection was only possible at very high bias voltages.

We studied the physical properties of the damage more in detail [4] for the three types of irradiation: muons, gammas and neutrons. Results

obtained by the method of Thermally Stimulated Current (TSC) measurement are shown in fig. 5. A peak corresponds to a characteristic defect, introducing an electrical level in the forbidden gap of the semi-conductor. We found that the defects, caused by the muons, can be annealed at 350°C, so that it is in principle possible to recycle diffused and ion-implanted detectors.

4. CALIBRATION OF THE DETECTORS

The sensitivity of the detectors to a homogeneous particle flux can be calculated from the dimensions. The thickness of the detector is well known, but the sensitive area is determined by the irregular shape of the epoxy mounting (fig. 4(a)). Moreover, we assume that the depletion layer extends laterally as well as perpendicularly in the Si-wafer, as is suggested in fig. 4(c). To the nominal sensitive area we add a lateral extension under the epoxy, corresponding to the detector thickness. So we find the theoretical sensitivity $S_D(\text{THEOR})$, defined as the number of minimum ionizing particles/cm² needed to obtain a charge of 1 pC in the detector

$$S_D = \left[\frac{401}{3.62} \times 1.6 \times 10^{-7} (\text{pC}) \times \text{thickness}(\mu\text{m}) \times \pi(\text{radius} + \text{thickness})^2 (\text{cm}^2) \right]^{-1}$$

(energy needed for creation of electron-hole pair in Si is 3.62 eV energy loss by minimum ionizing particle in Si is 401 eV per μm).

The actual sensitivities were measured for all detectors by comparing their output to those of two precisely calibrated detectors under the same incident muon flux. For this experiment we used the muons in the back-stop behind the g-2 target in FE 74, with 2,3 or 4 bunches at 20 GeV. Measurements were made for 8 different bias voltages and the flux on the detectors was varied by moving them in the shield. The obtained data were fitted by a least squares method as will be described for the relative calibration. A typical result is shown in fig. 6, where the complete charge collection is achieved between 180 V and 210 V bias voltage.

A complete list of the measured detector sensitivities for complete charge collection is given in table II, together with the theoretical S_D 's. There appears to be a constant difference of about 10-20%, except in some special cases. Individual variations on this rule must be explained by measurement errors, inversion layers extending under the epoxy mounting or resistivity variations in the silicon. For example detectors LBB 6 and 7 are manufactured from $5 \text{ K } \Omega \text{ cm}$ silicon and the others from $10\text{-}15 \text{ k } \Omega \text{ cm}$ material.

As for the systematic difference, we may underestimate the energy loss of the muons by treating them as minimum ionizing particles under restricted energy loss conditions. For the moment the NFM on-line calculations are made with the measured S_D 's, under subtraction of a supposed 20% delta rays contribution to the signal.

In the coming months relative calibrations of the detectors installed on the plates must be performed by comparing them to the detectors in the calibration box. This box should stay mostly outside the radiation, thus enabling variations of sensitivity due to radiation damage or other causes to be detected. The relative calibrations produce an immediate on-line result, but for better precision an off-line treatment of the data is preferred. All the calibration points for a detector x against a detector y in the calibration box during a certain period, say 1 month, are fitted to a straight line

$$V_x = G V_y + D,$$

using the least squares method with both variables subject to error. We suppose that both detectors have a linear response to the flux, of the form

$$V_x = C_x N_\mu + O_x.$$

C_x is the detector calibration factor, defined as

$$C_x = \frac{\text{sensitivity detector x}}{\text{gain amplifier}} = \frac{S_{Dx}}{S_{Ax}} \left[\frac{N_\mu}{\text{cm}^2 \cdot \text{pC}} \cdot \frac{\text{pC}}{V} \right].$$

S_A is the gain of the amplifier, attached to detector x

S_A = basic gain x variable gain,

basic gain = 10^{-4} V/pC or 2.5×10^{-5} V/pC,

variable gain = 1,2,4,5,16,32,64,128 (and 256 with reduced linearity),

N_μ is the number of particles per cm^2 ,

O_x is an offset in Volts,

S_{Dx} is the sensitivity of detector x, as defined.

The calibration factor, and thus the S_D of detector x is then calculated from the known values of detector y

$$C_x = C_y / G$$

and the offset

$$O_x = D + G \times O_y .$$

This procedure of relative calibration was used also for the old monitoring system and in the "g-2" detector test run (fig. 6).

The absolute calibration of the detectors in the calibration box will be done by counting the muon tracks in nuclear emulsions (Ilford, G5, 200 μm) which were exposed during a few SPS ejections only, mounted on the box perpendicular to the flux. An independent calibration will be possible once the fast-slow ejection operates, by electronically counting the single muons in a burst. With a detector of 25 mm^2 one can probably count fluxes up to 5000 muons/ cm^2 pulse. Apart from the muons, the flux inside the shielding consists of energetic knock-on electrons (δ -rays) for which a correction has to be applied. They are not easily distinguishable from muons in perpendicularly exposed emulsions but may be separated by measuring the multiple scattering in parallel exposed emulsion. Other possible methods are single-particle spectrometry in low fluxes with solid state detectors and differential measurements with detectors, using absorber materials. This last method can be used in high fluxes. For the moment we adopt the rather arbitrary value of 20% contribution to the signal by δ -rays.

Once the absolute calibration is established all other detectors can be derived from it by the coefficients measured in the relative calibration. A "reference box" similar to the calibration boxes, which travels from pit to pit serves the relative calibration between boxes.

REFERENCES

- [1] G. Cavallari and P. Jarron, Spécifications Générales pour l'Installation des Détecteurs de Muons sur le Site Neutrino 400 GeV, CERN/D.Ph.II/BEAM 75-1.
- [2] H.M. Heijne, Specifications for Muon-Flux-Detectors at the CERN-SPS Neutrino Beam, CERN/D.Ph.II/HH/jr, 8 September 1975.
- [3] H.M. Heijne, Preliminary Report on Silicon Detectors for the SPS Neutrino Beam monitoring, CERN-EF/HH/fv, 17 May 1976.
- [4] H.M. Heijne, J.C. Muller and P. Siffert, TSC Defect Level in Silicon Produced by Irradiation with Muons of GeV-Energy, Radiation Effects 29 (1976) 25-26.

TABLE I

Detector Characteristics

	detector size area mm^2	thickness μm	nominal sensitivity particles/cm ² .pC	lower flux limit output .1V gain 128×10^{-4}	upper flux limit output 9.5 V gain 2.5×10^{-5}	detector types available
A	30	100	1878	1.5×10^4	7×10^8	50 diffused 2 ion implanted
B	100	300	188	1.5×10^3	7×10^7	20 diffused 10 ion implanted 10 surface barrier
C	200	500	56.3	400	2×10^7	7 diffused 25 surface barrier
D	200	1000	28.2	220	1×10^7	35 surface barrier
DD	25	1000	225	intended for single particle counting		9 surface barrier

TABLE II

Theoretical and Measured Detector Sensitivity

N.B. Detectors are numbered by 3 letters and a cipher.

First letter: manufacturer

L = LASCO

O = ORTEC

P = PHILIPS

Q = QUANTRAD

S = SIMTEC

Second letter: type of detector

D = DIFFUSED

I = ION-IMPLANTED

B = SURFACE BARRIER

Third letter: size of detector

A,B,C,D,DD see table I.

Detector		S_D (THEOR)	S_D (MEAS)	Difference%
LIA	1	1750	1517	15
LIA	2	1667	1350	23
LIA	3	1762	1050	68
LIA	4	1762	1220	44
LBB	1	140.	117	20
LBB	2	166.	140	19
LBB	3	135.	108	25
LBB	4	142.	124	15
LBB	5	147.	125	18
LBB	6	179.	174	3
LBB	7	146.	135	8
LBB	8	177.	152	16
LBB	9	135.	118	15
LBB	10	130.	115	13
LBB	11	151.	119	27
LBB	12	160.	135	18
LBC	1	45.5	38.0	20
LBC	2	50.7	43.5	17
LBC	3	53.2	44.5	20
LBC	4	51.4	44.0	17
LBC	5	54.7	47.8	15
LBC	6	46.9	38.0	23
LBC	7	49.6	43.1	15
LBC	8	54.0	47.5	14
LBC	9	55.1	48.5	14
LBC	10	61.2	52.0	18

TABLE II (Cont'd)

Detector	S_D (THEOR)	S_D (MEAS)	Difference
LBD 1	25.0	22.5	11
LBD 2	25.1	22.5	12
LBD 3	24.9	22.4	11
LBD 4	25.1	22.5	12
LBD 5	24.3	23.0	6
LBD 6	25.2	22.0	15
LBD 7	23.0	19.8	16
LBD 8	21.5	19.5	11
LBD 9	21.5	17.5	23
LBD 10	25.1	23.5	7
LBDD 1	110.	111	- 1
LBDD 2	101.	154	-34
LBDD 3	120.	125	- 4
LBDD 4	118.	115	3
OIA 1			
OIA 2			
OIB 1	160	120	33
OIB 2	167	135	24
OIB 3	166	130	28
OIB 4	165	120	37
OIB 5	166	130	28
OIB 6	170	132	29
OIB 7	169	133	27
OIB 8	166	130	28
OIB 9	158		
OIB 10	162		
OBC 1	47.3	41.5	14
OBC 2	50.1	42.0	19
OBC 3	50.3	42.5	18
OBC 4	55.9	50.0	12
OBC 5	47.7	44.0	9
OBD 1	22.2	18.0	24
OBD 2	22.0	17.5	25
OBD 3	22.0	19.5	13
OBD 4	22.0	19.0	16
OBD 5	22.1	20.0	10
PBB 1			
PBC 1	51.3	44.0	17
PBC 2	49.0	42.5	15
PBC 3	49.0	42.0	17

TABLE II (Cont'd)

Detector	S_D (THEOR)	S_D (MEAS)	Difference
PBC 4	49.6	43.0	15
PBC 5	46.6	40.0	17
PBC 6	46.3	41.2	12
PBC 7	47.9	42.0	14
PBC 8	48.2	42.0	15
PBC 9	47.1	42.0	12
PBC 10	48.2	42.5	13
PBC 11			
PBC 12			
PBD 1	24.1	21.0	15
PBD 2			
PBD 3	21.4	19.0	13
PBD 4	22.6	19.0	19
PBD 5	21.0	18.0	17
PBD 6	21.0	19.5	8
PBD 7	20.9	19.0	10
PBD 8	21.1	19.0	11
PBD 9	22.2	20.0	11
PBD 10			
PBD 11	23.6	20.5	15
PBD 12	23.1	19.5	19
PBD 13	23.6	19.0	24
PBD 14	23.8	19.0	25
PBD 15	24.3	21.0	16
PBD 16	24.0	19.5	23
PBD 17	24.3	21.0	16
PBD 18	24.2	21.0	15
PBD 19	24.2	20.0	21
PBD 20	24.3	19.5	24
PBDD 1	92.1	86.5	7
PBDD 2	88.5	81.0	9
PBDD 3	87.8	84.0	5
PBDD 4	91.4	87.0	5
PBDD 5	85.3	81.0	5
QDA 1	1751	1500	17
QDA 2	1751	1540	14
QDA 3	1751	1600	9
QDA 4	1751	1630	7
QDA 5	1751	1480	18
QDA 6	1751	1600	9
QDA 7	1751	1560	12
QDA 8	1751	1550	13
QDA 9	1751	1400	25
QDA 10	1751	1800	-3
QDA 11	1751	1600	9
QDA 12	1751	1400	25

TABLE II (Cont'd)

Detector	S_D (THEOR)	S_D (MEAS)	Difference
QDA 13	1751	1500	17
QDA 14	1751	1550	13
QDA 15	1751	1550	13
QDA 16	1751	1550	13
QDA 17	1751	1550	13
QDA 18	1751	1650	6
QDA 19	1751	1600	9
QDA 20	1751	1600	9
QDA 21	1751	1550	13
QDA 22	1751	1600	9
QDA 23	1751	1550	13
QDA 24	1751	1570	12
QDA 25	1751	1630	7
QDA 26	1751	1650	6
QDA 27	1751	1550	13
QDA 28	1751	1500	17
QDA 29	1751	1550	13
QDA 30	1751	1650	6
QDA 31	1751	1500	17
QDA 32	1751	1650	6
QDA 33	1751	1520	15
QDA 34	1751	1540	14
QDA 35	1751	1640	7
QDA 36	1751	1570	12
QDA 37	1751	1600	9
QDA 38	1751	1540	14
QDA 39	1751	1650	6
QDA 40	1751	1550	13
QDA 41	1751	1460	20
QDA 42	1751	1500	17
QDA 43	1751	1550	13
QDA 44	1751	1600	9
QDA 45	1751	1600	9
QDA 46	1751	1500	17
QDA 47	1751	1550	13
QDA 48	1751	1530	14
QDA 49	1751	1550	13
QDA 50	1751	1600	9
QDA 51			
QDA 52			
QDB 1	176	220	-20
QDB 2	176	182	-4
QDB 3	176	178	-1
QDB 4	176	199	-12
QDB 5	176	206	-15
QDB 6	176	300	-41
QDB 7	176	177	-.7

TABLE II (Cont'd)

Detector	S_D (THEOR)	S_D (MEAS)	Difference
QDB 8	176	166	6
QDB 9	176	179	-2
QDB 10	176	188	-7
QDB 11			
QDB 12			
QDC 1	52.0	51.0	2
QDC 2	52.0	51.0	2
QDC 3	52.0	49.0	6
QDC 4	52.0	49.0	6
QDC 5	52.0	51.5	1

Fig. 1 Detector Support Plate

MOVEMENTS OF DETECTOR-SUPPORT PLATE AND CALIBRATION BOX -

SCALE: 1:18

Movements of detector-plane and calibration box. The plate is shown both in the wide-band position and in the limit right-up position. The area covered by the calibration box is indicated. N.B. is the actual narrow band beam position in pit V2.

Fig. 2

SILICON SURFACE BARRIER DETECTOR

Fig. 3

Typical mounting of silicon surface barrier detector.
A. Front view B. Side view C. Detailed view of the
edge, showing the effect of various applied bias-voltages.

Signals of a 500 μm Si-detector in the muon flux in gap 1
at various bias voltages, measured over 50 Ω termination
August 1975

(a)

18 bunches, fast ejection,

(b)

idem, bias 70 V, not fully depleted

(c)

bias 130 V, not fully depleted

(d)

bias 270 V, fully depleted, complete
collection in 70 ns

Fig. 4

Temperature ($^\circ\text{K}$)

Fig. 5 TSC curves in both n-type and p-type silicon after different doses of various irradiations.

PD 13 vs 44

Fig. 6 Relative calibration curves of detector PD 13 vs detector 44, for 8 bias voltages. The lines represent the least squares fit.