EUROPEAN ORGANIZATION FOR NUCLEAR RESEARCH

CERN-EP/87-193

9 October 1987

THREE-DIMENSIONAL GASEOUS DETECTORS

Fabio Sauli

CERN, Geneva, Switzerland

ABSTRACT

The gaseous multiwire proportional chamber was developed as a fast electronic detector of ionizing radiation about twenty years ago. The basic device has been used in a large variety of designs and applications, mostly for the needs of elementary particle physics. Some of the detectors developed are truly three-dimensional, i.e. provide the space coordinates of tracks without ambiguities, even for rather complex patterns. In the present paper I will briefly summarize the operating principles of such detectors and the latest advances in the field.

Invited talk given at the
London Conference on Position-Sensitive Detectors
London, 7-11 September 1987

1. INTRODUCTION

The original multiwire proportional chamber (MWPC), developed in the late sixties by Charpak and collaborators [1, 2] featured fast electronic detection of ionization produced by charged particles or photons in a thin layer of gas contained between grids or meshes of wires. Exploitation in various ways of the charge induced on cathode planes by the anodic avalanche allowed the achievement of accurate, two-dimensional localization of radiation [3]. Continuous tracks could then be reconstructed, stacking several layers of MWPCs, each performing independent two-dimensional localization.

It was soon obvious that efficient detection of events with large multiplicities or complex patterns was rather impractical with such an approach, mainly because of the combinatorial ambiguities arising when coupling various projected planes of measurement. One way out was offered by the exploitation of the drift-time information, also suggested in the early works on MWPCs; Allison and collaborators [4] designed and built the first large-volume drift chamber, ISIS, capable of providing an electronic image of a large number of ionizing tracks. Figure 1 shows an example of tracks recorded in the upgraded ISIS2, operational at CERN [5]. Each dot represents a point for which both the drift-time and the charge were measured.

The idea of coupling the drift-time measurement to the readout of signals induced on cathode wires or pads to obtain a three-dimensional localization appeared already in the early work of Charpak and collaborators [1]. It was further developed and extended by Nygren and collaborators, who named the new device the time projection chamber (TPC) [6]. In this detector, a MWPC serves as the amplifying and localizing element for the charge, the third coordinate information being derived from the drift-time of ionization electrons released by charged tracks in a large gas volume embedded in uniform electric (and often also magnetic) fields. Recording simultaneously the charge detected on the anode wires and on rows of rectangular pads on the facing cathode plane in regular short-time intervals, one could achieve true three-dimensional and ambiguity-free localization of tracks. The somewhat misleading name of time 'projection' derives from the fact that information is recorded in thin time slices. The first large TPC, built at LBL Berkeley for an experiment at the Stanford collider PEP, demonstrated the powerful tracking and particle identification properties of the device, and was soon followed by the construction of other similar detectors (for a review, see, for example, the Proceedings of the TPC Workshop in Vancouver [7]). Two TPCs are now under construction at CERN and will be used at the Large Electron-Positron storage ring (LEP) [8, 9].

The spread of the information along the time axis, which allows a very economical geometry of detection, has however the obvious drawback of resulting in a long memory-time. For high event rates, other designs are more suitable. They consist in large arrays of parallel wires filling a gas volume, usually in a cylindrical geometry; the drift-time information is still used, but the small anode-to-cathode distances result in shorter memory-times. An example is the jet chamber, whose name comes from the kind of events that the first device was designed to detect [10]. The three-dimensional information can be obtained in these detectors recording, together with the drift-time, the charge flowing from both sides of resistive anode wires (the current-division method).

In what follows I will briefly summarize the operating principles of several devices suitable for three-dimensional tracking of complex events, pointing out the latest achievements and the general trends of the research in this field.

2. RECENT ADVANCES CONCERNING GASEOUS PROCESSES

A full exploitation of detectors requires an in-depth knowledge of the ionization processes, of the drift and of the charge-multiplication properties in gases. In this section I will mention the most significant recent advances in the field, usually motivated by some specific requirements of a detector.

Charged-particle identification can be obtained from the measurement of the rate of energy loss, or dE/dx . Because of the intrinsic large fluctuations in the energy loss in thin layers of gas, a proper statistical analysis over repeated samples and an accurate knowledge of the concerned physical quantities is necessary in order to design a detector capable of a given identification power. The experimental points shown in fig. 2, obtained by the Berkeley group, give an example of the resolution that can be achieved in a gaseous sampling device [11]. In this case the TPC was operated with an argon-methane gas mixture at high pressure, and the energy loss estimated from a weighted average over about two hundred measured samples for each track.

Analytical and statistical methods have recently been developed to allow a detailed and numerically accurate description of the ionization energy loss by fast charged particles, particularly in the region of the relativistic rise [12, 13]. Based on the quantum mechanical one-photon exchange model, the theory allows computation of the ionization losses in thin layers of matter with great accuracy as far as the photon cross-sections for the components are known. The model proves also to be very accurate in predicting the distribution of energy loss in thin samples (such was not the case of previous theories); one can indeed use its results for a better design of detectors.

The motion of electrons in gases under the influence of electric and magnetic fields is well described by the classic transport theory, reviewed in modern terms by several authors during the early development of drift chambers [14–16]. The theory provides rather accurate predictions for the behaviour of drift velocity and diffusion of electrons in a wide range of fields. The result depends, however, on a precise knowledge of the elastic and inelastic electron-molecule cross-sections, often not very well known for molecular gases. For argon, methane, and their mixtures, a recent work has questioned the correctness of the classic values of the cross-sections, even for noble gases [17]. It must be said that often even the experimental measurements disagree with each other; it is not clear if this is due to unknown impurities in the gas, or to an improper estimate of the gas mixture. The practical lesson to be learned is that drift velocity should be carefully measured *in situ* for a proper exploitation of any detector (I will describe later the methods used for continuous monitoring of this quantity).

Detection and localization of ionized trails are performed after a convenient amplification, by a factor of 10^4 or more, of the original signal through a process of charge multiplication around the thin anode wires in the MWPC. A detailed description of the avalanche growth would be very helpful to better estimate the relevance of various space-charge-related effects that I will mention later. This is however complicated by the large number of inelastic competing processes intervening at high electric fields. A recent work [18] has discussed a Monte Carlo method capable of simulating the avalanche growth, a rather interesting approach since it avoids the formidable mathematical complications of an analytical treatment. It is hoped that work along this line will continue, leading to a better understanding of the avalanche growth and spread around the wires.

The process of signal induction and time development in gaseous detectors has also been extensively studied by the groups involved in the development of imaging chambers; since it is strictly connected with the particular geometry of the detectors, it will be described in the next sections under the appropriate heading.

3. TIME PROJECTION CHAMBERS

As discussed in the Introduction, this is perhaps the most powerful three-dimensional electronic imaging detector available to experimenters today; apart from its use in the field of elementary-particle physics, it is being considered for the study of rare events (e.g. double-beta decay) and very high multiplicity events in heavy-ion collisions. A TPC consists of a large barrel containing a high-purity gas, sometimes at high pressure, with at one end a MWPC where charge multiplication and detection is performed. A large and uniform electric field (several hundred volts

per centimetre or so) is applied across the gas volume, in order to drift the ionization trails smoothly into the MWPC; for this purpose, a high potential difference is applied between the upper electrode of the drift volume and the first cathode of the MWPC (usually grounded), and multiple guard electrodes on the sides of the drift volume are maintained at appropriate potentials to obtain a uniform and undistorted field. Detectors of this kind designed for experiments around colliders have a cylindrical shape, with the MWPC at one end, in order to allow their installation inside a solenoidal magnet for momentum analysis. As a further complication, vacuum tubes for the circulating beams have to run across the central axis of the detector, which has then an inner cylindrical field-shaping structure as well as an outer one.

Figure 3 shows an artist's view of one of the future LEP detectors, ALEPH, in which tracking is performed by a large cylindrical TPC (about 2 m in diameter) inserted in a solenoid. The detector consists, in fact, of two independent TPCs, mounted back to back, with the end-cap MWPCs arranged in sectors at each end, upstream and downstream. The geometry chosen for the end caps is better seen in fig. 4, which also shows the orientation of the circular-pad rows facing the anode wires (mounted tangentially to the pad rows in each sector).

The end-cap geometry in a TPC and the process leading to localization are schematically shown in fig. 5 [19]. Segments of ionized trails, with a length depending on the anode wire spacing and the angle of incidence, drift into the MWPC and experience avalanche multiplication on the sense wires. Negative signals are detected on the anode wires, and a profile of induced positive charge appears on the cathode-pad rows. One can then deduce the average location of each track segment along the y coordinate at position x from the analysis of the induced-charge distribution, the vertical z coordinate being provided by the drift-time.

The localization accuracy along y is determined by the fluctuations in the centre of gravity of induced charge, a quantity that depends on the width of the distribution (the smaller the better). The shape of the induced-charge distribution on cathodes has been analysed by many authors using various algorithms [20–22]; it appears that, for best localization accuracy, one has to use a pad width about equal to the standard deviation of the induced-charge distribution. The convolution of the intrinsic distribution with the pad size determines what is usually called the pad response function (PRF); both the physical track width and the diffusion of electrons during drift contribute to broadening the PRF and consequently the spatial resolution.

The presence of a strong magnetic field modifies the drift properties of electrons. For the particular case of $\vec{B}$ strictly parallel to $\vec{E}$ (a design goal for TPCs), the drift velocity remains unchanged, but in some gases (such is the case of argon–methane mixtures) the transverse diffusion coefficient, perpendicular to the drift direction, is strongly reduced. As a consequence, the PRF for tracks drifting from the far end of a TPC is much narrower than it would be in the absence of magnetic field. Figure 6 [23] shows the measured standard deviation of the PRF, normalized to the pad width Δ (8 mm in this case) for various distances of drift and at increasing values of magnetic field. Both the localization accuracy and the two-track resolution are greatly improved for long drifts.

Various disturbing effects appear when $\vec{E}$ and $\vec{B}$ are not parallel to each other. Both drift velocity and trajectory are modified, and corrections to the data are necessary to avoid distortions. Interestingly enough, one can use the measured distortions of known tracks (e.g. generated by an ionizing laser) to reconstruct the value of non-parallel components of the fields, or in other words to map the fields inside the TPC [24].

Upon approaching the anode wires, electrons drift in a region where the electric field (that tends to become radial) is no longer parallel to $\vec{B}$; they receive a transverse twist and, depending on the angle of the track segment with respect to the wires, the detected charge interests a shorter or longer segment of the anode (the so-called $\vec{E} \times \vec{B}$ effect). This again strongly affects the PRF and the

localization accuracy, which, when plotted as a function of angle of incidence of the track in the plane of the MWPC, largely deteriorate on both sides of a minimum (around 30° for the typical TPC geometries) [25].

To the above-mentioned sources of distortion one has to add those due to mechanical imperfections, temperature gradients, gas purity, etc.; use of the TPC at the nominal accuracy levels would be impossible without a continuous calibration system. Indeed this is an integral part of the recent TPC designs, and consists in one or several pulsed ultraviolet laser beams traversing the drift volume under various known angles [26]. Being undeflected by the magnetic field, ionized tracks generated by a laser must of course be measured as straight lines and, if such is not the case, one can pinpoint the possible sources of distortion. An example will be given in the next section.

The large amount of experience and the measurements realized in the last years on the operating TPCs as well as on reduced-size prototypes make one confident that the devices now under construction will indeed perform as expected. In particular, the problem of track distortions close to the edges, due to leakage currents and accumulation of positive ions, that plagued the first TPC, seems now completely solved with a better design of the field cage; dynamic distortions of electron trajectories within the drift volume, due to the accumulation of positive space charge at high rates, are minimized by a more careful design of the end-cap MWPC (reducing the feedback of ions) or by introducing a pulsed gating electrode to permit detection of selected tracks only [27, 28].

4. MULTIDRIFT AND JET CHAMBERS

The second family of three-dimensional detectors that I would like to describe can be grouped under the general name of multidrift chambers (MDC). These devices are built alternating many layers of parallel anode and cathode wires, usually in a cylindrical geometry; coordinates are obtained recording drift-time and charge on both sides of resistive wires, thus uniquely determining points in space (apart from a trivial right-left ambiguity). A proper design of the drift geometry and the choice of gas mixtures that enhance the isochronism of electrons released by a given segment of track have allowed average localization accuracies of $40\text{ }\mu\text{m}$ r.m.s. in the drift direction and of a few millimetres along the wires to be obtained, as for example in the Stanford Linear Detector (SLD) [29].

One of the MDC designs, the jet chamber [10], has been adopted for OPAL, one of the future LEP experimental apparatuses [30]. Figure 7 shows a cross-section of the prototype, two sectors out of a total of 24 that will constitute the full detector. As shown in the inset, the central wire plane consists in an alternation of anode and field wires, slightly staggered to resolve the right-left ambiguity. Wires in the cathode plane have a variable potential, radially increasing, in order to provide a uniform drift field. The detected charge is recorded on both sides of each wire at 10 ns intervals, using a system of 100 MHz flash analogue-to-digital converters (FADCs). The complete recording of the detected charge in short time intervals with FADCs allows extraction of both the amplitude and time information from the data. Various algorithms have been developed for this purpose. Perhaps the simplest and most effective one, named the method of difference of samples (DOS) is illustrated in fig. 8 [31]. The original charge profile for a multitrack event, recorded exposing the prototype jet chamber to a beam of minimum ionizing particles, is shown in the upper half of the figure; the fast rise-time followed by a slower decay-time is typical of MWPC signals detected with a fast amplifier (having typical shaping times of around a 100 ns). Tracks are recognized by eye, but largely overlap. The lower part of the picture shows the same event, after an operation that consists simply in subtracting each bin from the previous one; now tracks are easily identified by a simple threshold-crossing criterion; the time is computed taking the centre of gravity over a few samples immediately preceding and following the zero line crossing within each cluster. Timing accuracies of around 2 ns have been measured by this method, which is simple enough to be

implemented in hardware. A very good two-track resolution is also achieved, 2 mm for 80% efficiency of recognizing the second track. Note that this is a purely electronic resolution; there are indications (see below) that tracks detected in the same region of an anode wire strongly interfere with each other because of local creation of positive space charge.

As mentioned above, calibration systems based on the use of pulsed lasers are nowadays an integral part of most large-volume detectors. Two devices have been used for this purpose, N_2 and frequency-doubled Nd-yag lasers; the photon wavelength in both cases is insufficient to directly ionize the gas, and ionization is created by multiple excitation of the gas itself or, most likely, of trace impurities in the detector with lower ionization potentials. Various substances in very small fractions can be added to increase the ionization efficiency [32].

An example of a calibration run realized with the OPAL jet-chamber prototype is shown in fig. 9 [33]. Using an optical splitter, two parallel beams about 1 cm apart were sent through the gas volume in a radial direction. In the figure, the drift-time measured by all anode wires is shown as a function of wire number. A deviation from a straight line is apparent at the far end: it was identified as being due to defective wiring in the outer field cage. The time distance between the two tracks provides, of course, a direct measurement of the local drift velocity. In the course of the measurement it was found that if the two beams were simultaneously generated in the gas in such a way as to be detected by the same section of the anode wires, the charge and the time recorded for the second beam were noticeably modified (an observation already made by others [34]). The problem was solved by using a semi-transparent dielectric splitter, which, depending on its polarization, allows selection of either of the two beams in sequence; the observation should however be taken into serious account by groups engaged in the detection of very high multiplicities of charged tracks.

The maximum electron drift-time in the jet chamber, 1 or 2 μs , allows its operation at rates an order of magnitude higher than the TPC (having typical memory-times of 20 μs or so). For the kind of fluxes one expects very close to an intersect, or at the high-luminosity future colliders, one has to find other solutions. Sticking to gaseous detectors, and given the range of drift velocities in various gases, the only way to gain rate is to reduce the wire spacing. In our group at CERN we are developing a very high density, modular MDC, named the multidrift tube, in which, owing to a very small drift cell size, the maximum drift-time is about 30 ns [35, 36]. In the present design, the elementary drift cell is hexagonal in shape, with one anode wire in the centre of six cathodes, and has 1.5 mm radius; up to a hundred independent drift cells have been mounted within a hexagonal carbon-fibre envelope, ensuring mechanical stiffness as well as gas tightness. A close view of one end of a finished module is shown in fig. 10. The module itself has 30 mm diameter and is about 1 m in length. Drift-time is measured on each of the anodes, and provides the radial coordinate; the longitudinal coordinate, along the wires, can be obtained from current division, much in the same way as for the jet chamber.

The best results in terms of stability of operation and localization accuracy have been obtained using as gas filling dimethyl ether (DME) at atmospheric pressure; this is due both to the favourable ionization statistics (about twice as many primary interactions per centimetre as in argon) and to the small value of the electron-diffusion coefficient [37]. An example of a multitrack event is shown in fig. 11; the localization accuracy of each wire, deduced from a straight-line fit to the data, is about 60 μm r.m.s. Owing to the small wire spacing, the multidrift module has a very high rate capability, and very close tracks can be resolved.

A complete detector is then built piling up individual modules, for example in a cylindrical geometry; if the longitudinal accuracy of several millimetres, as provided by the current-division method, is not sufficient, groups of tubes can be mounted at a small stereo angle. The success of this modular approach to the problem of high-resolution detection will depend on the finding of cheap

and reliable construction methods, and on the development of a high-density, large-scale integrated circuit for the time and charge measurement.

REFERENCES

- [1] G. Charpak, D. Rahm and H. Steiner, Nucl. Instrum. Methods **80** (1970) 13.
- [2] G. Charpak, Annu. Rev. Nucl. Sci. **20** (1970) 195.
- [3] G. Charpak and F. Sauli, Annu. Rev. Nucl. Particle Sci. **34** (1984) 285.
- [4] W.W.M. Allison et al., Nucl. Instrum. Methods **119** (1974) 488.
- [5] W.W.M. Allison et al., Relativistic particle identification by dE/dx , Invited talk given at the Int. Conf. on Instrumentation for Colliding-Beam Physics, Stanford (1982).
- [6] A.R. Clark et al., Proposal for a PEP facility based on the TPC (PEP-4, 1976).
- [7] J.A. Macdonald, ed., Proc. Int. Conf. on The Time Projection Chamber, Vancouver, 1983 (AIP Conf. Proc. **108**, New York, 1984).
- [8] ALEPH technical report, CERN/LEPC/83-2 (1983).
- [9] DELPHI technical proposal, CERN/LEPC/83-3 (1983).
- [10] H. Drumm et al., Nucl. Instrum. Methods **176** (1980) 333.
- [11] H. Aihara et al., IEEE Trans. Nucl. Sci. **NS-30** (1983) 63.
- [12] W.W. Allison and J.H. Cobb, Annu. Rev. Nucl. Sci. **30** (1980) 253.
- [13] F. Lapique and F. Piuz, Nucl. Instrum. Methods **175** (1980) 247.
- [14] V. Palladino and B. Sadoulet, Nucl. Instrum. Methods **128** (1975) 323.
- [15] G. Schultz and J. Gresser, Nucl. Instrum. Methods **151** (1978) 413.
- [16] G.W. Fraser and E. Mathieson, Nucl. Instrum. Methods **A247** (1986) 544 and 566.
- [17] B. Schmidt, Nucl. Instrum. Methods **A252** (1986) 579.
- [18] M. Matoba et al., IEEE Trans. Nucl. Sci. **NS-32** (1985) 541.
- [19] L. Rolandi, Space resolution of the TPC, Univ. Trieste preprint INFN/AE-86/5 (1986).
- [20] E. Gatti et al., Nucl. Instrum. Methods **163** (1979) 83.
- [21] E. Mathieson and T.J. Harris, Nucl. Instrum. Methods **159** (1979) 483.
- [22] R. Bellazzini et al., IEEE Trans. Nucl. Sci. **NS-32** (1985) 389.
- [23] S. Amendolia et al., Nucl. Instrum. Methods **A252** (1986) 392.
- [24] M. Benetta et al., IEEE Trans. Nucl. Sci. **NS-32** (1985) 605.
- [25] D. Bryman et al., see Proc. ref. [7], p. 12.
- [26] H. Hilke, Nucl. Instrum. Methods **252** (1986) 169.
- [27] S.R. Amendolia et al., Nucl. Instrum. Methods **A252** (1986) 403.
- [28] C. Brand et al., Nucl. Instrum. Methods **A252** (1986) 413.
- [29] C.C. Young et al., IEEE Trans. Nucl. Sci. **NS-32** (1986) 176.
- [30] OPAL Technical Report, CERN/LEPC/83-4 (1983).
- [31] D. Schaile, O. Schaile and J. Schwarz, Nucl. Instrum. Methods **A242** (1986) 247.
- [32] A. Bamberger et al., Nucl. Instrum. Methods **A252** (1986) 517.
- [33] A. Wagner, private communication (1987).
- [34] J. Va'vra, IEEE Trans. Nucl. Sci. **NS-30** (1983) 82.
- [35] R. Bouclier et al., Nucl. Instrum. Methods **A252** (1986) 373.
- [36] R. Bouclier et al., preprint CERN-EP/87-89 (1987), to be published in Nucl. Instrum. Methods.
- [37] F. Villa, Nucl. Instrum. Methods **217** (1983) 273.

Figure captions

Fig. 1: A multitrack event recorded in ISIS [5].

Fig. 2: Differential energy loss as a function of particle momentum measured in the Berkeley TPC [11].

Fig. 3: Perspective view of the ALEPH detector at CERN [8].

Fig. 4: Layout of pads in the end cap of the ALEPH TPC.

Fig. 5: Schematics of the end-cap MWPC in a TPC. Ionized trails drift towards the anode wires and multiply; induced charges are picked up by rows of pads in the cathode plane [19].

Fig. 6: Width of the pad-response function as a function of magnetic field (parallel to the drift field) for various distances of drift [23].

Fig. 7: Schematics of the OPAL prototype jet chamber [30].

Fig. 8: Charge profile as a function of time recorded on a wire of the jet chamber with 100 MHz FADC (upper figure), and the corresponding difference of samples [31].

Fig. 9: Two tracks generated by a pulsed laser in the jet chamber. A distortion of the response, due to a malfunction of the field cage (later corrected), is visible at one edge [33].

Fig. 10: Close view of one end of the multidrift module [35].

Fig. 11: A three-track event recorded with the multidrift module in a beam of minimum-ionizing particles.

Fig. 1

Fig. 2

Fig. 4

Fig. 5

Fig. 6

Fig. 7

Fig. 8

Fig. 9

Fig. 11