Upgrade of the LHCb VELO detector

Mark Williams, CERN

On behalf of the LHCb Collaboration

European Physical Society Conference on High Energy Physics

Vienna, Austria, 24th July 2015

Overview

- Current LHCb detector
- Upgrade – why, what, how?
- Upgraded VELO detector
 - Layout, modules
 - Sensors
 - ASICs
 - Cooling
 - RF Foil
- Physics performance
- Recent test beam and lab results

Current LHCb Detector

Vertex LOcator:
silicon microstrip
detector surrounding
collision region

Provides excellent
Impact Parameter
resolution, and
identification of
secondary vertices

Run 1 (2010-2012) and Run 2 (2015-2018) will deliver $3+5 \text{ fb}^{-1}$

Already collected unprecedented samples of bottom and charm hadrons

Very successful physics program (250+ papers), 20+ analysis talks at this conference

Upgrade for Run 3 (starting 2021)

Why? To increase yields of hadronic channels, providing order-of-magnitude increases in precision on key parameters

How? Increase inst. luminosity fivefold to $20 \times 10^{32} \text{ cm}^{-2} \text{ s}^{-1}$

Luminosity increase not enough – hardware trigger throttles rates for many channels.

⇒ Move to software-based trigger – requires 40 MHz VELO read-out (current detector limited to 1MHz)

Main VELO changes:

- Higher track multiplicity ⇒ switch from Si microstrips → pixels
- Move closer to the beam (8.2 mm → 5.1 mm)
- Data-driven 40 MHz read-out
- New cooling system, new RF foil enclosure

Must be
radiation hard

VELO Upgrade Overview

As with current VELO, two halves can be moved apart for safe operation during beam injection

When closed, sensors within 5.1mm of beam

52 modules in total (26 per half), z positions optimised to give maximum tracking efficiency

Surrounded by aluminium RF Foil/Box to separate VELO from primary vacuum

Modules

Projective view of sensors (red) after VELO is closed.

In reality, half of sensors are mounted on the back ('b') to avoid gaps in acceptance

Four sensors per module, powered and read-out via hybrid board and Kapton cables

Mounted on silicon substrate, etched with internal micro channels to provide **CO₂ cooling**

Each sensor (43mm x 15mm) bonded to **three VeloPix ASICs**

Elongated pixels between ASICs give complete coverage

ASICs: TimePix3 and VeloPix

VeloPix: pixel readout chip designed specifically for VELO upgrade

- 256 x 256 pixel matrix
- 130 nm technology
- High data rates (800 Mhits/s)
- Binary readout

Design will be submitted for production later this year

Timepix3: precursor to VeloPix, similar, but...

- Analogue readout
- High precision timing information ($\sigma_t = 1.5$ ns)
- Lower (but still high!) data rate (80 Mhits/s)

⇒ Ideal chip for testing and characterising sensor performance.

Sensors

55 x 55 μm pixel size, with baseline thickness 200 μm

Currently undertaking extensive sensor evaluation program using test beam and source data:

- Two different vendors (Hamamatsu (HPK), Micron)
- n-in-p (baseline) and n-in-n type (150 μm thick)
- Different guard ring sizes (250-600 μm)
- Different implant widths (35-39 μm)

Sensor requirements:

- Thin (minimise material in acceptance)
- Capable of tolerating radiation dose $8 \times 10^{15} \text{ 1 MeV n}_{\text{eq}}$ highly non-uniform over sensor
- Can take 1000V bias after irradiation
- Hit efficiency >99% after irradiation

Cooling

Upgraded VELO will dissipate 1.6 kW of power

Sensors need to be kept at -20°C to mitigate radiation damage

⇒ Need cooling system with minimal material that can reach the ASICs close to the beam, and works in vacuum.

Solution: Two-phase CO_2 cooling in micro-channel substrate

Developing design using pyrex-backed prototypes:

- Measure pressure-flow relationship
- Heat-load tests
- Mechanical and thermal tests of fluidic connector

Cooling

Upgraded VELO will dissipate 1.6 kW of power

Sensors need to be kept at -20°C to mitigate radiation damage

⇒ Need cooling system with minimal material that can reach the ASICs close to the beam, and works in vacuum.

Solution: Two-phase CO_2 cooling in micro-channel substrate

Developing design using pyrex-backed prototypes:

- Measure pressure-flow relationship
- Heat-load tests
- Mechanical and thermal tests of fluidic connector

Prototypes comfortably achieve required performance.

RF Foil

Requirements:

- Air tight – must separate primary and secondary vacua
- Accommodate module geometry, but with low impedance
- As little mass as possible – dominates material in acceptance
- Thermally stable, radiation hard, ...

250 μ m thick aluminium (AlMg4.5), milled from solid block

Corrugated to minimise material traversed before first hit

RF Foil

Requirements:

- Air tight – must separate primary and secondary vacua
- Accommodate module geometry, but with low impedance
- As little mass as possible – dominates material in acceptance
- Thermally stable, radiation hard, ...

half-scale prototype

250 μ m thick aluminium (AlMg4.5), milled from solid block

Corrugated to minimise material traversed before first hit

Currently testing production with half-scale prototypes

Also testing local chemical thinning

Physics Performance

Performance tested using full simulation, with realistic detector model

Foil thickness most important factor for IP resolution:

Upgraded VELO

- 300 μm foil
- 200 μm foil
- 100 μm foil
- No foil

Improved decay time resolution

Track reconstruction efficiency (>99%)

Surpass current VELO performance, in all metrics, even with higher multiplicities

Test Beam and Timepix Telescope

Dedicated Timepix telescope provides precise measurement of particle locations and timing as they pass through the 'Device Under Test'

Have tested wide range of different sensors, before and after irradiation (including non-uniform dose, to best reflect final running conditions)

Supported with electrical data from lab tests, and radioactive source studies

Sensors tolerate required 1000V bias after irradiation

Test Beam Results

Small selection of results from test-beam analysis

Charge collection: At 1000V, collect >6000 electrons per hit (meets design specification)

Efficiency: After irradiation, overall efficiency meets requirements by 600V

Intra-pixel efficiency shows no losses at pixel edges

Efficiency variation over *single-pixel unit* (average over all pixels in ASIC)

Summary

- LHCb upgrade will boost trigger rates of important channels by factor 20+
- VELO upgrade capable of 40 MHz read-out, with improved tracking precision and efficiency
- Now in R&D phase, with all components having prototypes under test (sensors, ASICs, cooling, RF foil, module mechanics and read-out chain)
- Extensive testing program using lab, source, and test-beam data, and simulation, to evaluate design choices

On track for a strong finish