10th Hiroshima Symposium
Xi'An, Sep 25–29, 2015

The Upstream Tracker for the LHCb Upgrade

Olaf Steinkamp

on behalf of the LHCb UT group

[olafs@physik.uzh.ch]

**Universität
Zürich^{UZH}**

Current LHCb Detector

[JINST 3 (2008) S08005]

- **test Standard Model by precision measurements in (quark-)flavour sector**
 - no significant deviations after run 1
 - measurement precision allows for New Physics contribution at 10–20 % level
- **precision of most measurements will still be limited by statistics after run 2**
 - with current LHCb would then need > 10 years to again double precision

LHCb upgrade already in LS2:

- **5 × instantaneous luminosity**
- **pure software trigger → read out full detector at 40 MHz**

2010	run 1	0.037 fb ⁻¹ @ 7 TeV
2011		1 fb ⁻¹ @ 7 TeV
2012		2 fb ⁻¹ @ 8 TeV
2013	LS 1	minor maintenance work
2014		
2015	run 2	5 fb ⁻¹ @ 13 TeV
2016		
2017		
2018		
2019	LS 2	LHCb upgrade
2020		
2021	run 3	5 fb ⁻¹ / year @ 14 TeV
2022		
2023		
2024	LS 3	t.b.d.
2025		
2026		

Upgraded LHCb Detector

- new front-end electronics to match 40 MHz readout
- finer granularity to match $5 \times$ higher luminosity
- improved acceptance in forward direction (→ trigger)
- more radiation-hard silicon sensors to survive 50 fb^{-1}

[CERN-LHCC-2014-001]

**University of
Zurich^{UZH}**

UNIVERSITY OF
Cincinnati

Fluence and Dose

- up to $5 \times 10^{14} \text{ 1-MeV } n_{\text{eq}}/\text{cm}^2$
 - up to 40 MRad
 - to mitigate effects of radiation damage:
- after 50 fb^{-1} (including safety factor 2)

- keep sensors below -5°C
- n-in-p sensors in inner-most region (p-in-n in outer region to save cost)

- **four detection layers**
 - 2 × vertical strips
 - $\pm 5^\circ$ stereo views
- **three silicon sensor geometries**
 - coarser granularity in outer region
 - finer granularity in inner region
- **silicon sensors and read-out chips mounted onto 130 cm long “staves”**
- **to avoid gaps in acceptance**
 - detectors on both sides of stave
 - adjacent staves overlapping
- **to minimize acceptance loss around LHC beam pipe**
 - inner-most sensors circular cut-outs

99.5 mm
×
97.5 mm
512 strips
($p \sim 190 \mu\text{m}$)

p-in-n

99.5 mm
×
97.5 mm
1024 strips
($p \sim 95 \mu\text{m}$)

n-in-p

51.55 mm
×
97.5 mm
1024 strips

- **inspired by ATLAS stave concept**
 - detector modules mounted on both sides to provide full acceptance coverage
 - sensor + front-end hybrid + stiffener
- **precise positioning of detector modules**
 - rigid core consisting of sandwich structure
- **cooling of sensors and front-end electronics**
 - bi-phase CO₂ at ~ 30 bar as coolant
 - Titanium cooling pipe, 2 mm Ø
 - “snake design” to optimize heat path to ASICs
- **transport of signal readout, control signals, low voltage, bias voltage to detector modules**
 - Kapton flex cable mounted onto stave core, underneath detector modules

- **inspired by ATLAS stave concept**
 - detector modules mounted on both sides to provide full acceptance coverage
 - sensor + front-end hybrid + stiffener
- **precise positioning of detector modules**
 - rigid core consisting of sandwich structure
- **cooling of sensors and front-end electronics**
 - bi-phase CO₂ at ~ 30 bar as coolant
 - Titanium cooling pipe, 2 mm Ø
 - “snake design” to optimize heat path to ASICs
- **transport of signal readout, control signals, low voltage, bias voltage to detector modules**
 - Kapton flex cable mounted onto stave core, underneath detector modules

Module Design

- **ceramic stiffener: pyrolitic BN or AlN**
 - CTE ~ matching that of silicon
- **thermal interface material: non-hardening epoxy**
 - to permit module remove if needed

possibility of AlN hybrid
(thick-film technology)
under investigation

- **ASICs (estimated):**
 - 6 mW / channel → 68 W / stave
- **bulk leakage currents (after 50 fb⁻¹)**
 - < 260 mW / sensor
- **kapton-flex cable**
 - ~ 10% power dissipation

$$T_{\max}(\text{sensor}) < T(\text{CO}_2) + 6^\circ\text{C} \quad \checkmark$$

$$\Delta T(\text{sensor}) < 5^\circ\text{C} \quad \checkmark$$

$$T(\text{ASIC}) < T(\text{CO}_2) + 23^\circ\text{C} \quad \checkmark$$

Test setup using recirculating CO₂ system (TRACI)

cooling lines

- adjustable pressure
- pressure and temperature monitoring

cold box (shown open)

dummy stave

- 20 thermo couplers to simulate heat loads

cooling pipe:

- Titanium, snake design
- inner diameter 2.0 mm
- wall thickness 0.125 mm
- total length 3 m

Mock-up staves to test assembly procedures and mechanical properties

	Type A	Type B	Type C	Type D
Substrate Type	n (oxyg.)	p	p	p
Chip size x ($\perp$ strip) (cm)	9.75	9.75	9.75	9.75
Chip size y(strip)(cm)	9.95	9.95	5.155	5.155
Thickness (μm)	250/320	250	250	250
Wafer resistivity	3-5 K Ωcm	3-5 K Ωcm	3-5 K Ωcm	3-5 K Ωcm
# of strips	512	1024 (p ~ 190 μm)	1024	1024
Interstrip C (pf)	5-35	5-35	5-20	5-20
Breakdown V (V)	>700	>700	>700	>700
Total number	1020(888)	55(48)	20(16)	20(16)

**99.5 mm
long**

512 strips
(p ~ 190 μm)

**99.5 mm
long**

1024 strips
(p ~ 95 μm)

**51.55 mm
long**

1024 strips
(p ~ 95 μm)

**51.55 mm
long**

1024 strips
(p ~ 95 μm)

Circular cutouts (type D)

- layout of guard rings close to cut-out
 - charge collection efficiency, radiation hardness

Embedded pitch adaptors (type A)

- implemented as double-metal layer
 - reduce dead material
 - save one row of wire bonds
- two geometries under consideration
 - cross talk
 - charge loss
 } before and after irradiation
- external pitch adaptor as backup

Top-side biasing (all sensor types)

- connection to backplane via active edge
 - long-term performance, radiation hardness
- modified module design allowing for direct contact to backplane as backup

First prototypes from Micron and HPK

- not yet final thickness and technology
- irradiation with 24 GeV p at CERN irradi facility
 - up to $3.2 \times 10^{13}/\text{cm}^2$ (type A), $7.4 \times 10^{14}/\text{cm}^2$ (type D)
- test beam campaign using 180 GeV p at CERN
 - VELOpix beam telescope ($\rightarrow 3 \mu\text{m}$ resolution)
 - Beetle readout chip for detectors under test
- analyses underway

S/N ~ 13.4

okay for 200 μm thick sensors
and Beetle noise performance

- expect new set of prototype sensors with final specs by the end of 2015

SALT Read-Out Chip

Custom development in radiation-hard 0.13 μm technology (IBM $\rightarrow$ TSCM)

- 128 channels: front-end amplifier $\rightarrow$ shaper $\rightarrow$ ADC $\rightarrow$ pedestal subtraction
- zero-suppression $\rightarrow$ data compression $\rightarrow$ serialisation
- SLVS output drivers: (up to) five e-port links
- first version of full 8-channel prototype in hand, tests ongoing

- **first prototype produced in industry**
 - eye pattern for signal lines looks good
 - but yield problems at manufacturer

- **second-generation prototype produced with CERN workshop**
- **four copper layers:**
 - 2 × signal
 - digital power
 - analog power, bias voltage
- **just received first samples, tests starting**

- **LHCb upgrade in LHC long shutdown II to increase instantaneous luminosity and trigger efficiency**
- **Upstream Tracker (UT) to replace current TT station to**
 - cope with higher particle density and with 40 MHz readout
 - improve acceptance in forward direction for faster track reconstruction
- **collaboration of eight institutions from Italy, Poland, Switzerland, US**
- **R&D to demonstrate feasibility of key design aspects under way**
 - detector modules mounted on both sides of “staves” which provide mechanical support, precise positioning, cooling, electrical connections
 - silicon sensors with embedded pitch adaptor, top-side biasing, circular cutouts
 - new rad-hard front-end chip w/ pre-amp, shaper, digitization, zero-suppression
 - other important aspects (cooling, electronics) not mentioned due to time constraint
- **gradual transition to production phase to be ready for installation mid-2019**
 - challenging schedule, but well-trained army of experienced and motivated worriers

Thank you !

- ❑ Our testbeams will exploit a high precision tracking telescope developed by VELO/Timepix group.
- ❑ 8 detector planes, each with 55 μm x 55 μm pixels (as intended for upgraded VELO)
- ❑ TimePix3 R/O chips – triggerless readout, each hit time-stamped with sub-ns precision.
- ❑ Spatial resolution $\sim 3\mu\text{m}$ in center (SPS beam is 180 GeV/c, so MS very small)

- position bare stave on fixture with vacuum “riser blocks” for support during mounting operation
- apply epoxy film and heat
- apply epoxy dot for anchors via syringe
- vacuum pickup tool to transfer module
- precisely position and lower on pins
- repeat for all modules on first side of stave
- cure
- metrology

- use rotator mechanism to flip stave, which is now a high-risk object
 - mount rotator to stave
 - raise, flip, shift, lower
 - reposition on fixture
 - remove rotator
- repeat module mounting procedure for all modules on second side of stave
- cure
- metrology

Standoffs on frame

- stagger adjacent staves
- provide overlap between adjacent modules

Kinematic mounts at top and bottom of stave

- fixed at top
- slotted at bottom

Support, Frame and Box

left/right halves
can be retracted
horizontally for
installation and
maintenance

Titanium Tube Bending

bending tool based on design by Ian Mercer (Lancaster)

To measure wall thickness

- bend sections of tube, encase samples in epoxy
- grind radial and longitudinal cross sections, polish surface
- image under digital microscope
- measure points on radii

Wall thickness as a function of bend angle

- fish-shaped (as expected)
- inner bend thickening, wrinkling
- outer bend thinning
- bending bunches material forward into the bend
- results consistent with literature:

¹ Yang et al. / Chinese Journal of Aeronautics 25(2012)1.

² Tang / International Journal of Pressure Vessels and Piping, 77(2000)751.

Titanium Tube Bending

Wall thickness as a function of azimuthal angle

- Measure points on inner/outer surfaces at even intervals on circumference
- Slight egg-like shape (as expected), follows from longitudinal results

Tube Fittings

Option 1

Option 3

Option 2

- can consider double-sealing with external sleeve
- mate tube and fitting with insertion joint
- avoid thermal stressing tube, increase ease of construction, cost, etc.
- allows for the possibility of in-situ repairs

Samples tested

- Braze single joint
- Braze double joint
- Armstrong single joint (irradiated)
- Armstrong double joint (irradiated)
- Araldit double joint (irradiated)

Pressure tests (ongoing)

- raise sample to 150 bar
- measure leak rate of sample plus system
- repeat with **irradiated** samples (100 kRad ^{60}Co γ -rays)
- repeat with **thermal cycling** (5 cycles, RT to -15°C)
- repeat with **pressure cycling** (5 cycles, 1 to 150 bar)

All tested samples reached 150 bar without exhibiting any obvious leak, cracks, or other catastrophic failure modes

X4 PEPI Chassis Locations on both the Top and Bottom of the detector planes

X4 Service Bay Locations

Upper and lower rolling cable trays on both left and right sides of the beam pipe