UNIVERSITÀ
DEGLI STUDI DI BARI
ALDO MORO

DIPARTIMENTO INTERATENEO DI FISICA “M. MERLIN”

SCUOLA DI DOTTORATO IN FISICA XXVIII CICLO

SETTORE SCIENTIFICO-DISCIPLINARE FIS/01

Development of a timing detector for the TOTEM experiment at the LHC

PHD THESIS

NICOLA MINAFRA

Supervisors:

Dr. E. Radicioni

Dr. F. S. Cafagna

Coordinator:

Ch.mo Prof. G. Scamarcio

CERN Supervisor:

Dr. J. Baechler

Bari, March 2016

Faber est suae quisque fortunae

Appius Claudius Caecus

to my family

Acknowledgements

I would like to thank my supervisors Dr. Francesco Cafagna and Dr. Emilio Radicioni for their teaching and mentoring. Their knowledge, their expertise and their patience were essential for my growth as a student and as a researcher. I would also like to thank Dr. Joachim Baechler, my supervisor at CERN, and the CERN TOTEM group; Dr. Gabriella Catanesi and the INFN, Bari Division; the TOTEM's Spokesperson Dr. Simone Giani and the whole TOTEM Collaboration. Then, the "Scuola di Dottorato in Fisica" of University of Bari and its coordinator Ch.mo Prof. G. Scamarcio, the INFN and the CERN Doctoral Student program for supporting my research and this thesis. I am also very grateful to Dr. Nicolò Cartiglia and Dr. Salvatore My for reviewing this thesis. Thank you for all your time and precious comments to this work.

During this thesis I had the possibility to meet amazing people that were essential for my research and with whom I had the pleasure of sharing a lot of quality time. Unfortunately, I can not mention all the people with whom I have collaborated during the last three years.

I would like to thank all the members of the TOTEM Collaboration, and, in particular: Mirko Berretti, with its endless enthusiasm, a good companion during freezing nights and hot summer days in the experimental areas; Marco Bozzo, for its incredible experience in every field and for its multilingual capabilities to solve any kind of problem; Edoardo Bossini, Mario Deile, Dmitry Druzhkin, Josef Kopal, Michele Quinto, Nicola Turini and all the engineers from University of West Bohemia.

I am happy to express my gratitude to Benoit Salvaint and Nicolò Biancacci, Alessandro Danisi, Elias Métral and all the other people of the Impedance Team: I was welcomed in the team and instead of simple co-workers I found some friends.

Thanks to Christophe Royon, Matthias Saimpert, Dominique Breton, Jihane Maalmi, Victor de Cacqueray and Eric Delanges for the work done on the SAMPIC; without their

contribution the unprecedented results achieved in this thesis would have not been possible. Wolfgang Koenig, Michael Traxler, Gerzy Pietraszko and Robert Visinka at GSI for all the tricks that I learned from them and for their amazing knowledge of their field and for giving me the opportunity to study and test the HADES diamond detector and the TRB3 board.

Stefano Lagomarsino and Silvio Sciortino, together with Mirko Brianzi, Chiara Corsi and Giuliano Parrini that I met in Florence and with whom we started a very fruitful collaboration.

Thanks to the colleagues that lent us their equipment, as the GEM tracker, Eraldo Oliveri, Yorgos Tsipolitis and all the RD51 Collaboration; and the MCP, Krzysztof Piotrkowski and Laurent Forthomme, installed by Vladimir Samoylenko and Jonathan Hollar.

Thanks also to the responsible people for the experimental areas: Henric Wilkens, Lau Gatignon, Ilias Efthymiopoulos and Nikolaos Charitonidis at CERN and Marcel Stanitzki at DESY.

Thanks to my friends at CERN: Felice, sometime a brother, sometime a mother, always a friend; Isabel, Noemi and Francesco, always friendly and never complaining for my delays and irritability (sometimes); Silvio, Mirko, Maddalena and many more.

Thanks also to Giacomo and Claudia, Paolo and Nunzia and all *legnipregiati* for keeping high the value of what we created, also when I am not there, and for welcoming me when I am back.

I have no word to thank Paola, I can count on her even when I am far and her family, that have welcomed me in every occasion.

Last but not least, I thank all my family: my parents, my sisters, grandparents, cousins and uncles. If it is not easy to leave every time, it is your fault!

Contents

Introduction	13
1 The TOTEM experiment at LHC: status and upgrade	17
1.1 The Large Hadron Collider at CERN	17
1.2 The TOTEM Experiment	18
1.3 Future physics program	25
1.3.1 TOTEM-CMS Precision Proton Spectrometer	26
1.3.2 Running scenarios	27
1.4 Roman Pot system consolidation	28
1.5 Roman Pot system upgrade: the timing detector	30
2 Impedance optimization of the RPs	33
2.1 Impedance reduction using ferrite bars	33
2.2 Optimization of the geometry of the RPs	34
2.3 Test measurements on the prototypes	39
2.4 New RPs installed in the LHC	41
3 Diamond detectors for particles detection	45
3.1 Passage of particles through diamond	46
3.2 Principles of solid state particle detectors	48
3.3 Diamond properties	51
3.4 Single crystal diamond for particle detection	54
3.5 Deposition of metallic read-out electrodes	57
3.6 Graphitized read-out electrodes	58

3.7	3D diamonds	61
4	Front-end electronics	67
4.1	Equivalent circuit of the diamond detector	67
4.2	Polarization of the diamond	71
4.3	Toy model of the read-out electronics for a diamond detector.	71
4.4	Broadband amplifier	76
4.5	Charge sensitive amplifier	77
4.6	High input impedance amplifier	80
4.6.1	The HADES detector	84
4.6.2	TOTEM timing detector	85
4.7	Amplitude dependent shaper	87
5	Test methodologies	93
5.1	Characterization of a timing detector	93
5.2	Test using high energy beam	95
5.3	Test using β source	96
6	Data acquisition and processing	99
6.1	Data acquisition devices	99
6.1.1	High Speed Oscilloscope	100
6.1.2	TRB3 and PaDiWa: TDC on FPGA	102
6.1.3	SAMPIC: a fast sampling chip	103
6.2	Data Analysis Framework	108
6.3	Computation of the arrival time	111
6.3.1	Constant Fraction Discriminator	114
6.3.2	Time Over Threshold	115
6.3.3	Data pre-processing	118
6.3.4	Other algorithms	120
7	Measurement of performance	121
7.1	Tests performed using a particle beam	121
7.2	Performance of commercial diamond detectors and amplifiers	123

7.3	Performance of the HADES start detector	129
7.4	Performance of the TOTEM timing detector	131
7.5	Performance of the amplitude dependent amplifier	138
7.6	Performance of 3D diamonds	140
7.7	Summary of Experimental Results	143
Conclusions		145
Abbreviations		147
Bibliography		149

Introduction

The LHC is at present the world's largest and highest-energy particle accelerator, hosted at CERN, the European particle physics laboratory near Geneva. The TOTEM experiment was designed to measure the total pp cross section and to study elastic scattering and diffractive dissociation at LHC. The protons that underwent elastic interaction are lightly deflected and, to detect them, TOTEM has installed silicon strip detectors at more than 200 m from the interaction point that can transversally approach the beam down to few millimetres, thanks to a movable piece of the vacuum chamber called Roman Pot.

During the first period of operation of the LHC, the TOTEM run campaigns were accomplished during low luminosity dedicated data taking. However, to allow the investigation of rare phenomena, an upgrade program has been proposed by the TOTEM Collaboration, to make possible the data taking at higher luminosities. In particular, a cornerstone of the upgrade program is the inclusion of a fast timing detector in the experimental apparatus to improve the capability of the apparatus to work in high pileup conditions.

The main topic of this thesis is the design and the characterization of a fast timing detector for high energy protons. After a survey of the most promising sensor technologies available for fast timing measurements, it was proved, thanks to an extensive campaign of tests using particle beams, that the needed resolution, below 100 ps, was achievable using diamond sensors. In particular, different approaches for the front-end electronics were investigated: some commercially available amplifiers and the timing detector designed by the HADES Collaboration were characterized. Then, a diamond detector, fully compliant with the TOTEM requirements, was designed, tested and prepared for the installation in the RP system. In parallel,

other solutions were investigated, such as 3D graphitized diamond sensors and an amplitude dependent amplifier, designed to increase the signal to noise ratio: the gain of the amplifier is small for low amplitude input (noise) and higher in presence of a signal.

In particular, the first chapter describes the TOTEM experiment and the main physics results obtained during the first run of the LHC. Then, the physics motivation and the technological challenges of the consolidation and upgrade programs are discussed. Particular attention is given to the impedance optimization of the Roman Pot, described in the second chapter. In fact, the Roman Pot creates a cavity inside the primary vacuum that can resonate at the passage of the beam. This resonance can introduce instabilities in the beam and can, in the worst cases, damage the detector because of the excessive heat generated. The Roman Pot has been optimized in this sense and two new shapes have been designed and realized and, only thanks to this optimization, the Roman Pot can be safely inserted at few millimetres from the beam even at the highest intensities foreseen for the LHC.

In the third chapter, the properties of diamond are discussed, with particular attention to the properties important for particle detection, to understand why the diamond is a good candidate for fast and precise timing measurements. The main technologies used to manufacture the substrates and to create the electrodes for charge collection will be addressed, from the metallization of the diamond, the most common technique, to the graphitization, a promising method that uses a laser to create graphite electrodes on the surface of the crystal. Also, 3D diamond detectors are described.

In the forth chapter, the instrumentation used during the tests is described: a fast oscilloscope was used as a reference system, but the tests were also done using a Time to Digital Converted (TDC) and the SAMPIC read-out chip, a fast sampler that is capable of working at the rates expected for the TOTEM timing detector. A sampled signal gives the possibility to use complex algorithms to compute the time of arrival, as a Constant Fraction Discriminator, or to use the Time-over-Threshold to correct the measured time. A software framework has been implemented to read and analyse data from both the oscilloscope and the SAMPIC.

In the fifth chapter, the test methodologies developed for the characterization of a timing detector, using either a particle beam or a radioactive source, are described.

In the sixth chapter, different approaches for the front-end electronics are discussed. First, an equivalent circuit of the diamond is presented and then it is used to study the toy model of a diamond read using a resistor, an extremely useful exercise that allows to understand the dependence of the time resolution on the different components. Then, a broadband and a charge sensitive amplifiers are studied, together with an high input amplifier, that has been proven to be the best choice. Moreover, the circuit of the amplitude dependent amplifier is discussed in detail.

All the results of an extensive test beam campaign are presented in the seventh chapter. The first measurements were focused on the test of ready-to-use solutions available on the market; this products, manufactured by Cividec Instrumentation¹, were tested and they were also customized to further improve their time resolution. Although the results were better than expected, the time resolution was not compliant with the requirements of the TOTEM upgrade. Hence, a diamond detector designed by the HADES collaboration was tested, finding an excellent time resolution. The development of the TOTEM timing detector began, on the base of the HADES design and, after several modifications of the amplifier, the best performing solution was chosen for the prototypes to be installed in a Roman Pot. Also, the results of the tests done using the amplitude dependent amplifier and a 3D diamond are presented.

¹<https://cividec.at/>

Chapter 1

The TOTEM experiment at LHC: status and upgrade

The TOTEM experiment was designed to measure the total proton-proton cross-section at the LHC, with a luminosity independent method and to study elastic and diffractive scattering at the energy of the LHC. During the first run of the LHC, the TOTEM experiment has been operated in standalone mode or in conjunction with the CMS experiment, allowing, in the latter configuration, an unprecedented coverage in pseudo-rapidity for the study of rare processes. However, to fully exploit the increment of luminosity of the next phases of the LHC, the detector system needed to be upgraded, firstly to protect the detector electronics and the LHC machine itself and secondly to cope with the increased pile-up.

This chapter will introduce the physics achievements and future goals of the TOTEM experiment, briefly describing the experimental apparatus as installed during the first run of the LHC and the upgrade proposed for the second and third runs.

1.1 The Large Hadron Collider at CERN

The Large Hadron Collider (LHC) is at the moment the largest particle accelerator in the world, housed at the European Organization for Nuclear Research (CERN). Inside the Large Hadron Collider, two proton beams can be accelerated

at close to the speed of light around a circumference of nearly 27 km and then they are made to collide with energy up to 14 TeV in the centre of mass, in 4 different interaction points.

The TOTEM Collaboration designed its experimental apparatus to measure the total pp cross section and to study elastic scattering and diffractive dissociation at the LHC.

Among the other experiments built at the LHC, ATLAS and CMS (with which TOTEM shares the same interaction point) are two *general purpose* detectors that have been used to prove the existence of the Higgs boson foreseen by the Standard Model and to study its characteristics. The importance of the discovery has been recognised by the 2013 Nobel Prize awarded to Peter Higgs and François Englert who had theoretically foreseen the existence of the last particle to be found in the Standard Model. Thanks to the increasing luminosity of the LHC, in the next future, they might shed some light on unsolved problems i.e. dark matter and CP violation. In particular, the latter is addressed also by the a specialized detector, built by the LHCb Collaboration; while the behaviour of extremely high dense states, such as quark gluon plasma, is examined in depth by the detector built by the ALICE Collaboration.

It is worth mentioning that, as shown in fig. 1.1, a large part of the experiments at CERN are not directly linked with the LHC. Among the others: the Anti-proton Decelerator produces a beam of relatively cold and low energy anti-protons mainly used to create and study anti-hydrogen atoms; the neutron time-of-flight facility produces high energy (few MeV to several GeV) neutrons for the investigation of neutron-nucleus interactions; ISOLDE is the historical radioactive nuclei facility, for the study of short lived nuclei.

1.2 The TOTEM Experiment

The TOTEM experiment was designed to investigate phenomena that belong to the so called *forward physics*, in particular, the main objectives are [1]:

- measurement of the total cross-section using a luminosity independent method;

Figure 1.1: The CERN accelerator complex with some of the main experiments.

- study of diffractive dissociation, including single, double and central diffraction topologies, in combination with CMS.

In detail, the total proton-proton cross-section measurement technique is based on the Optical Theorem:

$$\mathcal{L} \sigma_{tot}^2 = \frac{16\pi}{1 + \rho^2} \frac{dN_{el}}{dt} \Big|_{t=0} \quad (1.1)$$

$$\mathcal{L} \sigma_{tot} = N_{el} + N_{inel}$$

where:

- N_{inel} is the inelastic interaction rate;
- N_{el} is the total nuclear elastic interaction rate;

- t is momentum transfer¹;
- $\left. \frac{dN_{el}}{dt} \right|_{t=0}$ is the nuclear part of the elastic cross section;
- $\rho = \frac{\mathcal{R}[f_{el}(0)]}{\mathcal{I}[f_{el}(0)]} = 0.1361 \pm 0.0015_{-0.0025}^{+0.0058}$, for $\sqrt{s} = 14$ TeV [2];
- $f_{el}(0)$ is the forward nuclear elastic amplitude.

The two equations set can be solved to find $\mathcal{L}$ and σ_{tot} :

$$\sigma_{tot} = \frac{16\pi}{1 + \rho^2} \frac{\left. \frac{dN_{el}}{dt} \right|_{t=0}}{N_{el} + N_{inel}} \quad \mathcal{L} = \frac{1 + \rho^2}{16\pi} \frac{(N_{el} + N_{inel})^2}{\left. \frac{dN_{el}}{dt} \right|_{t=0}} \quad (1.3)$$

This method does not need a direct measurement of the luminosity $\mathcal{L}$; however, $\left. \frac{dN_{el}}{dt} \right|_{t=0}$ has to be extrapolated to $t = 0$ and the precision of the measurement will be directly affected by the quality of this extrapolation.

To pursue this physics program, the TOTEM Collaboration has installed two gas telescopes per side, in the forward region on both sides of the CMS interaction point (IP5), as shown in fig. 1.2.

These detector telescopes, named T1, Cathode Strip Chamber (CSC) detector, and T2, a Gas Electron Multiplier (GEM) detector, cover a pseudo-rapidity² range respectively of $3.1 < |\eta| < 4.7$ and $5.3 < |\eta| < 6.5$. These telescopes are designed to detect particles in about 99.5% of all non-diffractive minimum bias events and 84% of all diffractive events [3].

The detection of protons that underwent elastic interaction and are lightly deflected is possible thanks to devices called Roman Pots. *Les pots de Rome*, where

¹In a two body scattering $a + b \rightarrow a + b$, defining the 4-momentums of in-going (p_1, p_2) and out-going (p_3, p_4) particles, the kinematics can be described using the Lorenz invariant Mandelstam Variables (s, t, u), that are defined as:

$$\begin{aligned} s &= (p_1 - p_2)^2 = (p_3 - p_4)^2 \\ t &= (p_1 - p_3)^2 = (p_2 - p_4)^2 \\ u &= (p_1 - p_4)^2 = (p_2 - p_3)^2 \end{aligned} \quad (1.2)$$

s represents the square of the centre of mass energy, while t is the 4-momentum transfer squared.

²The pseudo-rapidity η is defined as $\eta = -\ln(\tan(\frac{\theta}{2}))$. Additionally, the rapidity y is defined as $y = \frac{1}{2} \ln(\frac{E + p_z}{E - p_z})$ where E is the total energy and p_z is the momentum component parallel to the beam. For particle momentum $p \gg m$, the rapidity and pseudo-rapidity are approximately equal: $y \sim -\ln(\tan(\frac{\theta}{2})) \equiv \eta$, where m is the rest mass of the particle and θ is the angle between the beam and the scattered particle.

are critical operations and require a certain distance between the beam and the walls of the vacuum chamber. The solution is a part of the beam pipe that can be moved closer to the beam, after the above mentioned critical operations, only when needed, i.e. to study elastic interactions.

During the first phase of the LHC, the TOTEM Roman Pots were installed at 147 m and 220 m downstream of the interaction point and could be inserted down to 1 mm from the beam (depending on the beam configuration). RPs were grouped in units (stations) composed by three RPs: one approaches the beam from the top, another from the bottom and the last from the side. The detection of the protons is made possible thanks to the adoption of *edgeless* silicon strip detectors designed by the Collaboration to be efficient down to $\sim 50 \mu\text{m}$ from their edge [6], as shown in fig. 1.4. These silicon detectors are housed into the Roman Pots system and positioned as closed as possible to the beam.

Figure 1.4: Particle detection efficiency for a TOTEM silicon detector as a function of the distance (y) from its mechanical edge.

The TOTEM apparatus and the performance of the detectors are discussed in more detail in [7].

Thanks to its unique coverage in pseudo-rapidity on both sides of the interaction point, the TOTEM apparatus has been used to measure the elastic and inelastic cross-sections at $\sqrt{s} = 7 \text{ TeV}$ [9, 10] and the total cross-section, using the discussed method, at both $\sqrt{s} = 7 \text{ TeV}$ [11] and $\sqrt{s} = 8 \text{ TeV}$ [8] with a precision below 3% (fig.

Figure 1.5: Compilation of the total (*tot*), inelastic (*inel*) and elastic (*el*) cross-section measurements: the TOTEM measurements described in [8] are highlighted. The continuous black lines (lower for pp , upper for $\bar{p}p$) represent the best fits of the total cross-section data by the COMPETE collaboration [2]. The dashed line results from a fit of the elastic scattering data. The dash-dotted lines refer to the inelastic cross section and are obtained as the difference between the continuous and dashed fits.

1.5) and a coverage in rapidity high enough to infer a non exponential behaviour of the elastic differential cross-section $\frac{d\sigma_{el}}{dt}$ at low $|t|$ [12].

Moreover, the apparatus was also used to study inelastic interactions with particles in the forward region, distinguish, for example, the event topologies shown in fig. 1.6. The density of particles produced at different pseudo-rapidity has been measured [13], also virtually increasing the acceptance of the TOTEM detector using an interaction point displaced by 11.25 m from the nominal position. The result of the measurement is shown in fig. 1.7 [14]. Diffractive processes were studied [15] also during a combined data taking with CMS [16].

Figure 1.6: Graphical representation of the most common forward event types in $p - p$ collisions. The leftmost pictures are graphical representations of the processes and in the middle typical angular and pseudo-rapidity distributions are shown.

Figure 1.7: Charged particle pseudo-rapidity distributions obtained in pp collisions at $\sqrt{s} = 8 \text{ TeV}$ for inelastic events. The coloured bands show the combined systematic and statistical uncertainties and the error bars represent the η -uncorrelated uncertainties. The measurements are compared in each η region to the corresponding prediction from Monte Carlo generators. [14]

1.3 Future physics program

The TOTEM detectors were designed to measure the elastic, inelastic and total cross-sections and the possibility to collect data together with CMS offers an unprecedented possibility to study diffractive processes thanks to a particle coverage over 15 units of rapidity.

One of the main goal is the study of exclusive Central Diffractive (CD) processes: $p+p \rightarrow p \oplus X \oplus p$. The symbol $\oplus$ is used to indicate the *rapidity gap* (a region without primary particle production) between the protons and the X . Some interesting examples are shown in fig. 1.8.

Figure 1.8: Leading order diagrams for exclusive central diffractive χ_c (left), J/Ψ photoproduction (middle) and dijet production (right) in pp collisions [17].

CD reactions can be described by the exchange of a system of gluons g with neutral colour or photons γ : at leading order, the gluon system is called Pomeron, $\mathbb{P}$, and the main contributions to CD are due to $\mathbb{P}\mathbb{P}$ scattering and $\mathbb{P}\gamma$ interactions (*photoproduction*).

In these processes, the two protons remain intact and the four-momentum loss balances the central production of the state X . In case the state X is a particle, a fixed number of particles or jets, the process is considered to be *exclusive* as all the particles involved in the process can be detected. For these reactions the final state X has $J_z^{CP} = 0^{++}$ and its mass, M_X , can be reconstructed from the fractional momentum loss, $\xi = \frac{\Delta p}{p}$, of the scattered protons: $M_X \sim \sqrt{s\xi_1\xi_2}$. CD events resemble more electron-positron annihilation events than proton-proton collisions, in the sense that the initial state is well known and does not have the uncertainty due

to the Parton Distribution Functions. This is an excellent environment to search for glueball candidates, bound gluon states with no valence quarks predicted by QCD [18, 19]. As an example, an extremely interesting CD process is the exclusive production of $c\bar{c}$ states, as ξ_c because the mass of the central system is high enough to allow the use of perturbative QCD [20, 21].

In addition, CMS can measure simultaneously the equivalent mass from the particles detected in the central region and the momentum loss of the protons, giving an extremely precise tool for missing mass searches. In fact, in some scenarios, i.e. if new physics couples dominantly to gluons, the general purpose detectors may not be sensitive enough; see for example [22] or the background computation done in the fourth chapter of [22].

The study of CD events, however, requires the simultaneous detection of the two protons, strongly correlating the mass of the central state with the acceptance of the detector inside the RPs, being $M_X \sim \sqrt{s\xi_1\xi_2}$. Hence, the physics phenomena accessible by the TOTEM detectors depends mainly on the LHC optics configuration and on the minimum distance possible between the RPs and the beam.

1.3.1 TOTEM-CMS Precision Proton Spectrometer

The CMS and TOTEM Collaborations have planned the development and installation of the CMS-TOTEM Precision Proton Spectrometer (CT-PPS), that will use the LHC optics between the CMS interaction point and the RP installation point, ~ 200 m downstream as a magnetic spectrometer, during high luminosity runs. Its goal is to study rare phenomena that require a detector system that is fully capable to profit from the increasing luminosity of the third phase of the LHC.

In fact, a detector with these characteristics has unique sensitivity to physics behind Standard Model and to perform precise measurements of subtle QCD effects. For example, CD processes with central mass $M(X) \gtrsim 300$ GeV are in principle accessible during high luminosity LHC runs, but their cross-sections could be of the order of ~ 1 fb. This requires the detectors to be able to work in high pile-up conditions, i.e. with more than 30 inelastic interactions per bunch crossing.

Thanks to CD processes, the LHC can be considered as a photon-photon collider with an energy range up to $\sqrt{s_{\gamma\gamma}} \lesssim 1$ TeV with an energy that can be measured on every event with CT-PPS detectors with a precision of the order of $\sigma(\sqrt{s_{\gamma\gamma}}) \sim 10$ GeV. While CT-PPS will not be able to detect events with hadronic central states ($\gamma\gamma \rightarrow X$) because of the large background due to gluons exchange, it will be possible to discriminate leptonic central states ($\gamma\gamma \rightarrow e^+e^-, \mu^+\mu^-, \tau^+\tau^-$ and W^+W^-) even with 50 pile-up events [23]. In particular, the processes with $X = W^+W^-$ will be used to study quartic gauge-couplings of the gauge bosons W and Z , as done in [24] but improving the efficiency using the proton tagging. Moreover, it is also possible to study deviations from the expected WW mass spectrum due to possible processes not foreseen by standard model.

One of the other scenarios is the study of Z photoproduction $\text{IP}\gamma^* \rightarrow Z$. This process is similar to the photoproduction of ρ , J/Ψ and other vector mesons and can be interpreted as follows: one of the protons radiates a virtual photon that fluctuates to a $q\bar{q}$ pair that exchanges a IP with the other proton and forms a vector meson or the Z . The characteristic of this interaction is that the proton that emits the photon will have small $|t| \sim 0.1 \text{ GeV}^2$ as typical of Coulomb scattering, while the other proton will have a larger $|t| \lesssim 0.5 \text{ GeV}^2$ because it underwent a strong diffractive process. In case the decay products of the Z , i.e. $Z \rightarrow \mu^+\mu^-$, are detected, the kinematic of the process is fully pictured and it can be a useful tool to calibrate the momentum scale of the spectrometer.

1.3.2 Running scenarios

The running scenario expected after the LS1 is summarized in table 1.1.

It is worth noting that part of the physic program has to be fulfilled during dedicated runs, when the LHC is configured with high β^* optics. In this scenarios, according to the luminosity delivered, it is possible to study large cross-section phenomena as elastic scattering at low $|t|$ or soft diffraction up to the study of central diffraction processes with an equivalent mass in the central region smaller than ~ 250 GeV [17]. On the other hand, higher mass central diffraction topologies

β^* [m]	cr. angle [μ rad]	ε_N [μ m rad]	N [10^{11} p/b.]	k bunches	μ	Luminosity	
						[$\text{cm}^{-2} \text{s}^{-1}$]	
2500	0	2	$0.7 \div 1.5$	2	$0.004 \div 0.02$	$(1.2 \div 5.6) \times 10^{27}$	$= (0.1 \div 0.5) \text{nb}^{-1}/24\text{h}$
90	0	2	$0.5 \div 1.5$	156	$0.06 \div 0.5$	$(1.3 \div 12) \times 10^{30}$	$= (0.1 \div 1) \text{pb}^{-1}/24\text{h}$
90	100	2	$0.5 \div 1.5$	1000	$0.06 \div 0.5$	$(0.9 \div 7.7) \times 10^{31}$	$= (0.8 \div 7) \text{pb}^{-1}/24\text{h}$
0.5	$310 \div 390$	$1.9 \div 3.75$	1.15	$2520 \div 2760$ ($\Delta t = 25 \text{ns}$)	$19 \div 34$	$(0.8 \div 1.3) \times 10^{34}$	$= (0.7 \div 1.1) \text{fb}^{-1}/24\text{h}$

Table 1.1: Overview of expected running scenarios at $\sqrt{s} = 13 \text{ TeV}$ with their respective ranges of inelastic pileup μ and delivered luminosity, where μ indicates the mean of the Poissonian distribution that describes the number of inelastic pp interaction per bunch crossing. The precise values depend on the bunch size, the number of bunches, and the emittance [17].

are not accessible during dedicated runs and can be studied only acquiring data during the high luminosity, low β^* configuration of the LHC, dedicated to general purpose detectors.

The TOTEM infrastructure prior to LS1 was unable to efficiently reconstruct events with more than one proton detected by each Roman Pot. This limited the data taking to beam configurations with a probability of multiple interactions in a single bunch cross not much higher than 5%, limiting the bunch populations to $\sim 0.6 \times 10^{11}$ protons [17].

1.4 Roman Pot system consolidation

The RP system has been consolidated during LS1 to work at higher luminosities, coping with pile-up and multiple tracks.

The existing Roman Pot system was modified to improve multi-track event reconstruction and angular resolution: the Roman Pots installed at 147m from the IP5 were relocated at 200m, as shown in fig. 1.9 and one unit has been rotated by 8 degrees to improve multiple track detection capabilities, as suggested by Monte Carlo studies [25] and shown in fig. 1.10. A picture of the section of the LHC tunnel with all the RP installed is shown in fig. 1.11.

The acceptance has been increased installing downstream collimators: an increased protection of the superconductive magnets from secondary particles pro-

Figure 1.9: Schematic view of the RP system after LS1. The RP units at 212 m and 203 m have the horizontal RP equipped with the RF shield.

Figure 1.10: Monte Carlo study of multi-track resolution achieved by the rotation of one RP unit. The graphs show the ratio of the number of true tracks over all reconstructed track candidates (i.e. true tracks - lost tracks + ghosts) as a function of the rotation angle. For simplicity, parallel tracks were assumed [25].

duced by the material of the Roman Pots allows a closer insertion without compromising the safety of the machine.

Furthermore, to ensure the stability of the operations at higher beam currents, the RPs have been equipped with new ferrite materials and the horizontal RPs of the two relocated units have been optimized. Moreover, one cylindrical horizontal

RP was added on each side of the IP. At present, the shielded RPs are hosting the same silicon strip detectors as the other RPs, while the cylindrical RPs are equipped only with radiation and temperature monitors. In fact, the first period after LS1 has been dedicated to the study of the behaviour of the new designs that will be fully exploited during the next runs. A more detailed discussion about the optimization is done in chapter 2.

Figure 1.11: *Picture of 220m RPs after LS1*

1.5 Roman Pot system upgrade: the timing detector

The key player of the TOTEM upgrade program is the timing detector that, with a time resolution below 100 ps, will remarkably improve the efficiency of the whole detector in presence of pile-up. Indeed, due to the rapidity coverage of the RPs and to the LHC optics, the obtainable precision on the vertex position is not enough to efficiently associate the detected protons to the interaction vertex in presence of

multiple collisions in the same bunch crossing. As shown in fig. 1.12, measuring the arrival time of the protons can be used to reconstruct the longitudinal position of the interaction; in particular, when the two exiting protons are detected, a precise ($\lesssim 100$ ps) measurement of the time-of-flight difference between them yields to a resolution on the longitudinal vertex position of a few centimetres.

Figure 1.12: Due to the high rapidity covered by RPs, the different interactions cannot be discriminated using a tracking detector: the arrival time of the protons is recorded with respect to a central clock reference and it is used to reconstruct the longitudinal position of the different collisions: $z_1 \propto t_{1,sx}$.

The effectiveness of the pile-up suppression depends on the time resolution of the timing detectors: considering a sample of inclusive DPE with one central reconstructed vertex, a timing detector with a resolution of $\sigma_t = 50$ ps reduces the impurity of selected events from 22% to 5%. In case the time resolution were limited to $\sigma_t = 100$ ps, the expected impurity would be of 8.5% [26].

The sensors chosen for the timing detector are diamond sensors that, using a customized front-end and read-out electronics, are capable of a resolution of the order of ~ 100 ps. Every RP will be equipped with four planes of sensors to obtain an overall timing resolution of $\sim \frac{100}{\sqrt{4}}$ ps.

The timing detector needs to be segmented to cope with the expected pile-up: simulations were done to find the best geometry of the segmentation, while keeping relatively low (<16) the number of channels to simplify the read-out electronics [27]. In particular, the aim of the study is to find a geometry that minimize the

probability of double hits in the same channel: the signal produced by any existing particle detector cannot be fast enough to distinguish two hits with a time separation on the order of ~ 100 ps.

The geometry proposed is shown in fig. 1.13: it consists of 10 pads of different size arranged to have the smaller pads in the zone with the highest activity. A slightly modified version has been implemented using 8 diamonds per plane, as shown in fig. 1.14.

Figure 1.13: *Optimized segmentation of the timing detector to be used in the vertical RP [27].*

Figure 1.14: *Final geometry of the timing detector for the vertical RP [28].*

The timing requirement for CT-PPS are more stringent; moreover, the detectors will be used in higher luminosity runs.

Chapter 2

Impedance optimization of the RPs

The increased intensity of the LHC after LS1 required the optimization of all the equipment close to the beam. Every cavity created inside the primary vacuum can resonate at the passage of the beam and, if the shape of the vacuum chamber is not optimized, can interfere with the stability of the beam. In addition, the walls of the cavity will dissipate part of the energy of the beam as heat that, if not under control, could damage the equipment itself.

This chapter will describe the optimizations that were proposed to improve the behaviour of the RPs; two different designs were build and tested and then installed in the LHC: one completely new cylindrical RP and a shield that can be installed on the existing RPs.

2.1 Impedance reduction using ferrite bars

The usual approach to reduce the heat induced by the passage of the beam is to install bars of lossy material, i.e. ferromagnetic materials or ferrites, that can absorb the energy from the cavity and damp the resonances. However, in the case of the LHC this approach is not straightforward: the cavity is made by the vacuum chamber itself and the ferrites have to be placed inside the primary vacuum; when the temperature of ferrites increases, due to the power absorbed by the cavity, they will very likely out-gas, degrading the quality of the LHC primary vacuum or even creating Unidentified Falling Object (UFO). Moreover, ferrites, being ferromagnetic,

are effective only at temperatures below their Curie temperature T_C .

The RP system was already equipped with ferrites (4S60 from Ferroxcube [29] with a Curie temperature $T_C = 100^\circ\text{C}$) and no issues ascribable to the RP impedance were noted during the dedicated runs of the first LHC phase. However, during high-luminosity test insertions in 2012, the temperature inside the RPs increased and the quality of the LHC vacuum in the RP region was degraded, primarily because of a piece of broken ferrite that could have reached a temperature higher than 100°C .

Therefore, the ferrite material has been substitute with the model TT2-111R, produced by TransTech [30] that has a higher Curie temperature $T_C = 375^\circ\text{C}$ and has been proven to have a better vacuum compatibility [31] and the design flaw that lead to the breaking was improved in the RPs currently installed [32].

2.2 Optimization of the geometry of the RPs

To further improve the behaviour of the RPs during high-luminosity insertions, the geometry of the vacuum chamber was studied and optimized; indeed, the design of the new RPs was driven by numerical simulations of the wake-field produced by the passage of the beam.

The procedure followed during the optimization process was to study the vacuum chamber without using any lossy material, so that all the resonances were easily detectable. Then, the same lossy materials produced by TransTech, were used to further reduce the resonances that can be excited by the beam. In the case of the LHC, it means to address all resonances below $\sim 1.2\text{ GHz}$, as shown by the beam power spectrum plot in fig. 2.1.

All the RPs installed during run one, because of the box shaped internal detector container, had a cavity between the cylindrical flange and the detector housing that resonates at $\sim 500\text{ MHz}$, as shown in fig. 2.2 and is the main contribution to the impedance.

The reduction, or the complete elimination, of this empty space is, indeed, the first step to optimize the RP geometry. Two complementary solutions have been designed and built: a new RP with a cylindrical detector housing, and a shield that

Figure 2.1: LHC Power spectrum, measured before LS1 [33]. The power spectrum is more than 37 dB attenuated above ~ 1.2 GHz.

Figure 2.2: Before LS1 all Totem Roman Pots were box shaped (left). The empty space between the RP and the flange resonate at low frequency (~ 500 MHz) as visible in the simulated longitudinal impedance without ferrites (right).

can be installed around the old RPs with a box shaped detector housing. The shield has ventilation holes introduced to guarantee a good vacuum on both sides of the shield: thanks to the fact that the shield does not need to sustain any pressure, the walls can be made with a thin (~ 1 mm) copper foil. Moreover, the shield is shorter than the box RP so that the copper foil is not increasing the material budget in front of the tracking detectors housed inside the RPs. The two designs are shown in fig. 2.3.

Figure 2.3: The cylindrical RP (left) and the shielded RP (right), showed in their working position near the beam, were proposed to reduce the impedance of the TOTEM Roman Pots.

Numerical simulations of both RF [34] and thermo-mechanical behaviour led to a design optimized under several aspects. For instance, the cavity made between the walls of the flange and the detector housing has to be as small as possible; although, to ensure a safe movement of the RP, a clearance of 2.5 mm has been chosen.

As mentioned, the new designs, as the old one, make use of lossy materials to further reduce the impedance. However, ferrite material are brittle and with a low thermal conductivity: the position and the shape of the ferrite pieces were also optimized ensuring enough thermal contact with the stainless steel of the flange. The choice was a ring of ferrite made by 12 segments positioned as far as possible from the beam, inside a recess in the flange.

The impedance optimization has been done mostly focussing on the two most critical effects, as discussed in [34]: the RF induced heating, that can lead to damages of the equipment, and the impedance felt by the beam (effective impedance), that can lead to instabilities at high intensity.

The beam induced heat is strongly dependent on the beam characteristics; in particular, the beam current and the beam power spectrum [35]:

$$P_{loss} = 2I^2 \sum_{p=1, \dots, \infty} \Re[Z_{long}(pM'2\pi f_{rev})] PS(pM'2\pi f_{rev}) \quad (2.1)$$

where,

- $PS(pM'2\pi f_{rev})$ is the power spectrum;

- f_{rev} is the revolution frequency, 11245 Hz for the LHC;
- M' is the number of buckets, 1782 for the LHC with a bunch spacing of 50 ns, 3564 for 25 ns;
- $I = MeN_B f_{rev}$ is the beam current, with M number of bunches, e charge of the proton, N_B number of protons per bunch;
- Z_{long} is the simulated longitudinal impedance.

The sum can be computed for $0 < pM'2\pi f_{rev} < 2.7$ GHz, since the measurement of the power spectrum at larger frequencies is dominated by noise.

The induced heat reduction expected with the new designs is clearly visible in fig. 2.4.

Figure 2.4: The cylindrical and the shielded RPs have a 4 times lower heating than the box RP at 1 mm from the beam, with a 25 ns beam spacing, 2800 bunches and 1.3×10^{11} protons per bunch (beam current of 0.65 A) [36].

Then, the effective impedance Z^{eff} is correlated with longitudinal and transfer instabilities of the beam and is defined as:

$$Z^{eff} = \frac{\sum_f Z(f) \sigma(f)}{\sum_f \sigma(f)} \quad (2.2)$$

In particular, the imaginary part of the longitudinal effective impedance $(\Im Z_{long}/n)^{eff}$, where $n = f/f_{rev}$ is the harmonic number, is an indication of the dispersion of the beam when passing through the cavity: if $(\Im Z_{long}/n)^{eff} = 0$, the longitudinal shape of the beam is not distorted by the interaction with the cavity.

The effective longitudinal impedance has been simulated for the different designs with the RP inserted at various distance from the beam, as shown in fig. 2.5. The new designs behave generally better than the box RP: the improvement at 1 mm from the beam of the cylindrical RP is $\sim 50\%$. The shield has not a big impact on $(\Im Z_{\text{long}}/n)^{\text{eff}}$ because the impedance is mainly due to discontinuities in the walls of the vacuum chamber and, as visible in fig. 2.3, the shield is not modifying the part of the RP closer to the beam.

Figure 2.5: The cylindrical RP has a $\sim 50\%$ better $(\Im Z_{\text{long}}/n)^{\text{eff}}$ than the box RP at 1 mm from the beam [36].

The transverse effective impedance $(\Im Z_{\text{trans}}/n)^{\text{eff}}$ is, in a similar way, related to how the beam transverse shape is perturbed by the interaction with the cavity. Simulations showed that $(\Im Z_{\text{trans}}/n)^{\text{eff}}$ was not critical for the box RP; so the new designs were not optimized to reduce $(\Im Z_{\text{trans}}/n)^{\text{eff}}$.

Whereas with similar RF behaviour, the cylindrical RP has the advantage to have more space available inside the detector housing, as required by some of the timing detectors. However, the increased dimensions require a thicker wall of the vacuum chamber compared to the box RP to ensure the safety of the primary vacuum and this causes a more copious secondary particle production (~ 10 times more than the box RP[37]) and could eventually limit the minimal distance possible from the beam. Therefore, the cylindrical RP is the ideal solution if the detector requires the increased space, while the shielded RP is the best performing RP from the point of view of both impedance and secondary particle production.

2.3 Test measurements on the prototypes

The RF optimization was focussed on the working condition of the RP, i.e. distance from the beam, beam parameters, etc. However, before the installation in the LHC, the reliability of the simulations has been proven using the same numerical models to predict the behaviour of the new RPs in several test benches [38].

The measurements were performed stretching a wire at the centre of the beam pipe and studying the device using a Vector Network Analyser (VNA); a picture and the schema of the setup is shown in fig. 2.6. In fact, a current pulse travelling through the wire can excite the cavity and the transmission scattering coefficient S_{21} of the line is an indication of this excitation. To perform the measurement using a VNA it is necessary to attenuate the two lines connected to the device under test (DUT) and to match the impedance of the DUT with that of the VNA cables ($50\ \Omega$), using small axial-lead resistors soldered on the edges of the wire.

Figure 2.6: *Picture (left) and schema (right) of the setup used to test the RF behaviour of a prototype of the cylindrical RP. A wire is stretched along the device under test (DUT). The impedance matching is ensured by the network (block “ Z_m ”) and the series attenuator (block “A”) [38].*

The measurements were in good agreement with what expected from the simulations as shown in fig. 2.7 and fig. 2.8 for the cylindrical RP and in fig. 2.9 and fig. 2.10 for the box RP with the copper shield.

Other tests were performed, using two parallel wires and a probe. The first is useful to detect resonances with a transverse component while the second is used to measure the quality factor of the resonances. These methods and their results are

Figure 2.7: S_{21} for the wire test with the cylindrical RP with ferrite at 1 mm, 10 mm and 40 mm from the centre of the beam pipe.

Figure 2.8: Simulated S_{21} for the wire test with the cylindrical RP with ferrite at 1 mm, 10 mm and 40 mm from the centre of the beam pipe.

discussed in detail in [38].

Figure 2.9: Measured transmission parameter S_{21} for the wire test on shielded RP with ferrite at 10 mm and 40 mm from the centre of the beam pipe.

Figure 2.10: Simulated transmission parameter S_{21} for the wire test on shielded RP with ferrite at 10 mm and 40 mm from the centre of the beam pipe.

2.4 New RPs installed in the LHC

Both designs were implemented and all the tests were performed together with the team responsible for the impedance of all the equipment in the CERN accelerator complex. After the approval of the responsible committee, the RPs were

successfully installed in the LHC and inserted during high intensity runs. Studies of the temperature inside the RPs show that the beam induced heating has been sensibly reduced [39]. As an example, the temperature of the cylindrical RP is

Figure 2.11: Temperature increase of the cylindrical RP without cooling in function of the luminosity delivered by the LHC. Circles indicate the temperature increase after 2 hours from insertion, solid dots after 4 hours [40].

Figure 2.12: Temperature of the cylindrical RP without cooling during a test insertion at ~ 3 mm from the beam. The dark green dotted line represents the distance of the RP from the centre of the beam pipe, the red dashed line is the beam intensity; the blue solid line represent the temperature of the RP.

shown in fig. 2.11 and 2.12. The highest temperature after 10 hours with the RP

inserted at 3 mm from the beam with $\sim 2 \cdot 10^{14}$ protons, corresponding to a beam current of ~ 0.36 A, is $\sim 36^\circ$ C; in comparison, in 2011, with a similar beam current, temperature of $\sim 40^\circ$ C were recorded inside a not cooled RP, retracted at 40 mm from the beam [41], giving an additional indication of the reliability of the calculations. In fact, assuming similar thermomechanical characteristics, simulations (fig. 2.4) suggest a similar behaviour of the inserted cylindrical RP and the old style box RP when retracted.

Chapter 3

Diamond detectors for particles detection

The continuous evolution of the particles accelerators, together with the increasing complexity of high energy physic experiments, requires the development of faster and more reliable particle detectors. Solid state detectors are widely used to cope with the highest requirement of speed, resolution and robustness. Silicon based detectors are by far the most common among them: the industrial demands for silicon technologies has significantly reduced the cost of the silicon substrates and of the development process. However, some intrinsic properties of silicon pose a limitation to the achievable performance. In particular, the relatively low saturation velocity of the charge carriers limits the collection time.

Diamonds, on the other hand, have extremely attractive properties, i.e. low thermal noise, high resistivity and high drift velocities of both electrons and holes. Although, thanks to new technologies used to produce synthetic crystals, the quality of artificial diamonds is improving, their availability and cost are relevant downsides compared to silicon.

When a particle passes through matter releases part of its energy; the purpose of the detector is to convert this energy into a signal that can be acquired and recorded. In this chapter the principles of solid state, and in particular diamond, detectors will be presented, together with the most common approaches to use a diamond crystal

as a particle detector.

3.1 Passage of particles through diamond

For a charged particle, the mean rate of energy loss in matter, can be described modelling the interaction of the particle with the electron gas inside solids. The case of an infinitely-thin absorber was theoretically described by Bethe [42]:

$$-\left\langle \frac{dE}{dx} \right\rangle = K z^2 \rho \frac{Z}{A} \frac{1}{\beta^2} \left[\frac{1}{2} \ln \left(\frac{2m_e (\beta\gamma)^2 T_{max}}{I^2} \right) - \beta^2 - \frac{\delta(\beta\gamma)}{2} \right] \quad (3.1)$$

where,

- $\beta = v/c$, with v the speed of the particle and c the speed of light;
- $\gamma = \frac{1}{\sqrt{1-\beta^2}}$ is the Lorentz factor;
- $K \sim 0.307 \text{ MeVg}^{-1}\text{cm}^2$;
- m_e is the mass of the electron in $\frac{\text{MeV}}{c^2}$;
- z is the charge of the particle in units of the electron charge e ;
- ρ is the density of the absorber in g/cm^3 ;
- Z and A are respectively the atomic number and atomic mass of the absorber;
- I is the mean excitation potential of the atoms of the absorber;
- δ is a function of $\beta\gamma$ to include Fermi density corrections;
- T_{max} is the maximum kinetic energy that can be transferred to a free electron by the particle in a single collision:

$$T_{max} = \frac{2m_e \beta^2 \gamma^2}{1 + 2\gamma \frac{m_e}{M} + (\frac{m_e}{M})^2} \sim 2m_e (\beta\gamma)^2 \quad (3.2)$$

As an example, the stopping power for a pion passing through copper is shown in fig. 3.1. It can be noticed that, increasing the energy, the energy loss decrease, to

Figure 3.1: The energy released by a particle passing through matter as a function of the $\beta\gamma$ of the particle.

increase after a minimum when $\beta\gamma \sim 4$; particles in this kinematic state are referred as Minimum Ionizing Particles (MIPs).

For higher energies the stopping power increases slowly ($\sim \ln(\beta\gamma)$), however density corrections considerably limit the growth, reaching the so called Fermi plateau, since Fermi was the first to foresee this effect using classical electrodynamics [43]. For this reason, the stopping power of particles with $\beta\gamma \gg 1$ is usually approximated with the energy loss of a MIP.

This formula was derived using quantum mechanical perturbation theory and takes into account only energy loss due to the interaction of the particle with the electron gas of the absorber, neglecting bremsstrahlung, nuclear collisions, pair production, etc. Nevertheless, it is extremely useful to estimate the energy lost by single charged particles passing through diamond. For example, for MIP particles with $\beta\gamma \sim 4$ ($\beta \sim 0.97$) that pass through a diamond¹ crystal, the mean energy loss can be approximated to:

$$-\left\langle \frac{dE}{dx} \right\rangle \sim K 3.52 \frac{6}{12} \left[\frac{1}{2} \ln \left(\frac{(1\text{MeV})^2 (\beta\gamma)^3}{(75\text{eV})^2} \right) - 1 \right] \sim 6.3 \frac{\text{MeV}}{\text{cm}} \quad (3.3)$$

¹The value of the mean excitation energy is $I = 75.3\text{eV}$ [44].

A similar value can be computed with Monte Carlo simulations [45], as shown in fig. 3.2.

Figure 3.2: Stopping power for a muon passing through a diamond [45]. The value for a $\beta\gamma \sim 4$ is $1.76 \frac{\text{MeV cm}^2}{\text{g}} \sim 6.2 \frac{\text{MeV}}{\text{cm}}$.

For absorbers of finite thickness, a better description was obtained by Landau [46]. The energy loss has a probability distribution (Landau-Vavilov-Bichsel distribution [47]) and its most probable value is given by:

$$\Delta_p = \frac{K}{2} \frac{Z}{A} \frac{x}{\beta^2} \left[\ln \left(\frac{2m_e (\beta\gamma)^2}{I} \right) + \ln \left(\frac{\frac{K}{2} \frac{Z}{A} \frac{x}{\beta^2}}{I} \right) + j - \beta^2 - \delta(\beta\gamma) \right] \quad (3.4)$$

with x the thickness in g/cm^2 and $j = 0.200$ a constant. As for eq. 3.1, for high energy particles, the power loss reaches the Fermi plateau.

Using this formula, the computed most probable value for a MIP passing through $500 \mu\text{m}$ thick diamond crystal is:

$$\Delta_p \sim 240 \text{ KeV} \quad (3.5)$$

3.2 Principles of solid state particle detectors

The energy released by the particle can, in some cases, produce a signal in the absorber that can be collected with properly designed electrodes. For example, this

energy can ionize atoms in a gas.

In solids, atoms are closely packed in a lattice and their discrete energy levels are merged together into energy bands. The characteristics of these bands depend on the lattice and on the atoms that constitute it. At the absolute zero, all the electrons will occupy the lowest energy allowed by the Pauli exclusion principle and the highest energy they can have is called Fermi energy.

When the band below the Fermi energy is completely full, this band is called *valence* band, while the first band above the Fermi energy takes the name of *conduction* band: all electrons are in the valence band and there are no empty energy levels in that band. If an external field is applied, electrons can not be accelerated unless the energy is enough to make them jump into the conduction band. This is the case of insulators, in which applying an electric field, electrons cannot move to produce a current.

On the other hand, in a conductor, the Fermi energy is inside a band, i.e. valence and conduction bands are merged, and all electrons have energy levels available and can be accelerated.

At temperature higher than the absolute zero², thermal excitation can allow electrons in the conduction band, as shown in fig. 3.3. Thus, a material that is not conductive at low temperature can conduct current if the temperature is high enough; also, its resistivity becomes lower while increasing the temperature.

In some crystals, the Fermi energy can be controlled adding appropriate impurities in the lattice; these materials are called *semiconductors*. In particular, some impurities can introduce energy states so close to the conduction band (*donors*) that the electrons in these states can jump in the conduction band due to thermal excitation. In a similar way, other impurities (*acceptors*) introduce energy states close to the valence band: some electrons occupy these states, leaving a *hole* in the valence band. It is generally said that inside a semiconductor the current can flow thanks to the movement of electrons in the conduction band (same as a conductor) and holes in the valence band.

²At any temperature, the Fermi level is defined as the energy level with a 0.5 probability to be occupied.

The technological advantage of semiconductors is that, using two materials (or two region of the same material) with a different Fermi energy (*junction*), it is possible to control the flow of charge carriers: electrons will move only towards regions with lower energy levels available. This is the principle behind a *diode*.

The most common semiconductors are tetravalent atoms, like silicon, diamond and germanium; among this, silicon is widely used in electronics and particle detectors. Usually, pentavalent impurities like phosphorous or arsenic are used as donors and to dope silicon to create an *n-type* semiconductor; on the other hand, acceptors are trivalent atoms, like boron or aluminium, and are used to create *p-type* semiconductor.

A large number of applications are possible using semiconductors. A typical application in particle detection is shown in fig. 3.4. Here two electrodes deployed on the surfaces create an electrical field inside the semiconductors. The charges generated by the passage of a charged particle will drift toward electrodes, generating an electrical pulse that can be amplified and recorded.

Figure 3.3: At 0 K all electrons are in the valence band (red dashed line); however when the temperature increases (blue solid line) some electrons will have enough energy to jump in the conduction band.

Figure 3.4: *A particle passing through a diamond will create electron-hole pairs that will drift toward the electrodes because of the bias applied using the polarization circuit; the current induced on the read-out electrode can be amplified and acquired.*

3.3 Diamond properties

The most common semiconductor used for particle detection is silicon; however, thanks to some peculiar properties, diamond is a promising material. These properties are summarized in table 3.1, where properties of diamond are compared with the corresponding values for silicon.

Band gap The main difference between silicon and diamond is that diamond has a band gap almost 5 times bigger than silicon. The advantage of a bigger band gap is the lower number of electrons in the conduction band due to thermal excitation: this means a lower *dark current*, the amount of current that flows through the detector in absence of signal. A lower dark current corresponds also to lower power consumption when applying a bias voltage, hence a lower heat to be dissipated. Moreover, if the direct³ band gap is bigger than ~ 3 eV, electrons can not be excited by visible light. Thus, thanks to their high band gap, diamond detectors can operate without cooling or being enclosed in a dark box.

On the other hand, a wider band gap means that the energy needed to create an electron-hole pair is larger. For the same amount of energy released by the particle,

³It is the minimum energy needed to directly excite an electron, without transfer part of the momentum to the lattice.

		Silicon	Diamond
E_g	Band Gap (eV)	1.12	5.47 (7.5 eV direct)
E_b	Breakdown field ($\frac{V}{cm}$)	3×10^5	10^7
ρ_{el}	Resistivity (Ωcm)	2.3×10^5	$> 10^{15}$
ρ	Density ($\frac{g}{cm^3}$)	2.33	3.52
$E_{e/h}$	Energy to create e/h pair (eV)	3.6	13
E_{MIP}	Most probable energy released by MIP ($\frac{MeV}{cm}$)	3.21	4.69
$E_{e/h}$	Most probable number of e/h pair created by MIP ($\frac{N}{\mu m}$)	89	36
μ_e	Electron mobility ($\frac{cm^2}{Vs}$)	1350	4551 [48]
μ_h	Holes mobility ($\frac{cm^2}{Vs}$)	480	2750 [48]
v_e	e saturation velocity ($\frac{cm}{s}$)	$\sim 10^7$	$\sim 2.6 \cdot 10^7$ [48]
v_h	h saturation velocity ($\frac{cm}{s}$)	$\sim 7.5 \cdot 10^6$	$\sim 1.6 \cdot 10^7$ [48]
ϵ_r	Relative permittivity	11.9	5.7
T_d	Displacement threshold energy (eV)	36 [49]	37.5 - 47.6 [50]

Table 3.1: *Physical properties of silicon and diamond at room temperature [51].*

the number of pairs created, and the corresponding current, is also lower than the ones created in silicon. The energy needed to create a single electron-hole pair in diamond is 13 eV, 3.6 times larger than silicon. However, due to higher density of diamond, the energy lost by a crossing particle is also larger. In the end, for the same thickness the number of charge pairs created in a diamond by a MIP is ~ 2.5 times smaller than in silicon.

Drift velocity The second main difference between silicon and diamond is the saturation velocity of the charge carriers. For an applied electrical field E , the velocity of the carriers can be described by:

$$v = \frac{\mu E}{1 + \frac{\mu E}{v_s}} \quad (3.6)$$

where μ is the mobility of the carrier and v_s its saturation velocity. For low values of the applied field $v \sim \mu E$; above a certain value of the electrical field, the velocity increase is no longer linear and saturates as shown in fig. 3.5.

Figure 3.5: Saturation velocity of electrons and holes in silicon (respectively black full and open dots) and single crystal CVD diamond (respectively blue and red open dots), measured along the $[100]$ direction [48].

It is evident that, for both electrons and holes, the drift velocities are faster in diamond and this means a faster collections of the electron-hole pairs created in the ionization.

Relative permittivity For a given a geometry of a detector, its capacitance is proportional to the relative electrical permittivity ϵ_r . A diamond detector will have a capacitance smaller by a factor ~ 2 with respect to a silicon detector with similar geometry. A lower capacitance is advisable for a timing detector, as it will be discussed in detail in chapter 4.

Minimum displacement energy When a crystal is exposed to radiation, the lattice can be damaged if an atom is displaced from its position creating a defect

in the lattice (bulk damage) and this will degrade the performance of the detector. Diamond is well known as a material that can sustain an high dose of radiation and this is mainly due to the high energy that is needed to displace an atom.

In this thesis the radiation hardness will not be covered in detail because of the relatively low dose foreseen for the TOTEM timing detector. However, the advantage of diamond over silicon has been extensively discussed in literature; some example are [48, 52, 53].

3.4 Single crystal diamond for particle detection

The main disadvantage of diamond is by far its availability, and hence its cost. In fact, some of the properties discussed are strongly dependent on the quality of the crystal. As an example, fig. 3.6 shows how the production process of the diamond can affect the average energy needed to create an electron-hole pair, i.e. the amount of charge that can be collected at the passage of a particle. The reason for these differences is the amount of lattice defects or impurities.

Diamonds can be divided in two categories:

- single crystal: the whole diamond is a continuous lattice, i.e. all the symmetries are valid for the whole volume;
- polycrystalline: the diamond is made by randomly distributed single crystals of micro-metric sizes.

Then, diamonds can also be classified according to their purity:

- Type Ia: nitrogen impurities can be up to 3000 ppm; this strong presence of nitrogen compromises UV (and sometime blue) transparency of diamonds. A consistent part of natural diamonds belong to this category.
- Type Ib: nitrogen impurities are up to 500 ppm; the impurities are more spread and the diamond has a yellowish or brown colour.
- Type IIa: nitrogen impurities are very low, making the diamond transparent up to UV light.

Figure 3.6: The average energy needed to create an electron-hole pair is strongly dependent on the production process of the diamond: CVD diamonds require a lower energy, in average, to create an electron-hole pair than natural diamonds and HTHP diamonds [54].

- Type IIb: nitrogen impurities are very low, but small boron impurities give the diamond a light blue colour; this type of diamond behaves as a p-type semiconductor.

For particle detection the most important difference is the ability of the charge carriers to be collected by the electrodes: every impurity reduces the efficiency of this process. For example, nitrogen impurities or the boundaries of micro crystals in a polycrystalline can trap electrons, preventing their collection. Therefore, the diamonds used for particle detection are usually of type IIa.

Before years 2000s the purity of artificial diamonds was not sufficient for any electronics or particle detection applications. The production of synthetic diamonds was undertaken by *De Beers Industrial Diamonds*, now *ElementSixTM*⁴, that, collaborating with the Uppsala University, produced samples of high purity, single crystal artificial diamonds [55].

The samples were produced in a microwave plasma-assisted Chemical Vapour

⁴Element Six, a De Beers Group Company <http://www.e6.com/>

Deposition (CVD) reactor operating at $\sim 800^\circ\text{C}$ and a pressure $> 15\text{ KPa}$. Inside the reactor, a gas composed by hydrogen, methane and argon is ionized and the carbon atoms deposit on a single crystal substrate forming both diamond and graphite. However, the graphite will be removed by hydrogen, leaving, eventually, only diamond that does not react with hydrogen. The quality of the starting substrate is extremely important as every defect can be a source of dislocations in the deposited layers.

Even at present time, only few industrial suppliers worldwide can produce diamond with these characteristics. So far *ElementSixTM* produces diamond with the best quality, with the best reproducibility between samples and offers diamonds for “Quantum/Radiation detectors” with nitrogen and boron concentration typically lower than, respectively, 5 ppb and 1 ppb. The maximum available size is $4.5 \times 4.5\text{ mm}^2$ with a thickness of $500\text{ }\mu\text{m}$. This is an evident disadvantage of diamond for detector of considerable size, like, for example, the inner tracker of CMS or ATLAS. However, the quality of polycrystalline diamond is continuously improving and new companies are starting the manufacturing of good quality crystals.

To compare crystals, it is useful to define the Charge Collection Efficiency (*CCE*), the fraction of the generated charge that is actually collected by the electrodes, or, equivalently, the Charge Collection Distance (*CCD*), the average distance covered by an electron or a hole drifting in an electric field, more precisely:

$$CCD = v_{e,h}\tau_{e,h} \sim CCE \times d \quad (3.7)$$

with τ_e (τ_h) the lifetime of electrons (holes) and d is the thickness of the substrate. For a single crystal diamond, usual values are $CCE > 95\%$ or $CCD > 475\text{ }\mu\text{m}$ for a $500\text{ }\mu\text{m}$ diamond with 500 V applied. While, typical values for high quality polycrystalline substrates are $CCE > 36\%$ or $CCD > 180\text{ }\mu\text{m}$ for a $500\text{ }\mu\text{m}$ diamond with 500 V applied.

3.5 Deposition of metallic read-out electrodes

The usual way to apply an electrical field to a diamond, and to collect the charge carriers produced at the passage of a particle, is by mean of the deposition of a thin metal layer (metallization) on the two opposite faces of the crystal. Due to the high chemical inertness of diamond, it is not trivial to create a good ohmic contact between the diamond lattice and the metal: a bad interface leads to a Schottky barrier and to charge build-up that reduces the electrical field in the bulk. This phenomenon is also referred to as *polarization* of the diamond [56].

The details of the metallization method are mostly proprietary, however the two main techniques are:

- evaporation: a metal is heated inside a vacuum chamber where a diamond is placed, the atoms that evaporate from the metal will condensate on the diamond;
- sputtering: the metal is bombarded with high energy electrons or ions to eject atoms that will hit the diamond substrate with much more energy than using evaporation.

Regarding the choice of the metal there are two main approaches: metals like gold or lead that are not reacting with carbon [57] and carbide-forming metals, as titanium or chromium [58].

A carbide-forming layer has been proven to be the best choice [59]: a pre-treatment procedure is used to damage the surface of the crystal creating graphite, the latest is much more reactive than diamond; then, a layer of chromium or titanium is deposited. An additional layer of gold (CrAu) or platinum-gold (TiPtAu) or tungsten (TiW) is added and, finally, an annealing procedure is performed. The details of this procedure have to be carefully studied as small imperfection in the metallization will make the diamond unsuitable for particle detection, because of low collection efficiency and/or charge build-up.

It is possible to create electrodes of different size and shape using a mask during

the metal deposition or, alternatively, using chemical etching to remove the metalization from the unwanted regions.

Figure 3.7: Chemical etching, together with a laser LED to impress the photoresist, can be used to create different geometries of the electrodes [60].

Another possibility is to use a wet etching technique, as described in fig. 3.7: after the metallization, a liquid photoresist is applied on the diamond. A fast spinning of the substrate allows a uniform distribution of a thin film of photoresist. Then, a laser diode is used to print the geometry on the photoresist: the exposed region become soluble and can be removed. Finally, the proper etching fluid (for example aqua regia) is used to dissolve all the unprotected regions. More details are available in [60].

Diamonds used for the tests discussed in this thesis were metallized at GSI using CrAu coating; one of the prototype is shown in fig. 3.8. After the prototyping phase, the volume production for the final version of the timing detector was done at PRISM⁵ using TiW coating.

3.6 Graphitized read-out electrodes

An alternative way to guarantee good electrical and physical contact between the diamond and electronics for polarization and read-out is to create a graphite layer directly on the surface of the diamond crystal using a laser. This procedure is

⁵Princeton Institute for the Science and Technology of Materials
<http://www.princeton.edu/prism/>

Figure 3.8: Example of a diamond metallized (CrAu) at GSI; the pads were precisely drawn using wet etching.

called *graphitization* of the diamond.

A good laser source is a Nd:YAG that emits 8 ns pulses at 1064 nm [61]. The laser is focused on the surface of the diamond and, when the energy of the pulse is above a threshold (on the order of $10 \frac{\text{J}}{\text{cm}^2 \text{ pulse}}$) the diamond is “burned” into graphite. It is possible to draw lines of $\sim 10 \mu\text{m}$ width and with a depth that can be up to $\sim 50 \mu\text{m}$. There is no practical limitation to the patterns that can be drawn with this technique: an example of a diamond with graphitized electrodes is shown in fig. 3.9.

Figure 3.9: Picture of one diamond with pads graphitized at LENS laboratory in Florence (Italy).

The setup used to perform the graphitization is described in fig. 3.10: the beam produced by the Nd:YAG laser is expanded and focused on the surface of the diamond. The sample is fixed on a three-axis stage that can be controlled numerically with micrometric precision. Also, a low power laser diode, a digital

camera and a power meter are used to monitor in real time the process.

Figure 3.10: The diamond sample (in blue) is mounted on a three-axial micrometric stage which is exposed to the laser that is focused using an 8 mm lens (OB); the same optics transmit light into a digital camera and a laser diode which is, together with a power meter, used to check the proper alignment and to monitor the procedure [61].

The whole process is done without any particular cleaning procedure and without the need of a clean room; moreover, the procedure is fast and can be completed in only a few hours. This technique is faster and simpler than the deposition of metallic electrodes, that requires several days of work and highly specialized equipment.

A more detailed description of the procedure is available in [61].

After the graphitization, the connection to the electronics can be done using any conductive material, i.e. silver paste or even copper tape. Indeed, the ohmic contact with the diamond lattice is guaranteed by the graphite layer and the contact between two conductors (graphite and copper, for instance) is easily done without any risk of creating a Schottky junction.

The performance of a graphitized diamond are similar to an equivalent metallized diamond, as shown in fig. 3.11. However, the charge collected by the graphitized diamond is lower; this is due to the smaller active region and not to the graphite electrodes themselves. In fact, while the metallization is applied *on* the surface, the graphite layer goes deep up to $\sim 50 \mu\text{m}$ inside the diamond, hence reducing the active volume thickness.

Figure 3.11: Comparison of the amplitude of the signal produced by a metallized and a graphitized diamond using the same front-end electronics and a Sr^{90} radioactive source [61].

Moreover, a graphitized electrode has a lower material budget with respect to the metal layers; giving an advantage for the detection of low energy ions, for instance for dosimetry in cancer treatments [62].

In conclusion, graphitization can be considered a valid alternative to metallization for all the applications where a faster, simpler and more versatile method is advisable at the cost of a reduced active volume of the diamond. At present, more studies are needed, especially to understand the quality of the contact in presence of high radiation doses.

3.7 3D diamonds

A limitation of parallel plate particle detector is that the collected charge and the collection distance are strictly correlated: to increase the active volume, and thus the collectable charge, an obvious solution is to use a thicker diamond, increasing the distance between the collecting electrodes. This is a problem especially when the collection distance is limited by the quality of the substrate, as it is the case for low quality, polycrystalline or irradiated diamonds. Moreover, as discussed in

section 3.3, diamond is well known for its good resistance to irradiation; nevertheless, reducing the collection distance without reducing the active volume would further improve its radiation hardness.

Also, a shorter collection distance means a shorter collection time; hence, giving an advantage for timing measurement.

A solution, originally proposed for silicon detectors [63], adopts the creation of conductive columns to collect charges, as shown in fig. 3.12, forming a three dimensional layout; hence the conventional name of *3D* diamond.

Figure 3.12: *In a traditional detector, charges are collected by electrodes on the edge of the active material; the idea of a 3D detector is to bury the electrodes inside the bulk to collect the charges closer to their production [64].*

Thanks to the property of diamond and graphite it is also possible to create columns inside a diamond substrate: using a technique similar to the one described for the graphitization of the surface, it is possible to focus the laser inside the bulk and create a three-dimensional pattern.

The setup is similar to the one used for surface graphitization; however, using shorter pulses has been proven to have better performance [65]. The chosen laser was indeed a Ti:Sapphire that can emit 30 fs pulses at 800 nm; a picture of the result is shown in fig. 3.13.

The charge collection efficiency of a 3D diamond is close to 100 % as proven by the measurement done in [65] and reported in fig. 3.14. The full collection is reached with a bias lower than 10 V, with respect to 50 V of the planar detector.

One of the problem of 3D detector is that the electrical field inside the active volume is not uniform; hence, the collection time depends on the position of the

Figure 3.13: Picture of graphite columns inside a single crystal diamond. The columns on the right were done to calibrate the procedure and are not used.

Figure 3.14: Comparison of the collected charge of a 3D diamond done with the Ti:Sapphire laser and a reference planar detector with the same characteristics [65].

passage of the particle as shown in fig. 3.15. The effect is reduced for higher applied polarization voltages; however, being the distance between electrodes very small, the maximum sustainable biasing is lower with respect to an equivalent planar geometry.

To reduce the jitter due to this phenomenon it is possible to reduce the distance between the columns. However, graphite is less dense than diamond: a graphite column occupies a bigger volume than the diamond before the graphitization, producing some stress in the bulk. To guarantee a sufficient mechanical strength, the minimum distance between columns has to be $> 50 \mu\text{m}$. In particular, the chosen

Figure 3.15: The collection time is always very short (< 1 ns), however the signal is dependent on the region hit by the particle with respect to the position of the columns [66]. The red columns are connected to ground while the blue one is connected to the biasing potential; the graph on the right shows the shape of the signal for particle that hit the detector in different regions (A, B and C).

geometry is shown in fig. 3.16: columns on the same row are separated by $70\text{ }\mu\text{m}$, while the pitch between rows is $114\text{ }\mu\text{m}$. These columns are connected to one electrode, say the positive one, while the columns of the opposite polarity have the same geometry, but shifted in such a way that every negative column is surrounded by positive columns. A picture of an intermediate step of the production is shown in fig. 3.17; it is possible to notice that half of the column is still not wired.

Figure 3.16: The chosen distance between the columns is a compromise between the uniformity of the charge collection time and the mechanical stress produced inside the substrate.

Every column is $\sim 10\text{ }\mu\text{m}$ in diameter and $455 \pm 10\text{ }\mu\text{m}$ long: a shorter column produces a less uniform electric field, while a longer column could reduce the maximum sustainable biasing voltage. In fact, if one column reached the opposite

Figure 3.17: *Picture of graphite columns connected (only on one side) by graphite wires on the surface of the diamond.*

surface, the resistance between the electrodes would be sensibly reduced.

An other possible issue of 3D diamond is that columns have a high resistance: it can be up to $\sim 300\text{ K}\Omega$. This is not a problem when performing relatively slow measurements, i.e. for tracking or spectroscopy. However, this could severely limit the performance of a timing detector. New tests have shown a correlation between the resistivity of the columns and the duration of the laser pulse. Maybe a more refined technique could optimize the 3D diamonds under this aspect. It should be also noted that graphite can be etched using chemicals: it is possible to create a graphite column, then remove the graphite and fill the column with gold or another better conductor. Although the complication added by this step is not negligible, reducing one of the advantage of the graphitization: the relatively low complexity of the procedure.

Moreover, the capacitance of a 3D detector is 15 to 20 times larger than a planar detector of the same dimension. The impact of the capacitance of the detector, together with the impact of the high column resistance, will be discussed in the chapter 4.

In conclusion, 3D diamonds are promising for their radiation hardness and for their short collection time; however, at the moment of writing, not all characteristics are under control and it is not possible to foresee *a priori* the performance of a 3D

timing detector. The tests done on the 3D diamonds will be discussed in chapter [7](#).

Chapter 4

Front-end electronics

An important role in determine performance of a diamond detector is played by the front-end electronics. Indeed, the signal produced by a diamond at the passage of a particle is extremely fast and reproducible but, at the same time, very small.

The performance achievable using commercial amplifiers, as the ones produced by Cividex Instrumentation, have been proven, within the reference of this thesis, to be insufficient for the requirements of the TOTEM timing detector. Hence, the TOTEM Collaboration had to develop custom front-end electronics which will be discussed in detail in this chapter.

Starting from an equivalent model for a planar diamond detector different amplification techniques have been simulated. First, the read-out of a diamond using only a resistor is studied; this case, although impractical, is extremely useful to understand the main parameters that influence the performance of the detector. Then, after describing a broadband and a charge sensitive amplifiers, an intermediate solution will be analysed: an amplifier with high input impedance. Finally, an original shaping strategy is proposed to increase the signal to noise ratio.

4.1 Equivalent circuit of the diamond detector

A reliable simulation of any front-end electronics for a detector begins with a reliable model of the detector. The equivalent model of a parallel plate detector

consists in a current generator, in parallel with a capacitor and a resistor, as shown in fig. 4.1. The wire connecting the detector to the electronics has also to be considered

Figure 4.1: *Equivalent model of a diamond detector with parallel plate geometry.*

as a capacitor in parallel with a resistor and an inductor in series. However, some components can be neglected; for instance, the capacitance of the bonding wire is usually negligible with respect to the capacitance of the diamond. In the same way, the resistance of the diamond is usually $\gg \text{G}\Omega$ and can be approximated to an open circuit. Fig. 4.2 shows a measurement of the current flowing through a $500\text{ }\mu\text{m}$ diamond; the behaviour is not perfectly ohmic, but the maximum current of $\sim 35\text{ nA}$ when applying 1000 V corresponds to a resistance of $\sim 28\text{ G}\Omega$.

Figure 4.2: *Measurement of the current flowing through a $500\text{ }\mu\text{m}$ diamond for an increasing bias voltage.*

Usual values for R_W and L_W are on the order of $\sim \Omega$ and $\sim \text{nH}$ respectively.

The capacitance of the detector is given by:

$$C = \epsilon_r \epsilon_0 \frac{S}{d} \sim 50 \frac{S(\text{mm}^2)}{d(\text{mm})} \text{ fF} \quad (4.1)$$

where S and d are respectively the surface of the pad and the thickness of the diamond express in millimetres; ϵ_0 is the vacuum permittivity and ϵ_r is the relative permittivity of diamond.

For a diamond detector with a parallel plate geometry, the electrical field in the active volume can be assumed uniform; the current generated at the passage of a particle, using the Shockley-Ramo theorem, is:

$$i(t) = i_e(t) + i_h(t) = Q_{mov} E_w (v_e(E) + v_h(E)) \quad (4.2)$$

where,

- $Q_{mov}(t)$ is the charge drifting toward the electrodes;
- $E_w = 1/d$ is the *weighting field*;
- $v_{e,h}(E)$ is the drift velocity of electrons and holes, for an applied electric field E .

Assuming that electrons and holes have the same drift velocity and that their lifetime is longer than the collection time and can be assumed infinite, we have:

$$i(t) \sim 2 \frac{Q_{mov}}{t_{tr}} \theta(t - t_0) \theta(t_0 + t_{tr} - t) \quad (4.3)$$

where $t_{tr} = d/v_{e,h}(E)$ is the maximum transit time of a charge inside the detector and $\theta(t)$ is the Heaviside step function.

As shown in fig. 4.3, a MIP should generate uniformly pairs of charge carriers inside the whole active volume. Hence, the amount of charge drifting is maximum when the particles traverses the detector and decreases linearly until is zero for $t = t_{tr}$:

$$Q_{mov} = Q_{gen} \left(1 - \frac{t}{t_{tr}}\right) \quad (4.4)$$

Figure 4.3: Ionization process of a MIP passing through a 500 μm diamond simulated using Weightfield2 [67]. Electron-holes pair are generated uniformly (apart from Landau fluctuations) across the whole thickness of the diamond and then they drift following the electric field generated by the bias potential.

The current generated by the passage of a MIP through diamond is then:

$$i(t) \sim 2 \frac{Q_{gen}}{t_{tr}} \left(1 - \frac{t}{t_{tr}}\right) \theta(t - t_0) \theta(t_0 + t_{tr} - t) \quad (4.5)$$

For a 500 μm diamond with an applied bias of 1000 V and with $t_0 = 0$, typical values are $Q_{gen} = 2.88 \text{ fC}$, $t_{tr} = 5 \text{ ns}$:

$$i(t) \sim 2 \frac{2.88 \text{ fC}}{5 \text{ ns}} \left(1 - \frac{t}{5 \text{ ns}}\right) \theta(t) \theta(5 \text{ ns} - t) \quad (4.6)$$

A simulation done using Weightfield2 [67], without the approximations (i.e. $v_e \neq v_h$) is shown in fig. 4.4; the results are similar to what expected.

Figure 4.4: Signal produced by a MIP passing through a 500 μm diamond simulated using Weightfield2 [67]. The red dotted line represents electrons, the blue dashed line is for holes and the green solid line is the sum of the two contributions.

4.2 Polarization of the diamond

The polarization of the diamond can be done using two approaches, both shown in fig. 4.5:

- applying the bias voltage on the same electrode of the read-out;
- applying the bias voltage on the opposite electrode.

Figure 4.5: The polarization bias can be provided on the same electrode as the read-out (a) or on the opposite electrode (b).

The advantage of the first approach is that one of the electrodes is grounded while all the front-end electronics is connected to the other; however, the signal has to be read after a decoupling capacitor that can introduce noise, for instance due to the leakage current and the presence of two additional soldering points. In the second case, the decoupling is done by the diamond itself, but neither of the electrodes is connected to the ground.

From a practical point of view, the two approaches have the same performance; so it is possible to choose the one that best suits with the particular application.

4.3 Toy model of the read-out electronics for a diamond detector.

To understand the behaviour of a diamond detector and to optimize the front-end electronics, it is useful to analyse the simplest possible case: a diamond detector

read using a simple resistor, neglecting the contribution of the polarization and of the bonding wires. Although this scenario is not practically realizable, it is useful as toy model to understand how the time resolution is affected by the capacitance of the detector and by the value of the resistor. This model is shown in fig. 4.6.

Figure 4.6: The simplest way to read the current generated by a diamond detector is using a resistor.

The signal on the RC is given by the convolution of the current generated by the diamond and the impulse response of the RC network:

$$v_{RC}(t) = i(t) \star h_{RC}(t) = i(t) \star \frac{1}{C} e^{-\frac{t}{RC}} \quad (4.7)$$

Hence:

$$v_{RC}(t) = \begin{cases} 0 & \text{if } t < 0 \\ -\frac{2Q_{gen}}{t_{tr}^2} R e^{-\frac{t}{RC}} \left[RC + t_{tr} + (t - (RC + t_{tr})) e^{\frac{t}{RC}} \right] & \text{if } 0 < t < t_{tr} \\ \frac{2Q_{gen}}{t_{tr}^2} R e^{-\frac{t}{RC}} \left[RC \left(e^{-\frac{t_{tr}}{RC}} - 1 \right) - t_{tr} \right] & \text{if } t > t_{tr} \end{cases} \quad (4.8)$$

It is possible to define:

$$k_0 = \frac{2Q_{gen}}{t_{tr}^2} \quad (4.9)$$

$$k_1 = RC \left(e^{-\frac{t_{tr}}{RC}} - 1 \right) - t_{tr} \quad (4.10)$$

$$t_0 = RC + t_{tr} \quad (4.11)$$

so that eq. 4.8 becomes:

$$v_{RC}(t) = \begin{cases} 0 & \text{if } t < 0 \\ k_0 R \left(t_0 \left(1 - e^{-\frac{t}{RC}} \right) - t \right) & \text{if } 0 < t < t_{tr} \\ k_0 k_1 R e^{-\frac{t}{RC}} & \text{if } t > t_{tr} \end{cases} \quad (4.12)$$

The signal is faster for low values of R and C , however its amplitude is low. Some examples of $v_{RC}(t)$ are shown in fig. 4.7.

Figure 4.7: Examples of $v_{RC}(t)$ for various values of R ; the amplitude of the signals has been scaled for a better displaying: $v_{scaled}(t) = k_{scale} v_{RC}(t)$.

For $t > t_{tr}$ the signal can only decrease; hence, v_{RC} will assume its maximum value before t_{tr} , in particular:

$$t_{max} = -RC \ln \left(\frac{RC}{t_0} \right) \Rightarrow \quad (4.13)$$

$$V_{max} = v(t_{max}) = k_0 R \left(t_{tr} + RC \ln \left(\frac{RC}{RC + t_{tr}} \right) \right) \quad (4.14)$$

The signal will be affected by Johnson–Nyquist noise, in particular:

$$\sigma_V = \sqrt{v_n^2} = \sqrt{4k_B T R B} = \sqrt{\frac{k_B T}{C}} \quad (4.15)$$

where:

- $\sqrt{v_n^2}$ is the noise RMS;
- k_B is the Boltzmann constant;
- T is the temperature;
- B is the bandwidth, assuming a sharp frequency cut; in this case with only one pole $B = 1/4RC$ [68];

Thus, the SNR is:

$$SNR = \frac{v_{max}}{\sigma_V} = \frac{k_0}{\sqrt{k_B T}} \frac{1}{\sqrt{C}} RC \left(t_{tr} + RC \ln \left(\frac{RC}{RC + t_{tr}} \right) \right) \quad (4.16)$$

Adjusting the value of the resistor to keep RC constant, the SNR depends only on C . The behaviour of this function versus R is shown in fig. 4.8, for different values of C and at $T = 300$ K: for low values of R , the SNR decreases for increasing capacitance, then it saturates to:

$$\lim_{R \rightarrow \infty} SNR = \frac{k_0 t_{tr}^2}{2 \sqrt{k_B T}} \frac{1}{\sqrt{C}} \propto \frac{1}{\sqrt{C}} \quad (4.17)$$

To understand intuitively why SNR saturates, it is useful to consider the RC as an integrator: the signal produced by the detector has a finite integral (Q_{gen}) and a finite duration (t_{tr}). Hence, for $RC \lesssim t_{tr}$ the integration time is not enough to integrate the whole signal; for $RC \gg t_{tr}$ the collected information cannot further increase¹.

For instance, for a detector with $C = 1$ pF, the amplitude of the signal is bigger than the noise for $R \gtrsim 60\Omega$; an acceptable scenario is for $SNR \gtrsim 6$ which, corresponds to $R \gtrsim 430\Omega$.

Finally, the time resolution can be approximated to:

$$\sigma_t \sim \frac{\sigma_V}{dV/dt} \Big|_{t=t_{tr}} = \frac{\sqrt{\frac{k_B T}{C}}}{k_0 \left(\frac{t_0}{RC} e^{-\frac{t_{th}}{RC}} - 1 \right)} = \frac{\sqrt{k_B T C}}{RC} \frac{t_{tr}^2}{2 Q_{gen}} \frac{1}{\frac{t_0}{RC} e^{-\frac{t_{th}}{RC}} - 1} \quad (4.18)$$

¹The voltage signal on the resistor is increasing, however it is only due to an increased gain, hence the noise is increasing at the same rate.

Figure 4.8: *SNR of a diamond detector versus the resistor R used to read the signal at $T = 300$ K. The dashed black line indicates $\text{SNR} = 1$*

with t_{th} the threshold crossing time: dV/dt is decreasing with t , so the threshold should be as low as possible, but above the noise. For example a good choice is $v_{RC}(t_{th}) = 6\sigma_V$.

The time resolution is shown in fig. 4.9 and it is clear that the resolution achievable has a limit and is ~ 100 ps for a diamond detector with $C = 1$ pF. What is the limit depends on the capacitance of the detector, i.e. the geometry of the pad. It should be also noted that, increasing the value of R , the total duration of the signal is also increasing, limiting the maximum rate sustainable by the detector; hence, R should be chosen as the smallest value before the saturation of the time resolution, i.e. $R \sim 1$ K Ω for $C = 1$ pF.

Figure 4.9: *Time resolution expected for a diamond read on a resistor R for different values of C . The dashed black line represents the time resolution achievable for various C , varying accordingly R to have $RC = 1$ ns.*

The conclusion that can be drawn is that it is advisable to have a detector with the lowest possible capacitance; however, the detector has to be read using a resistance high enough to integrate all the signal generated by the diamond: $RC \lesssim t_{tr}$.

4.4 Broadband amplifier

The current generated by a diamond detector can be amplified using a broadband amplifier with a low input resistance. Several commercial amplifiers have bandwidth above 1.5 GHz and an input resistance $R_i = 50 \Omega$; the output signal will have a sharp rising edge, thanks to the high bandwidth, which is directly affecting the time resolution. However, the wide bandwidth and the small input impedance are also reducing the signal to noise ratio.

As explained before, the capacitance of the detector directly affects the performance of the detector. It is useful to separate two cases:

$$a) R_i C \gtrsim 1/2\pi f_{amp}$$

$$b) R_i C \lesssim 1/2\pi f_{amp}$$

where $R_i = 50 \Omega$ is the input resistance and f_{amp} is the bandwidth of the amplifier.

For the case *a* the dominating pole is due to the detector, hence the behaviour will be the analogue with what seen for a simple resistor. However, at the output of the amplifier, the signal is amplified of a factor G_{amp} and the total noise is [68]:

$$\sigma_V = \sqrt{v_n^2} = G_{amp} \sqrt{4k_B T R B F} = G_{amp} \sqrt{\frac{k_B T F}{C}} \quad (4.19)$$

where F is the noise figure of the amplifier, usually expressed in dB ($NF = 10 \log F$).

Thus, from eq. 4.16:

$$SNR = \frac{SNR_R}{\sqrt{F}} = \frac{k_0}{\sqrt{F}} \frac{R_i C}{\sqrt{k_B T C}} \left(t_{tr} + R_i C \ln \left(\frac{R_i C}{R_i C + t_{tr}} \right) \right) \quad (4.20)$$

For the case *b*, the bandwidth is limited by the amplifier; hence, both signal and noise will be independent from the detector capacitance. Assuming that the

amplifier has a dominant pole, it is possible to consider it as an RC network with $R = R_i = 50 \text{ } \Omega$ and $C_{amp} = \frac{1}{2\pi R_i f_{amp}}$. The SNR is given by eq. 4.20 substituting C with C_{amp} . Fig. 4.10 shows the SNR for typical values found in commercial broadband amplifiers.

Figure 4.10: SNR of a diamond detector versus its capacitance C read with a broadband amplifier with $R = 50 \text{ } \Omega$ and $NF = 1.8\text{dB}$ used to read the signal at $T = 300 \text{ K}$. The dashed black line indicates $SNR = 1$

It is clear that this solution cannot be used to detect MIPs with diamonds; nevertheless, one of the best dedicated amplifier on the market (at the moment of the tests) was purchased and tested, the Cividec C2 [69] with a gain of 40 dB, a bandwidth of 2 GHz and a RMS noise in output of 2.5 mV ($NF \sim 1.8\text{dB}$), confirming the theoretical calculations. However, it should be noted that these amplifiers are used in several applications to detect low energy particles or for beam monitoring using diamond detectors [70, 71].

4.5 Charge sensitive amplifier

A different approach consists in reading the detector on a capacitor instead than a resistor: the output voltage will be proportional to the charge instead than the current. This is called Charge Sensitive Amplifier (CSA) and its schema of principle is shown in fig. 4.11.

Figure 4.11: Schema of a diamond detector read using a charge sensitive preamplifier.

In first approximation it is possible to neglect the feedback resistor R_{CSA} , indicated with dashed lines in fig. 4.11, and to assume the amplifier *ideal* [72]:

- infinite input impedance;
- zero output impedance;
- infinite open-loop gain: $A_v = -\infty$;
- infinite bandwidth with zero phase shift and infinite slew rate;
- zero input offset voltage.

The charge generated by the passage of the particle will be shared by C_D and F_{CSA} : $Q_{gen} = Q_D + Q_{CSA}$; in particular, both capacitors are connected to the input of the amplifier, hence:

$$v_{in} = \frac{Q_D}{C_D} = \frac{Q_{CSA}}{C_{CSA}} \quad (4.21)$$

Thus:

$$Q_{CSA} = Q_{gen} \frac{1}{1 + \frac{C_D}{C_{CSA}}} \quad (4.22)$$

The output of the amplifier is given by:

$$v_{out} = -\frac{Z_{CSA}}{Z_{in}} v_{in} \quad (4.23)$$

where:

$$Z_{CSA} = \frac{1}{sC_{CSA}} \text{ is the feedback impedance;}$$

$Z_{in} = \frac{1}{sC_D}$ is the input impedance.

Finally, the output of the amplifier is proportional to the generated charge:

$$v_{out} = -\frac{C_D}{C_{CSA}} \frac{1}{1 + \frac{C_D}{C_{CSA}}} Q_{gen} \quad (4.24)$$

The gain of the amplifier depends on the ratio between the capacitance of the detector and the feedback capacitance: as for the other read-out configurations, a low capacity of the sensor is advisable to have good performance; also considering that, because of parasitic capacitances, it is difficult to have $C_{CSA} \lesssim 1$ pF, especially using discrete components.

However, this circuit is impractical in any realistic application, as both capacitors cannot be discharged: even for real devices, i.e. an amplifier with a finite input resistance, the discharge may take up to several milliseconds. If a second signal is generated by the detector, the collected charge will be added to the charge already present in the capacitor (and in the detector). As shown in fig. 4.12, the output baseline will shift with time and the amplifier will soon reach saturation.

Figure 4.12: If the discharge time of the feedback capacitor is longer than the time between two input pulses (red dotted line), the output (blue solid line) will diverge.

Hence, to reduce the discharge time, a resistor R_{CSA} is added in parallel to the

feedback capacitor: as shown in fig. 4.13, thanks to this modification, the amplifier is fast enough to sustain the high rate of input signals, even if with a much lower gain.

Figure 4.13: To improve the high rate capabilities of the CSA, a resistor is added in parallel to the feedback capacitance: the output (blue solid line) goes to zero before the arrival of the following input pulse (red dotted line).

Moreover, to improve the performance of the amplifier, usually a CSA amplifiers is followed by several stages dedicated to the shaping of the signal.

One of the best commercially available amplifier, expressly designed for diamond detectors, is manufactured by Cividex Instrumentation: the C6 amplifier has a gain of 5.4 mV/fC with ~ 750 electrons of equivalent noise; for a $500 \mu\text{m}$ scCVD diamond, the SNR expected is ~ 22 with an input capacitance of 4.3 pF[69]. A pair of Cividex C6 were purchased and tested using the diamond detectors produced by the same company.

4.6 High input impedance amplifier

As discussed in section 4.3, one of the way to obtain a good SNR and, consequently, a good time resolution, is to increase the input impedance of the front-end electronics. For example, for a detector capacitance $C \sim 1$ pF, the input resistance

should be $R_i \sim 1 \text{ k}\Omega$.

A good choice is a common emitter configuration, as shown in fig. 4.14, using high speed and low noise transistors, for instance SiGe transistors.

Figure 4.14: A common emitter configuration to read the diamond detector. The capacitance of the diamond is indicated as C_D , the resistance of the bonding wire is R_{bond} and the resistors used to polarize the transistor are R_b and R_c ; the output signal is read on a load resistor R_L . The polarization circuit of the diamond is not shown.

To understand the behaviour of the circuit, it is possible to use a simplified hybrid- π model of the transistor, shown in fig. 4.15, where all the parasitic capacitances of the transistor are neglected². Also the impedances of the bonding wires can be considered negligible at this stage.

Figure 4.15: Simplified model of the common emitter configuration shown in fig. 4.14, after using the hybrid- π model for the transistor.

The voltage signal on the collector is:

$$v_c(t) \sim -g_m v_{be}(t) R_P \quad (4.25)$$

²In this case, this is a legitimate approximation: the BDP740 is a SiGe transistor with $C_{be} \sim 0.35 \text{ pF}$ and $C_{ce} \sim 0.08 \text{ pF}$ that, even considering the Miller effect, can be neglected compared to the capacitance of the detector $C_D \sim 1 \text{ pF}$.

where $g_m = I_c/V_T$ is the transconductance given by the ratio between the collector current and the thermal voltage $V_T = \frac{k_B T}{e} \sim 25 \text{ mV}$; v_{be} is the voltage at the base and $R_P = R_L // R_c$. The voltage read on a resistor was computed in section 4.3, however in this case the resistance is given by the parallel between R_b and r_{be} , with:

$$r_{be} \sim \frac{V_T}{I_b} \quad (4.26)$$

Realistic values are:

$$R_b \sim 100 \text{ k}\Omega; \quad R_c \sim 50 \text{ }\Omega; \quad R_L \sim 50 \text{ }\Omega \quad r_{be} \sim 1 \text{ k}\Omega \quad (4.27)$$

Hence, $R_b // r_{be} \sim r_{be}$. Using eq. 4.12 and the definitions 4.9, 4.10 and 4.11 with $R = r_{be}$ and $C = C_D$:

$$v_{be}(t) = \begin{cases} 0 & \text{if } t < 0 \\ k_0 r_{be} \left(t_0 \left(1 - e^{-\frac{t}{r_{be} C_D}} \right) - t \right) & \text{if } 0 < t < t_{tr} \\ k_0 k_1 r_{be} e^{-\frac{t}{r_{be} C_D}} & \text{if } t > t_{tr} \end{cases} \quad (4.28)$$

Thus:

$$v_c(t) \sim -g_m R_P v_{be} \sim R_P \frac{v_{be}}{r_{be}} \quad (4.29)$$

$$v_c(t) \sim \begin{cases} 0 & \text{if } t < 0 \\ k_0 R_P \left(t_0 \left(1 - e^{-\frac{t}{r_{be} C_D}} \right) - t \right) & \text{if } 0 < t < t_{tr} \\ k_0 k_1 R_P e^{-\frac{t}{r_{be} C_D}} & \text{if } t > t_{tr} \end{cases} \quad (4.30)$$

The maximum of the signal is proportional to the maximum computed in 4.15:

$$v'_{max} \sim \frac{R_P}{r_{be}} v_{max} \quad (4.31)$$

while the thermal noise (eq. 4.19) is:

$$\sigma'_v = \sqrt{4k_B T F B R_P} \sim \sqrt{k_B T F \frac{R_P}{r_{be} C_d}} \sim \sqrt{F \frac{R_P}{r_{be} C_d}} \sigma_v \quad (4.32)$$

$$SNR' = \frac{v_{max}}{\sigma'_v} = \sqrt{\frac{1}{F}} \sqrt{\frac{r_{be}}{R_P}} SNR \quad (4.33)$$

The contribution of $\sqrt{1/F}$ can be as small as 5 % for modern SiGe transistors: the voltage on the collector has an amplitude proportional to R_P (instead of r_{be}), while the time constant and the noise depend on r_{be} , substantially increasing the SNR with respect to reading the diamond directly on a resistor $R = r_{be}$.

All these approximations are extremely useful to roughly understand the behaviour of the circuit and to individuate the components that mainly affect the performance. However, a more detailed simulation, like the one implemented in the SPICE program, is useful to have a more precise prevision; in particular, the simulated performance of the circuit shown in fig. 4.14 are shown in fig. 4.16 and 4.17. SNR and time resolution depend on the working point of the transistor, mainly on the value of the base resistor R_b .

Figure 4.16: Simulated SNR for a diamond read on the circuit shown in fig. 4.14 with the values in 4.27 versus the base resistor R_b and for different values of C_D .

Figure 4.17: Simulated time resolution for a diamond read on the circuit shown in fig. 4.14 with the values in 4.27 versus the base resistor R_b and for different values of C_D .

4.6.1 The HADES detector

The idea of using a first stage with an high input impedance was first used by the HADES collaboration at GSI for their diamond detectors that provide the start time in the time-of-flight system of their spectrometer [73]. A pair of prototypes of their detector was borrowed for testing.

The schema of the HADES amplifier is shown in fig. 4.18. The first stage is on the same board housing the diamond (the hybrid), to minimize the capacitance seen by the amplifier and to avoid long connections, while the following amplification stages are on a different board. The connection between the two boards is not critical as the line is adapted to $50\ \Omega$ to avoid reflections and reduce the attenuation. The second and the third stages are also used to shape the signal; in particular, the inductances on the two collectors are used to reduce the rise time of the signal.

A picture of the HADES hybrid with the diamond is shown in fig. 4.19. The diamond is divided in 8 segments, each of $\sim 2.2\text{ mm}^2$ that correspond to a capacitance of $\sim 0.2\text{ pF}$.

Figure 4.18: Schema of the detector designed for the HADES spectrometer. The circuit is split into two boards: an hybrid with the diamond and the first stage and a second board with the other two amplification stages.

Figure 4.19: Picture of the diamond board of the detector designed for the HADES spectrometer. The first stage is as close as possible to the diamond to reduce the capacitance of the connection.

4.6.2 TOTEM timing detector

Thanks to the experience gained with the HADES detector, the TOTEM collaboration has designed and produced its front-end electronics. The main challenge was to obtain performance similar to the HADES detector, but using a diamond with a capacitance 8 times larger. Indeed, as discussed in section 1.5, the geometry foreseen for the timing detectors requires pad surfaces up to 16 mm^2 .

Figure 4.20: Picture of the four channels prototype board of the timing detector developed by the TOTEM collaboration. The first stage of the 4 channels is close to the diamond to reduce the input capacitance.

Different prototypes with a single diamond, similar to the one shown in fig. 4.20, were made to find the best compromise between SNR and rise time.

Figure 4.21: Picture of one of the prototype boards of the timing detector developed by the TOTEM collaboration.

For all the prototypes, the first stage is a common emitter with high input impedance, as shown in fig. 4.21. Inspired by the design made by HADES, the first stage is as close as possible to the sensor to reduce the input capacitance. The following stages are on the same board, but a few centimetres away to reduce the exposition to the beam radiation and to facilitate the cooling inside the Roman Pot.

Once the final schema was defined, several boards (shown in fig. 4.22) were produced to host 8 diamonds of $4.5 \times 4.5 \text{ mm}^2$, according to project's requirements. The first test was done with 4 boards equipped with only 4 diamonds (8 channels)

Figure 4.22: Picture of the prototype installed in the Roman Pot for the first test on the LHC.

each. These boards were successfully installed in a Roman Pot on the LHC during the Technical Stop of November 2015 (TS3). The manufacturing of the boards with the full acceptance is in progress at the moment of writing and the installation is foreseen for the year 2016.

4.7 Amplitude dependent shaper

The usual approach to further improve the SNR is to introduce some electronic filters to reduce the bandwidth of the amplifier. In fact, the signal has a limited bandwidth, while *white* noise spans the full frequency spectrum. However, in our case, the bandwidth of the signal generated by the diamond would extend to several GHz and is already limited by the first stage; hence a different approach has been tested: a wide bandwidth amplifier but with a gain that depends on the amplitude of the signal.

To obtain this non linear behaviour, it is possible to use a common emitter configuration with a very high resistor to regulate the base voltage of a fast SiGe transistor, as shown in fig. 4.23. With no signal, the noise is attenuated, while when the signal is present, the amplifier increases its gain.

In absence of signal the voltage at the base is too low ($v_{be} \lesssim 0.7\text{ V}$) and the transistor is in the interdiction regime; when the input signal is negative, the voltage at the base of the transistor will be even lower than in absence of signal. However,

Figure 4.23: Common emitter configuration with a very high base resistor to have a low working point.

a positive signal, v_{be} will increase; if this increment is enough, the transistor will become active. A simulated response is shown in fig. 4.24: for a sinusoidal input with an amplitude of 15 mV, the output is attenuated, while for an input amplitude of 150 mV the output is amplified: only the positive part of the signal is amplified.

Figure 4.24: Simulated output of the amplifier shown in fig. 4.23 for an sinusoidal input (dashed green line) with an amplitude of 15 mV (output in red) and for 150 mV (output in blue).

The gain versus the amplitude of the input is shown in fig. 4.25. For this configuration, all signal below ~ 80 mV are attenuated, while all signals larger than ~ 200 mV will saturate the transistor³.

This circuit can be seen as a compromise between a filter and a discriminator,

³The gain curve has a temperature dependence, however, the SNR has a low dependence on the temperature.

Figure 4.25: Simulated gain of the amplifier shown in fig. 4.23, computed as $G = 10 \log \frac{\text{MAX}(|v_{out}|)}{\text{MAX}(|v_{in}|)}$.

but the information of the amplitude of the signal is not lost as in a discriminator and the recovery time is smaller since only very high signals saturate the transistor. The advantage of this configuration is that the SNR , defined by the ratio of the maximum when there is a signal and the noise in absence of signal, increases and the signal produced also has a faster rise time, thanks to the fast switching time of a SiGe junction. However, the disadvantage is that the linearity of the signal is lost and all the components have to be thoughtfully tuned and can not be used to precisely measure the energy deposited by the detected particles.

This idea has been implemented and tuned to read a diamond detector, following the principles used by HADES (see section 4.6). The final schema of the Amplitude Dependent Amplifier (ADA) is shown in fig. 4.26. The first stage is a common emitter, as discussed before. The second stage is a booster that prepares the signal for the non-linear third stage in a way that the signal generated by the most probable ionization has an amplitude high enough to be in the active region of the third, non linear stage.

It should be noted that ferrite beads have been used on the second and third stages to further reduce the high frequency noise. A ferrite bead was used instead of an inductor to regulate the bandwidth of the signal because at high frequency an inductor may introduce oscillations, while the ferrite bead acts simply like a frequency dependent resistor. The ferrite bead BLM15HB121, manufactured by Murata, and the dependence of its resistance with the frequency is shown in fig.

Figure 4.26: Schema of the Amplitude Dependent Amplifier (ADA) used to read a diamond detector.

4.27.

Figure 4.27: A ferrite bead acts like a frequency dependent resistor and can be used to define the bandwidth of the amplifier [74].

The simulated output signal for the most probable value of charge generated by ionization of a MIP (Q_{gen}) is shown in fig. 4.28. Its amplitude is ~ 230 mV and the noise without signal is $\sigma_v \sim 1.5$ mv. The expected power consumption in absence of signal is below 50 mW per channel, mostly due to the first two stages: ~ 15 mW and ~ 25 mW respectively. However, the last stage, in presence of signal can dissipate up to 100 mW.

Fig. 4.29 shows the amplitude of the output signal expected for various Q_{gen} .

The diamond was installed on a PCB hosting the first stage designed by HADES,

Figure 4.28: Simulated output of the ADA for $Q_{gen} \sim 2.88$ fC.

Figure 4.29: Simulated amplitude of the output signal of the ADA in function of the charge Q_{gen} generated by the ionization. The expected value for the most probable value of a MIP is $Q_{gen} \sim 2.88$ fC.

Figure 4.30: Photo of the PCB of the ADA, realized by the electronics CAD of the INFN, Bari Division.

only slightly modified, while for the following stages the PCB was designed and built by the electronics CAD of the INFN, Bari Division, shown in fig. 4.30. Particular

care had to be taken for the PCB manufacturing: for instance, the input and output lines have been adapted to $50\,\Omega$ and 0402 SMD components have been used for the signal path to reduce the contribution of the parasitic capacitances. Moreover, due to the high amplitude of the amplified signals, the high peak current needed to power the third stage has to be taken into account when designing the power and ground lines.

Chapter 5

Test methodologies

The characterization of a detector, together with the front-end electronics requires the measurement of several parameters; among these: noise, amplitude of the signal, rise time and efficiency. The first step in classifying different detectors is to prepare a test procedure to measure a relatively small number of meaningful properties of the device under test (DUT). This chapter will briefly describe the tests performed in order to characterize all the prototypes discussed in this thesis.

5.1 Characterization of a timing detector

The main goal of this work is the development of a diamond detector with a high efficiency ($> 90\%$) and a time resolution below 100ps.

A useful rule of thumb to compute the time resolution of a particle detector is given by:

$$\sigma_t \sim 1.25 \frac{\Delta t_{0.1-0.9}}{SNR} \quad (5.1)$$

where, $\Delta t_{0.1-0.9}$ is the rise time of the detector signal, measured as the time from 10% to 90% of the amplitude, and SNR is the signal to noise ratio.

This rule suggests that the development of a detector with a good time resolution has more stringent requirements with respect to a tracking detector:

- the SNR has to be as large as possible; for a tracking detector usually a

$\text{SNR} \gtrsim 10$ can be considered acceptable;

- the leading edge has to be as fast as possible; for a tracking detector the signal can be as slow as the rate of particles requires.

This rule gives an indication of what could be improved; however, the time resolution has to be measured directly. This direct measurement has to be performed either using a time reference, i.e. a detector with ~ 10 times better time resolution, or using two identical detectors.

Figure 5.1: *The time resolution can be computed studying the distribution of the difference between the arrival time measured by two identical detectors.*

Indeed, in a configuration similar to the one shown in fig. 5.1, the time difference between the two signals is expected to be constant with deviations on the order of $\sim \text{ps}$, mainly due to thermal fluctuations [75]. However, if the timing detectors have a time resolution of $\sim 100 \text{ ps}$, the actual measurement will have an error:

$$\sigma_{TOT}^2 \sim \sigma_{det1}^2 + \sigma_{det2}^2 \sim 2\sigma_{det1}^2 \quad (5.2)$$

A repeated measurement of the time difference will produce results distributed as a Gaussian with a sigma dependent on the time resolution of the two identical detectors:

$$\sigma_{meas} \sim \sqrt{2}\sigma_{det} \quad (5.3)$$

giving an elegant way to measure the time resolution of a detector without the need of a time reference.

To evaluate the efficiency properly, the ideal setup consists in placing the DUT between two scintillators smaller than the detector, as shown in fig. 5.2, and to expose it to MIPs. Then, the efficiency can be calculated as the ratio of the number of coincidences between the two scintillators to the number of coincidences between the two scintillators and the DUT:

$$\eta = N_T/N_D \quad (5.4)$$

Figure 5.2: The efficiency of the DUT is given by the ratio between triple and double coincidences.

However, this setup is not practical for detectors of the size of few millimetres.

Another way to properly measure the efficiency of the device under test is to use a particle beam and a tracker to measure the fraction of particle whose trajectory goes through the detector and gives a signal. However, due to the complexity required by the latest setup, it has been performed only on the detector subset that had a time resolution compatible with the requirements.

5.2 Test using high energy beam

The time resolution of a detector, as discussed, depends on the SNR that is strongly dependent on the amount of energy released inside the detector by the passage of a particle. Therefore, it is important to test the device recreating, as close as possible, the conditions of the final environment: a good choice is to use a beam of particles with a $\beta\gamma \gg 4$ to be sure that the energy deposition inside the detector is slightly lower than what expected for the LHC protons. This ensure

that, using a test setup as discussed and shown in fig. 5.1:

- the energy lost inside the first detector is negligible with respect to the total energy of the particle;
- the energy released inside the first detector has a small impact on the speed of the particle, i.e. the time difference between the two detector is independent of the energy released;
- the energy released in the two detectors has the same stochastic behaviour, i.e. same Most Probable Value (MPV), etc.

5.3 Test using β source

The tests using a particle beam are inherently complex and time consuming; often it is useful to test the equipment using a small radioactive source.

The radioactive material chosen is ^{90}Sr . The ^{90}Sr decays with an half life of 28.79 years, as [76]:

with the ^{90}Y decaying with an half life of 2.671 days as [76]:

The energy spectrum of the emitted electrons is shown in fig. 5.3.

Using a 500 μm thick diamond detector, all the electrons emitted with less than ~ 500 KeV will release all their energy inside the detector, that is more than twice the energy released by a MIP (~ 220 KeV, see section 3.3). However, selecting only electrons that have a sufficient energy, i.e. using a scintillator behind the detector, as shown in fig. 5.4, it is possible to have a behaviour very similar to MIPs.

Fig. 5.5 shows that an electron of 1 MeV can travel inside a diamond for ~ 1 mm. At the same time, the stopping power of dry air is negligible for a small setup, as shown in fig. 5.6.

Figure 5.3: Histogram of the number of electrons, $N(p)$, emitted by ^{90}Sr (a). Curve (b) represents the background, with the source shielded by a copper disk. The endpoint energies of ^{90}Y and ^{90}Sr are respectively: $E_{01} = 2279.5 \pm 2.9 \text{ MeV}$ and $E_{02} = 546.0 \pm 1.6 \text{ MeV}$ [77].

Figure 5.4: It is possible to acquire the signal of the diamond only when the electron emitted by the ^{90}Sr has enough energy to produce a signal in a downstream scintillator.

Figure 5.5: An electron of 1 MeV can travel for ~ 1 mm inside a diamond [45].

Figure 5.6: The energy loss for an electron of 1 MeV travelling in air can be considered negligible if the detector is at few cm from the source [45].

This method can be used to characterize a diamond detector, however can not be used to measure its time resolution using the method discussed in section 5.1. In fact, even for the most energetic electrons, the energy lost inside the first diamond is not negligible, strongly affecting the behaviour inside the downstream detector.

Chapter 6

Data acquisition and processing

The signal produced by a particle detector has to be processed by suitable electronics to extract the exact time of the particle passage. For different type of detector the needed processing can be different and often depends on the requirements of the final application. Therefore, different data acquisition devices were used to digitize the detector output, sampling or discriminating the analog signal of the detector and several different techniques were used to compute the arrival time.

In this chapter, these devices will be described, together with the software framework developed to analyse the acquired data. Special attention has been given to the algorithms used to compute the arrival time.

6.1 Data acquisition devices

The tests were performed using several acquisition devices: the first tests were done using a fast oscilloscope, considered as a reference system thanks to the fact that it is properly calibrated and it can be used to display the acquired waveforms in real-time. However, the rate expected for the timing detector, when installed in the LHC, is too high for any commercial oscilloscope; moreover, the cost and space needed per channel are, then, two further disadvantages that make the use of an oscilloscope impractical in an integrated system.

The usual approach for timing measurement is to use a discriminator and a

Time to Digital Converter (TDC) [78, 79]. This solution was tested using a TDC developed at GSI [80].

However, part of the information of the signal is lost after the discrimination and it would be useful to sample the signal to process it using off-line analysis. A smart solution is the SAMpler for PICOsecond time pick-off (SAMPIC) chip, designed and realized by a collaboration including IRFU/SEDI, Saclay and LAL, Orsay, that is capable of sampling the signal, record it with a dead time and a cost per channel that is comparable with the commercially available TDCs.

6.1.1 High Speed Oscilloscope

During the development of an electronic device, a good oscilloscope is essential for the tests; moreover, modern digital oscilloscopes have an operating system, usually Windows, that allows the user to develop a data acquisition system according to his needs.

The choice for our test was Agilent DSO9254A (fig. 6.1), with sampling rate up to 20 GSa/s [81]. The maximum rate that we discovered was sustainable by the oscilloscope is ~ 100 Hz.

Figure 6.1: *The reference system for the signal digitalization during the test was an Agilent DSO9254A oscilloscope.*

To increase the acquisition rate, it is possible to configure this oscilloscope in the so called *segmented mode*: it can acquire up to 8000 *segments*, store them in

a fast temporary memory and then, when the acquisition is completed, save them to disk. Thanks to this feature, it is possible to acquire data in bursts with dead time of less than $\sim 10 \mu\text{s}$ and then store everything after the acquisition. The main advantage of this configuration is that, when triggering the oscilloscope with an external signal with rate of the order of few kHz, as our test set-ups, the one to one correspondence between the trigger and the acquired data is ensured. Hence, it is possible to synchronize data acquired with the oscilloscope and with other systems, like, for example, the tracking telescopes.

Figure 6.2: *The tracker receives the trigger from the coincidence of the scintillators; when the event has been acquired it asserts a trigger out signal that is sent to the oscilloscope. The tracker will be in a busy state until it is rearmed by the trigger out of the oscilloscope, asserted when the oscilloscope has acquired data, ensuring a one to one correspondence.*

For instance, the setup shown in fig. 6.2 was used during the test at DESY. A pair of scintillators is positioned upstream and downstream a silicon tracker and the Device Under Test (DUT) is positioned between two sets of three pixel planes each. The trigger is generated by the coincidence of the signals from the scintillators and it is sent to the tracker. The tracker is not fast enough to acquire at every trigger, hence it is configured to assert a *trigger out* only when the event is recorded; then it waits for a signal to be rearmed. The oscilloscope, on the other hand, acquires when receives a *trigger out* from the tracker and its *trigger out* is used to rearm the tracker. The *segmented mode* is important to ensure that the oscilloscope acquires

every time it receives a trigger from the tracker. However, when the oscilloscope has acquired all the requested *segments*, it will be busy for several seconds: the tracker is not receiving any rearm signal and will not accept any trigger. If no trigger is accepted by the tracker, the oscilloscope will not receive any signal and, thus, will never rearm the tracker. To unlock the system, a watchdog sends a signal to rearm the tracker if the oscilloscope does not send trigger for a time longer, with the due tolerances, than it takes to save the *segments*.

The same schema has been used also during the test at the CERN SPS, but it has been adapted to the slightly different trigger logic of the GEM tracker. In fact, the veto of the trigger until receiving a rearm signal was not foreseen by the tracker trigger logic and has been implemented using external NIM electronics.

6.1.2 TRB3 and PaDiWa: TDC on FPGA

The TDC system chosen for the tests is the TRB3 board developed at GSI. The board has 4 FPGAs that can be programmed to be used as TDCs with up to 264 channels. Depending on the loaded firmware, it is possible to measure both the time of arrival and the time over threshold of the signal; it is also possible to increase the time resolution reducing the number of available channels.

The TDC works with LVDS inputs, however several add-ons are available to amplify and discriminate an analog input. Our choice was the PaDiWa board that has an internally matched $50\,\Omega$ wideband amplifier and a discriminator implemented using an FPGA that can be configured to detect the leading, the trailing edge or both.

Both systems have been designed following the “COME&KISS principle”: COMplex ComMERcial Elements & Keep It Small and Simple. In other words, it is advisable to use commercially available products (for data processing, network, etc.) and add only “small and simple” in house designed parts. In particular, a “small and simple” PaDiWa (shown in fig. 6.3 with its schematic) amplifies and discriminates the signal and the “COMplex ComMERcial” FPGAs of the TRB3 handle the high precision time to digital conversion.

Figure 6.3: The “small and simple” amplifier and discriminator is implemented in the PaDiWa add-on [80]

All the firmware and the software for control, data acquisition and data analysis is available under an open source licence.

The system configured for the tests is capable of a time resolution of 23 ps [82].

6.1.3 SAMPIC: a fast sampling chip

The SAMpler for PICOsecond time pick-off (SAMPIC) is a chip designed and manufactured by a collaboration including IRFU/SEDI, Saclay and LAL, Orsay. Originally designed to read out the forward time-of-flight detectors of ATLAS with a picosecond precision, it is a fast sampler designed to have high rate capabilities and relatively large integration to reduce power consumption and cost per channel.

The key idea is to join the versatility of a digitizer with the high rate capabilities proper of a TDC. This goal is achieved using a series of delay lines that controls a network of capacitors (64 per channel) that continuously samples the input signal with a frequency up to 10 GSa/s. When the input signal goes over a threshold, the sampling is stopped and a voltage ramp is generated while a 11 bit Gray counter is incremented; for every capacitor the logic compares the sampled value with the voltage of the ramp and stores the value of the counter when the values are the same (Wilkinson ADC). A schema of this design is shown in fig. 6.4.

With this system, the sampling time is independent from the conversion time; moreover, the conversion time depends on the duration of the voltage ramp: for the highest precision available (11 bits) the conversion takes $1.6 \mu\text{s}$ while for high rate application it is possible to speed up the ramp and use a counter with only 8 bits to

reduce the conversion time to 200 ns. The RMS noise measured using a 11 bit ADC is of the order of $\sim$ mV and increases of 15% when using only 9 bits for a faster conversion. Every SAMPIC chip can be used to acquire up to 16 channels.

Figure 6.4: The input signal is stored in an analog buffer, than it is digitized using a Wilkinson ADC.

The chip was used on the acquisition unit developed at LAL (fig. 6.5); it is composed by a motherboard hosting an FPGA that manages digital I/O as well as an USB 2.0, Gigabit Ethernet and optical fibre for control and data acquisition. One or two mezzanine boards with the SAMPIC chip can be plugged on the motherboard according to the number of channels needed.

Figure 6.5: Picture of the SAMPIC and its acquisition board, the SAMPIC chip is visible on the right of the board.

The unit is controlled using a software developed on Windows that can also perform some basic analysis on the acquired data, i.e. noise statistics and measure of the time difference between two channels, as shown in fig. 6.6.

Figure 6.6: Screenshot of the software to control and acquire data from the SAMPIC acquisition board. It is also possible to compute the time difference between two selected channels on the fly.

Due to the high precision needed for the delay lines and for the analog part of the chip, i.e. the switches of the capacitors, some calibrations are needed to profit of the full capabilities of the chip. In particular, the linearity of the Wilkinson ADC can be calibrated, cell by cell, sending a known signal, while the time delay between cells can be calibrated using an externally generated sine wave. As an example, a time resolution of ~ 13 ps was measured without any time correction [83], while, after applying the calibrations it is possible to improve the resolution to a value below ~ 3 ps; the result obtained in the laboratory is shown in fig. 6.7. For this work, all the calibration corrections are applied by the acquisition software, even if the 8 kB per channel needed for the calibration can be easily stored inside the control board that host also an FPGA with enough resources to apply corrections on the fly: this feature is foreseen for future updates.

Conversion and acquisition can be triggered in different ways, as shown in the scheme in fig. 6.8, that is:

Figure 6.7: Time difference measured in the laboratory using the SAMPIC between two signals generated by a digital function generator. The time resolution of a single channel is $\sim 4/\sqrt{2} \sim 2.8$ ps.

- local trigger: when an input goes above the threshold the acquisition of that channel is started;
- external trigger: when an external signal is provided, all the channels are acquired;
- central trigger: when any of the inputs goes above the threshold all the channels are acquired.

It is possible to choose between rising or falling edge discrimination and, for the local trigger, it is also possible to set a delay of 1 or 2 ns between the trigger and the acquisition. Moreover, the external trigger can be used as veto signal for the local trigger. This is useful in the case when particles are synchronized with an external signal, for example the LHC clock: only channels that have an input that exceed the threshold in sync with the external trigger are acquired. The advantage is an optimization of the read-out bandwidth and of the dead time: the probability that noise is triggering a conversion is reduced.

One limitation of the trigger electronics is that the trigger signal has to arrive to the SAMPIC at the same time of the detector signals: often, the electronics of the trigger, i.e. discriminators and coincidences, delays the signal of several nanoseconds with respect to the detectors that have cables of comparable length but do not have delays due to any additional electronics. The simplest solution of using longer cables

kHz, the trigger time is always recorded.

Data acquired by the SAMPIC can be saved in an ASCII file or in a binary file using the control software: the obvious readability advantage of the ASCII file is overcome by the increased size of the output files, making them impractical for long tests.

More details on the electronics of the SAMPIC are available in [83, 84].

6.2 Data Analysis Framework

Tests were performed using different acquisition devices; moreover, every device can be configured to save data in different modes. Furthermore, the time information can be computed from the acquired data using different algorithms. All combinations should be compatible and the results have to be directly comparable.

A versatile analysis framework has been developed to unify the analysis code. It has been developed using the C++11 programming language and the ROOT libraries [85].

The main schema of the framework is shown in fig. 6.10. During the analysis, data from all the devices under test have to be available on an event by event basis, where an event includes all the data acquired upon a trigger. A common data format is used and a module for every device has been implemented to convert the acquired data into the common format. Moreover, a *Montecarlo* module is available to test the time measurement algorithms [86].

The data analysis part computes the time difference between two selected channels. The exact time is computed using several algorithms implemented independently from the rest of the code and can be easily developed by other users without any knowledge of the rest of the framework.

The chosen tool to store and handle an arbitrarily large set of events is the **TTree** of the ROOT library, one of the most widely used data structure in HEP[87]. It is optimized to store and manage large amount of data using vertical storage techniques: several *branches* can be defined and, for every *entry*, the content of a branch can be accessed randomly or sequentially. Moreover, it is possible to save it

Figure 6.10: Overview of the Data Analysis Framework.

on file and store it on disk while it is being filled, to avoid memory problems with large amount of data. Data stored in the **TTree** are:

- **FileNumber**: it is possible to split the acquisition in several files and then merge the information in the same **TTree**;
- **HitNumber**: the number of the event, it starts from 0 for every file;
- **Channel**: the channel number, according to the acquisition device, i.e. from 1 to 4 for the oscilloscope, from 0 to 15 for the SAMPIC;
- **StartTime**: the time of the first sample with respect to the start of the acquisition when available, 0 otherwise;
- **TimeSamples**: vector of the time of each sample acquired, referred to the start of the sampling: the first point is always 0;
- **DataSamples**: vector of the sampled voltage value: each element in *TimeSamples* has a corresponding element in *DataSamples*.

Data stored in the **TTree** contains also some debug information that are not used for the computation of the precise time information.

The structure of the `TTree` has been defined as simple as possible and only using objects available in the C++ standard library to simplify the development of the modules for the different devices.

The data analysis part of the code consists in a steering class that extracts data from the `TTree` and handles the computing of the required information. In particular, the algorithms used to compute the exact time are implemented as functions with the following prototype:

```
double ExampleOfComputeExactTime (
    std::vector<double>& time,
    std::vector<double>& data,
    AlgorithmParameters& param )
```

Where `time` and `data` are respectively `TimeSamples` and `DataSamples`, while `AlgorithmParameters` is an user defined type with all the parameters needed by the algorithm like thresholds, polarity of the signals, etc. The function returns the computed time referred to the instant of the first sample.

The method `execute` of the steering class has to be called to start the analysis, specifying the root file (`TFile`) with the `TTree`, the function that computes the algorithm and the parameters:

```
template <class T>
double execute (
    TFile * out_f,
    double (*computeExactTime) (
        std::vector<double>&,
        std::vector<double>&,
        T& ),
    T& parameters)
```

This method takes care of preparing the pair of vectors with the sampled data for the user function and it creates all the histograms. In particular, it will create an histogram with the difference between the time computed for a pair of selected channels.

It is worth mentioning that data collected with TRB3 were analysed using the go4 framework [88] with libraries that have been developed for data monitoring and analysis.

6.3 Computation of the arrival time

Once the signal has been acquired, the exact arrival time has to be computed. The first step is to measure the instant when the signal goes above a threshold. The error on the arrival time is due to three contributes: *jitter*, *time walk* and *drift*.

Jitter is due to the electronic noise added to the signal: the higher the noise, the larger is the error done when trying to measure the threshold crossing time. In detail:

$$\sigma_{jitter} \sim \frac{\sigma_V}{dV/dt} \quad (6.1)$$

where, σ_V is the RMS of the electronic noise and dV/dt is the slope of the pulse. In other words, to minimize the error due to the jitter, it is advisable to have a signal with lowest possible electronic noise and the steepest possible rising edge. Moreover, the choice of the threshold has an impact on the maximum achievable time resolution: assuming a noise uncorrelated with the signal, σ_{jitter} is minimum if the threshold is crossed in correspondence of the maximum value of dV/dt .

Finally, the time walk is the error on the arrival time due to the non constant amplitude of the input signals.

As an example, it is possible to consider a Gaussian pulse:

$$V_{out}(t) = V_{max} e^{-\frac{(t-t_0)^2}{2\sigma^2}} \quad (6.2)$$

where,

- V_{out} is the output signal of the amplifier;
- V_{max} is the maximum amplitude of the signal;
- t_0 is the instant when the signal reaches its maximum¹.

¹In this simplified model the pulse has an infinite duration; hence, the only meaningful instant

The instant t_{th} of crossing a fixed threshold V_{th} depends on the amplitude of the signal, as shown in fig. 6.11; in particular it is given by:

$$V_{out}(t_{th}) = V_{th} \Rightarrow t_{th} = t_0 - 2\sigma \sqrt{\ln\left(\frac{V_{th}}{V_{max}}\right)} \quad (6.3)$$

Figure 6.11: t_{th} dependence on V_{max} .

It is clear that the instant t_{th} is a function of the amplitude of the signal, as shown in fig. 6.12.

Two of the most common approaches that may be used to reduce the time walk, for signals of variable amplitude, are a *constant fraction discriminator* and *time over threshold* corrections; both methods will be described in the following sections.

Drift is a long-term contribution due to temperature variations or ageing of the components; however, in the particular case of our application, this effect can be considered negligible.

In the end, the time resolution is given by the convolution of all the discussed contribution:

$$\sigma_t^2 = \sigma_{jitter}^2 + \sigma_{walk}^2 + \sigma_{drift}^2 \quad (6.4)$$

In particular, if the σ_{drift} can be considered negligible, the σ_{walk} can be corrected is t_0 .

Figure 6.12: t_{th} dependence on V_{max} .

and the main contribution to the uncertainty is due to jitter. For a quick estimate of the time resolution of a detector, if the rising edge may be assumed linear [89]:

$$\sigma_t \sim \sigma_{jitter} \sim \frac{\sigma_V}{dV/dt} \sim 1.25 \frac{\Delta t_{0.1-0.9}}{SNR} \quad (6.5)$$

where the Signal to Noise Ratio (SNR) is defined as:

$$SNR := \frac{V_{max}}{\sigma_V} \quad (6.6)$$

and the rise time $\Delta t_{0.1-0.9}$ is the time needed by the signal to rise² from $0.1V_{max}$ to $0.9V_{max}$.

The contribution of the acquisition device, i.e. the intrinsic jitter of the oscilloscope or of the discriminator, if present, can be considered negligible with respect to the discussed contributions introduced by the detector.

²The *rise time* here is intended for a positive pulse; however the same rule is true for negative pulse, using the *fall time*.

6.3.1 Constant Fraction Discriminator

As mentioned before, the instant of crossing the threshold depends on the amplitude of the signal (eq. 6.3). However, using a threshold that is proportional to the amplitude of the input signal $V_{th} = k_{cfd}V_{max}$ the crossing instant t_{cfd} is given by:

$$t_{cfd} = t_0 - 2\sigma \sqrt{\ln\left(\frac{V_{th}}{V_{max}}\right)} = t_0 - 2\sigma \sqrt{\ln(k_{cfd})} = t_0 + \text{const} \quad (6.7)$$

Whereas this method can be easily implemented in an off-line analysis where the signal has been sampled, like when using the oscilloscope or the SAMPIC, an on-line implementation is not trivial, requiring the measurement of the amplitude before the threshold is crossed.

Commonly, in the on-line implementation the signal is split: one line is delayed, attenuated and inverted and eventually summed to the other line:

$$V_{cfd} = V_{max} e^{-\frac{(t-t_0)^2}{2\sigma^2}} - k_{cfd} V_{max} e^{-\frac{(t+\Delta-t_0)^2}{2\sigma^2}} \quad (6.8)$$

The zero crossing instant of the produced signal is independent on the amplitude:

$$\begin{aligned} V_{cfd}(t_{cfd}) &= 0 \Rightarrow \\ \Rightarrow V_{max} (e^{-\frac{(t-t_0)^2}{2\sigma^2}} - k_{cfd} e^{-\frac{(t+\Delta-t_0)^2}{2\sigma^2}}) &= 0 \Rightarrow \\ \Rightarrow e^{-\frac{(t-t_0)^2}{2\sigma^2}} - k_{cfd} e^{-\frac{(t+\Delta-t_0)^2}{2\sigma^2}} &= 0 \end{aligned} \quad (6.9)$$

From the last row of eq. 6.9, it can be noticed that the dependence from V_{max} has been removed. A graphical representation of the on-line constant fraction discriminator is showed in fig. 6.13.

Using a noiseless Gaussian pulse, the constant fraction discriminator gives a result independent on the input amplitude for every value of $0 < k_{cfd} < 1$; however, for real signals, the value of the fraction affects directly the time resolution. In fact, as discussed before, to reduce the jitter, it is advisable to maximize the slope of the signal when crossing the threshold or, in the same way, to optimize the delay and

Figure 6.13: The method to implement an on-line constant fraction discriminator consists in subtract from the original signal (blue solid line) a delayed and attenuated signal (black dotted line); the zero crossing instant of the so generated signal (red dashed line) does not depend on the amplitude of the input signal.

the attenuation for the on-line implementation to maximize the slope of the zero crossing.

For a Gaussian pulse the slope is maximum for $t = \sigma$; hence, the best threshold V_{best} is:

$$V_{best} = \frac{V_{out}}{\sqrt{e}} \Rightarrow k_{cfd} \sim 60\% \quad (6.10)$$

In presence of noise, the value of the optimal k_{cfd} is not well defined: often best results are given by an average of the time computed using different k_{cfd} .

6.3.2 Time Over Threshold

An other way to reduce the time walk is to measure the width, instead of the amplitude, of the pulse and to use it to correct the measurement. The width of the signal depends on the amplitude and can be measured as the time between the two threshold crossing, as shown in fig. 6.14.

In general, it is possible to find a function f of the time over threshold t_{tot} in a way that $t_{corr} = t_{th} + f(t_{tot})$ does not depend on the amplitude of the signal. In the

Figure 6.14: The Time Over Threshold is defined as the time between the first and second crossing of a threshold.

case of a noiseless Gaussian pulse:

$$t_{tot} = t_{th2} - t_{th1} = t_0 + 2\sigma \sqrt{\ln\left(\frac{V_{th}}{V_{max}}\right)} - \left(t_0 - 2\sigma \sqrt{\ln\left(\frac{V_{th}}{V_{max}}\right)}\right) = 4\sigma \sqrt{\ln\left(\frac{V_{th}}{V_{max}}\right)} \quad (6.11)$$

Thus, $f(t_{tot}) = \frac{T_{tot}}{2}$:

$$t_{corr} = t_{th} + f(t_{tot}) = t_0 - 2\sigma \sqrt{\ln\left(\frac{V_{th}}{V_{max}}\right)} + \frac{4\sigma \sqrt{\ln\left(\frac{V_{th}}{V_{max}}\right)}}{2} = t_0 \quad (6.12)$$

For more complicated signal $f(t_{tot})$ may not be obtained analytically; however, it is always possible to find a function that minimize the time walk, thanks to the fact that the two time over threshold measurements t_{tot1} and t_{tot2} are uncorrelated as they depend on the charge released in two completely independent detectors. In fact:

$$\Delta t = t_{corr2} - t_{corr1} = t_{th2} + f_2(t_{tot2}) - (t_{th1} + f_1(t_{tot1})) \quad (6.13)$$

$$f_1(t_{tot1}) = t_{th1} - t_{th2} - f_2(t_{tot2}) \quad (6.14)$$

Averaging with respect to the time over threshold of the second detector $tot2$, the

only term that depends on $tot2$, $f_2(t_{tot2})$, is constant:

$$\langle f_1(t_{tot1}) \rangle_{tot2} = f_1(t_{tot1}) = t_{th1} - t_{th2} - \langle f_2(t_{tot2}) \rangle_{tot2} = -(t_{th2} - t_{th1}) + const \quad (6.15)$$

In the same way, the function $f_1(t_{tot1})$ that best fits the time difference $t_{th2} - t_{th1}$ versus t_{tot1} can be used to correct arrival time measurement. Two examples of $f(t_{tot})$ that can be used to correct the arrival time measurement are shown in fig. 6.15.

Figure 6.15: Two examples of $f(t_{tot})$ to correct the time walk using the time over threshold.

This algorithm is of particular interest because the information needed are only the two instants of the threshold crossing. These instants can be measured using an oscilloscope, a sampler, or even a TDC. However, using a sampled signal it is possible to interpolate the available data, as shown in fig. 6.16, to reduce the error on the crossing time.

A TDC will only be able to measure the threshold crossing with a precision depending on its bin width:

$$\sigma_{TDC} \sim \frac{\text{bin width}}{\sqrt{12}} \quad (6.16)$$

Finally, it should be noted that, using this method, it is not possible to select the threshold such as it is crossed always with the maximum slope, as it was the

Figure 6.16: Interpolating the sampled signal it is possible to compute the threshold crossing time even when the threshold is crossed between two samples. The figure shows the simple case of a linear interpolation.

case for the constant fraction discriminator.

6.3.3 Data pre-processing

The signal produced by the detector is always affected by noise; moreover, also the sampling device will introduce additional noise. It is useful to pre-process the sampled data to reduce the impact of the noise on the arrival time computation.

The first step is to compute the *baseline* for each event: if there is a low frequency component of the noise, the baseline of the signal may be shifted from the zero. The usual approach is to average the sampled points before the start of the signal, for example 1 ns before the threshold crossing.

Then, it is possible to reduce the noise that has higher bandwidth than the signal. A simple moving average is already effective in this case; however, the best approach is to use a low pass filter. In particular, the adopted algorithm makes the convolution of the signal for a *sinc* function:

$$\text{sinc}(t) = k \frac{\sin(2\pi ft)}{2\pi ft} \quad (6.17)$$

where k is a normalization factor and f is the cut-off frequency: the Fourier transform of this function is null for all frequencies above f . The frequency f has to be tuned to obtain the best performance depending on the characteristics of the signal. Usually it is important to remove all components above 900 MHz (mobile phones, WiFi, etc.); the effect of this filter is shown in fig. 6.17.

Figure 6.17: Example of signal smoothed using a sinc function that removes all the frequencies above 900 MHz.

It should be noted that the *sinc* is an even function that goes from $-\infty$ to ∞ ; hence, this filter can be only used when the full signal is available. Real filters (analog or digital) work on the signal in real time and they can only use information of the leading part of the signal, the trailing not being yet available. It is always possible to implement these filters off-line, designing, for instance, an analog filter to be added to the detector electronics.

To reduce the computing time it is possible to optimize the smoothing: for instance, it is possible to do a linear fit for the region close to the threshold and a parabolic fit in the region of the maximum.

6.3.4 Other algorithms

Thanks to the sampling of the signal, the possibilities of the off-line analysis are enormous. The algorithms presented here are only a selection of the most common ones, simple and nevertheless effective solutions.

To improve the time resolution, the general idea is to increase the amount of information used to compute the arrival time. For example, in the simplest implementation of a constant fraction discriminator, the algorithm actually needs only 3 sampled points: the maximum of the signal and the two samples trailing and following the threshold crossing. The uncertainty on these 3 points will directly affect the time measurement.

The pre-processing helps in reducing this uncertainty, but some algorithm may include all the sampled points in the computation: for instance it is possible to generate a template and to compare it to the signal. It is possible to define a function that is maximum (or minimum) when the superposition between the signal $s(t)$ and the template $g(t)$ is best. An example of a function with this behaviour is the cross correlation:

$$c(k) = \int s(t) g(t+k) dt \quad (6.18)$$

For a discrete signal the integral is substituted by a sum:

$$c[j] = \sum s[t_i] g[t_{i+j}] \quad (6.19)$$

The cross correlation is maximum for the time shift that best matches the signal and the template.

This method is extremely robust with respect to baseline shift and amplitude variations; however, it is much more complicated to implement and it requires to build a template for every different scenario. This algorithm has been implemented and its performance are discussed here [\[90\]](#).

Chapter 7

Measurement of performance

In the previous chapters, different approaches were discussed to develop a diamond detector with a time resolution on the order of 100 ps. In particular, first the test campaign were focused on commercially available devices; then, the diamond detector developed by the HADES collaboration has been proved to have excellent timing performance and the TOTEM collaboration started the development of a customized detector that has been tested and characterized. Beside these, other solutions were investigated too: the non linear amplifier discussed in 4.7 and a 3D diamond detector.

This chapter will describe the timing performance of the different solutions measured during an extensive campaign of tests with high energy beams.

7.1 Tests performed using a particle beam

Tests were done in several experimental areas and with different beam configurations, in particular:

- June 2014 at PSI: secondary beam of $130 \div 250 \text{ MeV}/c$ π^+ with a contamination of e^+ and μ^+ ;
- July and August 2014 at CERN (PS) (fig. 7.1): secondary beam of $10 \text{ GeV}/c$ π^+ with a small ($< 0.1\%$) contamination of e^- μ^- and K^- ;

- October 2014 at CERN (SPS): secondary beam of 180 GeV/c π^+ with a small contamination of μ^+ ;
- December 2014 at CERN (PS): secondary beam of 10 GeV/c π^+ with a small ($< 0.1\%$) contamination of e^- μ^- and K^- ;
- February and March 2015 at DESY: secondary beam of $4 \div 5$ GeV/c e^- ;
- several periods from June to November 2015 at CERN (SPS): secondary beam of 180 GeV/c π^+ with a small contamination of μ^+ .

The last period of test at CERN (SPS) can be considered as continuous: for more than 30 days the TOTEM team was in control of the whole beam line (*main user*) while during other periods it was still possible to make tests but the beam was controlled by other teams (*parasitic user*).

Figure 7.1: The setup at CERN PS tests (July 2014).

The first tests during 2014 were focused on the time resolution of the detectors, while during 2015 most of the data were acquired using a tracker for efficiency studies. In particular, in DESY and for one week at CERN SPS a silicon tracker, the MIMOSA pixel telescope [91], was used both upstream and downstream the

detector, as shown in fig. 7.2. For the following tests a GEM tracker has been installed on the CERN SPS beamline a few meters upstream the position of the detectors. Moreover, during the last tests of 2015 a RP station prototype was available to test the integration of the full system before the installation in the LHC.

Figure 7.2: *The test setup at DESY (January 2015) with the MIMOSA pixel telescope.*

All tests have been done using $500\text{ }\mu\text{m}$ thick scCVD diamonds.

7.2 Performance of commercial diamond detectors and amplifiers

Cividec Instrumentation is well known for its partnership with several collaborations at CERN and for the quality of its products. Indeed, Cividec catalogue includes both broadband and charge sensitive amplifiers, together with diamond substrates ($500\text{ }\mu\text{m}$ scCVD) already metallized (one single pad of $4 \times 4\text{ mm}^2$) and packed in a shielded aluminium box. This instrumentation was already characterized by other groups [92, 93] but never obtaining a time resolution below $\sim 250\text{ ps}$.

As discussed in section 4.4, when reading the diamond using a broadband am-

Figure 7.3: *The setup at PSI tests (June 2014).*

plifier (BDA) the SNR is not enough to detect all the particles. In fact, this was observed during the first test with a particle beam: depending on the charge released by the passage of the particle, some signals were separated by the noise, but the output signal corresponding to the Most Probable Value of the released charge was not distinguishable from the noise.

However, using a pair of Charge Sensitive Amplifiers (CSA) of the same company, it was possible to improve the results. During the test at PSI (fig. 7.3), the CSAs were tested using the reference oscilloscope or boosting the signals with the BDAs: thanks to the characteristics of the oscilloscope, no significant differences were noted in the performance. In particular, the scheme used for the following discussion is shown in fig. 7.4.

Figure 7.4: *The signal produced by the CSA at the passage of a MIP is on the order of 10 mV and it is possible to further amplify it using a 20dB BDA.*

The chosen polarization voltage for both diamonds was 500 V, as recommended by the producer. A different behaviour between the two CSAs was noted, but, being a commercial product, the reason of this difference can not be easily investigated. In fact, as shown in fig. 7.5 and 7.6, considering the 20 dB added by the BDA, the amplifier with serial number *C6HV0051* has a gain of ~ 3.2 mV/fC, while the other (SN *C6HV0061*) has a gain of ~ 4.3 mV/fC; also the noise is different, causing about the same *SNR* value of ~ 16 for both amplifiers. The rise time was lower for one of the devices too, as shown in fig. 7.6. These differences are due to the CSAs: exchanging the diamonds (or the BDAs) the performance did not changed.

Figure 7.5: The noise in absence of the signal (pedestal) and amplitude of the output signals for two Cividec C6 amplifiers, measured at PSI using a 250 MeV/c pion beam.

Figure 7.6: The rise time (from 10% to 90%) of the two CSAs measured using a 250 MeV/c pion beam.

Finally, the time resolution measured for this configuration was $\sigma_t \sim \frac{371}{\sqrt{2}}$ ps ~ 262 ps (fig. 7.7), obtained using a software Constant Fraction Discriminator, as discussed in 6.3.1.

Figure 7.7: The time resolution of the single detector, estimated measuring the time difference between the two nominally identical devices, is $\sigma_t \sim \frac{371}{\sqrt{2}} \text{ ps} \sim 262 \text{ ps}$.

These results were obtained using a 250 MeV/c pion beam, the maximum energy available, to have a good approximation of MIPs. At this energy the beam was mainly constituted by pions; however, for lower energy, the contamination of muons and electrons was more important: fig. 7.8 shows the difference between the arrival time (time of flight) and the RF of the accelerator for a selected momentum of 130 MeV/c. Due to the periodicity of the RF (50 MHz), the pattern is also periodic. Using the difference between the arrival time of pions, electron and muons, it was also possible to compute the distance of the detector from the target, where the secondary particles are produced.

Figure 7.8: Using the time difference between the RF of the accelerator and the arrival time it was possible to discriminate the different secondary particles populating the beam. It is also possible to compute the length of the path from the target to the detector.

It is also worth mentioning that some tests were done selecting pions of 130 MeV/ c , obtaining a time resolution of ~ 180 ps, because of the larger release of charge.

As discussed in 4.5, the behaviour of a CSA is directly dependent on the input capacitance. In our case, only a small fraction of the input capacitance is intrinsically due to the diamond; in fact, the diamond is mounted on a PCB that has a long path between the diamond and the connector. Moreover, a “I” joint was used to connect the modules and every connector increases the capacitance of ~ 0.5 pF. To reduce the overall capacitance, it was requested to Cividec, to modify the sensors PCB for us, as shown in fig. 7.9. The smaller dimension, along with the usage of a male SMA connector, led to a substantial reduction of the capacitance (from ~ 15 pF to ~ 5 pF). These detector were tested on a pion beam in the T9 area at CERN; a picture of the setup is shown in fig. 7.11.

Figure 7.9: To reduce the capacitance of the detector, Cividec has produced a custom PCB (b) with a shorter distance between the diamond and the SMA connector with respect to the standard one (a). The capacitance has been reduced from ~ 15 pF to ~ 5 pF.

The effect on the signal due to this reduction is clearly noticeable with a $\sim 15\%$ improvement in both SNR and rise time, as shown in fig. 7.10; in particular, the gain of the C6HV0051 is ~ 5.3 mV/fC. Unfortunately, one of the amplifiers (C6HV0061) had to be replaced with a similar one (C6HV0060) but with slightly different characteristics.

To study the improvement due to the reduced capacitance of the detector, the

Figure 7.10: Using the modified PCB for the diamond the rise time is reduced by $\sim 15\%$.

Figure 7.11: Setup of the test in the CERN T9 area. The PCB modified to reduce its capacitance is clearly visible.

Figure 7.12: The noise in absence of the signal (pedestal) and amplitude of the output signals for two Cividex C6 amplifiers using the modified version of the PCB used to connect the diamond. The measurement was done using a 10 GeV/c pion beam.

Figure 7.13: The rise time (from 10% to 90%) of the two CSAs measured using a 10 GeV/c pion beam.

Figure 7.14: The time resolution of the single detector, estimated measuring the time difference between the two nominally identical devices, is $\sigma_t \sim \frac{295}{\sqrt{2}} \text{ ps} \sim 208 \text{ ps}$.

same algorithm (CFD) was used to measure the time resolution with the modified PCB, obtaining $\sigma_t \sim \frac{295}{\sqrt{2}} \text{ ps} \sim 208 \text{ ps}$, that corresponds to a $\sim 20 \%$ improvement. In particular, the amplitude of the detected signals is shown in fig. 7.12, the measured rise time is shown in fig. 7.13 and the time difference between the two detectors is shown in fig. 7.14. Other results from these tests are reported in [94].

Even if these results are compatible with other commercially available solutions, for $500 \mu\text{m}$ thick scCVD diamonds, the time resolution achieved is still a factor 2 worse than what requested for the TOTEM timing detector.

7.3 Performance of the HADES start detector

A further improvement of the performance was obtained with a detector designed specifically for fast timing measurements. To our knowledge, the best diamond detector for MIP detection at the time, was designed by the HADES collaboration

for their time-of-flight system. The detector has been described in 4.6.1 and has been tested during our test beam campaign; a picture of the setup with two aligned detectors and the scintillators for the trigger, is shown in fig. 7.15.

Figure 7.15: Two planes produced by the HADES collaboration and tested in the North Area at CERN.

A detector prototype, kindly lent by the HADES collaborators, was tested to prove that this technology is suitable to obtain a time resolution below 100 ps. In fact, biasing the diamond at 800 V, a measured SNR around 25 (fig. 7.16) and a rise time of ~ 1.6 ns (fig. 7.17) were obtained, with a measured time resolution of $\sigma_t \sim \frac{117}{\sqrt{2}}$ ps ~ 83 ps (fig. 7.18).

Figure 7.16: The noise in absence of the signal (pedestal) and amplitude of the output signals for one channel of the HADES start detector. The measurement was done using a 180 GeV/c pion beam.

Figure 7.17: The rise time (from 10% to 90%) for the HADES start detector, measured using a 180 GeV/c pion beam.

Figure 7.18: The time resolution obtained with the HADES detector prototype, using a 180 GeV/c pion beam, is $\sigma_t \sim \frac{117}{\sqrt{2}} \text{ ps} \sim 83 \text{ ps}$.

In the first test, we reproduced the results published in [73]. It should be noted that these results were also foreseen using the simulations done in 4.6; in particular (fig. 4.17) the fact that, with a capacitance of 0.1 pF, it should have been possible to obtain a time resolution below 100 ps.

7.4 Performance of the TOTEM timing detector

Thanks to the experience acquired during the previous tests and characterizations, we started the design of a detector customized to the requirements of the TOTEM timing detector that was thoughtfully tested using a particle beam. A picture of the RP infrastructure installed in a test area at CERN is shown in fig. 7.19. The electronics was described in section 4.6.2; in this section the main results of the beam tests are discussed. In particular, the results that will be discussed were obtained using the pad number 3 in the schema of fig. 7.20 because of its

intermediate dimension of $4.20 \times 1.02 \text{ mm}^2$, that corresponds to $\sim 0.43 \text{ pF}$.

The SNR measured was ~ 26 (fig. 7.21) and, together with a rise time of $\sim 1.7 \text{ ns}$ (fig. 7.22), led to a time resolution of $\sim 95 \text{ ps}$ (fig. 7.23). This resolution was obtained using the reference oscilloscope; however, the same measurement was done using the TRB3, discussed in 6.1.2, and the Sampic, discussed in 6.1.3. The different measurements were done using the same channels in three consecutive data taking, in such a way the influence of all external factors, like beam condition or temperature and alignment could be minimized. in a way to minimize the influence of all external factors that can influence the measurement, i.e. beam condition, temperature, alignment, etc.

The Time Over Threshold method (see section 6.3.2) was implemented using the Go4 analysis framework developed at GSI [95], to correct the crossing time. Then,

Figure 7.19: The TOTEM timing detector during the test in the North Area at CERN.

Figure 7.20: Geometry of the pads of the TOTEM timing detector. Due to its intermediate dimensions, the pad number 3 was chosen for the following discussion.

Figure 7.21: The noise in absence of the signal (pedestal) and amplitude of the output signals for one of the channels of the TOTEM timing detector. The measurement was done using a 180 GeV/c pion beam.

Figure 7.22: The rise time (from 10% to 90%) of one of the channels of the TOTEM timing detector, measured using a 180 GeV/c pion beam.

Figure 7.23: The time resolution measured for one of the channels of the TOTEM timing detector, using a 180 GeV/c pion beam, is $\sigma_t \sim \frac{135}{\sqrt{2}} \text{ ps} \sim 95 \text{ ps}$.

the time difference between the corrected arrival time, detected by two identical channels, was measured; a screenshot of the result is shown in fig. 7.24. The time resolution of the detector read by the TRB3 is $\sim 126 \text{ ps}$, a $\sim 30 \%$ worse than the one obtained with the reference system. Some deterioration was expected because of the lower amount of information available for the crossing time computation using a TDC rather than a sampler, as discussed in section 6.3.2.

Figure 7.24: Screenshot of the result of the time difference between two channels of the TOTEM timing detector. The measured time resolution is $\sigma_t \sim \frac{178}{\sqrt{2}} \text{ ps} \sim 126 \text{ ps}$. The measurement was done in the same condition and with the same channels as fig. 7.23.

In fact, using the fast sampler (Sampic), the performance was compatible with the reference system. In detail, sampling the signal at 10 GSa/s with 11 bit resolution, the measured resolution was $\sim 95 \text{ ps}$ (fig. 7.25), exactly as with the reference system.

The time resolution was measured for all pairs of aligned channels using 3 identical boards; the results are shown in fig. 7.26. The channel numbers refer to the

Figure 7.25: The time resolution measured for one of the channels of the TOTEM timing detector, using the Sampic configured to acquire a 10 GSa/s with a resolution of 11 bits, is $\sigma_t \sim \frac{135}{\sqrt{2}}$ ps $\sim$ 95 ps. The measurement was done in the same condition and with the same channels as fig. 7.23.

layout shown in fig. 7.20. Due to the tolerances on the components, not all channels have the same performance; it is nevertheless evident that the time resolution improves reducing the size of the pad, hence its capacitance.

Figure 7.26: Black squares: time resolution computed using board 2 and 3; blue circles: time resolution computed using board 1 and 3; red triangles: time resolution computed using board 1 and 2. The channel numbers reference to the layout shown in fig. 7.20. Channel 1 of board 1 was not working properly during the test.

A series of tests were done to measure the efficiency of the developed detector: as described in section 5.1, this measurements can be done only using an external reference detector, in our case a tracker. In particular, it is possible to select a subset of hits where a particle can be tracked into the active area of the detector. The result increasing the selection threshold on the output signal is shown in fig.

7.27.

Figure 7.27: Efficiency of the diamond detector (channel number 7) varying the selection threshold on the output signal.

Moreover, using the tracker, it was possible to investigate the behaviour of particles that cross the detector in the peripheral region of the crystal, not completely covered by the metal electrodes, where the electrical field is lower. A lower electrical field means a longer collection time, hence a lower current signal induced on the electrodes. In fact, the amplitude of the signals produced in these cases are lower than what expected for a MIP, as shown in fig. 7.28. A similar behaviour of the measured amplitude is also visible in figs. 7.5, 7.12, 7.16 and 7.21.

Figure 7.28: Particles that are crossing the diamond outside the metallization, where the electrical field is lower, produce a signal lower than the one expected by a MIP.

Finally, a prototype of the time detector was installed in one of the TOTEM vertical RPs in the LHC; a picture of the installation is shown in fig. 7.29. Whereas the detector was not acquired in sync with the rest of the experimental apparatus, the installation is a good test bench for all the infrastructure shared with the other

TOTEM detectors, i.e. cooling and vacuum systems, remote control system, etc. Moreover, it is also useful to understand the behaviour of the electronics in the high radiation environment of the LHC.

Figure 7.29: The TOTEM timing detector developed during the last years during the installation in a Roman Pot.

The time resolution, measured as in the previous tests, is compatible with the results expected, as shown in fig. 7.30.

Figure 7.30: The time difference between two aligned channels of the TOTEM timing detector installed in one of the TOTEM Roman Pots in the LHC. The measured time resolution of $\sigma_t \sim \frac{129}{\sqrt{2}} \text{ ps} \sim 91 \text{ ps}$ is compatible with the resolution measured during the preliminary tests.

Similar results were presented at the LHC Committee by the TOTEM Collaboration [96].

7.5 Performance of the amplitude dependent amplifier

The same characterization procedure was used to study and optimize the behaviour of the Amplitude Dependent Amplifier (ADA) discussed in section 4.7. In particular, a $500\text{ }\mu\text{m}$ diamond, with only one pad of $4.20 \times 4.20\text{ mm}^2$ (1.76 pF), polarized with 800 V, was used.

However, due to the non linear behaviour of the amplifier, a different approach was developed for the measurement of the crossing time. In fact, the oscilloscope is able to acquire samples with a resolution up to 8 bits, limiting the maximum appreciable SNR to:

$$SNR_{max} \sim 2^8 = 256 \quad (7.1)$$

As shown in fig. 7.31, the SNR of this amplifier is ~ 100 for the MPV; however, it is very likely to have a bigger ionization, hence bigger SNR .

Figure 7.31: The noise in absence of the signal (pedestal) and amplitude of the output signals for a diamond read using the ADA. The measurement was done using a 180 GeV/c pion beam.

Thus, it is possible to:

- configure the oscilloscope with an acquisition window wide enough to appreciate the maximum possible amplitude (saturation of the amplifier); however, the acquired noise in absence of signal will be too small to be measurable;
- increase the sensitivity of the oscilloscope to appreciate the noise of the amplifier, clipping the part of the signal above a certain value.

In the first case the time resolution will be affected by the oscilloscope; while in the second it will be impossible to use a constant fraction discriminator during the analysis, due to the lack of information on the amplitude of the signal. However, it is still possible to use the time over threshold to correct the time measurement, even when no information on the amplitude is present. Experimental results have proven this second method to be the best.

It should be noticed that, even if the amplifier is not linear, it is tuned to have a linear gain in the expected range of signals (fig. 4.29); fig. 7.31 shows that the behaviour of the amplitude is still in good agreement with the expected Landau distribution.

The rise time of the output of the non linear amplifier is shown in fig. 7.32.

Figure 7.32: The rise time (from 10% to 90%) of a diamond read using the ADA, measured using a 180 GeV/c pion beam.

The time resolution was measured using a Microchannel Plate (MCP) as reference. In detail, the actual MCP is the PLANACON XP85012 [97], usually used for photon detection, for example in [98, 99]. The time resolution expected from the MPC is of the order of 20 ps. For the MCP the arrival time was computed averaging the result of a CFD with a threshold at 30% and 40% of the signal amplitude; while, for the ABA, the crossing time was corrected using the time over threshold (see section 6.3.2). In particular, the correction function that gave the best performance is:

$$f(t_{tot}) = \frac{1}{\sqrt{k_0 + k_1 x}} \quad (7.2)$$

The result of this test (using the ToT correction), shown in fig. 7.33, is a time resolution below 85 ps.

Figure 7.33: The time difference between a diamond read with the ADA and a MCP. Supposing a time resolution below 20 ps for the MCP, the resolution of the diamond detector is below 85 ps.

This result should be compared with a channel of the same size of the TOTEM timing detector, like the channel 7 in fig. 7.20. Hence, the same measurement was performed using board 1 and 2 of the TOTEM timing detector and is shown in fig. 7.34. The obtained result of ~ 100 ps has to be compared with the ~ 85 ps obtained for the ADA, proving a better timing performance for the latter.

Figure 7.34: The time difference between channel 7 of two prototypes of the TOTEM timing detector and a MCP. Supposing a time resolution below 20 ps for the MCP, the resolution of the diamond detector is around 100 ps.

7.6 Performance of 3D diamonds

The main obstacle in designing the front-end electronics for a 3D diamond is that it is not trivial to describe reliably the equivalent circuit of the sensor. Moreover, the not uniform electrical field inside the active volume will inevitably lead to a more complex behaviour of the generated signal. Hence, the 3D diamond prototype was tested using different read-out electronics: the best starting point is to use a linear

amplifier to acquire samples of the signals that have a shape as similar as possible to the signal generated by the diamond. The sample used for this test was 3.07 mm^2 , with a capacitance of $\sim 3.5 \text{ pF}$, measured directly on the electrodes. The column were spaced as discussed in sec. 3.7 and the bias voltage was 40 V; the usage of a higher voltage was not possible due to discharges inside the crystal. The best timing performance was obtained using a high input impedance amplifier.

Like as the 2D diamond case, using a BDA with 50Ω input impedance, the SNR is too low; however, using a design with higher input impedance it is possible to have good performance. Some examples of signal are shown in fig. 7.35: it is possible to note the not uniformity of the waveform shapes.

Figure 7.35: Example signals produce by a 3D diamond detector at the passage of a MIP.

This irregular behaviour is also noticeable in the distribution of the output amplitudes, shown in fig. 7.36: the charge release is supposed to be distributed following a Landau curve; however, the output signal is dependent on the current induced on the read-out electrode, that depends on the electrical field inside the substrate (Shockley-Ramo theorem, see eq. 4.2). Nevertheless, when a signal is detected, the SNR is good and also the rise time, shown in fig. 7.37, is comparable with what obtained using a similar amplifier with 2D diamonds.

Finally, the time resolution of a 3D diamond was measured using the ADA discussed before as a reference. A time resolution of $\sigma_t \sim 270 \text{ ps}$ was measured, as shown in fig. 7.38, using a CFD. The measured distribution is asymmetrical; in particular, the 3D signal is often delayed, very likely because of the weaker electrical field in some regions of the detector.

Figure 7.36: The noise in absence of the signal (pedestal) and amplitude of the output signals for a 3D diamond read using an amplifier with an high input impedance. The measurement was done using a 180 GeV/c pion beam.

Figure 7.37: The rise time (from 10% to 90%) for one of the 3D diamond detector, measured using a 180 GeV/c pion beam.

Figure 7.38: The time difference between a 3D diamond and a diamond read using the ADA. The measured time resolution of $\sigma_t \sim \sqrt{290^2 - 85^2} \text{ ps} \sim 280 \text{ ps}$; however, the time difference distribution cannot be considered Gaussian.

The measured performance is an indication that, although some improvements are required for both substrate manufacturing and for the read-out electronics, 3D diamonds are a promising technology for timing measurements, especially in high

radiation environments, where their robustness may be essential.

7.7 Summary of Experimental Results

It is useful to summarize the time resolution obtained for the different designs tested using particle beams.

	σ_t (ps)	Comments
Cividec BDA	N.A.	SNR too low
Cividec CSA	~ 262	Good SNR , time resolution not within requirements
Cividec CSA with modified diamond PCB	~ 208	Better SNR and faster signal, time resolution not within requirements
HADES prototype	~ 83	Good performance, but the size of the pad is too small
TOTEM timing detector	$\sim 90 \div 110$	Compliant with requirements, the time resolution depends on the size of the pad
Channel 3 (Oscilloscope)	~ 95	Time resolution with $4.20 \times 1.02 \text{ mm}^2$ pad (0.43 pF)
Channel 3 (SAMPIC)	~ 95	No performance degradation with respect to reference system
Channel 3 (TRB3)	~ 126	The small amount of information acquired using a TDC limits the time resolution
Amplitude Dependent Amplifier	~ 85	Best time resolution obtained with a planar diamond with $4.20 \times 4.20 \text{ mm}^2$ pad (1.76 pF)
3D diamond	~ 280	More optimization is needed

Table 7.1: Main experimental results obtained during the tests.

The best time resolution obtained using *plug-and-play* detector is ~ 208 . Although not compliant with the requirements of the TOTEM timing detector, the Cividec CSA amplifier, together with the Cividec diamond packaging, is a good solution for a fast and reliable timing detector with relatively limited time resolution. The electronics developed within the TOTEM Collaboration has a good timing res-

olution, with a good reproducibility and a reliability sufficient for the integration in the TOTEM Roman Pot. The best time resolution was measured with the HADES start detector; however, a similar result was obtained using the Amplitude Dependent Shaper with a diamond with a capacitance eight times larger.

Conclusions

The TOTEM upgrade program for the second run of the LHC was focused on the optimization of the experimental apparatus to exploit the physics possibilities offered by the increased luminosity of the LHC.

During this thesis, the Roman Pot (RP) system was optimized to cope with the increased intensity of the beams. In fact, the RPs installed during the first run of the LHC could be inserted only during dedicated low luminosity runs. Even with the RPs retracted, the temperature increase due to the RF interaction with the beam became critical during high luminosity operations. A new Cylindrical RP was designed, together with a shield that can be installed on the existing RPs. The new designs were realized, tested and installed in the accelerator. The test insertions at the highest luminosities delivered by the LHC confirmed the expected improvement over the first design.

Although these optimized RPs can be safely inserted during the high luminosity runs of the LHC, the detector system was incapable of working with the expected pile-up. Therefore, one of the cornerstones of the TOTEM upgrade program was the development of a timing detector with a geometrical acceptance similar to the already present silicon strip detectors and with a time resolution of ~ 50 ps. A detector based on a diamond substrate was chosen, but the first tests, in the summer of 2014, demonstrated that none of the commercially available solutions was compliant with the requirements on the time resolution and with the space limitations inside a RP. At the moment of writing, less than 18 months later, a diamond detector with custom read-out electronics has been designed, manufactured, optimized, characterized and installed in one of the TOTEM vertical RPs.

To guarantee a uniform occupancy of the detector, a geometry with segments of

different size was chosen; the time resolution, affected by the size (the capacitance) of the detector, is $\lesssim 110$ ps for the channel with the highest surface and goes down to ~ 90 ps for the smallest pad. Installing four aligned detectors in one RP is possible to achieve a time resolution of $\sim 100/\sqrt{4}$ ps ~ 50 ps. Nevertheless, the timing detector is still not integrated in the TOTEM DAQ and trigger systems, hence it is still not possible to use the detector during official data taking. The complete installation is foreseen for the first months of 2016.

Moreover, thanks to the experience gained on the design of front-end electronics for diamond detectors, an alternative design has been proposed and built, capable of a time resolution below ~ 85 ps: $\sim 20\%$ improvement over the resolution obtained with a diamond of equivalent capacitance but read using the amplification chain chosen for the installation. Due to time constraints, this design may only be considered for future upgrades of the timing detector.

Finally, some studies were performed on 3D diamonds: their radiation hardness and the relatively simple manufacturing procedure make them attractive for particle detection. However, because of the non uniform electrical field inside the active volume, their time resolution, at present time, is worse than an equivalent planar detector. More effort are required to optimize the substrate and to design a better performing front-end electronics.

Abbreviations

ADA	Amplitude Dependent Amplifier
ALICE	A Large Ion Collider Experiment
AD	Anti-proton Decelerator
ATLAS	A Toroidal LHC ApparatuS
BDA	Broadband Amplifier
CD	Central Diffractive (process)
CFD	Constant Fraction Discriminator
CSA	Charge Sensitive Amplifier
CERN	European Organization for Nuclear Research
CMS	Compact Muon Solenoid
DESY	German Electron Synchrotron
DPE	Double Pomeron Exchange
DUT	Device Under Test
GSI	Helmholtz Centre for Heavy Ion Research
HADES	High Acceptance Di-Electron Spectrometer
HEP	High Energy Physics
IP n	Interaction Point n , with $n = 1 \dots 8$ for the LHC
ISOLDE	Isotope Separator On Line DEtector
LHC	Large Hadron Collider
LHCb	Large Hadron Collider beauty
LS1	Long Shutdown 1, from February 2013 to May 2015
MCP	MicroChannel Plate
MIP	Minimum Ionizing Particle
PS	Proton Synchrotron

PSI	Paul Scherrer Institute
RMS	Root Mean Square
RP	Roman Pot
SiPM	Silicon Photo Multiplier
SNR	Signal to Noise Ratio
SPS	Super Proton Synchrotron
TCL n	Target Collimator Long n , on both sides of IP5, TCL5 is upstream the RPs while TCL6 is downstream
ToT	Time over Threshold
TOTEM	TOTAL cross section, Elastic scattering and diffraction dissociation Measurement the LHC
UFO	Unidentified Falling Object

Bibliography

- [1] V. Berardi, M. G. Catanesi *et al.*, *Total cross-section, elastic scattering and diffraction dissociation at the Large Hadron Collider at CERN: TOTEM Technical Design Report*, ser. Technical Design Report TOTEM. Geneva: CERN, 2004. <http://cds.cern.ch/record/704349>
- [2] J.-R. Cudell, V. V. Ezhela *et al.*, “Benchmarks for the forward observables at rhic, the tevatron-run ii, and the lhcb,” *Physical review letters*, vol. 89, no. 20, p. 201801, 2002.
- [3] G. Anelli, G. Antchev *et al.*, “The TOTEM Experiment at the CERN Large Hadron Collider,” *J. Instrum.*, vol. 3, p. S08007, 2008. <http://cds.cern.ch/record/1129807>
- [4] Jones, “Recent U.S. Work on Colliding Beams,” in *Proceedings, 4th International Conference on High-Energy Accelerators, HEACC 1963, v.1-3*. U.S. Atomic Energy Commission, 1963, p. 379.
- [5] U. Amaldi, R. Biancastelli *et al.*, “Measurements of small angle proton-proton elastic scattering at the cern intersecting storage rings,” *Physics Letters B*, vol. 36, no. 5, pp. 504–508, 1971.
- [6] G. Ruggiero, E. Alagoz *et al.*, “Planar edgeless silicon detectors for the totem experiment,” *Nuclear Science, IEEE Transactions on*, vol. 52, no. 5, pp. 1899–1902, 2005.
- [7] G. Antchev, P. Aspell *et al.*, “Performance of the Totem Detectors at the LHC,” *Int. J. Mod. Phys. A*, vol. 28, no. arXiv:1310.2908.

CERN-PH-EP-2013-173. TOTEM-2013-02, p. 1330046. 34 p, Sep 2013.
<http://cds.cern.ch/record/1598868>

- [8] G. Antchev, P. Aspell *et al.*, “Luminosity-Independent Measurement of the Proton-Proton Total Cross Section at $\sqrt{s} = 8$ TeV,” *Phys. Rev. Lett.*, vol. 111, no. TOTEM-2012-005. CERN-PH-EP-2012-354, p. 012001. 8 p, Nov 2012.
<http://cds.cern.ch/record/1495764>
- [9] G. Antchev, P. Aspell *et al.*, “Measurement of proton-proton elastic scattering and total cross-section at $\sqrt{s} = 7$ TeV,” *EPL*, vol. 101, no. TOTEM-2012-002. CERN-PH-EP-2012-239, p. 21002. 12 p, Aug 2012.
<http://cds.cern.ch/record/1472948>
- [10] G. Antchev, P. Aspell *et al.*, “Measurement of proton-proton inelastic scattering cross-section at $\sqrt{s} = 7$ TeV,” CERN, Geneva, Tech. Rep. TOTEM-2012-003. CERN-PH-EP-2012-352, Nov 2012. <http://cds.cern.ch/record/1495752>
- [11] G. Antchev, P. Aspell *et al.*, “Luminosity-independent measurements of total, elastic and inelastic cross-sections at $\sqrt{s} = 7$ TeV,” CERN, Geneva, Tech. Rep. TOTEM-2012-004. CERN-PH-EP-2012-353, Nov 2012.
<http://cds.cern.ch/record/1495761>
- [12] G. Antchev, P. Aspell *et al.*, “Evidence for Non-Exponential Elastic Proton-Proton Differential Cross-Section at Low $|t|$ and $\sqrt{s} = 8$ TeV by TOTEM,” CERN, Geneva, Tech. Rep. arXiv:1503.08111. CERN-PH-EP-2015-083, Mar 2015. <http://cds.cern.ch/record/2002559>
- [13] G. Antchev, P. Aspell *et al.*, “Measurement of the forward charged particle pseudorapidity density in pp collisions at $\sqrt{s} = 7$ TeV with the TOTEM experiment,” *EPL*, vol. 98, no. arXiv:1205.4105. CERN-PH-EP-2012-106. TOTEM-2012-001, p. 31002. 7 p, Apr 2012, comments: 7 pages, 3 figures.
<http://cds.cern.ch/record/1437021>
- [14] G. Antchev, P. Aspell *et al.*, “Measurement of the forward charged particle pseudorapidity density in pp collisions at $\sqrt{s} = 8$ TeV using a

- displaced interaction point,” CERN, Geneva, Tech. Rep. arXiv:1411.4963. CERN-PH-EP-2014-260, Nov 2014. <http://cds.cern.ch/record/1954699>
- [15] G. Antchev, P. Aspell *et al.*, “Double diffractive cross-section measurement in the forward region at LHC,” *Phys. Rev. Lett.*, vol. 111, no. arXiv:1308.6722. CERN-PH-EP-2013-170, p. 262001. 5 p, Aug 2013. <http://cds.cern.ch/record/1595226>
- [16] S. Chatrchyan, V. Khachatryan *et al.*, “Measurement of pseudorapidity distributions of charged particles in proton-proton collisions at $\sqrt{s} = 8$ TeV by the CMS and TOTEM experiments,” *Eur. Phys. J. C*, vol. 74, no. arXiv:1405.0722. CMS-FSQ-12-026. CERN-PH-EP-TOTEM-2014-002. CERN-PH-EP-2014-063, p. 3053. 36 p, May 2014. <http://cds.cern.ch/record/1699728>
- [17] TOTEM Collaboration, “Timing Measurements in the Vertical Roman Pots of the TOTEM Experiment,” CERN, Geneva, Tech. Rep. CERN-LHCC-2014-020. TOTEM-TDR-002, Sep 2014. <http://cds.cern.ch/record/1753189>
- [18] Y. Chen, A. Alexandru *et al.*, “Glueball spectrum and matrix elements on anisotropic lattices,” *Physical Review D*, vol. 73, no. 1, p. 014516, 2006.
- [19] V. Mathieu, N. Kochelev, and V. Vento, “The physics of glueballs,” *International Journal of Modern Physics E*, vol. 18, no. 01, pp. 1–49, 2009.
- [20] M. Albrow, T. Coughlin, and J. Forshaw, “Central exclusive particle production at high energy hadron colliders,” *Progress in Particle and Nuclear Physics*, vol. 65, no. 2, pp. 149–184, 2010.
- [21] L. Harland-Lang, V. Khoze *et al.*, “Standard candle central exclusive processes at the tevatron and lhc,” *The European Physical Journal C*, vol. 69, no. 1-2, pp. 179–199, 2010.
- [22] C. Royon, “Forward physics with proton tagging at the lhc,” *arXiv preprint arXiv:1305.0652*, 2013.

- [23] M. Albrow, M. Arneodo *et al.*, “CMS-TOTEM Precision Proton Spectrometer,” CERN, Geneva, Tech. Rep. CERN-LHCC-2014-021. TOTEM-TDR-003. CMS-TDR-13, Sep 2014. <https://cds.cern.ch/record/1753795>
- [24] S. Chatrchyan, V. Khachatryan *et al.*, “Study of exclusive two-photon production of W^+W^- in pp collisions at $\sqrt{s}=7$ TeV and constraints on anomalous quartic gauge couplings,” *J. High Energy Phys.*, vol. 07, no. arXiv:1305.5596. CMS-FSQ-12-010. CERN-PH-EP-2013-084, p. 116. 39 p, May 2013, comments: Updated author list. Previous version: replaced with published version; added journal reference and DOI. <https://cds.cern.ch/record/1550912>
- [25] TOTEM Collaboration, “TOTEM Upgrade Proposal,” no. CERN-LHCC-2013-009. LHCC-P-007, Jun 2013.
- [26] TOTEM Collaboration, “Addendum to the TOTEM TDR: Timing Measurements in the Vertical Roman Pots of the TOTEM Experiment LHCC document CERN-LHCC-2014-020 including questions/answers from/to the referees,” CERN, Geneva, Tech. Rep. CERN-LHCC-2014-024. TOTEM-TDR-002-ADD-1, Nov 2014. <http://cds.cern.ch/record/1968585>
- [27] M. Berretti, “Performance studies of the Roman Pot timing detectors in the forward region of the IP5 at LHC,” Aug 2014. <https://cds.cern.ch/record/1747282>
- [28] N. Minafra, “TOTEM Status report,” https://indico.cern.ch/event/389857/session/1/contribution/5/attachments/779712/1069147/TOTEM_STATUS_REPORT_June2015.pdf, 113th LHCC Open Session.
- [29] “Ferroxcube International Holding B.V.” <http://www.ferroxcube.com>.
- [30] “Trans-Tech, Inc. TT2-111,” http://www.trans-techinc.com/products_detail.asp?ID=151&Name=TT2-111.

- [31] G. Cattenoz, “Vacuum degassing test report of tt2-111r ferrite after bake out.” <https://edms.cern.ch/edmsui/#!master/navigator/document?D:1095678745:1095678745:subDocs>
- [32] J. Baechler, “Totem-cms consolidation and upgrade project,” in *LHC Working Group on Forward Physics and Diffraction*, 2014. <https://indico.cern.ch/event/297877/contribution/1/attachments/559372/770675/Baechler.pdf>
- [33] B. Salvant, O. Aberle *et al.*, “Beam induced heating,” 2012. <http://cds.cern.ch/record/1975499>
- [34] N. Minafra, “Rf characterization of the new totem roman pot,” Tech. Rep., 2013, cERN-TOTEM-NOTE-2013-003. <http://cds.cern.ch/record/1557361>.
- [35] M. Furman, H. Lee, and B. Zotter, “Energy loss of bunched beams in rf cavities,” Tech. Rep., 1986.
- [36] N. Minafra, “Beam impedance optimization of the totem roman pots,” in *Proc. 6th International Particle Accelerator Conference*, Richmond, VA, USA, 2015, pp. 452–454, iSBN: 978-3-95450-168-7.
- [37] F. Nemes, “Geant4 simulations for the TOTEM upgrade program,” Jun 2013. <https://cds.cern.ch/record/1555650>
- [38] O. Berrig, N. Biancacci *et al.*, “RF Measurements of the New TOTEM Roman Pot,” Aug 2015. <https://cds.cern.ch/record/2047461>
- [39] M. Deile, “TOTEM Status report,” <https://indico.cern.ch/event/443017/session/1/contribution/5/attachments/1158748/1667292/lhcc2015.pdf>, 123rd LHCC Open Session.
- [40] M. Deile, “Private communication,” unpublished.
- [41] J. Baechler, “TOTEM Status report,” https://indico.cern.ch/event/239117/session/1/contribution/19/attachments/402885/560085/LHCC_March2013_1.pdf, 122nd LHCC Open Session.

- [42] D. Groom and S. Klein, “Passage of particles through matter,” *The European Physical Journal C-Particles and Fields*, vol. 15, no. 1-4, pp. 163–173, 2000.
- [43] E. Fermi, “The ionization loss of energy in gases and in condensed materials,” *Physical Review*, vol. 57, no. 6, p. 485, 1940.
- [44] J. W. Wilson, Y. Xu, and E. Kamaratos, “Mean excitation energies for stopping powers in various materials using local plasma oscillator strengths,” National Aeronautics and Space Administration, Hampton, VA (USA). Langley Research Center, Tech. Rep., 1984.
- [45] Nucleonica GmbH, “Range & Stopping Power++,” <http://www.nucleonica.net/Application/RangePlus.aspx>, version: 2015.08.24.
- [46] L. D. Landau, “On the energy loss of fast particles by ionization,” *J. Phys.*, vol. 8, no. 4, pp. 201–205, 1944. <https://cds.cern.ch/record/216256>
- [47] H. Bichsel and S. Yu, “Straggling of relativistic charged particles: Corrections to the landau-vavilov straggling functions in the hydrogenic wave-function approximations,” *IEEE Transactions on Nuclear Science*, vol. 6, no. 19, pp. 172–174, 1972.
- [48] M. Pomorski, “Electronic properties of single crystal cvd diamond and its suitability for particle detection in hadron physics experiments,” *Wolfgang von Goethe University, Frankfurt am Main, Germany*, 2008.
- [49] E. Holmström, A. Kuronen, and K. Nordlund, “Threshold defect production in silicon determined by density functional theory molecular dynamics simulations,” *Physical Review B*, vol. 78, no. 4, p. 045202, 2008.
- [50] J. Koike, D. Parkin, and T. Mitchell, “Displacement threshold energy for type iia diamond,” *Applied physics letters*, vol. 60, no. 12, pp. 1450–1452, 1992.
- [51] H. Pernegger, “High mobility diamonds and particle detectors,” *physica status solidi (a)*, vol. 203, no. 13, pp. 3299–3314, 2006.

- [52] C. Bauer, I. Baumann *et al.*, “Radiation hardness studies of cvd diamond detectors,” *Nuclear Instruments and Methods in Physics Research Section A: Accelerators, Spectrometers, Detectors and Associated Equipment*, vol. 367, no. 1, pp. 207–211, 1995.
- [53] W. De Boer, J. Bol *et al.*, “Radiation hardness of diamond and silicon sensors compared,” *physica status solidi (a)*, vol. 204, no. 9, pp. 3004–3010, 2007.
- [54] M. Gabrysch, E. Marklund *et al.*, “Formation of secondary electron cascades in single-crystalline plasma-deposited diamond upon exposure to femtosecond x-ray pulses,” *Journal of Applied Physics*, vol. 103, no. 6, p. 064909, 2008.
- [55] J. Isberg, J. Hammersberg *et al.*, “High carrier mobility in single-crystal plasma-deposited diamond,” *Science*, vol. 297, no. 5587, pp. 1670–1672, 2002.
- [56] S. Schuwalow, “Polarization effects in radiation damaged scCVD Diamond detectors,” http://www-norhdi.gsi.de/talks/4th/S_Schuwalov.pdf, 2008, 4th NoRHDia Workshop.
- [57] T. Tachibana, B. Williams, and J. Glass, “Correlation of the electrical properties of metal contacts on diamond films with the chemical nature of the metal-diamond interface. i. gold contacts: A non-carbide-forming metal,” *Physical Review B*, vol. 45, no. 20, p. 11968, 1992.
- [58] E. Berdermann, M. Pomorski *et al.*, “Diamond detectors for hadron physics research,” *Diamond and Related Materials*, vol. 19, no. 5, pp. 358–367, 2010.
- [59] B. Kindler, W. Hartmann *et al.*, “Coating of diamonds for detector application,” *Journal of Radioanalytical and Nuclear Chemistry*, vol. 305, no. 3, pp. 963–969, 2015. <http://dx.doi.org/10.1007/s10967-014-3912-5>
- [60] C. Simons and R. Visinka, “Microstructuring of diamonds with laserlithography,” http://www-adamas.gsi.de/ADAMAS02/talks/simons_ADAMAS02.pdf, 2013, 2nd ADAMAS Workshop, Darmstadt (De).

- [61] G. Parrini, S. Lagomarsino *et al.*, “Laser graphitization for polarization of diamond sensors,” *PoS*, p. 017, 2011.
- [62] J. Lambert, T. Nakano *et al.*, “In vivo dosimeters for hdr brachytherapy: A comparison of a diamond detector, mosfet, tld, and scintillation detector,” *Medical physics*, vol. 34, no. 5, pp. 1759–1765, 2007.
- [63] S. I. Parker, C. J. Kenney, and J. Segal, “3d—a proposed new architecture for solid-state radiation detectors,” *Nuclear Instruments and Methods in Physics Research Section A: Accelerators, Spectrometers, Detectors and Associated Equipment*, vol. 395, no. 3, pp. 328–343, 1997.
- [64] S. Lagomarsino, “3D mono- and poly-crystalline diamond detectors: CCE characterization under beta-irradiation,” http://www-adamas.gsi.de/ADAMAS02/talks/lagomarsino_ADAMAS02.ppt, 2013, 2nd ADAMAS Workshop, Darmstadt (De).
- [65] S. Lagomarsino, M. Bellini *et al.*, “Three-dimensional diamond detectors: Charge collection efficiency of graphitic electrodes,” *Applied Physics Letters*, vol. 103, no. 23, p. 233507, 2013.
- [66] S. Lagomarsino, “Private communication,” unpublished.
- [67] F. Cenna, N. Cartiglia *et al.*, “Weightfield2: A fast simulator for silicon and diamond solid state detector,” *Nuclear Instruments and Methods in Physics Research Section A: Accelerators, Spectrometers, Detectors and Associated Equipment*, 2015.
- [68] P. Horowitz and W. Hill, *The art of electronics, third edition*. Cambridge Univ. Press, 2015.
- [69] “Cividec Instrumentation GmbH, Bäckerstrasse 1, A-1010 Vienna,” <http://www.cividec.at>.

- [70] H. Fraiss-Kölbl, E. Griesmayer *et al.*, “A fast low-noise charged-particle cvd diamond detector,” *Nuclear Science, IEEE Transactions on*, vol. 51, no. 6, pp. 3833–3837, 2004.
- [71] B. Dehning, E. Effinger *et al.*, “Diamond detectors as beam monitors,” Tech. Rep., 2010.
- [72] J. Millman and C. C. Halkias, “Electronic devices and circuits,” 1967.
- [73] J. Pietraszko, L. Fabbietti *et al.*, “Diamonds as timing detectors for minimum-ionizing particles: The hades proton-beam monitor and start signal detectors for time of flight measurements,” *Nuclear Instruments and Methods in Physics Research Section A: Accelerators, Spectrometers, Detectors and Associated Equipment*, vol. 618, no. 1, pp. 121–123, 2010.
- [74] Murata Manufacturing Company, Ltd., “BLM15HB121SH1,” Datasheet: ["http://www.murata.com/en-eu/api/pdfdownloadapi?cate=luNoiseSupprFilteChipFerriBead&partno=BLM15HB121SH1%23"](http://www.murata.com/en-eu/api/pdfdownloadapi?cate=luNoiseSupprFilteChipFerriBead&partno=BLM15HB121SH1%23).
- [75] K. Czuba and D. Sikora, “Temperature stability of coaxial cables,” *Physical Aspects of Microwave and Radar Applications*, vol. 119, no. 4, 2011.
- [76] Nucleonica GmbH, “Decay Engine++,” <http://www.nucleonica.net/Application/Decay.aspx>, version: 2015.08.24.
- [77] H. Hansen, “Measurement of the beta-ray spectra of ^{90}Sr - ^{90}Y ,” *The International Journal of Applied Radiation and Isotopes*, vol. 34, no. 8, pp. 1241–1247, 1983.
- [78] A. Akindinov, A. Alici *et al.*, “Design aspects and prototype test of a very precise tdc system implemented for the multigap rpc of the alice-tof,” *Nuclear Instruments and Methods in Physics Research Section A: Accelerators, Spectrometers, Detectors and Associated Equipment*, vol. 533, no. 1, pp. 178–182, 2004.

- [79] C. F. Bedoya, J. Marín *et al.*, “Electronics for the cms muon drift tube chambers: the read-out minicrate,” *Nuclear Science, IEEE Transactions on*, vol. 52, no. 4, pp. 944–949, 2005.
- [80] M. Traxler, E. Bayer *et al.*, “A compact system for high precision time measurements (< 14 ps rms) and integrated data acquisition for a large number of channels,” *Journal of Instrumentation*, vol. 6, no. 12, p. C12004, 2011.
- [81] “Agilent Infiniium 9000 Series Oscilloscopes,” <http://cp.literature.agilent.com/litweb/pdf/5990-3746EN.pdf>.
- [82] C. Ugur, W. Koenig *et al.*, “Field programmable gate array based data digitisation with commercial elements,” *Journal of Instrumentation*, vol. 8, no. 01, p. C01035, 2013.
- [83] E. Delagnes, D. Breton *et al.*, “The sampic waveform and time to digital converter,” in *2014 IEEE Nuclear Science Symposium and Medical Imaging Conference (2014 NSS/MIC), and 21st Symposium on Room-Temperature Semiconductor X-Ray and Gamma-Ray Detectors*, 2015.
- [84] H. Grabas and C. Royon, “Development of a picosecond time-of-flight system in the ATLAS experiment,” Ph.D. dissertation, U. Paris-Sud 11, Dept. Phys., Orsay, 2013, presented 3 Dec 2013. <http://cds.cern.ch/record/1700497>
- [85] R. Brun and F. Rademakers, “Root—an object oriented data analysis framework,” *Nuclear Instruments and Methods in Physics Research Section A: Accelerators, Spectrometers, Detectors and Associated Equipment*, vol. 389, no. 1, pp. 81–86, 1997.
- [86] V. de Cacqueray, “Master internship report, nuclear engineering,” Ph.D. dissertation, Ecole des Mines ParisTech, 2015.
- [87] I. Antcheva, M. Ballintijn *et al.*, “Root—a c++ framework for petabyte data storage, statistical analysis and visualization,” *Computer Physics Communications*, vol. 180, no. 12, pp. 2499–2512, 2009.

- [88] J. Adamczewski, M. Al-Turany *et al.*, “Go4 on-line monitoring,” *Nuclear Science, IEEE Transactions on*, vol. 51, no. 3, pp. 565–570, 2004.
- [89] H. Spieler, “Fast timing methods for semiconductor detectors,” *Nuclear Science, IEEE Transactions on*, vol. 29, no. 3, pp. 1142–1158, 1982.
- [90] D. Breton, V. De Caqueray *et al.*, “Measurements of timing resolution of ultra-fast silicon detectors with the sampic wtdc.”
- [91] I. Rubinskiy *et al.*, “An eudet/aida pixel beam telescope for detector development,” *Physics Procedia*, vol. 37, pp. 923–931, 2012.
- [92] N. Randazzo, S. Aiello *et al.*, “Comparative timing performances of s-cvd diamond detectors with different particle beams and readout electronics,” in *Nuclear Science Symposium and Medical Imaging Conference (NSS/MIC), 2012 IEEE*. IEEE, 2012, pp. 1949–1951.
- [93] M. Osipenko, S. Minutoli *et al.*, “Comparison of fast amplifiers for diamond detectors,” *arXiv preprint arXiv:1310.1000*, 2013.
- [94] M. Berretti, E. Bossini, and N. Minafra, “Timing performances of diamond detectors with Charge Sensitive Amplifier readout,” Sep 2015. <https://cds.cern.ch/record/2055747>
- [95] J. Adamczewski, M. Al-Turany *et al.*, “Go4 multitasking class library with root,” *Nuclear Science, IEEE Transactions on*, vol. 49, no. 2, pp. 521–524, 2002.
- [96] V. Avati, “TOTEM Status report,” <https://indico.cern.ch/event/460278/session/0/contribution/5/attachments/1197898/1741887/TotemReportVA.pdf>, 124th LHCC Open Session.
- [97] Photonis USA, “PLANACON XP85012,” Datasheet: "<https://www.photonis.com/uploads/datasheet/pd/PLANACON-8x8-datasheet.pdf>".

- [98] A. Lehmann, A. Britting *et al.*, “Systematic studies of micro-channel plate pmts,” *Nuclear Instruments and Methods in Physics Research Section A: Accelerators, Spectrometers, Detectors and Associated Equipment*, vol. 639, no. 1, pp. 144–147, 2011.
- [99] L. C. Garcia, L.-R. Collaboration *et al.*, “Testing micro-channel plate detectors for the particle identification upgrade of lhcb,” *Nuclear Instruments and Methods in Physics Research Section A: Accelerators, Spectrometers, Detectors and Associated Equipment*, vol. 695, pp. 398–402, 2012.