PREPARED FOR SUBMISSION TO JINST

CHEF2017 CALORIMETRY FOR HIGH ENERGY FRONTIER
OCTOBER 2-6 2017
LYON, FRANCE

A High-Granularity Timing Detector for the Phase-II upgrade of the ATLAS Calorimeter system: Detector concept description and first beam test results

Didier Lacour on behalf of the ATLAS LAr-HGTD group

*Laboratoire de Physique Nucléaire et de Hautes Énergies LPNHE CNRS/IN2P3,
4, place Jussieu 75005 Paris, France*

E-mail: lacour@cern.ch

ABSTRACT: The expected increase of the particle flux at the high luminosity phase of the LHC (HL-LHC) with instantaneous luminosities up to $7.5 \cdot 10^{34} \text{ cm}^{-2}\text{s}^{-1}$ will have a severe impact on the ATLAS detector performance. The pile-up is expected to increase on average to 200 interactions per bunch crossing. The reconstruction performance for electrons, photons as well as jets and transverse missing energy will be severely degraded in the end-cap and forward region. A High Granularity Timing Detector (HGTD) is proposed in front of the liquid Argon end-cap and forward calorimeters for pile-up mitigation. This device should cover the pseudo-rapidity range of 2.4 to about 4.0. Low Gain Avalanche Detectors (LGAD) technology has been chosen as it provides an internal gain good enough to reach large signal over noise ratio needed for excellent time resolution. The requirements and overall specifications of the High Granular Timing Detector at the HL-LHC will be presented as well as the conceptual design of its mechanics and electronics. Beam test results and measurements of irradiated LGAD silicon sensors, such as gain and timing resolution, will be shown.

KEYWORDS: High Granular Timing Detector ; Low Gain Avalanche detector LGAD ; Silicon sensors ; High Luminosity LHC

Contents

1	Motivation	1
2	Detector requirements	1
3	Design and assembly - Module components	2
4	Sensors and readout electronics	3
5	Prototypes testing	4
5.1	HGTD test beam results for non irradiated sensors	4
5.2	Sensors performance after irradiation	5
6	Conclusion	6

1 Motivation

The high-luminosity phase of the Large Hadron Collider (HL-LHC) at CERN is foreseen to start in 2026 and deliver an integrated luminosity of 4000 fb^{-1} in about 10 years [1]. Pileup is one of the main challenges at the HL-LHC. In the nominal collision scheme, the interaction region will be spread over about 50 mm RMS along the beam axis, producing up to an average of 1.6 collisions/mm for an average pileup of 200 simultaneous pp interactions, $\mu = 200$. A powerful new way to address this challenge is to exploit the time spread of the interaction region to distinguish between tracks originating in collisions occurring very close in space but well-separated in time. This requires the ability to measure the time of tracks with a precision better than the time spread of the HL-LHC interaction region. In this context, a High-Granularity Timing Detector (HGTD) is proposed.

2 Detector requirements

HGTD will be located at about $z = \pm 3.5 \text{ m}$ from the interaction region (Figure 1), just outside the Inner Tracker subsystem (ITk) volume and in front of the endcap and forward calorimeters. It will cover the pseudorapidity region from about 2.4 to 4. Main parameters are presented in Table 1. The exact number of layers (2 to 4) will be optimized according to the best compromise between performance and costs. The target is to achieve a time resolution of 30 ps per track. At the end of the HL-LHC, the maximum neutron-equivalent fluence at a radius of 120 mm ($\eta=4$) should reach $9 \times 10^{15} \text{ n}_{\text{eq}}/\text{cm}^2$ (including a safety factors). Consequently, $4.5 \times 10^{15} \text{ n}_{\text{eq}}/\text{cm}^2$ and 4.5 MGy are the maximum expected doses in the sensors and ASICs, suggesting a replacement of the innermost part of the detector after half of the HL-LHC program.

Figure 1. A photo of the current ATLAS layout (opened for maintenance), showing the gap between the ATLAS endcap calorimeter on the left and the tracking detectors on the right, where the HGTD will be installed. Currently the space is occupied by the MBTS (white disk, in front of the endcap calorimeter).

Pseudorapidity coverage	$2.4 < \eta < 4.0$
Position in z	$3420 < z < 3545$ mm including 50 mm of moderator
Position of active layers	$3435 < z < 3485$ mm
Radial extension (active area)	110-1100 mm (120 - 640 mm)
Time resolution	30 ps per track

Table 1. Main parameters of the HGTD.

3 Design and assembly - Module components

The HGTD detector concept is based on individual planar layers of LGAD sensors [2] to be fixed in front of both endcap calorimeter cryostats with active elements between 3435 and 3485 mm in $|z|$. On both sides of this cooling plate, individual identical modules consisting of LGAD sensors, ASIC and flex cables will be installed. The size of a module is 2×4 cm² corresponding to a single LGAD sensor with two ASICs of 2×2 cm² each bump-bonded on it. Figure 2 (left) shows three modules with the different components stacked in the z direction. First the ASICs will need to be bump-bonded to the LGAD sensor. This element will then be glued with accurate positioning on the flex cable used to transfer the signals. ASIC signals and HV connections will be performed by wire bonding to the flex cables. On the top and bottom sides of the cooling plate, the position of the modules is in a staggered arrangement. This configuration ensures a 20% overlap between modules. The modules disposition and stave orientation are still under optimisation. The modules located at a radius lower than approximately 300 mm are to be replaced after half of the HL-LHC program, due the radiation damage in the sensors and ASICs. An intermediate thin plate will be used to pre-assemble and glue the modules and later screw in the cooling plate to allow a fast dismounting of the inner ring in a long shutdown and re-mounting of new modules. This concept is presented in Figure 2 (right) where the green zone is the metallic plate at a radius lower than 300 mm. Yellow and blue squares represent the modules, orange and brown squares represent the flex cables.

Figure 2. Schematic views showing two adjacent modules on the top side and one on the bottom side of the cooling plate and their assembly in one cooling plate.

4 Sensors and readout electronics

The time resolution for the HGTD is required to be 30 ps per track over its full lifetime. The sensor pad size is restricted by occupancy, pad capacitance and the fill factor. A unified pad size of $1.3 \times 1.3 \text{ mm}^2$ everywhere with an expected capacitance of 3.4 pF is found to fulfill the requirements. The pads will be arranged in arrays of total area of $2 \times 4 \text{ cm}^2$ with a common backplane bias voltage connection. LGADs are planar silicon detectors with internal gain. Figure 3 shows one single pad sensor produced at CNM. They are n-on-p silicon detectors containing an extra highly-doped p-layer below the n-p junction to create a high field which causes internal gain as displayed in Figure 3.

Figure 3. One single pad LGAD sensor produced at CNM and working principle of LGAD sensor.

The sensors will be read out by dedicated on-detector front-end electronics ASICs (bump-bonded to the sensors) which should keep the intrinsic excellent time resolution of the LGAD. The contribution to the time resolution from the electronics is given by :

$$\sigma_{\text{elec}}^2 = \sigma_{\text{jitter}}^2 + \sigma_{\text{Time Walk}}^2 + \sigma_{\text{TDC}}^2 \quad (4.1)$$

where σ_{jitter} depends on the noise and the pulse slope. The requirements of the ASIC, driven by the targeted 30 ps time resolution per MIP after irradiation by combining the multi-hits information, are summarized in Table 2.

Each pixel readout channel will consist in a preamplifier followed by a discriminator, both defining elements for the overall electronics time performance (Figure 4). A first

Figure 5. Gain for the single pad sensor as a function of the position in the pad with a bias voltage of 220 V (left) and gain for the array sensors as a function of the position on the sensor (right)

Figure 6. Efficiency in percent for the single-pad sensor, as a function of the position on the pad (left) and ime resolution using the ZCD method as a function of the gain for single pad sensors and arrays (right)

Figure 6 (right) presents the time resolution as a function of the gain for single pads and arrays. The best performance is obtained for sensor with medium doping.

5.2 Sensors performance after irradiation

The gain was found to decrease with irradiation which was attributed to loss of the effective doping concentration in multiplication layer [4]. This can be observed in Figure 7 (left) for CNM devices. The gain steadily decreases with irradiation and after fluences of $6 \times 10^{14} \text{ n}_{\text{eq}}/\text{cm}^2$. There is little difference between standard PIN and LGAD devices. Nevertheless gains of $G=8$ were measured for devices irradiated to $4 \times 10^{15} \text{ n}_{\text{eq}}/\text{cm}^2$. The gain increases at lower temperatures due to an increase of impact ionization, whereas the breakdown voltage slightly decreases.

The timing performance of CNM LGADs irradiated to different fluences up to $2 \times 10^{15} \text{ n}_{\text{eq}}/\text{cm}^2$ is shown in Figure 7(right). For HPK LGADs, the time resolution was mea-

Figure 7. Most probable charge (or gain) dependence on bias voltage measured with ^{90}Sr beta particles (Left) and Time resolution of neutron irradiated and non-irradiated CNM LGAD (right).

sured with a ^{90}Sr setup using the time difference to a calibrated thin LGAD. These results show that the currently available LGAD sensors can be operated safely up to the fluence of $4.5 \times 10^{15} \text{ n}_{\text{eq}}/\text{cm}^2$, keeping a time resolution of 50 ps, below the required limit of 60 ps per layer, in case of a 4 layers /side layout.

6 Conclusion

Requirements and design of a High-Granularity Timing Detector (HGTD), to be installed in ATLAS during the shutdown, (end of 2023 - mid-2026) have been shown. First prototypes testing in beam tests and at lab have been presented. This is the result of two years of active R&D, especially on sensors and front-end electronics by ~ 21 institutes and ~ 120 collaborators, started in summer 2015. The HGTD should provide a timing resolution of ~ 30 ps for minimum-ionizing particles, covering the pseudorapidity region between 2.4 and 4.0. Intense R&D is ongoing with thinner sensors and different doping materials to increase even further the radiation resistance of the sensors.

References

- [1] *ATLAS Phase-II Upgrade Scoping Document*, tech. rep. CERN-LHCC-2015-020. LHCC-G-166, CERN, 2015.
- [2] G. Pellegrini et al., *Technology developments and first measurements of Low Gain Avalanche Detectors (LGAD) for high energy physics applications*, Nucl. Instrum. Meth. A765 (2014).
- [3] L. Masetti et al., *Beam test measurements of Low Gain Avalanche Detector single pads and arrays*, publication in preparation (2017).
- [4] J. Lange et al., *Gain and time resolution of $45 \mu\text{m}$ thin Low Gain Avalanche Detectors before and after irradiation up to a fluence of $10^{15} \text{ n}_{\text{eq}}/\text{cm}^2$* , JINST 12 (2017) P05003.