E²

KEK 93-11
SW 9411

KEK Report 93-11
November 1993
A

Injection Error Monitor for KEK 12 GeV PS

M. SHIRAKATA, H. SATO, T. TOYAMA and K. MARUTSUKA

CERN LIBRARIES, GENEVA

P00021757

**NATIONAL LABORATORY FOR
HIGH ENERGY PHYSICS**

© National Laboratory for High Energy Physics, 1993

KEK Reports are available from:

Technical Information & Library
National Laboratory for High Energy Physics
1-1 Oho, Tsukuba-shi
Ibaraki-ken, 305
JAPAN

Phone: 0298-64-1171
Telex: 3652-534 (Domestic)
(0)3652-534 (International)
Fax: 0298-64-4604
Cable: KEK OHO
E-mail: LIBRARY@JPNKEKVX (Bitnet Address)
library@kekvax.kek.jp (Internet Address)

Injection Error Monitor for KEK 12 GeV PS

Masashi Shirakata, Institute of Applied Physics, University of Tsukuba

and

Hikaru Sato, Takeshi Toyama and Katsumi Marutsuka,

National Laboratory for High Energy Physics

Abstract

The injection error monitor is now being developed for an easy tuning of the main ring beam injection at the KEK 12 GeV proton synchrotron. It is expected to perform the automatic injection tuning for the main ring by using this monitor system. The beam trajectory and the tuning ability of the injection equipment on the horizontal phase plane are obtained and confirmed by a test bench system. The injection error monitor has been proved to be efficient for the beam injection tuning.

I. Introduction

The proton synchrotron at KEK is a cascade-type accelerator consisting of a pre-injector, a 40 MeV linac, a 500 MeV booster and a 12 GeV main ring^[1]. In order to raise the efficiency of the main ring beam injection, some observation tools have been suggested and prepared. For example, beam profile monitors, beam position monitors and beam intensity monitors provide bunch shapes, positions and intensities. The 56 beam loss monitors which are prepared along the main ring provide the beam loss distribution. However, many experiences and intuitions are required to analyze the beam state from them and to correct it. At last skillful experts have been often required to use these monitors for actual injection tuning. The injection error monitor system is designed to be easy to use, easy to see and easy to tune the beam injection conditions by observing the beam state in phase space. It is expected to make an automatic beam injection system possible.

Two septum magnets and five kicker magnets are prepared in the first and second long straight sections in the first superperiod of the main ring as shown in Fig.1. The injected beam crosses the central orbit at the middle of the kicker magnets after traversing two quadrupole magnets and one bending magnet^[2,3] in the main ring. The kicker magnets bend the beam and put it on the central orbit.

I-1F, 2F: Focusing Quadrupole Magnet
 I-1D, 2D: Defocusing Quadrupole Magnet
 SEP1, 2: Septum Magnet
 ST8, 9: Steering Magnet
 MK1 to 5: Kicker Magnet
 PR7 to 9: Beam Profile Monitor

Figure 1. Schematic view of the injection block.

The beam profile can be seen by using beam profile monitors. In this case, three profile monitors PR7, PR8 and PR9 are available, which are located just after the septum magnet box and at both sides of the kicker magnets, respectively. The profile monitor PR7 provides the lateral shape and position after the septum magnets, where the beam might have a horizontal position and direction of about +60 mm and -15 mrad with respect to the central orbit. The beam, of course, must not hit the septum walls. The PR7 is prepared mainly to prevent the beam loss from the beam shaving by the septum wall. The beam profile loses a part after the septum magnets when the beam hits the septum wall. And then a corresponding peak appears on the beam loss distribution. The septum magnets are adjusted so that the beam profiles and the beam intensities become consistent between the booster extraction and the main ring injection by observing the beam profile, intensity and loss monitors. The peak of beam loss distribution decreases when the septum magnets are set in a proper operating point. The PR8 and PR9 are available to see whether the beam traverses the suitable positions in the main ring. The beam profiles on the PR8 and PR9 should appear at the opposite positions with equal distance from the central orbit as shown in Fig.2. When the kicker magnets are fired, the beam profile on the PR9 moves towards the center and the profile of the second turn beam may appear on the PR8. If there is no problem at this point, all the profile monitors are removed from the beam line. These procedures written above are the ordinary procedure of the beam course adjustment.

Figure 2. Beam profiles at PR8 and PR9 measured at 15:05 on July 14 in 1993.

The direction of ΔR axis of the 500 MeV B.T. is opposite to that of the main ring.

The fine adjustment of the beam position is performed by the septum magnets and three steering magnets ST6, ST8 and ST9 in the 500 MeV beam transport line in order to raise the injection efficiency. The transverse injection error is minimized by the septum magnets and steering magnets. The injection timing between the 500 MeV booster and the main ring is also adjusted to put the beam bunch into the center of the RF bucket observing the mountain view of the beam bunch monitor (I-2D) which is shown in Fig.3. The longitudinal beam oscillation which corresponds to the longitudinal injection error is not observed when the momentum-phase matching is performed. The mountains corresponding to the first and second beam bunches go straight, while those of the third beam bunch oscillate due to a longitudinal injection error. After the transverse and longitudinal adjustments the injected beam circulates along the closed orbit with the minimum injection errors.

In actual beam injection tuning, the bending magnet field of the main ring is also adjusted in order to get the injected beam closer to the central orbit if the closed orbit largely deviated from the central orbit. The fine adjustment has to be iterated after the closed orbit was changed.

Although the injection efficiency has been achieved to be over 90 % at the present day, much efforts are required every time. The beam trajectory just after the injection and the effect on the beam motion by the injection equipment are difficult to imagine concretely though they can be seen as a raw signal of ΔR monitor which is shown in Fig.4. Moreover the beam profile monitors are removed before the fine tuning, because they are the destructive type monitors and they are not so useful further due to their insufficient resolution. The most of tuning difficulties are caused by these blind states. The injection error monitor considered here is expected to eliminate these difficulties during the injection tuning.

Figure 3. The mountain view of the fast intensity monitor at I-2D, every 16 revolutions by K3 trigger. The K3 trigger means the trigger signals of the kicker magnets for the third beam bunch. The mountains go straight when the momentum matches the RF phase. (1-st and 2-nd bunches)

Figure 4. Raw signal of ΔR monitor at I-3F. (R_+)
Trigger: $K1+3.0 \mu s$

II. Injection Error Monitor

Principles

The motion of the center of mass of the injected beam on the horizontal phase plane is seen in Fig.5 where the origin of the coordinates is chosen on the closed orbit. The transverse injection error brings about a betatron oscillation and the beam plot changes its location drawing an ellipse with respect to the decimal place of the tune. The injection error is observed as the ellipse around the closed orbit. The large injection error makes the ellipse size big. When the ellipse is big enough to reach the walls of the beam pipe, the beam is shaved and lost. In order to achieve the good injection efficiency, the ellipse must be suppressed to be small enough with respect to the beam pipe walls.

Figure 5. Injection error on the horizontal phase plane.

The beam orbit circulating in the main ring is described by using a matrix M as

$$\begin{pmatrix} x \\ x' \end{pmatrix} = M_{(s|s_0)} \begin{pmatrix} x_0 \\ x'_0 \end{pmatrix}$$

where

$$M_{(s|s_0)} = \begin{pmatrix} \sqrt{\frac{\beta}{\beta_0}}(\cos\Delta\psi + \alpha_0\sin\Delta\psi) & \sqrt{\beta_0\beta}\sin\Delta\psi \\ -\sqrt{\frac{1}{\beta_0\beta}}\{(1 + \alpha_0\alpha)\sin\Delta\psi - (\alpha_0 - \alpha)\cos\Delta\psi\} & \sqrt{\frac{\beta_0}{\beta}}(\cos\Delta\psi - \alpha\sin\Delta\psi) \end{pmatrix}$$

ignoring the non-linear effects. The phase space variables i.e. position and direction at the arbitrary point can be acquired by measuring the beam positions at two points. Assuming that the positions, directions and twiss parameters at the positions s_1 and s_2 are indicated by $(x_1, x'_1, \beta_1, \alpha_1, \psi_1)$, $(x_2, x'_2, \beta_2, \alpha_2, \psi_2)$, the phase space variables at the reference point s $(x, x', \beta, \alpha, \psi)$ are obtained as follows:

$$x = \sqrt{\frac{\beta}{\beta_1}} \left(\cos \Delta\psi - \frac{\sin \Delta\psi}{\tan \Delta\psi_{12}} \right) x_1 + \sqrt{\frac{\beta}{\beta_2}} \frac{\sin \Delta\psi}{\sin \Delta\psi_{12}} x_2$$

$$x' = \frac{1}{\sqrt{\beta_1 \beta}} \left(\left(\frac{\alpha}{\tan \Delta\psi_{12}} - 1 \right) \sin \Delta\psi - \left(\alpha + \frac{1}{\tan \Delta\psi_{12}} \right) \cos \Delta\psi \right) x_1 + \sqrt{\frac{1}{\beta_2 \beta}} \frac{\cos \Delta\psi - \alpha \sin \Delta\psi}{\sin \Delta\psi_{12}} x_2$$

where $\Delta\psi = \psi - \psi_1$ and $\Delta\psi_{12} = \psi_2 - \psi_1$, and $|\sin \Delta\psi_{12}|$ must be chosen not to be zero. The values to be measured are the beam positions x_1 and x_2 . The other parameters are calculated by a simulation program.

The reference point of the phase space measurement was determined to be just after MK5 as shown in Fig.6 and the measurement points for beam positions x_1 and x_2 were determined to be at I-3F and I-4F, respectively. The beam position means the center of mass of the beam bunch. The injection error is obtained as an area of the ellipse drawn by the center of mass of the beam bunch in phase space.

Figure 6. Reference point of the phase space measurement.

The measurement errors of x_1 and x_2 propagate linearly to the results of the reference point. It is convenient for the accuracy that their coefficients are small; in other words, $|\sin \Delta\psi_{12}| = 1$. The actual value of $|\sin \Delta\psi_{12}|$ between the position monitors at the I-3F and I-4F becomes about one when the actual tune ν_H has the typical value of 7.12. The contribution to x and x' due to the tune error $\Delta\nu_H$, which is

about 0.02 at the most, is estimated to be less than 2%. The remnant error of the bending magnet field at the injection period is 0.064 %^[4] which is negligible. In addition, there is the pulse-to-pulse field fluctuation for the bending magnet which is the main source of the statistical error of x and x' . It will be discussed in chapter III.

It is natural to use two position monitors as written above since the beam positions are required to be measured at two points. It is also possible to go using only one beam position monitor because the circulated beam provides additional information in the same monitor. The single position monitor system, however, has not been adopted here, though it is simpler. Since the beam is shaved even in one turn when the injection error is large, the measured injection error becomes to be inaccurate. The betatron oscillation seems to vanish fast. It causes the confusion on dividing the effects of injection error and of tune spread $\Delta\nu$. The measurement accuracy of x and x' becomes worse a little since the value of $|\sin\Delta\psi_{12}|$ has the small value. It is essential to determine the two measurement points as near the injection point as possible.

Machine lattice

The lattices of the 500 MeV transport line and the main ring are tabulated in Table 1. (See Appendix A.) The horizontal betatron and dispersion functions from D1 in the 500 MeV B.T. to I-2D of the main ring are shown in Fig.7. Twiss parameters are calculated by a program SAD/FFS which is a simulator developed at KEK assuming the betatron tunes to be $\nu_H = 7.12$ and $\nu_V = 7.21$ which are the typical value of the actual run.

Figure 7. Horizontal betatron and dispersion functions from D1 to I-2D.

Table 1. Lattice structure of the beam injection section.

Section	Element	Effective length (m)	Bending angle (deg)	Focusing (kG/cm)
500 MeV B.T.	Q8	0.3075		0.1289532
	D12	0.9082		
	B2SC	0.75	8.273	
	D13	0.228		
	B2SC	0.75	8.273	
	D14-1	1.0807		
	ST6	0.250	-	
	D14-2	0.1745		
	ST7	0.150	-	
	D14-3	1.1536		
	Q9	0.3075		-0.1289532
	D15	5.445		
	Q10	0.3075		0.1289532
	D16-1	0.3145		
	ST8	0.250	-	
	D16-2	0.712		
	ST9	0.250	-	
	D16-3	0.3624		
	I-1F	BSP2	1.0	-5.30
		D17	0.1537	
		BSP2	1.0	-5.30
		D18	1.3596	
I-1D	QD	0.307525		-0.1225945
	L3	1.81654		
	B	3.2575	7.5	
I-2F	L1	0.37683		
	QF	0.307525		0.1216000
I-2D	L2	5.44470		
	QD	0.307525	7.5	-0.1225945
	L3	1.81654		
	B	3.2575		
	L1	0.37683		

D12 to D18 and L1 to L3: Drift Space
 Q8 to Q10, QF and QD: Quadrupole Magnet
 B2SC and B: Bending Magnet
 ST6 to ST9: Steering Magnet
 BSP2: Septum Magnet

Fast beam position measurement

The PS main ring has 56 wall-current type position monitors^[5,6] along the beam line with the same intervals corresponding to the betatron phase of about $\pi/4$. It is possible to choose the measurement points keeping the value of $|\sin\Delta\psi_{12}|$ to be one. These monitors are used in the slow position measurement at the present. The slow position means the time-averaged beam position and the individual position information of beam bunches are lost. On the contrary, the fast position measurement provides the

bunch positions. (See Appendix B.) In both cases, the same monitor head is available which is shown in Fig.8.

A beam position monitor head picks up wall-currents on the inner surface of the beam pipe with four split cylindrical electrodes. Each wall-current is extracted to the outside of the beam duct through a ceramic seal and then returns to the beam pipe through a signal transformer. Output signals from these transformers have amplitudes of 300 to 500 mV for the normal proton beam intensity of several 10^{12} ppp. The induced noise voltage on cables from the main ring tunnel to the control room has been measured to be less than 5 mV. The signal attenuation and induced noise are about 20 % and less than 2 %, respectively. It is accurate enough for the beam injection tuning. However, the signals had better be amplified just after the monitor heads for the heavier ion beams with long bunch lengths and low beam intensities of lower than 10^{12} ppp because the signal to noise ratio becomes worse. For example, the induced noise becomes about 10 % when the amplitude of the output signals are 50 to 80 mV for the deuteron beam of about 1×10^{12} ppp.

Figure 8. The beam position monitor head.
(wall-current detection type)

The conversion to the position from the wall-current signals is expressed as:

$$\Delta R = K \frac{R_+ - R_-}{R_+ + R_-}$$

where ΔR is the beam position in millimeter, R_+ and R_- are the pulse heights of the wall-current signals and K is the normalization factor which is measured to be 60.9. The accuracy of the beam position monitor system is estimated to be ± 0.5 mm in the slow position measurement.^[4] The same accuracy is expected also in the fast position measurement.

A typical pulse width of the wall-current signals is about 100 ns during the injection period as shown in Fig.9. This fast signal needs the fast sampling system over 100 MHz for an accurate pulse shape measurement, and large memories and calculation ability are required. For example, several ten kilobytes of memories are required per channel for ten revolutions which correspond to about one cycle of the beam trajectory on the horizontal phase plane. Since it is enough to get only pulse heights for the beam position, the data size can be substantially reduced by using the pulse height sampler which is being prepared now. Since the wall-current monitor has a cut-off frequency of a few hundreds kilohertz^[4], beam signal pulses tend to cancel the DC component. The pulse height sampler will contain of a baseline compensator and a fast peak/hold unit. Pulse height data are transferred to a computer through a CAMAC and VME bus system.

Figure 9. Shape of fast ΔR signal at I-3F. (R_+)
Trigger: K1+3.8 μ s

[†] It is estimated to be about 1 mm in absolute at the present.

C.O.D. measurement

The most important purpose is to put the beam on the central orbit which means the closed orbit but not a design orbit. It is necessary to measure the closed orbit distortion (C.O.D.) in order to detect the closed orbit at the reference point which has been determined to be just after MK5. The circulating beam changes its location in phase space according to the equation

$$\begin{pmatrix} x \\ x' \end{pmatrix} = \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix} \cos N\mu + \begin{pmatrix} \alpha & \beta \\ -\gamma & -\alpha \end{pmatrix} \sin N\mu \begin{pmatrix} x_0 \\ x'_0 \end{pmatrix}$$

where N is a revolution number, α , β and γ are the twiss parameters and μ is the phase advance given by $\mu = 2\pi\nu$. This transfer matrix suggests the rotation with respect to μ . As a result, the trajectory of the beam plot forms an ellipse and the center of the ellipse indicates the C.O.D. In the case of the PS main ring, the beam plot on the horizontal phase plane returns to the previous location in about 9 revolutions since the horizontal tune ν_H is set to 7.12.

Another method of C.O.D. measurement exists. The betatron oscillation vanishes for a few tens millisecond after the injection because the beam bunch form is smeared out in phase space due to the Δv . If the phase space measurement is continued for a few tens millisecond, it will be observed that the beam plot falls into the center of the ellipse little by little rounding around along the ellipse. The phase space plot after a proper time directly provides the C.O.D.

Test bench

A test bench consists of two digital oscilloscopes (LeCroy 9450, Hewlett Packard 5185) and a micro-computer (PC-9801VX) as shown in Fig.10. The oscilloscopes are used as a fast digitizing memory instead of a pulse height sampler. LeCroy 9450 is a 2 channel oscilloscope which has the specification of 400 MS/s, 300 MHz band-width and the memories of 50 kW/ch. HP 5185 is also a 2 channel oscilloscope which has a sampling rate of 250 MS/s and the memories of 64 kW/ch. The pulse data of wall-current signals are transferred through the GP-IB bus. The pulse heights are given by finding the pulse edge where the slope changes rapidly and the peak. Since the computer takes the whole data of the pulse shape and determines the pulse height by calculation, the processing ability is limited by the CPU capacity and it typically takes about six seconds for a one revolution event and over one minute for a ten revolution event. Unfortunately, the present data processing rate is too slow to apply for usual injection tuning. The VME computers are mainly used to control the

accelerator. The new computer system which can communicate them is required for the injection error monitor.

The beam injection error has six dimensions: four dimensions for transverse section and two for longitudinal. Although only two dimensions x and x' of the horizontal phase space of the transverse section can be measured in this test system, the proof of principle and the reliability of the injection error monitor can be obtained.

In one acceleration cycle, nine beam bunches are injected to the main ring with a time interval of 50 ms which is synchronized with the booster operation cycle. The timing pulses K1 to K9 which are the trigger signals of the kicker magnets for each bunch are applied to triggering the monitor system for the target bunch selection.

Figure 10. Schematic view of the test bench system.

III. Results and discussions

Beam trajectory in phase plane

Trajectories of the beam plots on the horizontal phase plane are shown in Fig.11 which shows the beam bunch locations of ten revolutions with two cases of the injection efficiency of 81% and 96%. The beam plot rotates clockwise about 2π radians along the ellipses within a period of about 10 revolutions which well agrees with the measured horizontal tune of 7.10. The ellipse size becomes smaller according to the injection error, i.e. the amplitude of the betatron oscillation. The center point corresponding to the closed orbit is determined by fitting the beam plots as an ellipse. The injection efficiency strongly depends on the location of the first beam plot on this plane.

Figure 11. Injection beam trajectory on the horizontal phase plane.

The error bars are statistical, which are one-sided to a certain direction because they mainly come from the pulse-to-pulse field fluctuation of the bending magnets in the main ring. The position changeability at I-2F section is shown in Fig.12 with respect to the bending magnet field at P1+100 ms. The P1 indicates the start time of the injection period. The injection period is defined from P1 to P2 (P1+510 ms). The bending magnet field varies cycle by cycle about 0.3 Gauss at the injection time. Although this fluctuation corresponds to at most 0.02% of the magnetic field during the beam injection, it brings about the position deviation of about 1.5 mm.

Figure 12. Orbit changeability during the beam injection.
Dashed line is the best fit line.

The trajectories of the beam plot just after the injection with respect to the set value of the current of the each injection magnet are shown in Fig.13. It can be thought as a tuning map. It is evident that this map is quite useful to the injection parameter tuning because it clearly shows the magnet to be changed and the changing direction of the magnet current. The injection parameters are two septum magnets SEP1 and SEP2, three steering magnets ST6, ST8 and ST9 and five kicker magnets MK1 to MK5. The effects of them are displayed individually. Since the MK4 and MK5 are downstream located from the MK1 of about 1450 mm, the trajectories for MK4 and MK5 rotate about 190 mrad with respect to that for MK1. The result well agrees the expectation. The ST6 has been experientially found to be effective when the injection tuning is suffering from the bad injection efficiency. The reason is now very clear. The septum magnets and the ST8 and ST9 cause the almost same effect on this plane. They are futile when the closed orbit is out of the tunable region of the kicker magnets because the tuning direction of septum magnets, ST8 and ST9 and that of the kicker magnets cross at almost right angles. The ST6 plays an important roll of helping the kicker magnets since the controllable range of them is not so wide. The ST6 is so efficient but it cannot be set arbitrarily. The controllable range of these injection parameters are limited by the apertures of, for example, the septum magnets which have a small space for the beam. This tuning map does not mention the safety with respect to the apertures. The orbit tracing should be needed to clarify it.

Figure 13. Beam plot trajectories just after the injection.
Kicker magnets MK1, MK4 and MK5 were varied
from the power-off value to the maximum.
With the injection bump orbit of about 20 mm

It might be happen that the operating point cannot be set on the closed orbit for all the support of the ST6. The difficulty can be avoided by making a bump orbit at the injection portion. The steering magnets are prepared for the C.O.D. correction in each section of the main ring. The kick angle required within the kicker magnets can be reduced by making a bump orbit at I-1F section which can be made by three steering magnets in IV-7F, I-1F and I-2F section, without interfering the circulating beam. In fact, the bump orbit of about 20 mm is set at I-1F section to decrease the angle between the injected beam and the circulating beam in the kicker magnets at present since the kicker magnets have been thought not to be strong enough for the beam injection. The effects of the bump orbits on the beam injection tuning are shown in Fig.14 for three cases of large, small and no bump orbit. These adjectives large and small are with respect to the present size and corresponds to about 31 and 15 mm, respectively. It shows the change of the beam injectable region. Black lines are the trajectories of the injected beam plots with respect to the current of septum magnets measured with the maximum kicker magnet power. The controllable region is localized to the lower side of them on account of the ability of the kicker magnets. It shows that the controllable region is widened toward the right-upper direction according to the bump orbit size. The trajectories of beam plots with respect to the current of kicker magnets should be parallel like those of the septum magnets. It is considered to be caused by measurement

Figure 14. Effect of the injection bump orbits.
Large bump orbit: ~31 mm
Small bump orbit: ~15 mm
The controllable region is widened
toward the right-upper direction
according to the bump orbit size.

errors and it is not so important in this discussion. In the cases of the small and no bump orbits, the closed orbit is out of the tunable region while the large bump orbit gets a wide margin of kick angles. The injected beam cannot be set on the closed orbit if the ST6 is fixed to the present operating point. It is apparent that the bump orbit is available to help the kicker magnets effectively. However, it has been proved that there is no need to make any bump orbit for the beam injection because the controllable range of the ST6 has been found to be wide enough with respect to the apertures.

Kick angle and the tuning ability

It has been doubted whether the ability of the kicker magnets is enough to kick the beam onto the central orbit. The injection error monitor can be applied to test the ability of the kicker magnets. The kicker system for the PS main ring consists of five fast kicker magnets with the effective length of 250 mm and the gap width of 50 mm[7]. The current monitors of the kicker magnets have been calibrated as shown in Table 2. The injection angle at the reference point was measured with respect to the total current of the kicker magnets as shown in Fig.15 as changing the current of MK1, MK4 and MK5. The kick angle with small current cannot be measured because the beam is lost by hitting the beam pipe before the position measurements at I-3F and I-4F. The kick angle per kicker magnet is about 1.4 mrad and the field strength is estimated to be 254 Gauss which well agrees with the theoretical value of 251 Gauss. The kicker magnets are proved to behave as expected.

Table 2. Calibration table for the MR kicker magnets.

measured values:		MK1	MK2	MK3	MK4	MK5
PFN monitor (V)		2.43	2.60	2.24	2.46	2.49
Primary voltage (V)		179	183	179	177	175
CT output (V)	max.	95.6	97.4	96.0	97.1	90.9
	min.	91.0	92.7	92.0	89.3	86.2
coefficients:						
PFN -> Primary voltage (V)		73.8	70.4	80.1	72.1	70.3
Primary voltage -> I_{kicker} (kA/V) $\times 10^{-3}$	max.	5.34	5.32	5.36	5.49	5.19
	min.	5.08	5.07	5.14	5.05	4.93
	ave.	5.21	5.19	5.25	5.27	5.06

Figure 15. Kick angle of the MR kicker magnets.

III. Conclusion

The test system of the injection error monitor has been built and worked very well. The beam trajectory at the injection point on the horizontal phase plane has been clearly observed and the tuning abilities of the injection equipment have been investigated. The beam injection process seems to be simple in principle. The good injection efficiency over 95 % is easily achieved by only using the test system for the transverse injection error. Although the actual beam injection process is more complex, for example, the vertical injection error, the longitudinal matching and so on, it has been proved that the injection error monitor is quite useful to tune the beam injection conditions. The final purpose of the injection error monitor system is to construct the automatic beam injection tuning system for the PS main ring. The results in this study are meaningful and suggest the concrete way of the beam tuning.

Appendix A. Schematic view of the 500 MeV B.T. to the main ring

The 500 MeV beam transport line consists of the ten quadrupole magnets, four bending magnets and nine steering magnets. The septum and kicker magnets are located on the beam line of the main ring. On August 4-th in 1993, the arrangement of these magnets from Q8 to QD in I-1D was measured and then it has been proved that very large differences exist between the computer code and the real arrangement in Q8 to Q9 and I-1F section. The schematic views of these sections are shown in Fig.A-1 to A-5 which are consistent to those measured from 1976 to 1986 by the vacuum group.

Fig.A-1 Schematic view of Q8 to Q9.

†: measured by the vacuum group

Fig.A-2 Schematic view of Q9 to Q10.
†: measured by the vacuum group

Fig.A-3 Schematic view of Q10 to the septum magnet box.

Appendix B. Fast and slow position measurements

The injection error monitor stands on the precise beam position measurement. The accuracy of the measured fast ΔR becomes the most essential quantity for the entire system. It is very important to check the accuracy of the fast position measurement. In the present test system, the same monitor heads of the slow position measurement were used for the fast position measurement by mechanically relaying the signal lines. The measured fast and slow positions must be consistent in principle. The beam positions with respect to some bump orbits are measured as shown in Fig.B-1. Unfortunately the appreciable difference is observed. It suggests the error due to the normalization factor because there is a difference in the slopes but not offsets. The slow position measurement system is shown in Fig.B-2. In the case of the slow position measurement, the wall-current signals are amplified and envelope-detected in the main ring tunnel before transferring to the control room. In this process, the high frequency components are discarded and the individual beam bunch position cannot be observed. The beam positions are calculated by the analog normalizer units which are prepared independently in the VME computing system and in the monitor crate. It has been proved that there are no problems in these signal normalizer units by using test signals. As shown in Fig.B-1, two results of the slow beam position measurements are consistent. It also indicates that the normalizer units work correctly.

Figure B-1. Beam positions between the fast and slow position measurements.

Figure B-2. Schematic view of the slow position measurement system.

The beam position is calculated by R_+ and R_- signals as

$$\Delta R = K \frac{R_+ - R_-}{R_+ + R_-}$$

where ΔR is the beam position, R_+ and R_- are the pulse heights of the wall-current signals and K is the normalization factor. If the R_+ and R_- signals have offsets, the normalization factor is effectively changed as follows:

$$\begin{aligned} \Delta R &= K \frac{(R_+ + \Delta R_+) - (R_- + \Delta R_-)}{R_+ + \Delta R_+ + R_- + \Delta R_-} \\ &= K \left[\frac{R_+ - R_-}{R_+ + R_-} - \frac{R_+ - R_-}{(R_+ + R_-)^2} \Delta E + \frac{R_+ - R_-}{(R_+ + R_-)^3} (\Delta E)^2 + \dots \right] \\ &\sim K \frac{R_+ - R_-}{R_+ + R_-} \left(1 - \frac{\Delta E}{R_+ + R_-} \right) \end{aligned}$$

where $\Delta E = 2\Delta R_+ \sim 2\Delta R_-$ is assumed. When the wall-current signals are small, the ΔR tends to be overestimated. This tendency has been seen in the low intensity beam during a deuteron beam run.

The characteristic of the head-amplifier was investigated as shown in Fig.B-3. The pulse generator provides rectangular pulses whose widths are fixed to 100 ns, a typical value of the proton beam bunches. The pulse height is set to 200, 300 and 400 mV. The pulse duration is also changed to be 200 ns, 400 ns, 1.0 μ s and 1.5 μ s. It has been proved that the nonnegligible signal offset exists because the slope deviation brought about by the head-amplifier depends on the input signal amplitude as shown in Fig.B-4. This signal offset is considered to be caused by a forward voltage reduction of the diodes which are used in the signal envelope detection. It must be noted that the slow position measurement tends to overestimate the beam position especially while the wall-currents are small. In the case of the fast position measurement, there is no need to worry about the contribution of this unnecessary offset to the position measurement because the wall-current signals are directly transferred to the oscilloscopes which are used as the digitizing memory. If some other offsets exists for any reason, they are discarded since the pulse heights are dynamically calculated by detecting the signal edges and peaks on the computer.

Figure B-3. Schematic view of the test system for the head-amplifier.
Attenuator: -1.07, -2.07, -3.11, -4.16 (dB)

In Fig.B-1, the sizes of bump orbits are calculated by using the current-angle table which provides the bending angle with respect to the current of the steering magnets arranged in the main ring. It must be also noted that the calculated bump orbit sizes do not provide the actual sizes because the current-angle table was calibrated by using the slow position measurement system. Fig.B-1 does not always suggest that the fast position measurement tends to underestimate the beam position. For the accuracy check of the fast beam position measurement, the other methods need to be considered because the results of the fast and slow position measurements cannot be compared directly.

Figure B-4. Characteristics of the head-amplifier.

Acknowledgment

The authors would like to thank Prof. M.Kihara, director of the PS division, and Prof. S.Mori for their encouragement and useful suggestions. They wish to thank the beam monitor group and the beam transfer group for their comments and suggestions. They also thank the vacuum group for the useful graphs of the beam line. Their special thanks go to many colleagues for their interest, discussions and continuous support.

References

- [1] T.Suzuki, "ORBIT ANALYSIS OF THE KEK SYNCHROTRON", KEK-74-4, June 1974.
- [2] A.Ando et al., Proc. 10-th International Conference on High Energy Accelerators, 1974.
- [3] K.Endo and M.Kihara, "DESIGN OF THE BENDING AND QUADRUPOLE MAGNETS FOR THE MAIN RING OF THE JAPANESE 12 GEV PROTON ACCELERATOR", KEK REPORT-3 (1972).
- [4] T.Kasuga et al., "Magnetic Field Measurements of the Main Ring Bending Magnets of KEK Proton Accelerator", The 5-th International Conference on Magnet Technology, Frascati, 1975.
- [5] K.Satoh, Rev. Sci. Instrum. 50 (1979) 450.
- [6] D.Arakawa et al., Proc. of 3rd Symp. on Accelerator Science and Technology, at Osaka, Japan, p169 (1980).
- [7] K.Takata et al., "FULL APERTURE KICKER MAGNETS FOR KEK PROTON SYNCHROTRON", KEK-76-21, March 1977.