The Upgrade of the LHCb RICH Detectors

Massimiliano Fiorini
(INFN and University of Ferrara)

on behalf of the LHCb RICH Collaboration

10th International Workshop on Ring Imaging Cherenkov Detectors
Moscow, 29 July – 4 August 2018

The LHCb Experiment

RICH Detectors

RICH1 (25-300 mrad)

$4 \text{ m}^3 \text{ C}_4\text{F}_{10}$ $n = 1.0014$, up to 60 GeV

RICH2 (15-120 mrad)

$100 \text{ m}^3 \text{ CF}_4$ $n = 1.0005$, up to ~ 100 GeV

Hit-map distribution

/RICH/Default

Run 209463, started 2018-05-29 12:54:54, duration: 00:24:03

RICH1 top panel

RICH1 bottom panel

RICH1

RICH2 right panel

RICH2 left panel

RICH2

Number of hits
in RICH1

Number of hits
in RICH2

Hit-map distribution

/RICH/Default

Run 209463, started 2018-05-29 12:54:54, duration: 00:24:03

RICH1 top panel

RICH2 right panel

RICH2 left panel

RICH1 bottom panel

RICH1

Talk by Silvia Gambetta on Monday
"The LHCb RICH detectors: operations and performance"

RICH2

Number of hits
in RICH1

Mean $\sim 2 \times 10^3$

Number of hits
in RICH2

Mean $\sim 2 \times 10^3$

LHCb Upgrade Program

- During Run 1 LHCb operated at leveled luminosities up to $4 \times 10^{32} \text{ cm}^{-2}\text{s}^{-1}$, $2 \times$ higher than design value
- In Run 2 we should collect $\sim 6 \text{ fb}^{-1}$ more
 - Main limitation: 1 MHz L0 trigger rate

	LHC era			HL-LHC era
Run (years)	Run 1 (2010-2012)	Run 2 (2015-2018)	Run 3 (2021-2023)	Run 4 (2027-2029)
Integrated luminosity	3 fb ⁻¹	9 fb ⁻¹	25 fb ⁻¹	50 fb ⁻¹
Instantaneous luminosity	$4 \times 10^{32} \text{ cm}^{-2}\text{s}^{-1}$		$2 \times 10^{33} \text{ cm}^{-2}\text{s}^{-1}$	

Current LHCb

Upgraded LHCb

■ LHCb Phase 1 Upgrade

LS2
LHCb Upgrade

- Operate detector at $2 \times 10^{33} \text{ cm}^{-2}\text{s}^{-1}$ instantaneous luminosity
- Read out the full detector at 40 MHz
- Install upgraded LHCb during long shutdown 2 (2019-20)

RICH upgrade in a nutshell

- Adapt the current RICH detectors to run at higher luminosity and with continuous 40 MHz read-out
- Mechanical and optical changes
 - RICH1 spherical mirrors focal length increased to reduce occupancy (optical system redesigned)
 - New support mechanics and cooling
- Electronics and data acquisition changes
 - Replace HPDs with commercial Multianode PhotoMultiplier Tubes (MaPMTs) with 64 channels
 - Use 40 MHz front-end electronics and data acquisition
 - CLARO8 amplifier / discriminator ASIC
 - FPGA-based digital board
 - GBT (GigaBit Transceiver) chip for data transmission

New mechanics (1)

- Peak occupancy should remain $< 30\%$ to maintain PID performance
- Focal plane and spherical mirror moved back to increase ring size
- New spherical mirrors with larger radius of curvature
- Larger gas enclosure
- Compact photo-detection system required

New mechanics (2)

- Peak occupancy should remain $< 30\%$ to maintain PID performance
- Focal plane and spherical mirror moved back to increase ring size
- New spherical mirrors with larger radius of curvature
- Larger gas enclosure
- Compact photo-detection system required

Upgraded RICH1

Photomultiplier tubes (1)

Photosensitive plane of the RICH2 detector

- Hamamatsu MaPMTs with 8×8 pixel matrix, arranged in Elementary Cells (EC)
 - 1" R13742 (from R11265 series)
 - 2" R13743 (from R12699 series)

- EC-H type: 2" MaPMT

- ~400 modules
- Outer regions of RICH2
- One R13743 MaPMT (larger model, 2×2 inches) per EC

- EC-R type: 4× 1" MaPMTs

- 2×2 matrix of R13742 MaPMT (smaller model, 1×1 inches) per EC
- ~2700 MaPMTs
- ~700 modules
- RICH1 and central regions of RICH2

Photomultiplier tubes (2)

- Hamamatsu MaPMTs
 - ❑ 3100 R13742 and 450 R13743, including spares
 - ❑ Super-bialkali photocathode
 - ❑ UV glass window
 - ❑ Minimum gain 1×10^6 at 1 kV
 - ❑ 1:3 pixel gain spread in single PMT, 1:3 spread in different PMTs
 - ❑ Low dark count rate
 - ❑ Single photon spectrum well separated from the noise pedestal

R13742 (1")
RICH1 and
RICH2

R13743 (2")
RICH2 only

Photomultiplier tubes (3)

- Higher quantum efficiency of MaPMT (super-bialkali photocathode) in the green wavelength region
 - Reduction of chromatic error

Magnetic shield

- MaPMTs are sensitive to magnetic fields
 - Degradation of detection efficiency and gain
 - Stray field can reach 25 G in RICH1 (~5 G in RICH2)
- Use “cross-shaped” local shielding structure in RICH1 only
 - Efficiency in the edge pixels at 30 G can go down to 50%
 - Full recovery in central pixels and >85% in the worst cases for edge pixels

The CLARO ASIC

- 8-channel amplifier / discriminator ASIC
 - ❑ Single-photon counting with MaPMTs
 - ❑ 0.35 μm CMOS technology from AMS (low cost, high yield)
 - ❑ 40 MHz operation (recovery time < 25 ns)
 - ❑ Power consumption ~ 1 mW / channel
 - ❑ Adjustable threshold and gain (6+2 bits), to compensate for PMT gain variation
 - ❑ Binary read-out
 - ❑ 128-bit register protected by triple modular redundancy
 - ❑ Radiation-hard by design cells
 - IMSE-CNM Sevilla

CLARO signals

- The amplifier and DAC of any channel are buffered to output pins through a multiplexer controlled by global bits in the configuration register
- LHCb RICH binary read-out: hit or no-hit information for each bunch crossing at 40 MHz
 - Hits are “collected” by FPGA and sent off-detector

Elementary Cell (EC)

Early Prototype
Version

CLARO FEBs
8 CLARO ASICs per FEB

Digital boards
Manage digital signals
processing and data
transmission

2×2 PMTs

Back-Board
Adapter to the digital board

Base-Board

Mechanics and cooling

Detector occupancies

- Expected peak occupancy in RICH1 is $\sim 27\%$
 - Using upgrade geometry and assuming Run 3 luminosity
 - Would have been $>40\%$ in peak region in case of no change in detector geometry

Cherenkov angle resolution

Contributions to resolution (in mrad)	RICH1-2015 current HPD	RICH1-upgrade MaPMT	RICH2-2015 current HPD	RICH2-upgrade MaPMT
Chromatic	0.84	0.58	0.48	0.31
Pixel	0.60, PSF=0.86	0.44	0.19 PSF=0.29	0.19
Emission point	0.76	0.37	0.27	0.27
Overall	1.60	0.78	0.65	0.45

- Resolution improved for upgraded geometry:
 - Chromatic error: MaPMT QE peaked at higher wavelength than that of HPD
 - Point spread function of the HPDs (PSF) contribution removed
 - RICH1 emission point error: improved optics

Digital board

- Capture (asynchronous) CLARO outputs, synchronize to LHC clock, data algorithm, format and transmission
- Motherboard with FPGAs and power distribution (PDMDB)
 - Each serves $4 \times$ half EC-R or $4 \times$ EC-H
 - Plugins for control and data link
- Thermally coupled to cooled column

Photon Detector Module

- PDM: 2 digital boards + 4 elementary cells
 - MaPMTs (magnetic shield for RICH1 only), CLARO ASIC read-out, FPGA read-out, fast data transmission

RICH columns

- Mechanical support for Elementary Cells, PDMDB, harness and cooling
 - Easy to remove a column for maintenance
 - Same mechanical structure for columns in RICH1 and RICH2 but different supports

Radiation hardness

- High radiation levels expected for the whole upgrade phase (50 fb^{-1}) at the RICH photodetector plane location
 - 200 krad , $3 \times 10^{12} \text{ 1 MeV } n_{\text{eq}}/\text{cm}^2$, $1.2 \times 10^{12} \text{ HEH}/\text{cm}^2$
- The read-out (CLARO and FPGA) have been tested for Single Event Effects (SEE) and Total Ionizing Dose (TID)
 - CLARO uses radiation-hard by design cells (IMSE-CNM Sevilla)

CLARO Single Event Upset (SEU)

CLARO Single Event Latchup (SEL)

- Xilinx Kintex-7 FPGA is suitable for operation in LHCb RICH
 - Periodic scrubbing foreseen for error mitigation

Beam and lab tests (1)

- A compact detector based on solid radiator (plano-convex lens) has been used to measure the performance of close-to-final opto-electronics chain in several test beams with 180 GeV/c hadrons

Beam and lab tests (2)

- Operation of a complete setup in a realistic environment
 - CLARO chip calibration, linearity and noise studies
 - Threshold scan studies
 - Cross-talk studies
 - Resolution studies
 - Photon yield analysis
 - Thermal behavior
 - Validation of both EC types

PDM integration in RICH2

Photon Detector Module
(pre-production components)

Top view of PDM installed in
RICH 2, synchronized with
LHCb clock and trigger

Integrated Cherenkov light
from LHC collisions

- Production components have or are being tested for Quality Assurance (QA)
 - ❑ MaPMTs: all tested (3100 R13742 and 450 R13743)
 - ❑ CLARO: >90% tested (33 thousand produced in first production lot) with automated pick-and-place
 - ❑ Test of all printed circuit boards
 - ❑ Test of the Elementary Cells
 - ❑ Test of the Columns

- Production components have or are being tested for Quality Assurance (QA)

- MaPMTs: all tested (3100 R13742 and 450 R13743)

- CLARO: >90% tested (33 thousand pre 1 production lot) with automated

- Test of all printed

- T

Poster by Konstantin Gizdov

"Strategy and Automation of the Quality Assurance Testing of MaPMTs for the LHCb RICH Upgrade"

LHCb Phase 2 Upgrade

- LHCb is proposing a Phase 2 Upgrade to take full advantage of the flavour physics opportunities at the HL-LHC
 - Ten-fold increase in luminosity compared to the Phase 1 upgrade ($1-2 \times 10^{34} \text{ cm}^{-2}\text{s}^{-1}$)
 - Operation from 2030 on
- The design of a very challenging RICH detector is being evaluated by the Collaboration
 - Idea presented during RICH2016 by C. D'Ambrosio
 - Different related contributions presented in RICH2018

- The LHCb RICH Phase 1 Upgrade is well under way
 - ❑ Proposed to cope with $2 \times 10^{33} \text{ cm}^{-2}\text{s}^{-1}$ luminosity and full-detector read-out at 40 MHz
 - ❑ Aim to collect 50 fb^{-1} during Run 3 and 4
 - ❑ New photo-detectors and electronics chain
 - ❑ Modified RICH optics and mechanics
 - ❑ Maintain (even improve) current RICH performance at 40 MHz
- The whole upgrade program is on schedule for installation during the LHC long shutdown 2 (2019-2020)
 - ❑ Complete opto-electronics chain validated in beam and lab tests
 - ❑ All components of PDM and mechanical/optical structure have been successfully reviewed for production readiness
 - ❑ Production and quality assurance have started
 - ❑ Installation starting soon!

SPARES

θ_c versus Momentum

- Using isolated tracks for RICH1

CLARO timeline

- (2011)
 - Design of the 4 ch. CLARO prototype
 - Deep characterization on the test bench
- (2012)
 - First tests with R11265 MaPMTs and Silicon Photomultipliers
- (2013)
 - Radiation hardness tests
 - More tests with the R11265 MaPMTs
 - Chosen as the baseline front-end ASIC for the LHCb RICH Upgrade
- (2014)
 - CLARO8 designed and produced (v0, v1)
 - CLARO8 bench, beam and radiation hardness tests
- (2015)
 - CLARO8 v2 designed and produced
 - CLARO8 v2 bench and beam test
- (2016)
 - CLARO8 v3 designed, produced and tested
 - CLARO8 Production Readiness Review (PRR)
- (2017)
 - CLARO8 v3 pre-production and quality assurance
 - CLARO8 v3 production (2nd half of 2017)

Trigger concept for upgrade

- Main bottlenecks for going to high readout rate:
 - Current front-end max readout rate is 1.1 MHz
 - Level-0 hardware trigger (E_T and p_T in calorimeter and muon detectors) → limited discrimination power → yields saturate in hadronic channels

RICH1

Hybrid Photo-Detectors

- Pixel HPD developed in collaboration with industry
 - Vacuum technology and silicon pixel read-out
- 484 HPDs for a total area of 3.3 m²
- 32 × 32 = 1024 pixels, 0.5 × 0.5 mm²
- Very good QE (~27% @270nm)
- Silicon sensor bump-bonded to binary read-out chip (1.1 MHz)
- Very low noise
 - 145 e⁻ (signal 5000 e⁻ typ.)

References: NIMA 595 (2008) 142
EPJ C 73 (2013) 2431

Online calibrations (1)

- Performed online since the beginning of Run 2
- Refractive index
 - May change due to temperature, pressure and gas mixture variation
 - Fit the Cherenkov angle distribution for $\beta=1$ tracks

Online calibrations (2)

■ HPD image

- Position of the photocathode image on the anode can change due to charging effects
- Anode images are cleaned and a Sobel filter used to detect the edge
- Automatic update of the photo-cathode center position

Radiators and material budget

Parameter	C_4F_{10}	CF_4
L [cm]	~ 110	167
n	1.0014	1.0005
$\theta_c^{\max}$ [mrad]	53	32
$p_{\text{thresh}}(\pi)$ [GeV/ c]	2.6	4.4
$p_{\text{thresh}}(K)$ [GeV/ c]	9.3	15.6
$p_{\text{thresh}}(p)$ [GeV/ c]	17.7	29.7

Item	RICH 1	RICH 2
Entrance window	0.001	0.014
Gas radiator	0.026	0.017
Mirror	0.015	0.079
Exit window	0.006	0.014
Total (X_0)	0.048	0.124

Magnetic field corrections

- HPD image distortion due to magnetic field
- Projection of test pattern with and without magnetic field to extract correction parameters

- Many components aligned with an accuracy of 0.1 mrad
 - Whole detector, detector halves, mirror segment and HPD

- Then use reconstructed Cherenkov angle for $\beta=1$ tracks
 - Misalignment observed as shift of track projection point w.r.t. the center of the corresponding Cherenkov ring

Cherenkov angle resolution

- Single photon resolution
 - Distributions for saturated ($\beta=1$) tracks

PID algorithm

- Consider all photons and all tracks and all radiators at once and maximize likelihood function:

$$L = L(n_{pixel}, \sum_{track} e_{pixel, track}, b_{pixel})$$

- Take all PIDs to be pions
 - Estimate background parameter b_{pixel} per HPD
- Calculate likelihood of given pixel distribution
- Iterate
 - Change PID hypothesis one track at a time
 - Recalculate likelihood
 - Choose change that had biggest impact
 - Assign new PID to that track
- Until no significant improvement is found
 - As signal photons are now identified better, update background estimate and start a 2nd (and usually final) iteration

PID Performance (1)

- PID performance evaluated from data for Run1
- Genuine $\pi/K/p$ samples identified from kinematics only

PID Performance (2)

- Invariant mass distribution for $B \rightarrow h^+h^-$ decays
 - Before (left) and after (right) using RICH PID information

- Signal: $B^0 \rightarrow \pi^+\pi^-$ (turquoise dotted line)
- Other contributions are eliminated ($B^0 \rightarrow K\pi$, $B^0 \rightarrow 3\text{-body}$, $B_s \rightarrow KK$, $B_s \rightarrow K\pi$, $\Lambda_b \rightarrow pK$, $\Lambda_b \rightarrow p\pi$)

Current PID Performance

- PID performance evaluated from data
 - Genuine $\pi/K/p$ samples identified from kinematics only

for Run2

Upgrade PID performance

- Probability for pion to be misID as kaon Vs kaon ID efficiency
- Average PID in the 2-100 GeV/c range for different DLL cuts
- Improved performance obtained for upgrade configuration