KEK Preprint 95-62
June 1995
A

Recalibration of Position Monitors with Beams

K. SATOH and M. TEJIMA

500 953 0

*Presented at the 1995 Particle Accelerator Conference and
International Conference on High-Energy Accelerators,
May 1 - 5, 1995, Dallas, Texas, U.S.A.*

National Laboratory for High Energy Physics, 1995

KEK Reports are available from:

Technical Information & Library
National Laboratory for High Energy Physics
1-1 Oho, Tsukuba-shi
Ibaraki-ken, 305
JAPAN

Phone: 0298-64-5136
Telex: 3652-534 (Domestic)
(0)3652-534 (International)
Fax: 0298-64-4604
Cable: KEK OHO
E-mail: Library@kekvax.kek.jp (Internet Address)

RECALIBRATION OF POSITION MONITORS WITH BEAMS

Kotaro Satoh and Masaki Tejima, National Laboratory for High Energy Physics, Oho 1-1, Tsukuba, Ibaraki 305 Japan

Abstract

This paper proposes a method to find the geometrical center of a position monitor from its beam signals. The method will be useful for accelerators where the optics is very sensitive to the orbit. Beam-test results are also presented.

I. INTRODUCTION

A beam-position monitor system is operated for two kinds of orbit measurements: a relative measurement and an absolute measurement. The former is used to measure the orbit displacement from the initial or standard orbit when some optics perturbation is applied. The latter case is to measure the orbit position relative to the geometrical monitor center. This function will be essential for maintaining stable operation in a ring where the optics depends strongly on the orbit, particularly at nonlinear optics elements. The dependence will surely appear in future B-factories, where strong sextupole magnets are to be installed and a small vertical emittance is required.

The output data from a position monitor system usually show the orbit position relative to the electric monitor center, not the geometrical center. The electric center, however, may drift due to an unpredictable imbalance among the output signals from the pick-up electrodes, because they must travel through separate paths, cables, connectors, attenuators and switches, and are then measured by detectors.

This paper proposes a method to estimate the imbalance and to find the geometrical monitor center from four output signals of a pick-up unit. It should be noted, however, that the method is not workable in monitor systems where the number of output signals is less than four, as in an AM/PM system.

II. MODELING OF OUTPUT DATA

Consider a pick-up unit having four electrodes and four processed output data (V_i 's), as shown in Fig.1. The data can be given by

$$V_i = g_i \cdot q \cdot F_i(x, y), \quad i = 1, 2, 3, 4,$$

where q measures the beam charge, and x/y are horizontal and vertical displacements of the beam relative to the geometrical monitor center. The functions $F_i(x, y)$ stand for the response of four electrodes, and are normalized as $F_i(0,0)=1$. Hence, the origin of arguments of the response function defines the geometrical center. No symmetry condition is required among the response functions. The g_i 's indicate the overall gains of each electrode. Notice that g_i also includes the impedance imbalance through

vacuum connectors, and the capacitance imbalance among electrodes, and that the present idea can be applied to the calibration of a pick-up unit itself for modeling its response function.

Figure 1. Model monitor system.

Further analysis is based on two assumptions. One is that the response functions never change, and can be well known by calibration or a calculation. Since the response function depends only on the geometrical structure of the pick-up unit, this assumption is reasonable. The second assumption is that all of the effects which displace the electric center can be included into the g_i 's. This assumption is acceptable, at least in a case when the signals are processed with a narrow frequency-band monitor system.

The objective of this paper is to show a possible way to estimate the gains and to recover the geometrical center.

III. GAIN ESTIMATION

Consider the case when the beam positions are measured m times with a pick-up unit, and at each measurement the orbit at the monitor is intentionally changed, for example, with steering magnets. The beam charge may be varied at each measurement, although the variation is not important for a gain estimation. Then, the data from the i -th electrode at the j -th measurement can be given by,

$$V_{ij} = g_i \cdot q_j \cdot F_i(x_j, y_j).$$

Based on the fact that only the relative imbalance among the gains contributes to shifting the electric monitor center, g_1 can always be set to 1 with a proper scaling factor for the beam charge. This means that there exist only 3 unknown gains (g_2, g_3 and g_4). At each measurement, although 3 unknown parameters (q_j, x_j and y_j) are generated, 4 quantities (V_{1j}, V_{2j}, V_{3j} and V_{4j}) can be measured. After the m -th measurement the number of unknown parameters is $3+3m$, whereas that of the known parameters

is 4m. When m is larger than 4, the latter number exceeds the former, and, hence, the unknown parameters, including the gains, can be estimated using a nonlinear chi-square method [1].

The present nonlinear model is rewritten as

$$\begin{aligned} V_{ij} &= g_i \cdot q_j \cdot F_i(x_j, y_j) \equiv V(i, j; \mathbf{a}), \\ i &= 1, \dots, 4, \quad j = 1, \dots, m, \\ \mathbf{a} &= (g_2, g_3, g_4, q_1, x_1, y_1, \dots, q_m, x_m, y_m), \end{aligned}$$

where $\mathbf{a}$ is an array of fitting parameters. The unknown parameters can be estimated by minimizing the chi-square,

$$\chi^2(\mathbf{a}) = \sum_{i=1}^4 \sum_{j=1}^m \frac{[V_{ij} - V(i, j; \mathbf{a})]^2}{\sigma_{ij}^2},$$

where σ_{ij}^2 is the data error of the i-th electrode at the j-th measurement. For simplicity, the data errors are assumed to be the same as $\sigma_{ij} = \sigma_0$.

The curvature matrix ($[\alpha]$), defined by

$$\alpha_{k\ell} \equiv \frac{1}{2} \frac{\partial^2 \chi^2(\mathbf{a})}{\partial a_k \partial a_\ell}$$

is very important, not only for performing the minimization, but also for determining the variance and the covariance of the fitting parameters. The covariant matrix ($[C]$) is just equal to the inverse of the curvature matrix at the minimum point. The diagonal element gives the variance of the estimated parameter in such a way that

$$\sigma^2(a_k) = C_{kk} = \alpha_{kk}^{-1},$$

and the off-diagonal element ($C_{k\ell}$) shows the correlation between a_k and a_ℓ .

IV. SIMULATION RESULTS

Imagine a circular pipe having four electrodes, as shown in Fig.2. This pick-up model has such a symmetry that all of the response functions can be expressed by only one function, $F_1(x, y)$.

$$\begin{aligned} F_2(x, y) &= F_1(-x, y), & F_3(x, y) &= F_1(-x, -y), \\ F_4(x, y) &= F_1(x, -y). \end{aligned}$$

Figure 2. Circular pick-up unit model.

If the electrode dimensions are chosen so as to be sufficiently small, the response function can be given by the

wall-current distribution at the electrode location. With a pipe radius of b , the response function to the 3-rd order is

$$\begin{aligned} F_1(x, y) &= 1 + \frac{\sqrt{2}}{b}(x + y) + \frac{4}{b^2}xy \\ &\quad + \frac{\sqrt{2}}{b^3}(-x^3 + 3xy^2 - y^3 + 3x^2y). \end{aligned}$$

In simulations the pipe radius is 50 mm. The first step is to give reasonable values to the gains as well as to the charge and displacements at each measurement. The relative gains (g_2, g_3 and g_4) are typically not far from 1. A simulating measurement is done at 5 or 9 displaced positions, as shown in Fig.3. The charge (q_j) is chosen to be around 1 with proper scaling. The second step is to calculate output data from the model monitor using the assumed response functions. Finally, estimations of the gains and beam parameters at each measurement is carried out, based on the simulated data, with the chi-square method. At the same time the variance of the estimated parameter is obtained.

Figure 3. Orbit displacements at the model monitor.

The simulation results are summarized in Table.I, which show values given to relative gains and displacements, and the variance of each parameter. With an expected error of $\sigma_0 < 10^{-3}$, which is estimated from the TRISTAN monitor system, the geometrical center can be found within 100 μm in Case 1 and Case 2. A further improvement can be seen in Case 4 with the nine-point measurement.

V. BEAM TEST

The present method was tested with a stripline monitor in TRISTAN. The measurement was performed with a single beam, an electron beam or a positron beam. The configuration of the four striplines and the monitor chamber is the same as that of the numerical model. The stripline monitor is 150 mm long, and its inner radius is 42 mm, which is the only necessary parameter for a position estimation.

Each stripline electrode has two output ports for ensuring signal directivity. The directivities of the four striplines may be different, and also dependent of the beam direction. In this experiment, not only the upstream port signals, but also the downstream signals, are analyzed.

This test provides an ideal setting to demonstrate the usefulness of the present method. The relative gains are

Table I

Preset values and simulation results for the variance of the estimated parameters.

Case 1 : m=5					
	g_2	g_3	g_4	q_j	x_j, y_j
preset	1	1	1	1	± 5.0 mm
σ/σ_0	5.5	7.7	5.5	3.9	98
Case 2 : m=5					
	g_2	g_3	g_4	q_j	x_j, y_j
preset	0.9	0.95	1.1	1	± 5.0 mm
σ/σ_0	5.0	7.5	6.1	3.9	100
Case 3 : m=5					
	g_2	g_3	g_4	q_j	x_j, y_j
preset	1	1	1	1	± 1.0 mm
σ/σ_0	25	35	25	18	440
Case 4 : m=9					
	g_2	g_3	g_4	q_j	x_j, y_j
preset	1	1	1	1	± 5.0 mm
σ/σ_0	3.3	4.7	3.3	2.6	63

different on the upstream and downstream sides. Due to the variation of the directivities, the range of the relative gains on the downstream side are wider than that of the upstream. An estimation of the beam position can be made using either the upstream or downstream data independently; the results are compared with each other.

The position measurement was made for 9 different orbits at the monitor. The signal detection was made with a narrow-band detector, sampling a 500MHz frequency component, with the help of a coaxial switch, choosing one among 8 output signals.

The test results are summarized in Table II, and shown in Figures 4 and 5. The directivity, the ratio of downstream/upstream, was 17~20%. The measurement error was not analyzed, but may be the same on the upstream and downstream sides, because the signal was detected with the same detector gain. With a typical relative error of 10^{-3} on the upstream side, the measurement error would be $\sim 3 \times 10^{-4}$, which is consistent with the difference between the positions estimated independently from the data on either side. The covariant matrix also shows a strong positive correlation among the estimated positions. This fact can be seen in the figures as an offset between the two sets of estimated positions.

The beam test was so successful that the present method will surely be helpful for finding the geometrical monitor center in future accelerators having the optics extremely sensitive to the orbit, for example, in the KEKB.

References

- [1] W. Press, B. Flannery, S. Teukolsky and W. Vetterling, Numerical Recipes (Cambridge University Press).

Table II

Estimation for gains and the variance of the fitting parameters in the beam test.

Electron beam					
Upstream					
	g_2	g_3	g_4	q_j	x_j, y_j
fit	1.045	1.031	1.037	~ 0.35	Fig.4
σ/σ_0	10	14	9.2	3.0	160
Downstream					
	g_2	g_3	g_4	q_j	x_j, y_j
fit	1.121	0.987	1.049	~ 0.065	Fig.4
σ/σ_0	57	73	49	3.0	880
Positron beam					
Upstream					
	g_2	g_3	g_4	q_j	x_j, y_j
fit	1.027	1.009	1.039	~ 0.25	Fig.5
σ/σ_0	12	17	12	2.4	200
Downstream					
	g_2	g_3	g_4	q_j	x_j, y_j
fit	1.068	1.043	1.032	~ 0.045	Fig.5
σ/σ_0	70	98	66	2.4	1100

Figure 4. Estimated positions with an electron beam.

Figure 5. Estimated positions with a positron beam.