CM-P00058423

EUROPEAN ORGANIZATION FOR NUCLEAR RESEARCH

ISR-300-GS/67-29

CERN LIBRARIES, GENEVA

CHARACTERISTICS OF TYPICAL ACCELERATORS

by

M. Hildred Blewett

(to be published in Annual Reviews of Nuclear Science, 1967)

Geneva - May 24, 1967

CHARACTERISTICS OF TYPICAL ACCELERATORS

by

M. Hildred Blewett

(to be published in Annual Reviews of Nuclear Science, 1967)

INTRODUCTION

The various categories of particle accelerators are distinguished, primarily, by the method of applying the electric field which provides the accelerating force. Electric fields are the only means used for acceleration since mechanical forces and gravitational fields are too weak and magnetic fields produce only a change in direction, although their use for this purpose is incorporated in several types of machines. Many kinds of charged particles can be accelerated : electrons, positrons, protons, deuterons, singly and multiply charged light and heavy ions, and even "ions" of metallic particles of diameters in microns. However, in the higher-energy machines, the particles to be accelerated are usually restricted to electrons and protons. Energetic (to several tens of MeV) beams of neutrons are obtained by bombarding suitable targets (D, Li, Be, etc.) with charged particles, usually electrons or deuterons.

The simplest type of electric field is provided by applying the required amount of voltage directly between two terminals. Not only was this the method in the first use of an accelerator in nuclear physics¹⁾, but even today well over half of all accelerators are of this direct-potential type, or modifications thereof. A semi-direct method of obtaining an electric field is used in the betatrons where a changing magnetic flux in the central core of a cylindrical electromagnet induces a circumferential electric field that accelerates the particles.

All other types of accelerators use various forms of radio-frequency electric fields, at relatively low voltages, that are

applied many times to the particles and are prevented from influencing them when the rf field is reversed. The application of the rf field can be made at many places along a straight path, as in the linear accelerators; or a magnetic field can bend the particles into a circular or spiralling path in order to pass one or several rf sources a large number of times as in the various types of cyclotrons and synchrotrons. The spatial distribution of the magnetic field determines the strength of the focusing forces on the beam during its acceleration. The methods of applying the accelerating field and the ways of using magnetic fields for bending and focusing are summarized in Table 1, together with the present maximum energy values. In the higher-energy machines, it is usual to find two, three, or more, accelerators in series, each serving as an injector for the next stage in energy.

Probably the prime motivation in the development in accelerators has been the desire for higher energies and, during the almost four decades of accelerator-building history, the maximum energy has risen by a factor of ten about every six or seven years. Detailed designs of proton accelerators have been made in the United States for 200 GeV²⁾ and in Western Europe for 300 GeV³⁾ and the start of their construction seems imminent; groups in both the United States and the Soviet Union have considered designs for 1000 GeV^{4,5)}. However, the reduction in the fraction of energy available in the center-of-mass system for the production of new particles and interesting reactions from high-energy particles hitting a fixed target has led, at the same time, to the demand for and construction of storage rings for colliding beams where the total kinetic energy of both beams is useful.

Along with the drive to higher energies, the need for greater precision in experiments and the search for rarer processes have emphasized the desirability of higher intensities in all types of accelerators. The strong focusing arising from the alternating-gradient principle, the better understanding of particle dynamics

and the extensive studies on space-charge effects have all contributed to obtaining and designing for higher intensities. New ion sources, particularly the duoplasmatron type, new rf power sources, and other technological improvements have resulted in beams of greater intensity, with smaller energy spread, beam size and divergence.

In recent years, accelerator literature has increased in volume to a fairly substantial level. Descriptions of most types of modern machines and their special components are presented in books by Livingood⁶⁾ and by Livingston and Blewett⁷⁾; more specialized theoretical treatments are available in books by Kolomensky and Lebedev⁸⁾ and by Bruck⁹⁾; somewhat more elementary treatises are those by Wilson and Littauer¹⁰⁾ and by Lapostolle¹¹⁾; a recent book by Livingston¹²⁾ includes many of the historic papers of accelerator development. Review articles on cascade generators, Van de Graaff generators, betatrons, cyclotrons, linear accelerators and synchrotrons appear in Volume 44 of the Handbuch der Physik¹³⁾. Many of the lower-energy accelerators are now produced commercially and their specifications and performance ratings are given in company brochures. Specific problems of construction and operation, of components, of possible new designs, etc., are treated in considerable detail in the reports given at various conferences that have been held on both a limited and a wide range of accelerator types; the proceedings of the most recent of these conferences are listed in the bibliography^{14,15,16,17,18,19)}.

DIRECT-VOLTAGE ACCELERATORS

The high voltage required for these direct potential-drop accelerators is obtained through two basic methods: (1) by means of electric circuitry as in cascade rectifiers and transformers or (2) by charging up a terminal through the actual transportation of charge as in electrostatic (Van de Graaff) generators. In general, accelerators of the former type are somewhat simpler and offer

higher average currents whereas the latter have been developed to give higher energies. Both provide beams of high precision with low energy spread and divergence.

Cascade-Rectifiers and Transformers

Simple transformer-rectifier circuits are sufficient for voltages up to 100-200 kV but higher voltages in cascade-rectifiers are reached through several stages of a voltage-doubling circuit. In such a circuit, two capacitors are charged on alternate half-cycles from an ac source then, with rectifiers acting as switches, double the voltage appears across the capacitors when they are connected in series. Voltages of 150 to 200 kV per stage are common and several-stage generators provide from a few hundred kV to 3 or 4 MV; an extra stack of smoothing capacitors filters the total voltage ripple to a few hundred volts. With an appropriate ion source and a carefully designed discharge tube, the resultant accelerator is sometimes called a Cockcroft-Walton generator. Currents up to 10 mA can be obtained in dc operation and over 100 mA pulsed.

Voltage multipliers can be operated with either polarity and higher currents can usually be obtained with electrons than with positive ions. The electron machines have recently found a new application in large electron microscopes, e.g., the 1.5-MeV generator for the microscope at Toulouse, France. With positive ions, they are prevalent as neutron generators, particularly through the $T(d,n)He^4$ reaction. Pulsed positive-ion machines are used as the first acceleration stage to feed the injector linacs of the large proton synchrotrons (cf. Table 9).

Conventional cascade rectifiers are available commercially from several firms, e.g., the Philips Company in Holland, from Haefely Limited in Switzerland and from Hitachi Limited in Japan. Neutron generators, operating at about 200 to 300 keV are obtainable from the Texas Nuclear Corp., Des Plaines, Illinois.

A somewhat different type of cascade-rectifier system is the "Dynamitron" manufactured by Radiation Dynamics, Inc., Westbury, New York. These units operate at high frequency (120-300 kHz) and use much smaller capacitors to produce accelerated beams of either electrons or positive ions up to 3 and 4 MeV. Some typical 3-MeV installations for research can be found at the University of Arizona, Brookhaven National Laboratory, Cornell University, University of Mexico, University of Mississippi, NASA Lewis Research Center, Cleveland, and the National Bureau of Standards has a 1.5-MeV Dynamitron. Other 3-MeV units are being prepared for Auburn University, Alabama and the University of Ottawa, Canada; 4-MeV units are in production for the State University of New York at Albany, N.Y., the University of Montreal, Canada, and the Technische Hochschule, Stuttgart, Germany.

Resonant transformers up to 1 MV have been in use for many years particularly in the production of X-rays in medical applications and radiography. Although they have been mainly supplanted by other sorts of high-voltage generators, electron beams of 1 and 2 MeV can be obtained with transformers such as those made by the General Electric Company for the Max Planck Inst., at Mühlheim, Germany; series units for 4 MV have also been produced.

A new type of transformer is the Insulating-Core Transformer made by High Voltage Engineering Company, Burlington, Mass., which can provide accelerating voltages for either electrons or positive ions up to 4 MV. It consists of a series of secondary windings excited by a sectioned core whose segments are insulated from each other. The ac output from each secondary is rectified and then connected to the others in series. The company is also applying the tandem principle (cf next section) to these machines in order to accelerate positive ion beams to about 8 MeV.

Characteristics of some of these DC accelerators together with those of the next section are given in Table 2.

Electrostatic (Van de Graaff) Generators)

In the Van de Graaff generator, charge from a low-voltage supply is sprayed on a rapidly moving belt of insulating material, from a row of corona points, and carried to a field-free region inside a spherical metal terminal. Here the charge is removed by another set of corona points and flows to the outer surface of the terminal. The potential of the terminal then rises, as the charge is carried there, until the process is stopped or breakdown occurs. The terminal is supported by an insulating column and voltage-dividing resistors connect intermediate planes along the column to provide a carefully controlled gradient.

Inside the terminal is located an ion source (or filament for electrons) and, after passing through focusing electrodes, the particles are guided into an accelerating tube inside the column where they are subject to the electric field. The whole is enclosed in a tank usually kept at a pressure of 10 to 25 atm of insulating gas such as nitrogen, freon, or sulphur hexafluoride. The structure may have either a horizontal or vertical axis.

Theoretically, any type of charged particle can be accelerated, the polarity of the terminal being dependent upon the polarity of the belt-charging system. Some machines are designed solely for electrons and with heavy-atomic-weight targets are a prolific source of X-rays; some are designed solely for positive ions and some have interchangeable polarity. The most common use for positive ions has been with isotopes of hydrogen or helium but heavier ions have also been accelerated, such as lithium, bromine, iodine and, recently, uranium.

Maximum constant potentials of 10 MV at the terminal have been reached but the majority of single-stage Van de Graaffs operate at from 1 to 6 MeV, with the possibility of varying the voltage down to 0.3 to 0.1 of the maximum. Voltage stability of 0.1 per cent is common and special controls can reduce this to a few hundred volts of ripple. The output beam can be either dc or

pulsed with pulse lengths of several microseconds, or special nano-second pulses can be provided.

The electron machines have currents of the order of 1 mA dc, and several hundred mA peak on pulsed operation, although currents as low as 10^{-10} A have been used for special purposes. The X-ray output for the 3 and 4-MeV electron machines is of the order of 1500 to 3500 R/min at 1 m. Positive-ion outputs are considerably smaller, of the order of tens of μ a dc but with higher peak values when pulsed. With light atomic-weight targets (frequently Be), neutron fluxes of about 10^{12} per second are obtained.

There are well over 500 Van de Graaff generators in operation in many countries and a very large fraction of these have been constructed by the High Voltage Engineering Corp., of Burlington, Mass. Some locations where the H.V.E.C. 5.5-MeV single-stage Van de Graaffs have been installed in the United States are : Columbia University, Iowa State University, University of Kentucky, Oak Ridge National Laboratory, Ohio State University, Pennsylvania State University, University of Pittsburgh, Rice Institute, University of Texas, University of Virginia; others are found in Canada, various countries in Europe and Asia and many more are in use for commercial and medical applications.

Energies for positive ions can be pushed into the tens of MeV range in Van de Graaff accelerators by using the tandem principle. Negative ions are accelerated from ground up to the high-voltage terminal where they are stripped of their electrons and then accelerated as positive ions by the same potential back down to ground. For simple ions the total energy is, thus, twice that of a beam originating at the terminal; in the case of heavier ions, multiple electron stripping can produce energies of $V(1 + n)$, where V is the terminal potential and n is the number of electrons removed from the neutral atom, e.g., uranium atoms of over 250 MeV have been produced in this manner. Three-stage tandems are also operating where negative ions are first accelerated in a separate

machine and then enter a two-stage tandem for two more accelerations. Currents in tandem Van de Graaff accelerators vary from about 0.1 to 10 μ A, although a few hundred μ A have been produced in development programs. For higher currents, the High Voltage Engineering Corp. has been using its Insulating-Core Transformer (cf previous section) to provide power in the first stage.

Over 40 tandem Van de Graaff accelerators are in operation in the world, again with the majority of them having been made by High Voltage Engineering Corp. Their latest "Emperor" model can probably attain 30-MeV and the one recently installed at Yale University has reached 24 MeV with currents of 10 μ A at 20-MeV and 25 μ A at 15 MeV. Machines similar to the one at Yale are being installed at the University of Minnesota, the University of Rochester and at the Chalk River Laboratory in Canada. The more conventional 12-MeV tandems can be found in the United States at Argonne National Laboratory, California Institute of Technology, Florida State University, University of Pennsylvania, Rice Institute, University of Wisconsin, and 15-MeV models are at Rutgers University and Stanford University. Three-stage tandems are located at Los Alamos Scientific Laboratory (15 MeV), University of Pittsburgh (18 MeV), University of Texas (17.5 MeV) and University of Washington (21.5 MeV). Other H.V.E.C. tandems can be found in many countries throughout the world. In England, 11.5-MeV tandems have been built by personnel of the Atomic Energy Authority and Vickers Limited; they are located at A.E.R.E., Harwell and at Aldermaston. These vertical machines provide protons and deuterons with currents up to 8 μ A at lower energies.

Another type of electrostatic generator is made by the SAMES Company of Grenoble, France. In this machine, the belt of the Van de Graaff is replaced by a ceramic cylinder revolving around its axis in an atmosphere of pure hydrogen. Charge is sprayed on one side of the insulating rotor, from several places to give uniform distribution, and then carried to collectors from whence it flows to a high-potential terminal. A semi-conductive stator

gives a smooth distribution of the tangential component of the electric field. Such a cylindrical generator of 16-in diameter, rotating at about 3000 rpm, can give about 50 mA currents at 800 - 1000 keV, but average currents are usually lower than this. Series units are made with voltages up to about 2 MV.

BETATRONS

Betatrions have been used exclusively to accelerate electrons (hence the name) and employ, as previously mentioned, the transverse electric field induced by a time-varying magnetic flux. It can be considered that the electrons behave somewhat like a secondary winding of many turns in a transformer. In structure, a central flux core is surrounded by a toroidal bending and focusing magnet between whose poles the electrons circulate inside a doughnut-shaped vacuum chamber for many hundred thousands of turns and with continuous acceleration during the whole period of action. As the flux inside the particles' orbit increases and they gain momentum, the magnetic bending field must also rise to provide sufficient centripetal force to keep the electrons in their circular paths of almost constant radius.

For stable operation, the average rate of change of the flux density within the particles' orbit must be twice the rate of change of the flux density at the orbit. At the same time, the guiding field must be shaped to provide proper focusing in both radial and vertical directions: it must decrease radially to give vertical focusing and yet decrease more slowly than $1/r$ (r = radius of the orbit) for radial focusing. With such a field pattern, the particles can have stable oscillations both radially and vertically about an "equilibrium" circular orbit; it is customary to call these oscillations "betatron" oscillations and they also occur in other types of circular accelerators.

Betatrions usually operate at about 200 cps with an acceleration period of about 10 ms, and the magnet, made of transformer laminations, is resonated with a capacitor bank. The injector is a simple gun spraying the electrons at 50 - 100 keV, in a direction tangent to their orbits, into the vacuum chamber. The fully accelerated beam can either hit an internal target or it can be extracted with the use of magnetic shields. Intensities of the resultant X-rays can be from 100 to 20,000 R/min at a meter from the target.

Since relativistic electrons moving on a circular path radiate electromagnetic energy, and this loss disturbs the relationship between average flux and orbit flux density, there is an upper limit to the energy achievable in a betatron. Most machines of this type operate at around 25 MeV where this loss is not noticeable, but special compensation can be added and, at the University of Illinois, a 320-MeV betatron has been in operation for many years; this is probably the practical maximum.

Betatrions have been made commercially by several firms, e.g., General Electric Co. and Allis-Chalmers Co. in the United States, Philips Company of Holland and Brown-Boveri Co. of Switzerland. Characteristics of some typical betatrions are shown in Table 3. These accelerators have been widely used in medical and radiological applications but, in nuclear physics, in recent years they have been supplanted by electron linear accelerators and synchrotrons. In the lower-energy ranges, however, they are relatively inexpensive and simple in operation.

CYCLOTRONS

Classical Fixed-Frequency Cyclotrons

The classical cyclotron is a positive-ion accelerator where a constant-frequency rf field is produced between the gaps of two hollow D-shaped electrodes ("dees"), each of which covers almost half the area of the cylindrical poles of an electromagnet. The

magnetic field is constant in time and is almost uniform over the region between the poles but decreases slightly with radius, for focusing.

As in all types of accelerators where particles of mass m and charge e , are kept on a circular path of radius r by a magnetic field of flux density B , the electromagnetic force must at all times balance the centrifugal force, i.e.,

$$\frac{mv^2}{r} = e v B.$$

Thus, the angular velocity, $v/r = eB/m$, i.e., it is independent of the radius and of the particles' energy. With this condition, if an rf field of frequency

$$f = \text{the frequency of rotation of the particles} = \frac{eB}{2\pi m}$$

is applied between the dees, those particles which arrive at the gap at an accelerating phase will continue to do so while they travel on orbits that are half circles of ever-increasing radius.

From the resonance relations given above, it can be seen that, for a given magnetic field and a given fixed frequency, a cyclotron can accelerate all particles which have the same charge-to-mass ratio, i.e., if it is designed to give 20-MeV deuterons, it can also accelerate helium ions to 40 MeV and protons in the form of single-ionized molecular ions to 10 MeV.

The charged particles originate in a suitable ion source located near the center of the accelerator. They are accelerated by voltages of 100 to 500 kV across the dees at frequencies that are usually between 10 and 20 MHz. Internal currents from 0.1 to 1 mA are common and, by means of simple deflectors inserted to act on the final turn, from about 10 to 25 percent can be extracted for external use.

There is an upper limit to the energy attainable in a classical cyclotron that is due to two effects: first, since the magnetic

field must decrease slightly with radius to give good focusing, when the particles reach larger radii they tend to fall out of resonance with the accelerating field; second, as the particles' energy increases, the relativistic increase in their mass will also make them fall out of resonance. By increasing the dee-to-dee voltage and, thus, decreasing the number of revolutions required to reach maximum energy, both of these effects can be somewhat alleviated. Although about 30 MeV for protons is a theoretical design limit, the maximum that has been reached is about 25 MeV with 500 kV on the dees. Both the synchrocyclotron and the more recent azimuthally-varying-field cyclotrons can circumvent these difficulties (cf next sections).

About ten years ago, there were about 80 fixed-frequency classical cyclotrons reported to be in operation or under construction in various countries. Since that time, quite a number of these have been converted into the AVF type and, for many others, designs for such conversion are under consideration. In Table 4 are listed typical characteristics of some classical cyclotrons presently in operation in the United States.

Classical cyclotrons have the advantage of relatively low cost, simplicity and reliability for beams of good intensity but of relatively large energy spread and beam size. Modern technology would be able to provide beams of better quality through the various types of feed-back systems which have been developed but modification programs for these machines usually include the addition of AVF focusing to provide higher energy and greater flexibility in the variation of energy and type of particle.

Synchrocyclotrons

After the discovery of the phase-stability principle, independently by McMillan and Veksler in 1945^{20,21)}, it was realized that the accelerating frequency of a cyclotron could be slowly decreased to match the decreasing frequency of revolution of the particles, due to the relativistic effects mentioned above, and the

particles would make stable oscillations about an "equilibrium" phase of the rf system. The behaviour can be described as follows: the particles which arrive at the accelerating field at such a phase that they receive too much energy will travel on a path with larger radius than an "equilibrium" particle, will take longer to arrive the next time and will be later in phase; those that arrive at a phase that gives them too little energy will move on a path of smaller radius than an "equilibrium" particle and on the next turn will arrive earlier. Thus, if the equilibrium phase is chosen on the falling side of the rf wave, i.e., between 90° and 180° , the off-phase particles will return at phases more nearly correct and stable motion will result.

Such phase stability made it possible to push the energy of the synchrocyclotron (sometimes called a frequency-modulated cyclotron or, in the U.S.S.R., a phasotron) into the range from one to several hundred MeV. About a dozen were constructed, with the largest around 700 MeV, and some of their characteristics are shown in Table 5. However, the great size of the cylindrical magnet and the difficulties in rf tuning in the synchrocyclotron, followed by the success of the early proton synchrotrons, made the latter seem more suitable for the billion-volt range of energy.

With the variation in frequency over the accelerating period, it is not possible to have the continuous operation in the synchrocyclotron that exists in the fixed-frequency machines. They must be pulsed and, therefore, the output currents are considerably lower: of the order of a few μA for internal beams and about 10 percent of this, or less, for extracted ones. The accelerating systems in the synchrocyclotrons operate at much lower voltages (tens of kV) which is applied to a single dee. But the system must be resonant over a fairly wide frequency range, dropping in some cases to about 60% of the initial value. This tuning is provided by either a rotating condenser or a vibrating-reed type of capacitor. These mechanical variations in capacity are repeated at rates that are usually a few hundred per second and determine the beam's pulse

rate in the accelerator.

The synchrocyclotrons, like the cyclotrons, are used only with positive ions, usually protons. However, in some of them, changes in frequency of the rf system can provide for acceleration of other ions. For example, in the L.R.L. synchrocyclotron, by changing the frequency range from that shown in Table 5 to the range 18 - 13.5 MHz, and with 6 kV from dee to ground, this machine can accelerate deuterons to 460 MeV, α -particles to 910 MeV and He^3 ions to 1140 MeV.

The beam in a synchrocyclotron follows a spiralling orbit which has a much smaller increase in radius per turn than in the fixed-frequency cyclotrons so that the extraction method is more complicated. Basically, it consists of adding perturbing magnetic fields near the maximum radial position which induce large oscillations in the accelerated beam so that it can then enter a suitable deflector. In some cases, the beam is merely scattered out but then the intensities obtained are quite low.

Most of the synchrocyclotrons shown in Table 5 are some 15 to 20 years old but modification programs are being planned for many of them utilizing developments that, over the past decade, have shown ways for increasing performance in beam intensity and quality. First, the general knowledge, from theory and measurements, of the behavior of charged particles in the various types of cylindrical accelerators has increased enormously, giving understanding of the effects of magnetic-field disturbances, space-charge effects, etc., which may lead to beam loss. Second, the early success of the AVE cyclotrons showed the power of this type of focusing and corroborated theoretical calculations on relevant beam dynamics; the behavior of particles in magnetic fields with complicated patterns could be quite accurately predicted.

Reports on the plans at various synchrocyclotron laboratories for redesign and improvements have been presented at the latest conferences^{16,17)}. These modifications fall into three main categories: (i) the addition of a certain amount of sector focusing,

usually not enough to make the synchrocyclotron isochronous but added in various locations to improve focusing conditions; (ii) the installation of a higher intensity source and modifications to improve the initial capture and prevent beam loss in the early revolutions; (iii) the redesign of the mechanical tuning system to give considerably higher repetition rate and the ability to withstand higher dee voltage.

Isochronous, Azimuthally-Varying-Field (Sector-Focused) Cyclotrons

There is another method of overcoming the energy limitations in the classical cyclotron. With a fixed frequency the resonant conditions would hold, as the particles' mass increased relativistically, if the magnetic field increased with radius. For a field that is constant in azimuth, such a radial increase would give axial defocusing but, as early as 1938, Thomas²²⁾ had suggested that axial focusing could be obtained through azimuthal variations in the magnetic field. However, with the development of the frequency-modulated synchrocyclotrons, except for some modest attempts, these ideas were not followed up until after the introduction of the alternating-gradient magnetic field in the high-energy proton synchrotrons. With this method of producing strong focusing in both radial and axial directions, and with the development of methods for numerical calculations of the detailed behavior of charged particles under the influence of magnetic fields that are complicated functions of three-dimensional space, truly isochronous cyclotrons with variable energy and for acceleration of many types of particles were designed, built and operated successfully. There are now over 40 in operation or under construction, with a top energy still below 100 MeV; a number more are in various stages of design for energies up to almost 1000 MeV and for high intensities (meson factories)¹⁷⁾.

The AVF cyclotron has a much more complicated mechanical structure than other cyclotrons in order to provide the required large variations in magnetic field. The magnet, still cylindrical, has two main forms of geometry: the radial-sector type has three,

four or more, almost triangular-shaped radial hills separated by valleys of about the same size and shape; the spiral-ridge type has somewhat narrower hill sections spiralling out from the center toward the edge of the magnet, with a spiral angle of magnitude between 30° and 70° , differing from one machine to another.

The variability for both energy and for ions of different charge-to-mass ratios is a very useful feature in the AVF cyclotrons but this requires changing the distribution of magnetic fields. In most cases this is done by changing the currents in a fairly complex arrangement of pole-face windings and sets of hill and valley coils. In some machines other methods are used, e.g., the AVF cyclotron at the University of Manitoba has no auxiliary coils but controls the magnetic-field shape through temperature-controlled Invar blocks and movable center plugs; at Orsay, partial adjustment is made through the use of materials of different permeability.

This versatility for energy and particle also requires similar variability in the acceleration system. Some machines can be tuned over a wide frequency range, about 3:1, others operate at a multiple of the particles' revolution frequency. The dee structure in some cases is similar to that in conventional cyclotrons, but in others it is specially shaped and fitted into the valley regions.

Extraction of the beam from an AVF cyclotron appeared at first to be difficult since the particles' orbits are very close together at the outer edge of the magnet, but two general methods have proved successful. The first circumvents the problem by accelerating negative hydrogen ions; a thin foil is inserted at the radius corresponding to the desired energy, the negative ions are stripped of charge to become positive and then the reversed curvature of their orbits brings them out of the machine. This method has been very successful but more intense negative-ion sources are needed to reach better intensity values. The second method depends upon the proper inclusion of disturbing magnetic fields which can cause the beam to build up resonant oscillations and, thus, provide sufficient separation between successive

revolutions for the insertion of a deflecting field. Efficiencies of extraction by this method can be 100% although, in practice, are somewhat less.

By means of modern methods for stabilizing both the magnetic fields and the frequency and voltage of the rf system, high-quality beams are obtained from the AVF cyclotrons. Typical values for energy spread are about 0.3% and emittance values (beam size times divergence) about 15 mm-mrad.

Characteristics of some typical AVF cyclotrons now in operation are given in Table 6. Several commercial firms construct this type of accelerator, e.g., the Cyclotron Corporation and Allis-Chalmers in the United States, the Philips Company in Holland, the Compagnie Générale de Télégraphie sans Fils (CSF) in France, Allgemeine Electricitats-Gesellschaft (AEG) in Germany. Fairly complete status reports on existing machines, designs planned and a general summary are given in the proceedings of the Gatlinburg Conference¹⁷⁾.

In addition to the cyclotrons shown in Table 6, the following are either in operation or scheduled for completion before the end of 1967:

in the United States - Brookhaven National Laboratory, 40 MeV (60-in. conversion); University of California, Berkeley, 18 MeV He³; University of California, Davis, 75 MeV; University of California, Los Angeles, 50 MeV; University of Colorado, 30 MeV; Duke University, 15 MeV (for injection into a tandem Van de Graaff); University of Illinois, 15 MeV; University of Michigan, 37 MeV; Texas A and M University, 60 MeV; U.S. Naval Radiological Defense Laboratory, 95 MeV; U.S. Naval Research Laboratory, 75 MeV; Washington University, 29 MeV;

in other countries - Santiago, Chile, 11 MeV; Grenoble, France, 60 MeV; Saclay, France, 29 MeV; Juelich, Germany, 90 MeV; Amsterdam Free University, Holland, 33 MeV; Delft, Holland, 12 MeV (the first AVF cyclotron); Philips Research Laboratory, Holland, 30 MeV; Amersham, U.K., 25 MeV; Birmingham University, U.K.,

12 MeV; Alma Ata, U.S.S.R., 50 MeV; Dubna, U.S.S.R., 14 MeV. Recently, approval was given for a 500-MeV AVF cyclotron of high intensity (meson factory) to be built at the Swiss Federal Institute of Technology, Zurich.

Microtrons

The microtron (sometimes called an electron cyclotron) was first proposed by Veksler in his paper on phase stability. It is an accelerator for electrons with a uniform, constant magnetic field, and a constant high-frequency (about 3000 MHz) accelerating field. The particles' orbits are circles of increasing radius whose centers moved across the magnet's diameter, but they have a common tangent point where the accelerating field is located. If the energy gain per turn is so adjusted that on each successive revolution the particles take one rf period longer to return than on the previous one, they can then be accelerated again and the motion is stable in phase; the time of revolution in the first orbit must also be an integral number of rf periods.

An important parameter in the microtron is the ratio of the energy gain per turn to the rest energy of the particle and, in existing machines this ratio has a value of the order of unity. This constitutes a basic difference between this type of accelerator and the other phase-stable circular machines where this ratio is very small. It is also the reason why the microtron has been used only to accelerate electrons whose rest energy (511 keV) is smaller than that of positive ions. To provide these large increments in energy, the accelerating system consists of a resonant cavity with a high-power microwave generator, frequently a magnetron of 100 - 200 kW.

Focusing of the electrons occurs as they pass through the electromagnetic field of the rf cavity whose apertures for beam passage must be properly shaped for good performance. Thus, it is not necessary for the field of the magnet to decrease with

radius as in the cyclotrons and betatrons. But the magnetic field, which is usually quite low in magnitude (around 2 kG), must be extremely uniform with the permissible degree of inhomogeneities being inversely proportional to the square of the number of orbits. This number in existing machines varies from about 10 to 30.

However, at the University of Western Ontario, Canada, a "racetrack" microtron has been built which incorporates field-free spaces in its magnet along four chords that radiate from the common tangent point of the orbits and the edge fields provide focusing forces.

One advantage of the microtron lies in the relative ease of extraction of the accelerated beam. At the point opposite the cavity, the orbits are quite well separated by a distance that is usually about 3 cm; this distance is proportional to the rf wavelength. Thus, a simple magnetic shield can be inserted and the extraction efficiency is close to 100%. Care must be taken that the main magnetic field is not distorted unduly by the shield. Intensities in these machines are high, ranging from about 30 to over 100 mA, with pulse lengths of a few μ s. Energy spread is of the order of a few tenths percent, beam diameters of 5 mm or less, and divergences of a few mrad.

There are not many microtrons in existence and Table 7 lists characteristics of most of them. Two, those at Lund University and the Lebedev Institute, are used as injectors for electron synchrotrons; the 30-MeV one at Dubna is used as an injector for a pulsed fast-neutron reactor. The highest energy reached, as yet, is 32 MeV. Inherently, this type of accelerator could reach higher energies but this would require a larger number of orbits and a larger magnet with even higher tolerances on the field. But the "racetrack" design may lead to machines of higher energy. Of course, more power in the accelerating cavities would also help and perhaps some of the developments in superconducting linac cavities can be useful, not only to increase the energy but to increase the pulse length for higher average intensity.

LINEAR ACCELERATORS

Linear accelerators (frequently called "linacs") are used to accelerate electrons, positrons, protons and heavy ions. The particles reach their final energy after only a single passage through a structure which is, essentially, a long cylindrical cavity where the axial component of a high-frequency electromagnetic wave provides the accelerating force.

Such axial electric fields exist in a cavity excited in the TM_{01} waveguide mode where the maximum electric-field strength occurs on the axis and then falls to zero at the walls. At the same time magnetic fields, in planes normal to the axis, increase from small values on the axis to maximum strength at the walls and the external rf power sources are coupled to these magnetic fields through loops, or other devices, in order to excite the system. To attain the high energies desired in a structure of moderate length, the accelerating fields in the waveguide cavity must be of the order of several MV per meter and the power inputs must be on the megawatt scale. Along with these high electric fields, the correspondingly high magnetic fields give rise to currents that flow in the walls and they are responsible for large power losses. The high cost of the components needed to provide these high levels of rf power makes the linear accelerator relatively expensive compared with circular machines for the same energy.

One great advantage of the linear accelerator is the ease of extraction of the beam at its high-energy end and these emergent beams are well collimated in the forward direction with small spreads in energy. Another advantage is that the energy of a linear accelerator can be increased by adding on extra sections or, with electron linacs the addition of more power sources can increase the energy per unit length.

Linear accelerators can be operated with either standing-wave or traveling-wave patterns; however, in practice one finds the

former in the machines for protons and heavy ions and usually the latter in those for electrons. But the structure of the waveguide depends on whether or not the particles are highly relativistic. Since electrons reach very nearly the velocity of light at fairly low energies (at 1 MeV, about 0.94 c) they can travel in step with an rf wave whose velocity is constant along the length of the accelerator; protons and heavy ions travel much more slowly and do not reach constant velocity until they have energies in the GeV range. Thus, the construction is quite different for electron linacs and proton (and heavy ion) linacs.

Electron Linear Accelerators

With the traveling-wave system that is common for electron linear accelerators, the phase velocity of the wave, i.e., the velocity at which the field pattern progresses along the pipe, must be made equal to the velocity of the particles. But the phase velocity in empty waveguides is greater than the velocity of light and so must be decreased by loading the system. This is done by adding a series of annular disks (irises) with their centers along the line of the beam; their dimensions and spacing determine the degree of modification. It has already been mentioned that electrons rapidly reach the velocity of light so that, for energies above 1 or 2 MeV, all sections of the accelerator can be made to have phase velocities equal to c. This results in a fairly simple form of construction. The constant velocity also means that the whole accelerator can operate, although at reduced energy, should the rf excitation fail in one section, or sections can remain unexcited if variation in energy is desired. But the phase velocity must be held very accurately for the electrons to remain at an accelerating phase of the rf wave and this requires high mechanical tolerances and precise control of operating temperatures.

It is desirable that the rf frequency be as high as possible since the losses per unit length decrease in proportion to the

square root of the frequency. But with higher frequency, the diameter of the accelerating cavity decreases and, consequently, the aperture available to the beam. Frequencies up to about 3000 MHz result in suitable beam apertures and, for historical reasons, several electron linacs in the United States operate at 2856 MHz.

The rf power is usually provided by klystrons with outputs around 20 MW peak; such a klystron can excite axial fields of about 10 MV per meter in a section of waveguide 3m long. A very large fraction of this power goes into rf losses in the cavity but, for high currents, the amount of power required by the beam itself is not negligible, e.g., 100 mA at 100 MeV needs 10 MW. Thus, with a fixed amount of power available, the top energy with a beam is lower than the nominal peak energy under no-load conditions. Also because of the high power levels, the duty cycle (fraction of time when beam is produced) is low. Pulses are usually of a few μ s duration but with a repetition rate of several hundred per second; nanosecond pulses are also provided in some cases, particularly for neutron studies. In many machines, it takes almost a microsecond to build up the accelerating fields in the cavity.

Injection into an electron linac is from a conventional electron gun at energies of a few tens of kV. Following the injection, most designs have a section with an increasing accelerating field where the beam becomes bunched around a particular value of phase and increases in energy to several MeV. The following sections, all alike as mentioned above, have constant accelerating fields. Typical dimensions for these sections, when excited at 2856 MHz, are a diameter of 8.25 cm with irises spaced 2.3 cm apart having a central hole of 2.1 cm diameter for passage of the beam.

For producing high energies in electron linacs, most designs are based on the work of the group at Stanford University who first successfully operated an electron linac (the Mark III) in the 1-GeV range; this machine is to be increased to about 2 GeV

during 1967-8. Also at Stanford, at S.L.A.C., the construction was recently completed of the two-mile-long linac which reached its design energy of 20 GeV early in 1967, the highest energy for electrons in any type of accelerator; with the addition of more power sources, this machine can reach about 40 GeV in a second stage of development. Linacs similar to the Stanford 1-GeV accelerator have also been built for 1.3 GeV at Orsay, France (it is also to be increased to 2.35 GeV during 1967) and for 2 GeV at Kharkov, U.S.S.R. Some of their pertinent parameters are shown in Table 8.

Since the 20-GeV accelerator at S.L.A.C. is unique and is the most recent achievement in accelerator technology, a little further description will be included. It is almost 10,000 ft long, is composed of 960 sections and power is provided by 245 klystrons, each rated at 24 MW peak. The phasing of the klystrons throughout the length of the machine is corrected through the use of the beam itself as reference. Each four sections are mounted on a 40-ft long girder which not only supports the structure but also contains a "light pipe" that is part of the alignment system. This uses a laser beam whose source is located at the end of the accelerator, it is detected near the injector and can be intercepted by retractable Fresnel targets located at the end of each girder. From measurements of the displacement of the laser beam at the targets and adjustment to the girders through jacks, the accelerator was aligned to ± 0.5 mm.

Injection is from an electron gun at 80 kV and the pulse length and current can be selected, from pulse to pulse, from 3 sets of predetermined values so that beams of different pulse lengths and intensities can be accelerated. A triggering system for the klystrons can also provide variable energy and pulse rate. Thus, experiments with different requirements can be carried out during the same period of time. After injection, there are three special sections all fed by a single klystron for phase synchronization: a pre-bunching cavity, one where the beam is bunched in

phase, and another 10-ft long cavity where it is accelerated to about 30 MeV. At the end of each 333-ft length of the accelerator, there is a special section where focusing and steering magnets are located together with beam-observing equipment.

Although this machine first operated successfully at almost full energy with about half of its design intensity of 50 mA (peak), early attempts were unable to increase the intensity and the beam appeared to be breaking up in the higher-energy sections. Similar phenomena had been observed on some other linacs with high intensity. Further observations at S.L.A.C. have resulted in understanding the effect as being due to the excitation, by the beam itself, of transverse modes in the cavities which deflect the beam sideways. The addition of focusing quadrupoles has helped to reduce this effect and further modifications should result in the attainment of the design intensity very soon.

During the period of time when the 1-GeV electron linacs were being developed, many others were constructed for energies below 100 MeV, and for higher currents, in England, Europe, Japan and the U.S.A. They have been used extensively for producing neutrons, for X-ray production and radiographic work in medical and commercial applications. Some locations, other than those given in Table 8, where these lower-energy linacs are being used for physics research are: University of California, Livermore, 16 MeV and 30 MeV; University of California, San Diego, 20 MeV; M.I.T., 18 MeV (a standing-wave linac); A.E.R.E., Roskilde, Denmark, 10 MeV; Saclay, France, 30 MeV; University of Bonn, Germany, 20 MeV; Technische Hochschule, Darmstadt, Germany, 35 MeV; Tokyo, Japan, 25 MeV; A.E.R.E., Harwell, U.K., 30 MeV. They are also used as injectors for electron synchrotrons (cf Tables 10 and 13).

In the last few years, with the development of reliable high-power rf sources, several electron linacs with high currents have been built for energies above 100 MeV; an example is the one made by Varian Associates, Palo Alto, California, for the Frascati

Laboratory in Italy, to accelerate both electrons and positrons to almost 400 MeV for injection into the ADONE storage ring. Others are listed in Table 8. Still others are in construction including the following : at Oak Ridge National Laboratory, 150 MeV; M.I.T., 600 MeV; new injectors for the synchrotrons, DESY, 300 MeV and C.E.A., $\sim$ 100 MeV.

Several modern electron linacs are also used to accelerate positrons which are created by the electrons at lower energy through the insertion of a metal-foil converter. For example, at S.L.A.C., such a converter is placed after the first one-third of the linac's length and the positrons, which travel 180° out of phase to the electrons, can be accelerated to almost 15 GeV. At Frascati, the converter is inserted at the 65-MeV point, where electron currents are about 0.5 A, and this machine has successfully produced a 930- μ A positron beam at 347 MeV, with about 380 μ A inside a 1% energy interval.

Electron linear accelerators are built by several commercial firms, such as, Varian Associates in the United States, M.E.L. Equipment Limited and Vickers Limited in England, Compagnie Générale de Télégraphie sans Fils (CSF) in France, Philips Company in Holland, Mitsubishi Heavy Industries and Toshiba Electric Co. in Japan.

Positive-Ion Linear Accelerators

The much lower velocities of protons and heavy ions at million-electron-volt energies has already been mentioned and it would be extremely inefficient to try to load a waveguide structure in the same manner as that described for the electron machines. Such structures, however, might be suitable for acceleration of protons above a few hundred MeV. These low velocities give rise to many other problems so that proton linacs are much more difficult to construct and are more complex than those for electrons.

For this reason, the highest proton energy reached to date (1967) in a linear accelerator is 68 MeV at the University of Minnesota. However, a 100-MeV proton linac is being built as an injector for the 70-GeV proton synchrotron at Serpukhov, U.S.S.R., and is expected to be in operation very soon. Because of the ease of extraction and the well-collimated beam, other proton linacs are also in use as injectors for synchrotrons as shown in Table 9. Most of these machines have followed the design principles of the 32-MeV linac first operated at Berkeley²³⁾ and now at the University of Southern California. Studies for constructing machines for several hundred MeV have been undertaken at many laboratories and one for 200-MeV is to be part of the improvement program for the Brookhaven A.G.S. Recently, a group at the Los Alamos Scientific Laboratory has been designing a proton linac for 800 MeV, with high currents for use as a "meson factory", and approval of construction funds has just been granted (1967).

Existing linear accelerators for protons utilize standing-wave patterns which are set up in cavities many meters in length, excited in the TM_{010} mode where the axial field is uniform throughout its length. For shielding the protons during the time when the rf wave is reversed, a series of "drift tubes" is mounted along the axis and the particles are accelerated by the electric fields in the gaps between these drift tubes. As the particles' velocity increases, the drift tubes must also increase in length and they are specially shaped to provide proper field patterns at their ends and to reduce losses. However, this type of structure becomes quite inefficient for acceleration above 100 - 200 MeV and, in recent years, much study has been given to devising rf structures for proton linear accelerators above this energy. Since this report is mainly concerned with existing accelerators, the details of the various proposals for accomplishing this will not be given; it will merely be pointed out that structures of more complicated geometry will probably be used in the higher-energy sections of the proton linacs now being designed or contemplated for several

hundred MeV.

At the injection end of a proton linac, since the length of the drift tubes becomes very small and other types of construction and operating difficulties arise, it is advantageous to have the injection energy much higher than is the case for electron linacs. Therefore, proton machines use a pre-accelerator, frequently a Cockcroft-Walton generator at about 500 to 750 keV. However, at 750 keV the protons' velocity is still only 0.04 c and, at this phase velocity, the field inside the linac varies strongly over radial distances proportional to the square root of the frequency. To keep this variation small over an aperture large enough to accommodate the beam, the frequency of the rf wave is limited to about 200 MHz or less; in heavy-ion linacs, it is about 70 MHz. For frequencies of this value, the size of the accelerating structure is much larger than for electron linacs, e.g., at 200 MHz the cavity has a diameter of about 1 m and its length is about 50 cm/MeV. The copper walls, required to decrease rf losses, are sometimes quite thin and the cavity is supported inside a steel vacuum tank; in other linacs the cavity is made of copper-clad steel in a single-walled structure.

There is phase stability in proton linear accelerators with respect to a phase that is on the rising part of the accelerating field, i.e., between 0° and 90° , in distinction from the synchro-cyclotrons discussed earlier. This is because a particle which arrives at one of the accelerating gaps (between drift tubes) too soon, will receive less energy than one at the "equilibrium" phase and so it will take longer to reach the next gap where it will be more nearly correct; if it reaches the gap later than at the stable phase, it will gain too much energy and will arrive at the next gap sooner, again closer to the proper value. The closer the value of this stable phase is to 0° , the larger is the range of values that can be accepted and the larger is the fraction of the injected beam that will be accelerated but, on the other hand, values of stable phase near 90° require lower peak voltages for

the same rate of acceleration. Typical values that represent a compromise are around 60° with a phase-acceptance range resulting in about one-quarter of the injected beam being accelerated. To increase the acceptance, it is common to add a special "buncher" cavity between the injector and the linac.

It is essential to provide radial focusing in proton linacs. The electric-field pattern in the accelerating gaps is such that, as the protons leave a drift tube to enter the gap, the field is focusing but it is defocusing as they leave the gap to enter the next drift tube. Since the field is rising with time, the defocusing forces are the stronger. In modern proton linacs, alternating-gradient focusing is provided through the insertion of quadrupoles inside the drift tubes. Earlier machines used grids in the gap to change the field pattern but these are unsatisfactory since they intercept part of the beam and reduce intensity.

Just as in the electron linacs, operation of proton linacs is pulsed but the pulse lengths are usually longer, several hundred microseconds. Because of the low frequencies, the time taken to build up the accelerating field is of the order of 200 μ s. For some time, currents in proton linacs were dependent to a large extent on the ion sources feeding the pre-accelerator but modern developments have now resulted in ion sources giving several hundred mA and higher currents being accelerated in the linacs, e.g., the CERN 50-MeV proton linac has accelerated over 130 mA. However, this now gives rise to problems in the linac itself: firstly, space-charge effects may disturb the accelerating field and, hence, the beam's stability; secondly, beam-loading requires not only more power but may also disturb the rf fields.

Characteristics of most of the proton linear accelerators are shown in Table 9. The research machines are also used to accelerate polarized protons, e.g., the Rutherford P.L.A. can provide a beam of about 5×10^8 p/s with 50 to 60° polarization.

Linear accelerators for heavy ions are made with similar structures to proton linacs and two almost identical machines are in operation at the Lawrence Radiation Laboratory (called "Hilac") and at Yale University in the United States and one of somewhat different structure at Manchester University in England. They accelerate ions of masses up to about argon to energies of about 10 MeV/nucleon.

Injection into the Hilac is from a Cockcroft-Walton generator which gives about 70 keV/nucleon to the ions and the accelerator is divided into two sections. With the frequency of the rf wave at 70 MHz, the tanks are about 10 ft in diameter. In the first section, the ions are accelerated to about 1 MeV/nucleon and, between the sections, electrons are stripped by passage through a thin foil of beryllium oxide; the ions then enter the second section where they are accelerated to full energy. Recent developments allow the accelerators at L.R.L. and Manchester to accelerate ions to partial energy, by special tuning, to values between 4 and 8 MeV/nucleon.

In the Hilac, currents up to 50 μ A have been reached for D^2 , He^4 and to 10 μ A for N^{14} and O^{16} , with somewhat lower values for other ions. This machine operates with pulse lengths of 2 to 8 ms and up to 40 pulses per second.

SYNCHROTRONS

The word "synchrotron" appears first in the title of McMillan's paper on phase stability²⁰⁾ where he pointed out that, although the cyclotron was limited in energy because as the particles became relativistic their angular velocity changed, one could keep in step with this change either by changing the frequency of the accelerating fields or by changing the magnetic field, or both. As mentioned earlier in the discussion on synchrocyclotrons, particles arriving at the location of the accelerating field somewhat off the correct value in phase will tend to be corrected and

can keep in step with a changing frequency. Since rf techniques at that time would not provide the large changes in frequency necessary for the acceleration of electrons, McMillan proposed changing the magnetic field. If this is changed to keep in step with the particles' energy, the orbits are of almost constant radius and he pointed out that the magnet need only be ring-shaped, rather than cylindrical as in the cyclotrons, and its size and cost would be reduced. He proposed an electron machine for about 300 MeV (which was subsequently built, dismantled in 1959 and is now in the Smithsonian Museum) and forecast that this method could be used to obtain billion-volt energies for both electrons and protons. At approximately the same time, Veksler also realized these phase-stability properties²¹⁾ and made similar suggestions for this type of accelerator which, in the Soviet Union, is called a synchro-phasotron.

It has also been mentioned that, in circular accelerators, the magnetic field must provide focusing forces to keep the particles within the limits of the vacuum chamber and that such forces will result from shaping the magnet's poles to give a field that varies with radius. Synchrotrons fall into two categories: (1) weak-focusing, constant-gradient (CG) synchrotrons where a small negative radial gradient has a constant value in azimuth and (2) strong-focusing, alternating-gradient (AG) synchrotrons²⁴⁾ where large radial gradients alternate in sign with azimuth. In the weak-focusing case, it can be shown from the equations of motion of the particles that, for stability in both the radial and vertical directions, the radial-field index $\overline{n} = (dB/dr)(r/B)$ must have values between 0 and 1; usual values are near 0.7 to make the more expensive vertical size of the magnet gap smaller than its radial extent. In the alternating-gradient synchrotrons, the magnetic field changes by several percent per cm radially and such high gradients provide large focusing forces in one transverse plane but equal defocusing forces in the other. However, as in optical-lens systems, a "strong-focusing" combination can result

from an alternation of focusing and defocusing sections. In higher-energy synchrotrons, the annular magnet consists of many sections separated by field-free regions which are useful for injection, rf accelerating stations, for target locations, for beam observation and control mechanisms.

Electron Constant-Gradient Synchrotrons

Immediately after the discovery of the phase-stability principle, several electron CG synchrotrons were constructed for energies in the range 300 to 350 MeV (several have now been dismantled), primarily for the production of mesons. Somewhat later, two machines for energies over 1 GeV were completed at the California Institute of Technology, U.S.A. (the magnet was a quarter-scale model for the L.R.L. Bevatron) and at the Istituto Nazionale di Fisica Nucleare at Frascati, Italy. Characteristics of some of the machines still in operation are shown in Table 10. Further CG machines have not been built since the alternating-gradient design is less costly for higher energies and, for energies of several hundred MeV, the linear accelerator provides higher intensity and an easily extracted beam.

In the early electron synchrotrons, injection was from an electron gun at 50 to 100 keV and the first stages of acceleration were accomplished through betatron action. Small iron bars located inside the orbit provide a magnetic flux that changes with time to give a steady azimuthal accelerating field. These bars saturate at about the time the electrons reach the velocity of light (2 to 4 MeV) and then an rf field in a resonant cavity is applied at a frequency equal to or a multiple of the particles orbital frequency. In the higher-energy synchrotrons, special injectors provide sufficient energy that the betatron core is not necessary.

The annular magnet in these accelerators can be either H-shaped or C-shaped (usually with the open gap facing the center of the orbit); those which are pulsed many times a second are made of transformer laminations about 0.14 in. thick. Sometimes

the magnet is resonated with a shunt capacitor bank and driven either directly from the ac power lines or by a power-oscillator circuit. Others use grid-controlled rectifiers to discharge the capacitor bank into the magnet coils. The aperture between the magnet's poles, i.e., the region where a suitable magnetic-field pattern is available, is usually about 5 to 10% of the orbit radius in the radial direction and about half that vertically, e.g., in the Cal. Tech. machine, the aperture is about 18 cm by 7.5 cm.

With an internal target, the output of the electron synchrotron, like that of the betatron, is a continuous spectrum of x-rays. Targets may be inserted at radial locations that are either inside or outside the particles' orbit and the beam can be made to strike them by adjustment of the rf or of the magnetic field to produce either short or long bursts. The beam can also be extracted, if desired.

The loss of energy through radiation in electron circular accelerators has already been mentioned in the section on betatrons. This loss is proportional to the fourth power of the energy (but inversely to the first power of the radius) and its rapid increase appeared to set a limit on energy for circular electron machines. In the early versions of the electron synchrotron, there was only a single rf cavity, built into the vacuum chamber between the poles of the magnet and the voltage that could be applied was limited by breakdown in the cavity. But with the later addition of field-free regions between magnet sections, more cavities could be added. However, the discovery of the alternating-gradient method of strong focusing has led to the higher-energy electron synchrotrons being constructed of this design.

Proton Constant-Gradient Synchrotrons

The first accelerator to reach an energy above 1 GeV was a proton CG synchrotron, the Brookhaven Cosmotron²⁵⁾ and proton synchrotrons have been built only for energies in the GeV range since the synchrocyclotron can accelerate positive particles up to several hundred MeV.

Although the general principles of operation of an electron and a proton synchrotron are similar, the proton machines are much larger and more complex, with correspondingly greater difficulties in construction. With the low velocities of the protons, it is no longer possible to avoid the problems of varying the frequency of the rf accelerating system over a wide range, but it must be strictly controlled to keep in step with the particles as they gain energy. Those particles which are not of exactly the correct phase, but are oscillating both in phase and in energy, consequently execute radial "synchrotron" oscillations which can be several inches in magnitude (much larger than for electrons). In the early CG proton machines, the rf frequency was that of the frequency of revolution of the particles but, in newer accelerators, a higher harmonic is used and this reduces the size of the oscillations.

In order to accommodate the synchrotron oscillations and the betatron oscillations, already mentioned in the section on betatrons (the result of small errors in injection position, divergence and magnetic field), in the CG synchrotrons the aperture over which the magnetic field must be available is very large, several feet radially and several inches vertically, e.g., the L.R.L. 6-GeV Betatron has poles 5 ft wide and a gap height of 12 in. This is an H-shaped magnet with magnetic return paths on both sides of the particles' orbit; also H-shaped is the 35000-ton magnet at Dubna. The magnets for the machines at the Rutherford, Princeton and Saclay Laboratories have C-shapes with the open part of the gap facing away from the center. At the Argonne

Laboratory, the magnet has a "picture-frame" design, for giving higher fields which are radially uniform throughout the length of its octant sections and focusing in this "zero-gradient" synchrotron is achieved by the fields of the specially shaped ends of the octants.

These large magnets have stored energies, at full field, of tens of megajoules and rapid pulsing would require very large amounts of power. Also, the volts-per-turn which must be provided by the rf system is proportional to the rate of rise of the magnetic field. To simplify both systems, proton synchrotrons take about 1 second to reach full energy and are pulsed at rates of 10 to 20 per minute. Power for the magnet is supplied, in most cases, by an alternator, motor-generator, flywheel system. However, with the experience gained on other machines, the Princeton-Pennsylvania accelerator has a relatively smaller aperture and pulses 19 times per second; its magnet is part of a resonant circuit with large capacitor banks and chokes.

Since it is difficult to overcome the effects of eddy currents and other magnetic-field distortions at low values, the protons are first accelerated to several MeV by a pre-accelerator before injection. In the smaller CG proton synchrotrons, the injectors are Van de Graaff generators but the larger ones employ linacs; both types provide beams of low energy spread and small divergence.

Phase stability in the proton CG synchrotrons is, as in the synchrocyclotrons, on the falling side of the rf wave. Voltages of a few kV per turn are required and the rf accelerating systems frequently operate at a stable phase near 150° so must provide a peak voltage of twice this amount. Most accelerating units consist of a ferrite-loaded resonant cavity, continuously tuned by a bias magnetic field in the ferrite together with a high-power amplifier system.

Some characteristics of proton CG synchrotrons are shown in Table 11. Most of these have extensive experimental programs apread over wide areas outside the heavy shielding walls. Internal targets of various sorts produce bursts of secondary particles of either short duration for bubble chambers or long bursts for electronics experiments, in which case the magnetic field is kept constant ("flat-topped") over several hundred ms. The beam can also be extracted in short or long pulses with efficiencies of about 50 percent. One method displaces the beam inward by causing it to lose a small amount of energy through hitting a specially designed target. It can then enter an auxiliary deflecting magnet which bends it outward where it can be further deflected and emerge. These auxiliary magnets are frequently made in a C-shape with a return winding that is a thin septum covering the open side, thus only small deflections of the beam are required to bring it inside the magnet's aperture and if the beam is intercepted only a small part of it will be lost. If such a magnet is placed near the beam, current distributions in the outside winding can ensure that outside stray fields are negligible and do not disturb the beam being accelerated. Other methods of extraction use magnetic bumps in the orbit, made by rapidly pulsed coils and cause oscillatory behavior which can bring it into the auxiliary deflecting magnets.

Proton Alternating-Gradient Synchrotrons

The highest energies yet achieved in any accelerator have been in the proton AG synchrotrons. Two very similar machines are in operation at the Brookhaven National Laboratory, U.S.A. (top energy 33 GeV) and at the international C.E.R.N. Laboratory near Geneva, Switzerland (top energy 28 GeV). Both of these are about half a mile in circumference. Another synchrotron, also quite similar but larger (for 70 GeV), is almost completed in the Soviet Union, near Serpukhov. Pertinent characteristics of these and other existing proton AG synchrotrons are shown in Table 12; approval for one about 40 GeV, in Japan, has just been made (1967);

and others are under consideration in several countries. At present, there is no obvious limitation to the energy that can be reached with this type of accelerator, other than cost. A 200-GeV machine is in the beginning stages in the United States and plans for a 300-GeV one are under discussion in Europe. Recently, a 1-GeV "cybernetic" model has been built in the Soviet Union to test design ideas for a 1000-GeV accelerator.

With the strong focusing arising from the alternating magnetic-field gradients, the aperture required by the particles is much smaller than in the CG designs so that the cost per unit energy is reduced, e.g., in the Brookhaven A.G.S. the aperture is 7 cm vertically by 15 cm radially. In AG accelerators, the betatron oscillations have wavelengths that are only a fraction of the circumference (rather than almost equal to it as in CG designs) and care must be taken that the number of these oscillations per revolution is nonintegral. Otherwise the perturbing effects, of errors in alignment and magnetic field, would build up in resonance and the beam would be lost. The strong forces, although beneficial for focusing, require great precision of alignment (of the order of 0.1 mm) and uniformity (less than 0.1% variation) of the magnet sections to keep the beam stable and within the vacuum chamber. The group at Moscow hopes to control the beam automatically, through continuous monitoring, and their 1-GeV "cybernetic" model has an aperture only 1.6 cm by 2.1 cm.

The C-shaped magnets have a cross-section about 1 m by 1 m and have flaring poles whose curved profiles are approximately hyperbolic to give the desired field pattern; the open and closed sides of the flares alternate around the circumference. Interspersed among the many magnet sections (in the A.G.S. there are 240) are auxiliary quadrupoles and other multi-poled magnets which can provide changes in magnetic-field shape, as desired, either for correction at injection or at high fields when the iron begins to saturate, or for controlling the beam for targeting or ejection.

Since the radius of a synchrotron is determined by the top energy and the maximum practical magnetic field (of the order of 12 kG), unless the injection energy is fairly high the magnetic field at injection will be so low that the necessary accuracy will be difficult to obtain. When the Brookhaven and CERN machines were being designed, the quality of the beam from a proton linac made it appear the best choice for an injector and 50 MeV seemed to be the highest energy that was practical at that time. However, since then further developments in accelerator technology and the fact that both of these machines are now limited in intensity by space-charge effects (which can be reduced with higher injection energy) have led to plans for new injectors of higher energy. At Brookhaven, a 200-MeV linac will be used and at CERN it is probable that another circular machine will be inserted between the linac and the synchrotron.

Although the magnetic apertures in the AG machines are smaller than in the CG designs, the greater circumference and the needs of the rf systems result in pulse rates that are only slightly faster than in the CG types and, again, acceleration takes place over about one second. However, in operation, it is often customary to pulse at faster rates, albeit at lower energy, if the experimental program is suitable, since then these experiments can be completed in shorter time. But, again in the interests of increasing the number of protons available per second, both the Brookhaven and the CERN accelerators are including, in their current improvement programs, new magnet power supplies that can give repetitions of pulses about once per second with consequent shorter acceleration times and new rf systems. The present and future magnet power supplies are similar to those described for the CG designs: alternator, motor-generator, flywheel systems.

The strong restoring forces in AG synchrotrons give rise to further effects. One is that the variation of radius with particle momentum is greatly decreased; this momentum compaction is about one hundred times smaller than in CG machines. Phase

stability is also affected and one finds that below a certain energy, the "transition energy" (usually a few GeV), stability is on the rising side of the rf wave, above this energy it is on the falling side and just at this energy there is no phase stability. But theoretical studies, and an electron analog built at Brookhaven, showed that transition phenomena would not preclude successful passage through this energy although synchrotron oscillations would grow somewhat.

Tolerances on the frequency of the accelerating system are more severe, particularly near the transition energy, and control is through feedback from the beam itself. The accelerating units are again ferrite-loaded tuned cavities and several of them (cf Table 12) are distributed around the circumference to provide the required voltage per turn that is of the order of 100 kV. To observe the beam, many pickup electrodes, that detect the beam through the charge induced by its passage, are also distributed around the circumference.

The beam can be extracted from these accelerators and the method depends upon whether it is desired to bring all or part of the beam out quickly or whether it is to be spilled out over a longer period. For fast extraction, a rapidly pulsed "kicker" magnet can deflect the beam into a septum-magnet which can then bend it into further deflecting magnets that bring it out of the accelerator. Efficiency with this method is about 100%. For slower extraction, the beam must be induced to have large resonant oscillations, by changing the magnetic-field patterns, so that small portions of it can enter the septum-magnets over periods of hundreds of milliseconds. Such a slow-extraction system is in use at the CERN-PS (with present efficiencies of about 50%) and a similar one is being installed at Brookhaven during 1967.

Many types of secondary beams are available at these accelerators arising from internal targets placed at several locations so that a great many different experiments can take place

simultaneously. Portions of the beam can be made to strike targets for long or short bursts, depending on the experiment, either through adjustment of the rf system or by rapidly pulsed magnetic-field bumps. For long bursts, the magnetic field is held constant, flat-topped, for several hundred ns. At intermediate energies, short bursts can be obtained through simple beam gymnastics, but for longer bursts the magnet cycle must be programmed to give constant field for the required length of time before it rises again and the rest of the beam is accelerated to full energy.

Although in the early days of the design of the large AG synchrotrons at CERN and at Brookhaven there seemed to be many difficult problems, the outstanding success of these machines in producing intensities more than an order of magnitude above what had been hoped for, their reliability of operation and the ease with which many types of beams can be provided, have all contributed to the enthusiasm for extending this type of accelerator into much higher energy ranges. But the present levels of intensity in these machines are giving rise to some phenomena which are being carefully studied to learn about the behavior of large quantities of circulating charge and how interactions of the beam with itself and with components in the accelerator affect performance. However, as already mentioned, both of these accelerators are now in the process of being modified with the expectation that another order of magnitude or more in intensity can be attained.

Electron Alternating-Gradient Synchrotrons

In general principles, electron and proton AG synchrotrons are similar, but for electrons several significant differences in construction arise, chiefly from two effects: the electrons reaching constant velocity, c , at low energies and their loss of energy through radiation.

With the constant velocity of the electrons, the accelerating frequency can be constant and high-Q resonant cavities can be used. But, because of the radiation losses, much power is needed

in the rf system; for machines of several GeV, the maximum voltage required per turn is several MV. To reduce the size of the cavities and for greater efficiency, frequencies of several hundred MHz are usual at a very high harmonic of the particles' orbital frequency. Some systems employ many cavities distributed around the circumference, e.g., the Cambridge Electron Accelerator (C.E.A.) has 16 double cavities, whereas in others more cavity-cells are concentrated at few locations, e.g., the Cornell 10-GeV machine has four 34-cell units, each somewhat like an electron linac.

Since radiation losses are inversely proportional to the radius, the electron AG accelerators have relatively larger radius and correspondingly lower peak magnetic fields than the proton machines, e.g., at Cornell, the field at 10 GeV is only 3.3 kG. The general cross-sectional shapes of the magnets for electron machines are similar to those for protons and alignment and uniformity must be of the same degree of precision. But they are pulsed more rapidly, up to 60 cps, and eddy-current effects must be taken into account in the design of the coils and the ends of the magnet sections. Other characteristics of electron AG synchrotrons are shown in Table 13.

The vacuum chamber in these accelerators presents special problems. First, because of the rapid cycling rate, it cannot be the simple metal pipe that is found in the proton machines because eddy currents would distort the field; however, its surface must be conducting to prevent charge accumulation. Because of the high radiation levels, it must be made of a material that will not quickly deteriorate from radiation damage and it must be mechanically strong to withstand the atmospheric pressure. Several structures have been tried, for example slotted steel chambers covered with epoxy-loaded glass cloth, composites of titanium ribbon, glass and epoxy, etc. But at both DESY and C.E.A., radiation damage in their vacuum chambers has led to plans for

replacement with alumina-ceramic sections, with strips of metallic film inside to provide surface conductivity.

Injection energies in these accelerators are not only high enough to bring the electrons to constant velocity but also above the transition energy which, for typical parameters, is of the order of a few MeV. In the larger machines, linacs of several tens of MeV serve as injectors but improvement programs are already under way for even higher-energy injectors at DESY (300-MeV linac) and at C.E.A. ($\sim$ 100-MeV linac) to give higher intensities and to provide for injection and acceleration of positrons.

A variety of beams for experimental use can be obtained and, as with the proton machines, the large electron accelerators provide for many simultaneous experiments. Internal targets can give photon beams or the electron beam can be extracted by methods similar to those used for protons. Much more intense photon beams can be obtained with the extracted beam since it can be focused on a target located near the experiment. Positron beams can be produced through conversion and double conversion systems can give "tagged" photons.

Fixed-Field Alternating-Gradient Accelerators

The large momentum compaction resulting from alternating-gradient focusing means that particle orbits are very closely spaced over a very wide range of momenta. Thus, it would be possible to build an accelerator whose magnetic field would be constant in time, but varying with radius, and all particle orbits would be contained in an annular ring whose width was considerably smaller than its radius. Such a fixed-field alternating-gradient (FFAG) accelerator would not have the problems associated with pulsing and acceleration could take place at a faster rate. Much higher intensities could be achieved by accelerating the particles to their maximum energy and "stacking" them at their high-energy orbit.

A great many studies on this type of accelerator have been made at the MURA (Midwestern Universities Research Association) Laboratory and this group has built several models, including one for 50 MeV. Similar work on FFAG accelerators has been done at the Lebedev Institute, Moscow, U.S.S.R. Early designs at MURA were of the radial-sector type where the magnet is broken into wedge-shaped sectors with the field increasing strongly with radius but reversed in sign in alternate sectors. Later models, more efficient and with better operation, have spiral ridges on the magnet poles to give regions of stronger fields and placed to give alternate focusing as the particles' orbits cross them. The magnetic field also varies strongly with radius but does not change sign. Additional coils are inserted in the spaces between ridges to give further changes in field shape and controlled adjustment, since great precision is necessary. Magnets for full-sized accelerators of this type would be very large, e.g., a design for 10 GeV would have a radial aperture of 2.5 m and a total weight of steel of 35000 tons compared with the 3500 tons of steel in the 33-GeV A.G.S. magnet.

The MURA group proposed several designs for FFAG accelerators of 10 to 30 GeV but funding was not granted. However, their studies have made great contributions to the understanding of particle behavior in complex magnetic fields, e.g., in the development of the AVF cyclotrons, and their studies on stacking electron beams in the 50-MeV model to the understanding of problems connected with high-intensity beams and space-charge effects.

COLLIDING BEAMS AND STORAGE RINGS

When high-energy particles hit a fixed target, only a fraction of the energy is available for the creation of new particles and processes as the greater part of it gives kinetic energy to the secondary particles and the target nucleon. For example, when 30-GeV protons hit a fixed target, only 5.86 GeV is available for particle production and, with increasing energy of the incident

particle, this amount goes up very slowly, approximately only as the square root. But, if two such accelerated beams could collide head-on, all of their kinetic energy (i.e., 60 GeV) would be useful for such processes. However, the number of collisions per unit area would be very small unless the beams have intensities of the order of amperes. When the MURA group was investigating the possibilities of stacking many pulses in FFAG accelerators, they suggested²⁶⁾ that this might be a way of obtaining sufficient intensity to have useful colliding beams. Shortly thereafter, O'Neill²⁷⁾ and others proposed a less expensive solution wherein existing accelerators could be used if one could store many pulses in a magnetic ring for long enough to acquire the necessary intensity.

There are certain considerations and problems connected with storage rings that are not present in accelerators. The beams must be kept circulating for fairly long periods of time (at least tens of minutes), in order to accumulate them and then to use them for experimental studies, thus, a quite high vacuum is required, of the order of 10^{-9} to 10^{-10} torr. Also the experimental use is difficult since the processes take place within the ring's vacuum chamber and the placement of detectors must not interfere with the beams. Only stable particles can be stored so that studies of collisions involving kaons appear unlikely although those with antiprotons may be possible. Finally, secondary particles are produced at such low intensities that they cannot be used to make beams like those that are provided by accelerators and fixed targets.

Several storage rings have now been built in France, Italy, the Soviet Union and the United States all, so far, for electrons or electrons and positrons. Many details of their construction and operation are covered in the reports presented at the International Symposium on this topic held at Saclay in 1966¹⁹⁾. Pertinent characteristics of some of those in operation and under construction are given in Table 14 (the initials by which

some of them are known are those of the words storage ring or colliding beams in the respective languages). The first in operation was a single ring (AdA) for electrons and positrons each at 250 MeV, at Frascati, Italy, soon followed by electron-electron rings for 500 MeV each at Stanford University, U.S.A. (a Stanford-Princeton collaboration) and for 130 MeV each (VEP-1) at Novosibirsk, U.S.S.R. Both of these e^-e^- rings are tangent at one point for experimental studies of the collisions. Some of the smaller storage rings have been used mainly for studying operational problems or to serve as models for larger ones.

In early operations, several unforeseen phenomena occurred which prevented the attainment of the necessarily large circulating currents both in single beams and, later, after a second beam was introduced. Some of these effects are similar to the space-charge problems in conventional accelerators where the fields associated with large quantities of circulating charge not only influence the beam's structure but can change the magnetic-field patterns, induce disturbing currents in the vacuum-chamber walls and interact with the rf cavities. The introduction of a second beam causes many sorts of beam-beam interactions with resultant coherent and incoherent types of instabilities. Extensive investigations have been made of the behavior of beams in storage rings and most of these effects are now understood, at least in principle.

Storage rings can be built in several forms. In some the magnets are weak-focusing, others have typical AG magnets and some have strong focusing but with separate bending magnets and focusing quadrupoles (separate function). In some cases, injection is from a separate accelerator at the desired energy for collision, in others the beams are injected at a lower energy and accelerated in the storage ring. An rf system is necessary, even without acceleration, to move the particles from their injection orbit and to stack them in their circulating orbits. The need for very low pressures in the vacuum chamber requires many special

REFERENCES

1. Cockcroft, J.D., and Walton, E.T.S., Proc. Roy. Soc. (London) A 136, 619 (1932).
2. Lawrence Radiation Laboratory, 200 BeV Accelerator Design Study, UCRL - 16000 (June 1965).
3. CERN Study Group on New Accelerators, Report on the Design Study of a 300 GeV Accelerator, CERN/563 (November, 1964).
4. Brookhaven National Laboratory, Design Study for a 300 - 1000 GeV Accelerator, BNL 772 (1961).
5. Burshtein, E.L., Vasiljev, A.A., Mints, A.L., A 1000 GeV Cybernetic Accelerator, Proc. of International Conference on High Energy Accelerators, 1963 (Eng. transl. AEC Report Conf. - 114, p. 65).
6. Livingood, J.J., Principles of Cyclic Particle Accelerators (D. Van Nostrand Co. Inc., Princeton, N.J., 392 pp., 1961).
7. Livingston, M.S., and Blewett, J.P., Particle Accelerators (McGraw-Hill Book Co. Inc., New York, 666 pp., 1962).
8. Kolomensky, A.A., and Lebedev, A.N., Theory of Cyclic Accelerators; Eng. transl. by Barbier, M. (North-Holland Publishing Co., Amsterdam, 1966).
9. Bruck, H., Circular Particle Accelerators: Introduction to the Theory, (Presses Universitaires de France, Paris, 358 pp., 1966).
10. Wilson, R.R., and Littauer, R., Accelerators; Machines of Nuclear Physics (Anchor Books, Doubleday and Co., New York, 196 pp., 1960).
11. Lapostolle, P., Particle Accelerators (in French) (Editions Fayard, Paris, 151 pp., 1964).

12. Livingston, M.S., The Development of High-Energy Accelerators (Dover Publications Inc., New York, 1966).
13. Handbuch der Physik, Vol. 44 (S. Flügge ed., Springer, Berlin, 1959).
14. Proceedings V International Conference on High Energy Accelerators, 1965 (Comitato Nazionale Energie Nucleare, Rome, Italy, 1966).
15. The First National Particle Accelerator Conference, 1965, IEEE Trans. Nucl. Sci. NS-12 [3] (1965).
16. Conference on High Energy Cyclotron Improvement (Williamsburg; College of William and Mary, 1964).
17. International Conference on Isochronous Cyclotrons, Gatlinburg, 1966, IEEE Trans. Nucl. Sci. NS-13 [4] (1966).
18. Proceedings of the 1966 Linear Accelerator Conference, Los Alamos Scientific Laboratory, LA-3609 (1966).
19. Proceedings of the International Symposium on Electron and Positron Storage Rings, Saclay, 1966 (Presses Universitaires de France, 1967).
20. McMillan, E.M., Phys. Rev. 68, 143 (1945).
21. Veksler, V., Journal of Physics, U.S.S.R., 9 (1945).
22. Thomas, L.H., Phys. Rev. 54, 580 (1938).
23. Alvarez, L.W., et al., Rev. Sci. Instr. 26, 111 (1955).
24. Courant, E.D., Livingston, M.S., and Snyder, H.S., Phys. Rev. 88, 1190 (1952).
25. Cosmotron Staff (ed. M.H. Blewett), Rev. Sci. Instr. 24, 723 - 870 (1953).
26. Kerst, D.W., et al., Phys. Rev. 102, 590 (1956).
27. O'Neill, G.K., Phys. Rev. 102, 1418 (1956).

TABLE 1

Accelerator Type	Particle Orbit	Magnetic Field	Method of Acceleration	Maximum Energy (1967)
Cascade-rectifier and transformer	straight line	none	direct potential drop	4 MeV
Electrostatic generator (Van de Graaff)	straight line	none	direct potential drop	single stage: 10 MeV tandem: 25 MeV
Betatron	circle of constant radius	increasing in time; decreasing slightly with radius	electric field due to chang- ing flux in magnetic core	320 MeV
Cyclotron	circle of increasing radius	constant in time; decreasing slightly with radius	rf of constant frequency (about 10 MHz)	~ 25 MeV (p)
Synchrocyclotron	circle of increasing radius	constant in time; decreasing slightly with radius	rf of decreasing frequency (about 30 - 20 MHz)	740 MeV
AVF isochronous cyclotron	circle of increasing radius	constant in time; large vari- ations with azimuth	rf of constant frequency and variable (5 - 20 MHz)	80 MeV
Microtron	circle of increasing radius; centers move	constant in time; uniform	rf of constant frequency (3000 MHz)	32 MeV
Electron linear accelerator	straight line	none	rf of constant frequency (1300 to 3000 MHz)	20 GeV
Proton linear accelerator	straight line	none	rf of constant frequency (120 to 200 MHz)	68 MeV
Electron constant- gradient synchrotron	circle of constant radius	increasing in time; decreasing slightly with radius	rf of constant frequency (about 40 MHz)	1.5 GeV
Proton constant- gradient synchrotron	circle of constant radius	increasing in time; decreasing slightly with radius	rf of increasing frequency with large ranges	12.5 GeV
Electron alternating- gradient synchrotron	circle of constant radius	increasing in time; large grad- ients alternate azimuthally	rf of constant frequency (100 to 700 MHz)	7 GeV
Proton alternating- gradient synchrotron	circle of constant radius	increasing in time; large grad- ients alternate azimuthally	rf of increasing frequency with large ranges	33 GeV
Fixed-field alternating- gradient synchrotron	circle of increasing radius	constant in time; large vari- ations in azimuth and radius	rf of increasing frequency	(models only)

TABLE 2

Characteristics of Some Direct-Voltage Accelerators

Type of Accelerator	Energy	Particle	Current
	MeV		
Neutron generator (Texas Nuclear)	0.15 - 0.3	electrons protons (neutrons at 14 MeV)	to 30 mA to 8 mA $10^{12}/s$
Cockcroft-Walton pre- injector for A.G.S. (BNL) (Philips Co.)	0.75	protons	~ 100 mA pulsed
Cascade-rectifier (Haefely Ltd.)	1.5 4.0	electrons protons	6 mA aver. 5 mA
Dynamitron (Radiation Dynamics)	3 and 4	electrons pos. ions	5 - 10 mA dc 1.5 mA dc
Insulating-Core Trans- former (High Voltage Engineering Co.)	1.5 - 3 1.5 - 4 to 3 (tandem)	electrons pos. ions pos. ions	to 20 mA dc to 3 mA dc 2 μ A
Resonant Transformer (General Electric)	to 2	electrons	6 mA aver.
SAMES Electrostatic generator	to 2	protons	to 50 mA
Van de Graaff (H. V. E. C.)	4 5.5	electrons pos. ions	1 mA 70 μ A
Van de Graaff 2-stage tandem (H.V.E.C.)	8	pos. ions	50 μ A
Van de Graaff 2-stage tandem (H.V.E.C.)	15	pos. ions	0.5 μ A
Van de Graaff 2-stage "Emperor" (H.V.E.C.)	25 - 30	pos. ions	10 μ A at 20 MeV 25 μ A at 15 MeV
Van de Graaff 3-stage tandem (H.V.E.C.)	15 - 20	pos. ions	0.5 μ A

TABLE 3.

Characteristics of Some Typical Betatrons

Betatron	Energy	Magnetic Field at Orbit	Orbit Radius	Pulse Rep. Rate	X-Ray Intensity at 1 meter
	MeV	kG	cm	sec ⁻¹	roentgen/min
University of Illinois	320	9	123	6	20,000
University of Illinois	25	4.3	19	180	to 200
Allis Chalmers Betatrons	22	5	19	180	150 - 200
Brown-Boveri Betarons	31	12.3	29	50	1000

TABLE 4

Characteristics of some Classical Fixed-Frequency Cyclotrons

Location	Energy Particle		Magnet		Accelerating System		Intensity	
			Diam.	Field	Frequency	D-D volts	Int.	Ext.
	MeV		inch	kG	MHz	kV	mA	μ A
Argonne National Laboratory	10.8	- p (H_2)	60	15	11.2	310	0.6	100
	21.6	- d					1.0	200
	43.2	- α					0.6	100
	32	- He^3					0.3	
University of Indiana	11.4	- d	54	16	10.5	100	0.5	150
	11.4	- He^+						
	22.8	- α						100
Lawrence Radiation Laboratory	5 - 18	- d	90	2 - 9 (variable)	4 - 11 (variable in steps)	170	1.0	100
	10 - 36	- α						15
University of Michigan	15	- d	50	15	10.2	100	0.8	200
	30	- α						
Ohio State University	12.4	- d	47	15	11.2	120	0.2	50
	19.5	- He^3						
	24	- α					0.1	
Purdue University	10	- d	36.5	16	12.4	80		
	20	- α						
University of Washington	22	- d	60	19	11.6	250	0.5	250
	44	- α						

TABLE 5

Some Characteristics of Synchrocyclotrons

Location	Energy	Magnet		Accelerating System		Pulse Rep. Rate	Intensity	
		Diam.	Max. Field	Freq. Swing	Volts		Internal	External
	MeV	inch	kG	MHz	kV	sec ⁻¹	μA	protons/s
<u>United States :</u>								
Lawrence Rad. Lab	740	183	23.3	36 - 18	10	64	1	1 - 5 x 10 ¹¹
Univ. of Chicago	460	170	18.6	28 - 18	14	85	1	2 x 10 ¹⁰
Carnegie Inst. of Tech.	437	142	20.5	32 - 20	10	200	1	~ 10 ⁸ (scattered)
Columbia Univ.	385	164	17.8	28 - 17	6 - 10	60	0.5 - 1	none
Univ. of Rochester	240	130	16.8	30 - 18	15	200 - 330		
Harvard Univ.	168	95	19.7	30 - 23.6	9	to 300	0.5	5 x 10 ¹¹

<u>Other Countries :</u>								
Dubna, U.S.S.R.	680	(6.0 m)	16.8	26 - 13	15	120	2.4	8 x 10 ¹¹
CERN, Geneva, Switz.	600	(5.0 m)	19.5	30 - 16.4	5 - 30	54	1.8	5 x 10 ¹¹
U. of Liverpool, U.K.	383	156	19	30 - 18	5	115	1	2 x 10 ¹¹
Uppsala, Sweden	185	(2.3 m)	21.5	33 - 25.8	5 - 10	250	1	4 x 10 ¹⁰
Harwell, U.K.	160	110	16.2	26 - 19	10	200	1.5	10 ⁷ to 10 ⁸ (scattered)
Orsay, France	160	(2.8 m)	16.3	25 - 20	25	450	4	4 x 10 ¹²
McGill U. Canada	100	82	16.8		12	400	1	1 x 10 ¹¹

TABLE 6

Characteristics of Some AVF Isochronous Cyclotrons

Location	Energy	Particles	Magnet						RF System			Current	
			Diam.	Max. Field	No. of Sectors	Spiral Angle	Trim Coils		No. of Dees	Width	Frequency Range	Int.	Ext.
	MeV		cm	kG		deg.	prs.	prs.		deg.	MHz	μ A	μ A
Oak Ridge Natl. Lab., U.S.A.	10 - 70	p, (also d, He^3 , C, heavy ions)	193	17.2	3	30	4	10	1	180	7.5-22.5	500 ^x	100
U. of California, Berkeley, U.S.A.	10 - 55	p, (also d, α , He^3)	224	17.1	3	56	5	17	1	180	5.5-16.5	1000 ^x	100
Mich. State U. U. S. A.	23 - 55	p, (also d, He^3 , C, heavy ions)	163	15.2	3	10	1	8	2	134	13.8-21.8	40 (H^-)	40
U. of Manitoba, Canada	25 - 50	p	117	19.7	4	47.5	0	0	2	45	14 - 29	100 (H^-)	2
Orsay N.P. Inst. France	40 -140	N^{5+} , (also α , He^3 , C, O, A, Kr)	200	15	3	0	2	0	1	180	4 - 11	500 ^x	50
Karlsruhe, Germany	50	d (and α)	225	14.7	3	0	5	0	3	40	35 (fixed)	100	20
AERE, Harwell U.K.	to 50	p (also other ions)	178	17	3	45	3	12	1	180	7.6-22	500 ^x	100

^x Currents shown are design aim; usual operation is considerably less.

TABLE 7

Characteristics of Typical Microtrons

Location	Energy	Magnet Diameter	No. of Orbits	Current
	MeV	cm		mA
University of Western Ontario, Canada	4-12	50	8	10
Lund University, Sweden	6.4	50	10	50
Lebedev Institute, Moscow, U.S.S.R.	7	60	10	110
Inst. for Phys. Problems, Moscow, U.S.S.R.	15	75	17	35
Joint Inst. for Nucl. Res., Dubna, U.S.S.R.	30	110	30	60
Inst. for Phys. Problems, Moscow, U.S.S.R.	32	110	28	50

TABLE 8

Characteristics of Some Electron Linear Accelerators

Location	Energy	Frequency	Pulse Rep. Rate	Pulse Length	Current (peak)
		MHz	sec ⁻¹	μs	mA
S.L.A.C. Stanford, U.S.A.	11 - 23 GeV e ⁻ 7 - 15 GeV e ⁺	2856	1 - 360	0.01 - 2.1	35
Kharkov, U.S.S.R.	2 GeV	2797	50	1.5	
Orsay, France	1.3 GeV e ⁻ 1.0 GeV e ⁺	2998	50	1.5	80
Stanford Mk III	1.2 GeV	2856	60	1.5	3 μA average
Frascati, Italy	400 MeV e ⁻ 360 MeV e ⁺	2856	250 - 700	0.01 - 3.2	100 e ⁻ 0.9 e ⁺
Kharkov, U.S.S.R.	360 MeV	2797	50	1.5	130
Mainz University, Germany	300 MeV		to 500	0.2 - 2.6	300 at 2.6 μs 600 at 0.2 μs
U.S. National Bureau of Standards	150 MeV	1300	to 720	0.01 - 7	350 at 7 μs 2000 at 0.2 μs
U. of Saskatchewan, Canada	136 MeV	2856	to 1400	0.005 - 1	166
General Dynamics, (Gen.Atom.Div.) U.S.A.	80 MeV e ⁻ (also e ⁺)	1300	180	0.01 - 14.5	2000 at 0.01 μs and 45 MeV, e ⁻ ; 0.5 e ⁺ at 30 MeV
Yale University, U.S.A.	to 80 MeV	1300		0.1 - 4.5	600
Rennselaer Poly. Inst., U.S.A.	to 70 MeV	1300	7 - 720	0.01 - 4.5	2000 at 0.1 μs
Euratom, Geel, Belgium	58 MeV	2998	to 1000	0.01 - 1.0	3000 at 0.01 μs 200 at 1.0 μs
U.S. Naval Res. Laboratory	60 MeV e ⁻ 35 MeV e ⁺	2856	1 - 720	0.02 - 0.6	400

TABLE 9

Characteristics of Some Proton Linear Accelerators

Location	Energy	Injector	Frequency	Pulse Rep. Rate	Pulse length	Current
	MeV		MHz	sec ⁻¹	μ s	mA
<u>Research Machines</u>						
University of Minnesota, U.S.A.	68	500 - keV AC Transformer	202.5	30	200	$2 - 3 \times 10^{-5}$ aver.
Rutherford High Energy Research Lab., U.K. (P.L.A.)	50	515 - keV Cockcroft-Walton gen.	202.5	50	200	$2 - 3 \times 10^{-3}$ aver.
University of Southern California, U.S.A.	32	4 - MeV Van de Graaff gen.	202.5	15	400	4×10^{-4} aver.
<u>Synchrotron Injectors</u>						
Serpukhov, U.S.S.R. (70-GeV P.S.)	100	700 - keV Pulse Transformer	148.5	0.2 - 1	12 - 40	(operation expected, 1967)
C.E.R.N., Geneva, Switzerland (28-GeV C.P.S.)	50	515 - keV Cockcroft-Walton gen.	202.5	1	10 - 20	135 (peak)
Brookhaven National Lab., U.S.A. (33-GeV A.G.S.)	50	750 - keV Cockcroft-Walton gen.	201	2.5	20	~ 50 (peak)
Argonne National Lab., U.S.A. (12.5-GeV Z.G.S.)	50	750 - keV Cockcroft-Walton gen.	200	1 - 10	50 - 500	20 (peak)
Lawrence Rad. Lab., Berkeley, U.S.A. (6-GeV Bevatron)	19.3	480 - keV Cockcroft-Walton gen.	200	2	to 580	40 (peak)
Rutherford H.E.R.L., U.K. (7-GeV Nimrod)	15	600 - keV SAMES generator	115	to 2	to 1500	40 (peak)

TABLE 10

Characteristics of Some Electron Constant-Gradient Synchrotrons

Location	Energy	Mean Radius	Injector	No. of RF Cavities	Frequency	Harmonic Number	Repetition Rate	Intensity
	MeV	m			MHz		sec ⁻¹	electrons/s
California Institute of Technology, U.S.A.	1500	3.76	10-MeV linac	1	40.2	4	1.1	10 ¹¹
Inst. Naz. Fis. Nucl. Frascati, Italy.	1200	4.37	2-MeV Cockroft-Walton	2	43.7	4	20	1.2 x 10 ¹¹
Lebedev Institute, Moscow, U.S.S.R.	680	2.4	7-MeV Microtron		20		1/5	
Glasgow University, U.K.	450	1.25	-	2	38	1	5	
Purdue University, U.S.A.	330	1.2	-					1.8 x 10 ¹⁰
M.I.T., U.S.A.	320	1.3	-	1	46.5	1	2	1.5 x 10 ¹⁰
National Bureau of Standards, U.S.A.	180	0.84	-				60	6 x 10 ⁹
Nucl. Phys. Institute Novosibirsk, U.S.S.R.	130	1.0	3-MeV linac	1	110	3	3	100 mA peak in 20-ns pulses

TABLE 11

Characteristics of Proton Constant-Gradient Synchrotrons ^x

Location	Energy	Mean Radius	Injector	No. of RF Cavities	Frequency Range	Harmonic Number	Repetition Rate	Intensity
	GeV	m			MHz		min ⁻¹	protons/pulse
Argonne National Lab., U.S.A. (Z.G.S.)	12.5	27.4	50-MeV linac	1 (triple)	4.2 - 14.4	8	15	2×10^{12}
Joint Inst. Nucl. Res., Dubna, U.S.S.R.	10	30.5	9-MeV linac	2	0.19- 1.45	1	5	$1 - 2 \times 10^{11}$
Rutherford Laboratory U.K. (Nimrod)	7	23.6	15-MeV linac	1 (double)	1.4 - 8.02	4	28	1.5×10^{12}
Lawrence Radiation Lab., U.S.A. (Bevatron)	6.2	18.2	20-MeV linac	1	0.36- 2.46	1	11	5×10^{12}
Princeton/Pennsylvania Princeton, U.S.A. (P.P.A.)	3.0	12.5	3-MeV Van de Graaff	4	2.4 - 29.6	8	19/s	$10^{12}/s$
Saclay Laboratory France. (Saturne)	3.0	11	3.7-MeV Van de Graaff	1	0.76- 8.44	2	19	3×10^{11}

^x The first proton CG synchrotron, the Brookhaven 3-GeV Cosmotron, ceased operation in Dec. 1966; also the 1-GeV proton CG synchrotron (recently used for accelerating deuterons) at Birmingham Univ., U.K., stopped operation in March 1967.

TABLE 12

Characteristics of Proton Alternating-Gradient Synchrotrons

Location	Energy	Mean Radius	Injector	No. of RF Stations	Frequency Range	Harmonic Number	Repetition Rate	Intensity
	GeV	m			MHz		min ⁻¹	protons/pulse
Serpukhov, U.S.S.R.	70	235	100-MeV linac	53		30	5 - 10	(operation expected 1967-8)
Brookhaven National Lab., U.S.A. (A.G.S.)	33	128.5	50-MeV linac	12	1.4 - 4.46	12	20	2×10^{12}
C.E.R.N., Geneva Switzerland (C.P.S.)	28	100	50-MeV linac	16	2.9 - 9.55	20	20	1.3×10^{12}
I.T.E.P., Moscow, U.S.S.R.	7.3	40		11	0.65- 8.0	7	15	6×10^{10}
Radio-Technical Inst., Moscow, U.S.S.R.	1 (model for 1000)	8.5	1-MeV Van de Graaff		1.25-25	5	30	(initial operation)

TABLE 13

Characteristics of Electron Alternating-Gradient Synchrotrons

Location	Energy	Mean Radius	Injector	No. of RF Cavities	Frequency	Harmonic Number	Max. Volts per Turn	Repetition Rate	Intensity
	GeV	m			MHz		MV	sec ⁻¹	electrons/s
Cornell University U.S.A.	10	100	150-MeV linac	4 (34-cell)	714		10.5	60	(operation expected 1967)
Hamburg, Germany (DESY)	6.5	50.4	40-MeV linac	16	500	528	1.5	50	5×10^{12}
Cambridge, Mass., U.S.A. (C.E.A.)	6	36	30-MeV linac	16 (double)	476	360	4.5	60	5×10^{12}
Inst. of Physics, Erevan, U.S.S.R.	6	34.5	50-MeV linac	24	133		4.4	50	(operation expected 1967-8)
Daresbury Lab., U.K. (NINA)	4.5	35.1	40-MeV linac	5 (triple)	408	300	1.1	50	$\sim 10^{12}$ (initial operation)
Cornell University, U.S.A.	2.5	7.25	10-MeV linac		87.6	15	0.4	30	$\sim 10^{12}$
Bonn University, Germany	2.3	11.1	20-MeV linac		500	116		50	8×10^{11} (initial operation)
Tokyo University, Japan	1.3	5.5	6-MeV linac	1	138	16		21.5	6×10^{11}
Lund University, Sweden	1.2	5.3	6-MeV microtron	1	402	45		12.5	3×10^{10}
Bonn University, Germany	0.5	2.4	3-MeV Van de Graaff	6	177	9		50	$\sim 10^{12}$

TABLE 14

Storage Rings in Operation and under Construction

Location	Energy Each Beam	Particles	Mean Radius	No. of Rings	Injector	Magnet	No. of RF Cavities	Frequency	Intensity	Comments
	GeV		m					MHz		
C.E.R.N., Geneva Switzerland (I.S.R.)	25	p, p	150	2 intersect	25-GeV C.P.S.	A-G	6	9.5	10 - 20 A (aim)	under constrn. aim: 1971
Novosibirsk, U.S.S.R.	25 6	$\bar{p}$, $\bar{p}_+$ e^- , e^+	45 +	1	1-GeV synchr.	A-G			$10^{14} p$, $10^{10} \bar{p}$ (aim)	under constrn. aim: 1970
Novosibirsk, U.S.S.R.	3.5	e^- , e^+	7.5 +	1	1-GeV synchr.	A-G				under constrn. aim: 1968
Cambridge, Mass., U.S.A. (C.E.A.)	3	e^- , e^+		(to be stored and accelerated in C.E.A. + bypass)					100 mA (aim)	under constrn.
Frascati, Italy. (ADONE)	1.5	e^- , e^+	16.7	1	400-MeV linac	A-G Sep. Funct.	2 (double)	8.6	2×10^{11} particles (aim)	operation expected 1967.
Novosibirsk, U.S.S.R. (VEPP - 2)	0.700	e^- , e^+	5	1	synchr.	A-G	1	25.1	40 mA e^- 5 mA e^+	
Stanford/Princeton Stanford, U.S.A.	0.550	e^- , e^-	1.4	2 tangent	linac	weak- focusing		25.4	60 mA	higher currents in separate beams
Orsay, France. (ACO)	0.500	e^- , e^+	3.5	1	linac	A-G Sep. Funct.	1	27	30 mA e^- only	initial operation
Frascati/Orsay (AdA)	0.250	e^- , e^+	0.58	1				147		used to study operational problems
MURA, Madison, U.S.A.	0.200	e^- , e^+	1.5	1	50-MeV FFAG Accel.	A-G Sep. Funct.	1	31.9	1 A e^- 0.1 A e^+ (aim)	operation starting 1967
Lebedev Institute, Moscow, U.S.S.R.	0.170	e^- , e^+		(stored and accelerated in synchrotron)						
Novosibirsk, U.S.S.R. (VEP - 1)	0.150	e^- , e^-	0.43	2 tangent	synchr.			221	50 mA	
Kharkov, U.S.S.R.	0.100	e^- , e^-	1	2 tangent	linac		1			