A NEW HIGH-RESOLUTION TOF TECHNOLOGY

P.Fonte^{1,2,*}, A.Smirnitski³, M.C.S.Williams^{1,4}

¹ CERN, EP Division, Geneva, Switzerland

² LIP-Coimbra, Coimbra, Portugal

³ ITEP, Moscow, Russia

⁴ INFN Bologna, Bologna, Italy

Abstract

In the framework of the ALICE collaboration we have recently studied the performance of multigap Resistive Plate Chambers operated in avalanche mode and at atmospheric pressure for time-of-flight measurements. The detector provided an overall (detector plus electronics) timing accuracy of 120 ps sigma at an efficiency of 98% for MIPs.

The chambers had 4 gas gaps of 0.3 mm, each limited by a metallised ceramic plate and a glass plate, with an active dimension of $4\times 4\text{cm}^2$. The gas mixture contained $\text{C}_2\text{H}_2\text{F}_4+5\%\text{isobutane}+10\%\text{SF}_6$.

A few percent of streamer discharges, each releasing about 20 pC, was tolerated without any noticeable inconvenience.

This detector opens perspectives of affordable and reliable high granularity large area TOF detectors, with an efficiency and a time resolution comparable to existing scintillator-based TOF technology but with significantly, up to an order of magnitude, lower price per channel.

Submitted as a Letter to Nuclear Instruments and Methods in Physics Research

* On leave of absence from Instituto Superior de Engenharia de Coimbra, Coimbra, Portugal.

§ Corresponding author: P. Fonte, CERN/EP, CH-1211 Geneve 23, Switzerland. (paulo.fonte@cern.ch)

The ALICE experiment at the Large Hadron Collider heavy ion program at CERN will include a large area Time of Flight (TOF) system, spanning over a hundred square meters with around 100.000 individual read-out channels. Up to 10.000 charged particles are detected per unit of rapidity per event at midrapidity by this detector; particle identification of most of these particles is covered by the TOF technique. Several types of TOF detectors, including gaseous, have been considered for this application, aiming to provide the required timing accuracy at an affordable cost [1].

One new possibility is the Resistive Plate Chamber (RPC) described in this letter, that was recently developed and tested. Our approach contrasts with a previous application of RPCs to TOF (the Pestov counter [2]) in that we operate a multigap [3] detector in avalanche mode with a non-flammable gas mixture at atmospheric pressure, although at the sacrifice of some timing performance.

The detector is formed by two identical square-shaped RPC cells electrically connected in parallel. Each cell has an active area of $4 \times 4 \text{ cm}^2$ and it is constituted by two metallic electrodes placed on each side of a central glass plate, defining two gas gaps. No electrical connection is made to the central glass plates, that are made with a commercial variety of dark glass having a resistivity around $10^{12} \Omega \cdot \text{cm}$. The metallic electrodes were deposited on profiled ceramic plates [4] and the electrical contact made through a small perforation in the plate, placed outside the active gap volume. The width of each gas gap was defined by a set of four spacers placed in the corners of the ceramic plates, also lying outside the active gap volume. A schematic description of the detector is shown in figure 1.

The chamber signals were amplified by a 2 ns rise-time current amplifier developed specially for this application [5], followed by a fixed threshold discriminator connected to a TDC with a 50 ps bin width. The output of the amplifier was also sent to a charge integrating ADC that measured the fast signal charge. The charge information was used to correct offline for the finite rise time of the amplifier (slewing correction). The contribution of the electronics noise to the timing jitter was measured to be 50 ps sigma for a signal level of 1.5 pC, with a discriminator level of 20 fC.

The detector was filled with a non-flammable gas mixture consisting of $\text{C}_2\text{H}_2\text{F}_4 + 10\% \text{SF}_6 + 5\% \text{isobutane}$ [6] and tested at the CERN PS using a secondary beam of 7 GeV pions. Two identical scintillation counters provided a time reference with a resolution of 120 ps sigma and a scintillator-based telescope selected those particles that crossed the detector in a central area of 1 cm^2 .

The fast charge spectrum for minimum ionizing particles is shown in figure 2, corresponding to an average fast signal of 1.5 pC in avalanche mode. The sharp left cutoff corresponds to the ADC pedestal and the narrow peak close to 6 pC corresponds to the saturation of the ADC. The overall shape of the spectrum above 2 pC is influenced by the non-linearity of the electronics. About 2% of the particles triggered the formation of streamers, each developing about 20 pC, in qualitative agreement with [7]. A typical streamer pulse is shown in figure 3.

In figure 4 we show a typical time difference spectrum between the start counters and our detector, with a resolution of 107 ps sigma, after quadratic subtraction of the start counters contribution (120 ps).

At counting rates below 800 Hz/cm² the timing resolution for MIPs was between 100 and 120 ps with a detection efficiency above 98% (figure 5). The performance was degraded for higher counting rates, presumably due to time-dependent voltage drops across the resistive plate.

Other similar detectors with gas gaps of 0.4 and 0.6 mm were also tested and the available data (figure 6) suggest that the timing resolution of thin gap parallel geometry detectors depends mainly on the width of the gas gap. One can approximately describe this dependency by a straight line with a slope of 40 ps/0.1 mm.

This observation suggests that in principle further gains in timing accuracy may be achieved by reducing the gap width. For very small gas gaps one expects a reduction in efficiency, but this can be compensated by increasing the number of intermediate resistive plates. However, in order to reach timing resolutions comparable to those featured by the Pestov Counter [2] (30 ps sigma), but working in proportional mode and at atmospheric pressure, further progress in electronics must also be made.

The following colleagues, from our home institutes, contributed to this work: A. Akindinov, E. Cerron-Zeballos, R. Ferreira-Marques, V. Golovine, D. Hatzifotiadou, J. Lamas-Valverde, A. Martemianov, V. Petrov, F. Piuz, A. Policarpo, K. Voloshin.

- [1] *ALICE - Technical Proposal for A Large Ion Collider Experiment at the CERN LHC*, CERN/LHCC/95-71, December 1995.
- [2] V.V. Parchomchuk, Yu. N. Pestov and N.V.Petrovykh, *Nucl. Instrum. Meth.* 93 (1971) 269.
- [3] E. Cerron Zeballos et al., *Nucl. Instrum. Meth.* A 374(1996)132.
- [4] V. Akimov et al., *Nucl. Instrum. Meth.* A344 (1994) 120.
- [5] R.D'Alessandro et al., Preprint ITEP 51-95.
A.Martemianov, *Proceedings of the first workshop on electronics for LHC experiments*, Lisbon, 11-15 Sept., 1995.
- [6] P. Camarri et al, *Nucl. Instrum. Meth.* A (414)2-3 (1998) 317.
- [7] E. Cerron Zeballos et al., *Nucl. Instrum. Meth.* A (411)1 (1998) 55.
- [8] H.Raether, *Electron Avalanches and Breakdown in Gases* (London, Butterworths, 1964).
P.Fonte et al., *Nucl. Instrum. Meth.* A310, pp.140, 1991.
P.Fonte, *IEEE Trans. Nucl. Sci.* vol.43, pp.2135, 1996.

Figure captions

- Figure 1 – Schematic representation of the structure of a single RPC cell, made with two metalised, profiled, ceramic plates placed on each side of a central glass plate. Two of such cells are electrically connected in parallel to form a single detector.
- Figure 2 - Fast charge spectrum for MIPs, corresponding to an average charge of 1.5 pC. Above 2 pC the shape of the spectrum is influenced by the non-linearity of the amplifier.
- Figure 3 – Typical streamer current pulse directly observed on a 50 Ω resistor. The horizontal scale corresponds to 20 ns/division and the vertical scale to 1 mA/division. Each square corresponds to a charge of 20 pC. A clear precursor avalanche is visible 15 ns before the main pulse, which corresponds to the development and quenching of the streamer [8].
- Figure 4 – Typical time difference spectrum between the start counters and our detector, with a resolution of 107 ps sigma, after quadratic subtraction of the start counters contribution ($\sqrt{161^2 - 120^2} = 107$).
- Figure 5 - Timing resolution and efficiency as a function of the counting rate per unit area. For counting rates below 800 Hz/cm² a resolution better than 120 ps sigma was achieved with efficiency above 98%.
- Figure 6 - Tests performed with other detectors featuring different widths of the gas gap suggest that the main contribution to the time jitter is associated to the amplification process in the gas. The timing resolution seems to depend almost linearly on the gap width, with a slope of approximately 40 ps/0.1 mm.

Figure 1

Figure 2

Figure 3

Figure 4

Figure 5

Figure 6