CERN-EP/83-55
27 April 1983

EFFECTS OF A MAGNETIC FIELD ON THE OPTICAL PROPERTIES
OF DIELECTRIC MIRRORS

E. Iacopini^{*)}, G. Stefanini and E. Zavattini,
CERN, Geneva, Switzerland

PACS 42.00; 78.20; 78.65.

ABSTRACT

We have measured the changes in the polarization state of a monochromatic ($\lambda = 514.5$ nm) light beam on reflection at normal incidence by a multilayer dielectric mirror placed in a time modulated magnetic field.

The dominant effect is a Faraday rotation $\Phi \approx 3.7 \times 10^{-10}$ rad/G.

The sensitivity (around 40 Hz) obtained is $\approx 6 \times 10^{-9}$ rad/ $\sqrt{\text{Hz}}$, which is dominated by the shot-noise limit (100 mW of light power).

(Submitted to Applied Physics A)

*) Present address: Istituto di Fisica dell'Università, Pisa, Italy, and INFN, Sezione di Pisa, Italy.

1. INTRODUCTION

This paper reports the measurement of the time-dependent optical rotation and ellipticity induced on a linearly polarized, monochromatic light-beam when reflected, at quasi-normal incidence, by a multilayer dielectric mirror placed in a time-modulated magnetic field.

The investigation was motivated by the planning of an experiment [1],[2] to detect the vacuum birefringence induced by a strong modulated magnetic field $B(t)$, where one needs to detect a peak ellipticity of 10^{-11} rad or smaller. An essential part of the apparatus in this experiment is a multipass optical cavity [3] in which ≈ 700 reflections can be obtained [2] with a very small beam depolarization (extinction factor $\sigma^2 \approx 10^{-6}$). The static changes produced by a multipass cavity on the light-polarization state have been investigated by Bouchiat et al. [4]. In the experiment described in ref. [1], we were mainly concerned with time-varying coherent effects: in particular, since the vacuum birefringence is modulated proportionally to $B^2(t)$, any change in the light-polarization state produced by the stray component of the magnetic field on the cavity mirrors would constitute an unwanted coherent background, indistinguishable from the signal.

The results presented here were obtained for magnetic field intensities smaller than 24 G on the mirror.

A short theoretical discussion based on the matrix formalism developed by Abeles [5],[6] is given in the Appendix.

2. EXPERIMENTAL APPARATUS

The experimental apparatus is shown in fig. 1. The spherical mirror M, with a multilayer dielectric coating¹ deposited on BK7, has a reflectivity $R = 0.995$ for $\lambda = 514.5$ nm, a radius of curvature of 14 m, and a diameter of 11 cm. This mirror is one of those which constituted the optical cavity described in ref. [2] .

The coil C (200 turns, 120 mm diameter) is wound on an aluminium former around the mirror M, and is mechanically isolated from the mirror support. The coil produces a magnetic field $B(t)$ modulated at frequency f_e : $B(t) = B_0 \sin(2\pi f_e t)$, which can be aligned parallel or perpendicular to the mirror surface. The perpendicular component is continuously monitored by the pick-up coil PC (10 turns, 40 mm diameter) placed near the reflecting surface of the mirror, and aligned to within 20 mrad with the mirror axis.

The assembly is contained in a vessel which can be evacuated down to 10^{-3} Torr to avoid Faraday contributions from the air. Moreover, the assembly is shielded with mu-metal cylinders in order to reduce the stray component of the magnetic field on all the optical elements.

The entrance window of the vessel is a BK7 optical flat, 9 mm thick, mounted on a tube extension with adjustments to minimize the stress birefringence due to pressure differentials. The peak magnitude of the modulated magnetic field at the window is reduced to less than 10^{-6} G by a shield made of several concentric mu-metal cylinders (see fig.1).

¹ M.T.O., 91302 Massy, France.

The light source is a CW argon-ion laser² tuned to $\lambda = 514.5$ nm.

The polarization of the incident beam is defined by the Glan-Thompson prism polarizer³ P along the vertical axis. The prism is followed by a quarter-wave plate QWP1, which compensates any residual static ellipticity.

The beam hits the mirror M at an angle of incidence of 5×10^{-3} rad in the horizontal plane. The reflected beam, picked-up by a 10 mm diameter dielectric mirror M1, at an angle of incidence of $\approx 2 \times 10^{-2}$ rad, passes through the Faraday cells FG (glass) and FA (air). The cell FG introduces a modulation in the light-polarization state which acts as a carrier for the effect to be measured. The cell FA is used to normalize the sensitivity by producing a well-known and constant modulation of 5.48×10^{-8} rad (peak amplitude).

The beam is then directed onto the analyser A, oriented for maximum extinction. The transmitted beam is focused on the PIN photodiode D1, whilst the reflected beam, containing the total incident power, is monitored by the diode D2 after a suitable attenuation. The two photodiodes D1 and D2, used in photovoltaic mode, are connected to low-noise current-to-voltage amplifiers with feedback resistors of 400 M Ω and 500 Ω , respectively.

² Model CR 2, made by Coherent Radiation, Palo Alto, Calif., USA

³ Karl Lambrecht, Chicago, Ill., USA.

3. THE METHOD

The light power $W(t)$ on the photodiode D1 is given, to first approximation, by [1]:

$$W(t) = W_0 \{ \sigma^2 + [\psi_g(t) + \psi_a(t) + \phi(t) + \beta(t)]^2 \}, \quad (1)$$

where

i) $W_0 \approx 90$ mW is the light power before entering the analyser A;

ii) $\sigma^2 \approx 1 \times 10^{-7}$ is the over-all extinction factor;

iii) ψ_g is the Faraday rotation angle introduced by FG:

$$\begin{aligned} \psi_g &= \Psi_g \sin(2\pi f_g t); \\ \Psi_g &= 3.0 \times 10^{-4} \text{ rad}, \quad f_g = 351.5275 \text{ Hz}; \end{aligned}$$

iv) ψ_a is the Faraday rotation angle introduced by FA:

$$\begin{aligned} \psi_a &= \Psi_a \sin(2\pi f_a t); \\ \Psi_a &= 5.48 \times 10^{-8} \text{ rad}, \quad f_a = 39.0625 \text{ Hz}; \end{aligned}$$

v) ϕ is the angle to be measured:

$$\phi = \Phi \sin(2\pi f_e t),$$

produced by the modulating coil C at the frequency

$$f_e = 39.0445 \text{ Hz};$$

vi) β is the unavoidable misalignment between the prisms P and A, which may drift slowly in time.

Since the angles Ψ_a , Φ , and β are much smaller than Ψ_g , the photodiode current $i(t)$ is given, to a very good approximation, by:

$$\begin{aligned}
 i(t) = \eta W(t) = \eta W_0 \left(\sigma^2 + \frac{\Psi_g^2}{2} - \frac{\Psi_g^2}{2} \cos(4\pi f_g t) \right. \\
 + 2\Psi_g \beta \sin(2\pi f_g t) \\
 + \Psi_g \Psi_a \{ \cos[2\pi(f_g + f_a)t] - \cos[2\pi(f_g - f_a)t] \} \\
 \left. + \Psi_g \Phi \{ \cos[2\pi(f_g + f_e)t] - \cos[2\pi(f_g - f_e)t] \} \right) \quad (2)
 \end{aligned}$$

where η is the photodetector efficiency ($\eta = 0.2$ A/W) .

The noise level is essentially fixed by the shot-noise limit

$$\langle i_{\text{shot}} \rangle \approx 3.5 \times 10^{-14} \text{ A}/\sqrt{\text{Hz}} \quad (3)$$

since the other relevant noise contributions from the diode-amplifier system and from the laser intensity fluctuations [2] are

$$\langle i_{\text{ampl}} \rangle \approx 10^{-14} \text{ A}/\sqrt{\text{Hz}}, \quad (4)$$

$$\langle i_{\text{laser}} \rangle \approx 2.5 \times 10^{-14} \text{ A}/\sqrt{\text{Hz}}. \quad (5)$$

Since the preamplifier following the diode D1 has a feedback resistor of 400 M Ω , the noise on the voltage signal $V(t)$ from this preamplifier, due to the above-mentioned noises (3), (4), and (5), is

$$\langle V_{\text{tot}} \rangle \approx 18 \text{ } \mu\text{V}/\sqrt{\text{Hz}} \quad (6)$$

and this fixes the limit for the sensitivity of the apparatus at (for a $S/N = 1$)

$$\Phi_{\text{sens}} = 5.7 \times 10^{-9} \text{ rad}/\sqrt{\text{Hz}}, \quad (7)$$

which is only 25% above the shot-noise limit.

The voltage signal $V(t)$ is processed by four independent two-phase

lock-in amplifiers⁴, according to Table 1. The lock-in outputs are digitized at fixed time intervals of 50 ms and stored on tape, together with the following signals:

- a) D_1 and D_2 , integrated over $\tau = 0.3$ s,
- b) current in the cells FG and FA,
- c) current in the main coil C,
- d) voltage on the pick-up coil PC,
- e) reference signals to the lock-ins PSD3, PSD4.

The output of the lock-in PSD2 is used in a feedback loop acting on the prism A to keep the misalignment B smaller than 10^{-5} rad so as to avoid saturation in the lock-in amplifiers PSD3 and PSD4.

The off-line data analysis is based on the Fourier transform of the outputs of PSD3 and PSD4. A typical frequency spectrum of the output from the lock-in PSD4 is shown in Fig.2. The frequency resolution is 1 mHz and the integration time 10000 s.

⁴ Model Ortholoc-SC 9505 E, Brookdeal, Bracknell, England.

Table 1: Lock-in signals

Lock-in	Reference frequency (Hz)	Spectral component	Frequency (mHz)	Spectral (*) amplitude
PSD1	703.0550	$f_{ref1}-2f_g$	0	$\Psi_g/2$
PSD2	351.5275	$f_{ref2}-f_g$	0	2B
PSD3	390.6250	$f_{ref3}-(f_g+f_e)$	53	Φ
		$f_{ref3}-(f_g+f_a)$	35	Ψ_a
PSD4	312.5000	$f_{ref4}-(f_g-f_e)$	17	Φ
		$f_{ref4}-(f_g-f_a)$	35	Ψ_a

(*) The spectral amplitudes are normalized to $\eta W_0 \Psi_g$

4. RESULTS

The rotation Φ of the polarization plane, for different amplitudes B_0 of the modulated field component $B(t)$ perpendicular to the mirror surface, is given in Table 2 .

A linear fit of the data $\Phi = a + b B_0$ gives

$$a = (-0.09 \pm 0.05) \times 10^{-9} \text{ rad} \quad (8)$$

$$b = (0.374 \pm 0.003) \times 10^{-9} \text{ rad/G} \quad (9)$$

with a χ^2 of 0.76 per degree of freedom. The very good linear dependence of Φ on B suggests that the rotation Φ is due to the Faraday effect in the dielectric layers.

We point out that the error values quoted in Table 2 are very near

to the theoretical limit given by eq.(7). This shows that no other noises, apart from the ones considered in eqs. (3), (4), and (5), were present during the measurements quoted in Table 2.

To check for systematic errors produced by the small residual stray component of the magnetic field on the optical elements, we have measured the effect Φ by keeping the current in the coil C constant, and by placing the mirror at different positions along the coil axis. The current in the coil C was such as to generate a magnetic field amplitude B_0 of 24 G (peak value) at its centre.

The results of these measurements are shown in fig. 3. The perpendicular component of the magnetic field at the mirror surface is deduced by the signal from the pick-up coil PC. According to these data, the possible systematic effects produced at 24 G of magnetic peak amplitude do not exceed the statistical error bar affecting our angular measurements. In fact, by a linear fit we find

$$\Phi = [0.106 \pm 0.070 + (0.364 \pm 0.004) B_0] \times 10^{-9} \text{ rad} . \quad (10)$$

Table 2: Rotation induced by perpendicular field component

B_0 (G)	Φ (10^9 rad)	Φ/B_0 (10^9 rad/G)
24	8.86 ± 0.06	0.369 ± 0.002
16	5.91 ± 0.07	0.369 ± 0.004
8	2.94 ± 0.06	0.367 ± 0.007
4	1.38 ± 0.06	0.345 ± 0.015
24	8.96 ± 0.07	0.373 ± 0.003

To search for a modulated ellipticity $\theta(t) = \Theta \sin(2\pi f_e t)$ due to the magnetic field, we have introduced an additional quarter wave-plate QWP2 in the reflected beam just after the mirror M1. The fast axis of the plate was aligned to the prism P.

A perfect $\lambda/4$ retarder would act on the reflected beam in such a way that the intermodulation with Ψ_g would only be possible for the ellipticity $\theta(t)$, whilst being entirely suppressed for the rotation $\phi(t)$. To take into account the imperfections of the plate QWP2, an additional Faraday cell in air FA', modulated at a frequency $f'_a = 39.1115$ Hz, has been introduced between M1 and QWP2. The modulation detected at $f_g \pm f'_a$ gives the deviation of the plate from $\lambda/4$, and is used to subtract the residual intermodulation, due to $\phi(t)$, from the detected signal at $f_g \pm f_e$. For this purpose we have checked, by comparison with an air cell, that the ellipticity introduced by the modulator FG at f_g is less than 0.3% of the rotation Ψ_g . The corresponding limiting sensitivity for the measurement of ellipticity is $\approx 3 \times 10^{-11}$ rad.

We have found, for $B_0 = 24$ G, the value

$$\Theta = 2.1 \pm 1.1 \times 10^{-10} \text{ rad} \quad (11)$$

which we estimate to be compatible with zero.

We have also investigated the effects of a modulated magnetic field parallel to the mirror surface, and we find that they are compatible with the possible residual component of the magnetic field perpendicular to the mirror surface, as monitored by the pick-up coil PC.

5. CONCLUSIONS

The Faraday rotation dominates the over-all changes in the light-polarization state occurring at near normal reflection from a dielectric mirror placed in a modulated magnetic field.

This effect can be estimated by using the method outlined in the Appendix. From eq. (A17), and assuming for the refraction indices n_1 , n_2 and the Verdet constants V_1 , V_2 of the two layers the values⁵

$$\begin{aligned} n_1 &\approx 1.5 & V_1 &\approx 0.02 \text{ min/G cm} \\ n_2 &\approx 2.4 & V_2 &\approx 0.10 \text{ min/G cm} \end{aligned} \quad (12)$$

we have

$$\frac{d\phi}{dB} = \frac{\lambda}{2n_0(n_2^2 - n_1^2)} [n_2^2 V_1 + n_1^2 V_2] \approx 0.72 \times 10^{-9} \text{ rad/G}, \quad (13)$$

in rough agreement with the measured value (9).

On the basis of the results shown in fig. 3, the unwanted perturbations due to the stray field components in the experiment described in ref. [1] will be negligible if the magnetic field at the mirror surfaces is reduced to less than 10 μ G by suitable shieldings.

⁵ The exact chemical composition is not available from the manufacturer.

6. APPENDIX

Coherent interference between multiple reflections takes place when a light-beam impinges on a dielectric layer having a thickness h comparable with the radiation wavelength λ in vacuum (thin layer).

A matrix formalism to calculate the amplitude transmittance t and reflectance r from a thin layer has been established by Abeles [5],[6].

In this formalism a thin layer of refraction index n , traversed by an electromagnetic plane wave at an angle β , is represented by the 2x2 unitary matrix

$$M = \begin{vmatrix} m_{11} & m_{12} \\ m_{21} & m_{22} \end{vmatrix} = \begin{vmatrix} \cos x & i u^{-1} \sin x \\ i u \sin x & \cos x \end{vmatrix}, \quad (A1)$$

where

$$x = \frac{2\pi}{\lambda} (n h \cos \beta) \quad (A2)$$

$$u = \begin{vmatrix} n/\cos \beta & \text{parallel} & \text{(TM)} \\ n \cos \beta & \text{perpendicular} & \text{(TE)} \end{vmatrix} \quad (A3)$$

depending on whether the light is linearly polarized perpendicular (TE wave) or parallel (TM wave) to the plane of incidence.

If the media before and after the layer have refraction indices n_0 and n_f , respectively, then the amplitude transmittance t and reflectance r of the layer are related to the elements of the characteristic matrix M according to the following equations:

$$t = \frac{2n_0}{n_0 m_{11} + n_f m_{22} + n_0 n_f m_{12} + m_{21}}, \quad (A4)$$

$$r = \frac{n_0 m_{11} - n_f m_{22} + n_0 n_f m_{12} - m_{21}}{n_0 m_{11} + n_f m_{22} + n_0 n_f m_{12} + m_{21}} . \quad (A5)$$

In general the coefficients t and r are complex numbers. They are related to the intensity transmittance T and reflectance R in the following way:

$$T = \frac{n_f}{n_0} |t|^2 , \quad R = |r|^2 \quad (A6)$$

and to the phase changes occurring in transmission δ_t and in reflection δ_r , according to:

$$\delta_t = \arg t , \quad \delta_r = \arg r . \quad (A7)$$

For a system of m layers, the characteristic matrix M is the product of the matrices M_j associated with the various layers (see fig. 4).

In many applications the multilayer coating is obtained by repeating k times a simpler structure constituted by only two thin films. In this case the matrix M is the k^{th} power of the product Z of the matrices M_1 and M_2 of the two layers

$$Z = M_1 M_2 = \begin{vmatrix} z_{11} & z_{12} \\ z_{21} & z_{22} \end{vmatrix} , \quad (A8)$$

and its k^{th} power, as shown in ref. [6], can be written in the following way:

$$Z^k = \begin{vmatrix} z_{11} S_{k-1}(a) - S_{k-2}(a) & z_{12} S_{k-1}(a) \\ z_{21} S_{k-1}(a) & z_{22} S_{k-1}(a) - S_{k-2}(a) \end{vmatrix} , \quad (A9)$$

where $a = z_{11} + z_{22}$ and $S_k(a)$ is the first-kind Chebychev polynomial of rank k .

In our dielectric mirror, each of the two fundamental layers present, as usual, an equivalent optical thickness of $\lambda/4$ at normal incidence. According to (A1), (A2), and (A9), this implies that

$$\begin{aligned} z_{11} &= -u_2/u_1 & z_{22} &= -u_1/u_2, \\ z_{12} &= 0 & z_{21} &= 0, \end{aligned} \quad (\text{A10})$$

i.e. the well-known expression for the reflectivity [7]:

$$r_0 = \frac{n_0 (u_2/u_1)^k - n_f (u_1/u_2)^k}{n_0 (u_2/u_1)^k + n_f (u_1/u_2)^k}. \quad (\text{A11})$$

Let us now assume that the refraction indices n_1 and n_2 of the two characteristic layers are functions of a parameter ϵ (by definition, for $\epsilon = 0$, they assume the value giving an optical thickness of $\lambda/4$ to the layers). The derivative of r with respect to ϵ , calculated at $\epsilon = 0$, is given by⁶

$$\begin{aligned} r'_0 &= \frac{2 n_0 n_f}{\text{sh}^2(\xi) [n_0 \exp(-k\xi) + n_f \exp(k\xi)]^2} \left\{ a' \{ k \text{sh}(\xi) - \text{sh}(k\xi) \text{ch}[(k-1)\xi] \} \right. \\ &\quad + \text{sh}(\xi) \text{sh}(k\xi) [\exp(k\xi) (-z'_{11} - n_f z'_{12}) \\ &\quad \left. + \exp(-k\xi) (z'_{22} + z'_{21}/n_f)] \right\}, \end{aligned} \quad (\text{A12})$$

where $\exp(\xi) = u_1/u_2$ ($\epsilon=0$).

To have good reflectivity, the condition $k|\xi| \gg 1$ should be fulfilled. In this hypothesis, eq. (A13) becomes

⁶ To shorten the notation, we use the symbol f' to indicate the derivative of f with respect to the parameter ϵ , calculated at $\epsilon = 0$.

$$r'_{0} \approx \frac{-n_0}{2n_f \operatorname{sh}^2(\xi)} \{a' \exp(-\xi) + 2\operatorname{sh}(\xi)[z'_{11} + n_f z'_{12}]\}, \quad \xi > 0, \quad (A13)$$

$$r'_{0} \approx \frac{-n_f}{2n_0 \operatorname{sh}^2(\xi)} \{-a' \exp(-\xi) + 2\operatorname{sh}(\xi)[z'_{22} + (z'_{21}/n_f)]\}, \quad \xi < 0,$$

Since the reflectance r is, in general, a complex number, one has

$$r = \rho \exp(-i\delta) \quad \rho > 0; \quad 0 < \delta < 2\pi,$$

where $\rho^2 = R$ is the power reflectivity from the multilayer and δ is the phase change introduced at the reflection. From eq. (A14) one has

$$\rho'(\epsilon=0) = 0 \quad \text{i.e.} \quad R' = 0, \quad (A14)$$

$$\delta'(\epsilon=0) = \frac{-i z'_{21}}{n_0 \operatorname{sh}(\xi)} \quad \xi < 0, \quad (A15)$$

$$\delta'(\epsilon=0) = \frac{i n_0 z'_{12}}{\operatorname{sh}(\xi)} \quad \xi > 0. \quad (A16)$$

As a consequence of eq. (A14), when light is reflected at normal incidence by a perfect $\lambda/4$ dielectric mirror placed in a modulated magnetic field, the changes of the indices n_1 and n_2 for the two fundamental layers, due to the Faraday effect, do not produce, to the first order, any intensity change. In general there is, however, a change in the polarization state. As a matter of fact, if the light impinging on the mirror is linearly polarized, the reflected beam is still linearly polarized but the polarization plane is rotated by an angle α such that, according to eqs. (A15) and (A16), one has

$$\frac{d\alpha}{dB} = \frac{\lambda}{2n_0(n_2^2 - n_1^2)} [n_2^2 V_1 + n_1^2 V_2], \quad \xi < 0, \quad (A17)$$

$$\frac{d\alpha}{dB} = \frac{\lambda n_0}{2(n_1^2 - n_2^2)} [V_1 + V_2], \quad \xi > 0, \quad (A18)$$

where the positive direction of the magnetic field is the one of the reflected beam and V_1 and V_2 are, respectively, the Verdet constants for the substances constituting the two layers.

AKNOWLEDGEMENTS

We thank E. Polacco for stimulating discussions and F. Jeanmairet for his skilled mechanical job.

References

- [1] E. Iacopini and E. Zavattini , Phys. Lett. 85B, 151 (1979).
- [2] E. Iacopini, B. Smith, G. Stefanini and E. Zavattini,
Il Nuovo Cimento 61B, 21 (1981).
- [3] D.R. Herriott and H.J. Schulte, Appl. Opt. 4, 883 (1965).
- [4] M.A. Bouchiat and L. Pottier , Appl. Phys. B29, 43 (1982).
- [5] F. Abeles, Ann. Phys. (France) 5, 596 (1950).
- [6] F. Abeles, Ann. Phys. (France) 5, 706 (1950).
- [7] M. Born and E. Wolf, Principles of optics, Third edition
(Pergamon Press, Inc., New York, 1965), p.69.

FIGURE CAPTIONS

Fig. 1: Schematic layout of the experimental apparatus.

Fig. 2: Fourier transform amplitudes of the signal from the lock-in PSD4, for an integration time of 10000 s.

The spectral amplitude at 17 mHz gives the polarization plane rotation due to the magnetic field on the mirror; whereas the spectral amplitude at 35 mHz is proportional to the polarization plane rotation produced by the Faraday cell FA (5.48×10^{-8} rad).

Fig. 3: Polarization plane rotation Φ , measured at different mirror positions along the axis of the main coil C, as a function of the magnetic field intensity on the mirror surface, measured by the pick-up coil PC.

The current in the main coil C was such as to produce, at its centre, a magnetic field amplitude B_0 of 24 G.

Fig. 4: Schematic view of a periodic multilayer dielectric mirror.

Fig. 1

Fig. 2

Fig. 3

Fig. 4