Instrumentation of a Level-1 Track Trigger in the ATLAS detector for the High Luminosity LHC

Dr Véronique Boisvert, Royal Holloway, University of London
on behalf of the ATLAS Collaboration

Introduction

- HL-LHC in 2020: $L=5 \times 10^{34} \text{cm}^{-2}\text{s}^{-1}$ and 3ab^{-1} of data per experiment
- Need lepton triggers at thresholds of $p_T \sim 25 \text{ GeV}$
- But event rates: $\sim x 5$ and number of interactions per bunch crossing: $\langle \mu \rangle \sim 120$

Current ATLAS L1 Trigger and upgrades

- Hardware L1: 40 MHz to 75 kHz, software L2 (RoI scheme): 3kHz, Event Filter: output rate: $\sim 300 \text{ Hz}$
- L1: Coarse calorimeter and muon information, latency $< 2.5 \mu\text{s}$
- Want to keep single lepton trigger rate below 20kHz
- During the long shut down of ~ 2018 :
 - complete replacement of Inner Detector tracker
 - replace almost all of the on-detector FE electronics
 - FE not replaced: muon drift tube chambers $\rightarrow$ L1A $\sim 200 \text{ kHz}$ and latency $\sim 20 \mu\text{s}$

Benefits of Tracking at L1

- Reduce L1A rate (eg current HLT)
- Ensure objects are from Primary Vertex
- Possible track based isolation
- Added flexibility to trigger system

Option 1: L0/L1 trigger design using a Double Buffer Front-End Architecture

- L0: upgraded Calo+Muon triggers, 500kHz, latency $< 6.4 \mu\text{s}$, builds RoI
- L1: Track Trigger, final L1 Accept within $20 \mu\text{s}$

Bandwidth reduction:
Bandwidth = $(100\text{kHz} + 500\text{kHz} \times 10\%) \times \text{event size}$
size = $150\text{kHz} \times \text{event size}$
 $\rightarrow 1.5$ times bandwidth without track trigger

Schematic of FE readout configuration:

ABC130 chip Hybrid Chip Controller

Results:

- For $\langle \mu \rangle = 200$, L0A=300kHz, L1A=75kHz, R3=3kHz (fROI=1%)
- 160Mb/s link shared between R3 and L1 is optimum
- 98.5% of R3 data is received within 5.5 μs
- separate buffers on the HCC for R3 and L1 (R3 prioritized)
- bandwidth required: 125 Mb/s (for $\langle \mu \rangle = 140$, L0A=500kHz, L1A=200kHz, R3=50kHz, fROI=10%)

Benefits:

- minor changes to new tracker design
- low momentum tracks
- isolation criteria possible

Option 2: Single hardware trigger level by using trigger layers in the new tracker

- filter high momentum tracks using doublet layer coincidences in closely spaced layers
- 2 local filtering methods studied, bandwidth reduction factor: 12-25

Cluster Size Method:

utopia design: strip sensors tilted by 10°

- cluster size is reconstructed on FE
- lower p_T tracks $\rightarrow$ charge sharing over several adjacent strips
- optimized cut: $N \leq 2$

Offset Method:

- set stereo angle to 0
- match hits in inner and outer layers
- azimuthal distance related to p_T

• Best is to combine Cluster Size and offset

Global track reconstruction:

- hits from 2 or 3 layers combined, helix fitted and χ^2 cut applied
- will be done by associative memory

Track trigger rates of order 1 MHz achieved for $p_T > 10-15 \text{ GeV}$, with $\sim 75-80\%$ eff

Benefits:

- no majors changes to FE of subdetectors
- finds all ID tracks
- provides redundant information