PD

INSTITUT FÜR HOCHENERGIEPHYSIK DER ÖSTERREICHISCHEN AKADEMIE DER WISSENSCHAFTEN

2 October 1997

HEPHY-PUB 674-97

Diamond Particle Detectors*

RD42 Collaboration

Sw 9916

Abstract

To continue the exciting research in the field of particle physics new accelerators and experiments are under construction. In some of these experiments, e.g. ATLAS and CMS at the Large Hadron Collider at CERN or HERA-B at DESY, the detectors have to withstand an extreme environment. The detectors must be radiation hard, provide a very fast signal, and be as thin as possible. The properties of CVD diamond allow to fulfil these requirements and make it an ideal material for detectors close to the interaction region of these experiments, i.e. the vertex detectors or inner trackers. The RD42 collaboration is developing diamond detectors for these applications. The program of RD42 includes the improvement of the charge collection properties of CVD diamond, the study of the radiation hardness and the development of low noise radiation hard readout electronics. An overview of the progress achieved during the last years will be given.

*Contribution to the 6th International Workshop on Vertex Detectors VERTEX 97. Rio de Janeiro, Brazil, August 31 - September 5, 1997. Presented by M. Krammer.

The RD42 Collaboration

W. Adam¹, C. Bauer², E. Berdermann³, F. Bogani⁴, E. Borch⁵, M. Bruzzi⁵,
C. Colledani⁶, J. Conway⁷, W. Dabrowski⁸, P. Delpierre⁹, A. Deneuille¹⁰, W. Dulinski⁶,
B. van Eijk¹¹, A. Fallou⁹, D. Fish⁷, F. Foulon¹², M. Friedl¹, K.K. Gan¹³, E. Gheeraert¹⁰,
E. Grigoriev², G. Hallewell⁹, R. Hall-Wilton¹⁴, S. Han¹⁵, F. Hartjes¹¹, J. Hrubec¹,
D. Husson⁶, H. Kagan¹³, D. Kania¹⁶, J. Kaplon⁸, R. Kass¹³, K.T. Knöpfle²,
M. Krammer¹, P.F. Manfredi¹⁷, D. Meier⁸, M. Mishina¹⁸, F. LeNormand⁶, L.S. Pan¹⁹,
H. Pernegger¹, M. Pernicka¹, V. Re¹⁷, G.L. Riestler⁶, S. Roe⁸, D. Roff¹⁴, A. Rudge⁸,
S. Schnetzer⁷, S. Sciortino⁵, V. Speziali¹⁷, H. Stelzer³, R. Stone⁷, R.J. Tapper¹⁴,
R. Tesarek⁷, G.B. Thomson⁷, M. Trawick¹³, W. Trischuk²⁰, R. Turchetta⁶, A.M. Walsh⁷,
R. Wedenig⁸, P. Weilhammer⁸, H. Ziock¹⁵, M. Zoeller¹³

¹ *Institut für Hochenergiephysik der Österr. Akademie d. Wissenschaften, A-1050
Vienna, Austria*

² *MPI für Kernphysik, D-69029 Heidelberg, Germany*

³ *GSI, Darmstadt, Germany*

⁴ *LENS, Florence, Italy*

⁵ *University of Florence, Florence, Italy*

⁶ *LEPSI, CRN, Strasbourg 67037, France*

⁷ *Rutgers University, Piscataway, NJ 08855, U.S.A.*

⁸ *CERN, CH-1211, Geneva 23, Switzerland*

⁹ *CPPM, Marseille 13288, France*

¹⁰ *LEPES, Grenoble, France*

¹¹ *NIKHEF, Amsterdam, Netherlands*

¹² *Centre d'Etudes de Saclay, 91191 Gif-Sur-Yvette, France*

¹³ *The Ohio State University, Columbus, OH 43210, U.S.A.*

¹⁴ *Bristol University, Bristol BS8 1TL, U.K.*

¹⁵ *Los Alamos National Laboratory, Research Division, Los Alamos, NM 87545, U.S.A.*

¹⁶ *Lawrence Livermore National Laboratory, Livermore, CA 94550, U.S.A.*

¹⁷ *Universita di Pavia, Dipartimento di Elettronica, 27100 Pavia, Italy*

¹⁸ *FNAL, Batavia, U.S.A.*

¹⁹ *Sandia National Laboratory, Livermore, CA 94550, U.S.A.*

²⁰ *University of Toronto, Toronto, ON M5S 1A7, Canada*

1 Introduction

High energy physics experiments are investigating the subnuclear structure of matter at ever higher energies and continue to search for the appearance of increasingly rarer events. The requirements particle detectors have to meet become more and more severe. Besides being very precise instruments to determine the energy, momentum, track position etc. of particles the detectors have to be very fast to handle extreme particle rates. Moreover the detectors in the inner regions of experiments at the LHC, TEVATRON or HERA-B have to sustain enormous radiation levels. As an example

at a radius of 7.5 cm the inner tracker of LHC detectors will have to survive charged particle fluences of about $2 \times 10^{14}/\text{cm}^2$ and neutron fluences of about $3 \times 10^{13}/\text{cm}^2$ per year of operation [1].

The present state of the art technology for vertex or inner detectors is based on silicon strip or pixel detectors. Silicon detectors can easily fulfil the requirements concerning the spatial resolution and the read out speed but although silicon is a very radiation hard detector the hostile environment for example at the LHC places a limit on the detector lifetime.

The performance of irradiated silicon detectors is deteriorated by the following effects:

- change of the doping concentration
- increase of the leakage currents
- increase of the detector capacitances
- signal loss due to carrier trapping or incomplete depletion.

The first effect will most probably be responsible for the final failure of silicon detectors. Due to the creation of acceptors in the silicon bulk the n-type material (usually used for detectors in high energy physics) converts after a fluence of $1-2 \times 10^{13}$ particles/ cm^2 to p-type material. After the conversion the steady increase of acceptors demands an increasing bias voltage to ensure full depletion of the bulk. At bias voltages of about 500 V breakdown effects will prevent a further increase. With an optimum choice of the ambient temperature during data taking, but also in shutdown periods (around 0°C), it is expected that silicon strip detectors will keep their functionality in regions where the total particle fluence does not exceed 10^{14} particles/ cm^2 .

CVD diamond material is expected to work even after receiving much higher radiation fluences. In the LHC experiments at radii below 20 cm and in the forward regions (at small angles with respect to the beam axis) diamond is most probably the only material which will survive the full lifetime of the experiment. This application in mind the RD42 collaboration [2] was founded in 1994 with the aim to develop position sensitive diamond detectors which can be placed at smallest possible radii in the LHC experiments.

2 Diamond material

2.1 Basic properties

The first diamond detectors were made using natural diamond [3] more than 20 years ago. However, for high energy physics experiments the demands on the detector material in particular on the electronic properties, the size and also the costs, can only be satisfied using artificially grown diamond material. We therefore use commercially grown chemical vapour deposited (CVD) diamond. The results presented in this paper are obtained using material from the diamond manufacturers St. Gobain/Norton

* and De Beers [†].

CVD diamond grows in a polycrystalline columnar structure along the growth direction. The material starts with small grain sizes ($\approx 1 \mu\text{m}$) on the substrate side. These grains grow in size with material thickness and eventually reach diameters of about $100 \mu\text{m}$ on the growth side. The thickness of the samples ranges from $300 \mu\text{m}$ up to almost 3 mm. CVD diamond is not homogenous through the material and consequently also the electronic properties vary with the thickness.

The basic properties of CVD diamond and silicon are compiled in table 1. An important parameter to compare is the band gap between the valence band and the conduction band. This parameter determines many characteristics important for particle detection. The band gap of CVD diamond is 5.47 eV, which is about five times that of silicon (1.12 eV). As a consequence there are very few free charge carriers present in CVD diamond at room temperature, the resistivity is very high and the leakage currents are very small. Therefore diamond detectors need not be depleted and thus no diode structure is necessary as in silicon detectors. However, the large band gap results also in a serious drawback of CVD diamond: The energy necessary to create an electron-hole pair is rather high in diamond (13 eV) compared to silicon (3.6 eV). A minimum ionising particle traversing a diamond detector of $300 \mu\text{m}$ thickness will release only 10800 electron-hole pairs on average. But other figures like the low dielectric constant, the high electron and hole mobility, the high saturation velocity and the larger radiation length make CVD diamond a very appealing material for charged particle detection.

2.2 Charge collection

The polycrystalline CVD diamond is at present grown on 10 cm diameter wafers and then cut into test samples. The samples are metallised on both sides with ohmic contacts (CrAu or TiAu). Between the two contacts a voltage is applied to generate an electric field in the bulk. A charged particle (mip) traversing the detector loses on average $469 \text{ eV}/\mu\text{m}$ and liberates on average 36 electron-hole pairs per μm ($q=36 \text{ e-h}/\mu\text{m}$). The electrons and holes separate under the influence of the electric field and this drift induces charge in the contacts. A charge integrating amplifier followed by a shaper circuit gives a signal, whose amplitude is proportional to the induced charge.

In diamond the average distance the electrons and holes drift apart until they are trapped is smaller than the detector thickness. This distance, called the collection distance, is given by $d_c = \mu\tau E$, where μ is the mobility of the charge carriers, τ is the mean lifetime and E is the applied electric field. We measure the average d_c using a ^{90}Sr source and by comparing the generated charge $Q_{gen} = qd$ (d is the detector thickness) with the measured induced charge $Q_{ind} = q\langle d_c \rangle$. We use $\langle d_c \rangle$ to characterise the quality of each diamond sample. During the past years large progress has been

*St. Gobain/Norton Diamond Film, Goddard Road, Northboro, MA 01532

[†]De Beers Industrial Diamond Division Ltd., Charters, Sunninghill, Ascot, Berkshire, SL5 9PX England

Material	silicon	diamond
Band gap [eV]	1.12	5.47
Mass density [g/cm ³]	2.33	3.5
Dielectric constant [As/Vm]	11.9	5.7
Resistivity [Ω cm]	2.3×10^5	$>10^{11}$
Breakdown field [V/ μ m]	30	1000
Electron mobility [cm ² /V s]	1350	1800
Hole mobility [cm ² /V s]	480	1200
Saturation velocity [km/s]	82	220
Thermal expansion coeff. [10^{-6} /K]	2.6	0.8
Thermal conductivity [W/cm K]	1.5	10..20
Radiation length [cm]	9.4	12
Specific ionisation loss [MeV/mm]	0.321	0.469
Energy to create eh-pair [eV]	3.6	13
Ave. no. of eh-pairs/mip [e/0.1 mm]	8900	3600
Ave. no. of eh-pairs/mip [e/0.1% X ₀]	8400	4500

Table 1: Material properties of silicon and CVD diamond at 293 K

made in producing material with ever increasing $\langle d_c \rangle$. At present material of up to $\langle d_c \rangle = 250 \mu\text{m}$ is available.

As already mentioned CVD diamond is not homogenous and we have evidence that d_c increases linearly with the detector thickness starting from almost $d_c = 0$ at the substrate side. Fig. 1 shows results from different samples, where a fraction of the material has been removed from the substrate side by lapping. We observe that the average charge collection distance increases about linearly when removing the low quality material from the substrate side. Fig. 2 shows a measurement of the charge collection distance as a function of the electric field. This sample (DBDS39) was grown to a thickness of 1.6 mm and then lapped to 1.1 mm. At an electric field of $1 \text{ V}/\mu\text{m}$ the sample exhibits a charge collection distance of $d_c \approx 210 \mu\text{m}$, which corresponds to a mean signal of about 7500 electrons.

3 Radiation hardness

CVD diamond detectors exposed to irradiation show a remarkable effect at low doses. The charge collection distance increases until it reaches a plateau, which is 50% to 100% above the original pre-irradiated value. The saturated value is reached at about 10 krad. This effect is attributed to charged traps being filled up and neutralised by the initial irradiation. This state, we refer to as the "pumped state", is stable for months provided the diamond is kept in the dark and at room temperature. Exposure

Figure 1: Relative signal size as a function of the material removed from the substrate side

Figure 2: Charge collection distance and mean charge as a function of the applied electric field

Figure 3: Increase of the charge collection distance during the exposure to a ^{90}Sr source

to light brings the diamond back to the pre-irradiated value, corresponding to the unpumped state. This effect is reproducible. Fig. 3 shows the development of the charge collection distance in time when the sample is exposed to a ^{90}Sr source. Given the fluxes in LHC experiments we anticipate that detectors will remain in the pumped state throughout the experiment.

For the application of position sensitive detectors in the inner regions of the LHC experiments one expects the neutron and pion fluxes to be the most harmful radiation sources for the detectors. Irradiation studies with these particles were done using samples with a charge collection distance of about $50\text{ }\mu\text{m}$. During the irradiations all the samples were kept under bias voltage.

For irradiation with neutrons the ISIS spallation source at the Rutherford Appleton Laboratory in England offers a very good test environment. The energy spectrum of ISIS has two peaks at energies of 10 keV and 1 MeV. Diamond samples were exposed to fluences of up to 8×10^{14} neutrons/ cm^2 and the charge collection distance was measured before and after the irradiation. Fig. 4 shows the normalized charge collection distance as a function of the neutron fluence. Up to a fluence of about 5×10^{14} neutrons/ cm^2 we do not observe any degradation. At a fluence of 8×10^{14} neutrons/ cm^2 we see a decrease of the charge collection distance by about 15%.

To test the radiation hardness of CVD diamond with pions we have used a pion beam at the Paul Scherrer Institute in Switzerland. Diamond samples were exposed

Figure 4: Normalized charge collection distance as a function of the neutron fluence

to 300 MeV/c positive pions with fluences of up to 1.8×10^{15} pions/cm². Fig. 5 shows the normalized charge collection distance as a function of the pion fluence. Up to the highest fluence we do not see any significant decrease of the charge collection distance.

These results prove the expected radiation hardness of CVD diamond for the material quality tested so far. In the LHC environment these diamond detectors would survive 10 years of operation even at the smallest envisaged radii (e.g. 7.5 cm in the CMS experiment).

Irradiation studies with protons, gammas, electrons and alpha particles were also performed by the RD42 collaborations, e.g. see reference [4]. At present we are preparing irradiation tests using the latest and best quality diamond samples.

4 Tracking detectors

4.1 Strip detectors with very low noise electronics

Diamond samples with the quality described in the previous chapters were used to build position sensitive strip detectors. This is done by metallising one side of the diamond with a pattern consisting of strips with a strip pitch of 50 μm (100 μm) and a strip width of 25 μm (50 μm). The second surface is fully metallised. The strip detectors have a dimension of 8 mm x 8 mm with a strip length of 6.4 mm. A guard ring is used to keep edge surface currents out of the active region.

Figure 5: Normalized charge collection distance as a function of the pion fluence

The strips are wire bonded (DC coupled) to the individual channels of the front end chip. The chip used is the VA2 circuit [5] with a shaping time of $2 \mu\text{s}$ and an equivalent noise charge of $80 e^- + 11.3 e^-/\text{pF}$. To test and calibrate the electronics a 1.8 pF capacitor is bonded to one input channel of the VA2.

The detector tests were performed in a high energy pion beam at CERN using a precision reference telescope consisting of eight silicon detectors arranged in four sets of x-y planes.

The improvement of the detector quality measured in the source tests is reproduced in the beam tests of the strip detectors. We therefore show only the latest results here. Fig. 6 shows the pulse height distribution of the tracker D39 (pumped) in a recent testbeam. In the figure the charge sum of three strips ($50 \mu\text{m}$ pitch) closest to the predicted impact point is plotted. The mean value of the distribution is 7450 electrons, which is consistent with the measured charge collection distance of $210 \mu\text{m}$. The insert in fig. 6 shows an enlarged view of the histogram around the origin with the pedestal distribution overlaid. The signal-to-noise ratio is about 50 and the signal is reasonably well separated from the pedestal.

Using the telescope information the position resolution of the detector was extracted. The distribution of residuals is shown in fig. 7. The position resolution is about $16.5 \mu\text{m}$ with slight non-Gaussian tails.

Figure 6: Pulse height distribution of tracker D39 with VA2 electronics. Insert: Enlarged view with pedestal overlaid

Figure 7: Residual distribution of tracker D39, VA2 electronics

Figure 8: Pulse height distribution, tracker D39 connected to electronics with 25 ns shaping time (the solid line indicates the range used for the fit)

4.2 Strip detectors with LHC compatible fast read out electronics

Ultimately the strip detectors employed in LHC experiments have to be read out using very fast and radiation hard electronics. It is this electronics in connection with the quality of the diamond material which has to provide a sufficiently high signal-to-noise ratio for a safe operation in the LHC experiments.

We present here preliminary results obtained with the tracker D39 connected to such a read out chip. The chip is the SCT32A [6] built in DMILL radiation hard technology developed for the ATLAS silicon tracker. The shaping time of the chip is 25 ns. The equivalent noise charge is approximately $550\text{ e}^- + 70\text{ e}^-/\text{pF}$ (at $I_C = 25\text{ }\mu\text{A}$). This chip is designed for the use with silicon detectors and is therefore not optimized for a low capacitance detector like diamond.

Preliminary results from a beam test are shown in fig. 8 and in fig. 9. The mean of the pulse height distribution of a three strip sum is 46.1 ADC counts, which corresponds to a value of about 7 in terms of the signal-to-noise ratio. The plot of the residual distribution yields a position resolution of about $21.6\text{ }\mu\text{m}$.

4.3 Pixel detectors

Closest to the interaction region in both experiments ATLAS and CMS several layers of pixel detectors are foreseen. This is the region with the highest particle

Figure 9: Residual distribution of tracker D39, electronics with 25 ns shaping time (the solid line indicates the range used for the fit)

fluxes and therefore is the preferred place where one would consider to use CVD diamond detectors.

To prove that CVD diamond can also be used for pixel detectors we have metalised a diamond sample with an array of 16×16 pixels, each pixel measuring $150 \mu\text{m} \times 150 \mu\text{m}$. As real LHC pixel front end chips were not available we have used a ceramic fan out bump bonded to the detector. Each pixel is connected to an input channel of a VA3 chip.

In fig. 10a the beam profile seen by this detector is plotted. Although the detector used had only a charge collection distance of about $45 \mu\text{m}$ the low channel noise of $\text{ENC} \approx 75 \text{ e}^-$ results in a signal-to-noise ratio of 22. The x and y projections of the track residuals are shown in fig. 10b. As expected for this device the spatial resolution is about $50 \mu\text{m}$ for both coordinates.

5 Summary

In the past years substantial progress has been made in fabricating CVD diamond material with excellent electric properties. The material available now has a charge collection distance of up to $250 \mu\text{m}$ which corresponds to a mean charge of 9000 electrons measured by the electronics. This material was used to demonstrate the functionality of strip and pixel detectors. Diamond strip detectors with $50 \mu\text{m}$ strip

Figure 10: a.) Beam profile measured with the diamond pixel detector. b.) x and y projection of the track residuals.

pitch connected to low noise electronics with a peaking time of 2 μ s have reached a signal-to-noise ratio of up to 50 and a spatial resolution of 16.5 μ m. In a very recent measurement the same tracker was read out by fast (25 ns) and radiation hard electronics exhibiting a signal-to-noise ratio of about 7.

The irradiation studies performed with CVD diamond confirm the radiation hardness of this material. Diamond samples with about 50 μ m collection distance were irradiated with neutrons and pions. Up to fluences of 5×10^{14} neutrons/cm² and 1.8×10^{15} pions/cm² we do not observe a significant degradation of the charge collection distance and therefore the signal output.

We conclude that CVD diamond is a radiation hard material for position sensitive detectors. It is an almost ideal material for regions in experiments where other detectors cannot withstand the high radiation doses.

References

- [1] CMS Technical Proposal, *CERN/LHCC* 94-38,
- [2] The RD42 Collaboration, *CERN/LHCC* 97-3,
- [3] S.F. Kozlov et al., *IEEE Trans. Nucl. Sci.* NS-22 (1975) 160,
- [4] C. Bauer et al., *Nucl. Instr. Meth.* A383 (1996) 64-74,
- [5] O. Toker et al., *Nucl. Instr. Meth.* A340 (1994) 527-579,
- [6] F. Anghinolfi et al., submitted to *IEEE Trans. Nucl. Sci.*,