EUROPEAN ORGANIZATION FOR NUCLEAR RESEARCH

CERN - SPS

CERN LIBRARIES, GENEVA

CERN-SPS/ARF/78-17

CM-P00051830

THE HIGH FREQUENCY LONGITUDINAL AND TRANSVERSE
PICK-UPS USED IN THE SPS

by

T. Linnecar

ABSTRACT

Part I of this report describes the various wideband longitudinal and transverse pick-ups which are used in the SPS for beam observation. The detailed design of each pick-up is given, together with a description of its performance and how it is used in the machine.

Part II describes in similar detail two narrowband pick-ups, the phase pick-up used in the phase loop of the low-level radio frequency accelerating system, and the Schottky scan pick-up, a tunable high frequency pick-up used for measurements of momentum spread in the proton beam.

Geneva - August 1978

Table of Contents

	<u>Page</u>
<u>PART I : THE WIDEBAND PICK-UPS</u>	
1. INTRODUCTION	1
2. GENERAL REQUIREMENTS FOR THE PICK-UPS	1
3. THE ELECTROSTATIC PICK-UP	3
3.1 Theory and design	3
3.2 Results	5
3.2.1 Tests on the bench	5
3.2.2 Tests with cable	6
4. THE WALL-CURRENT PICK-UP	6
4.1 Theory and design	6
4.2 Results	11
4.2.1 Tests on the bench	11
4.2.2 Tests with cable	12
4.2.3 Position sensitivity tests	13
5. THE DIRECTIONAL COUPLER PICK-UP	13
5.1 Theory	13
5.1.1 Constant coupling	14
5.1.2 Exponential coupling	16
5.2 Design	18
5.3 Results	19
5.3.1 Transverse wideband pick-up	19
5.3.2 Response of the longitudinal pick-up	21
5.3.3 Connections for the directional coupler pick-up	22
6. WAVEGUIDE MODE TRAPS	22
6.1 Theory and design	23
6.1.1 Modes in the vacuum chamber	23
6.1.2 Possible damping elements and materials	24
6.1.3 Distribution of ferrite beads in the trap	26
6.1.4 The power test	27
6.1.5 Other design details	27
6.2 Results	28
7. CONCLUSIONS AND FINAL DETAILS	28

	<u>Page</u>
<u>PART II : THE NARROWBAND PICK-UPS</u>	29
1. INTRODUCTION	29
2. THE PHASE PICK-UP	29
2.1 Theory and design	29
2.2 Results	31
3. THE SCHOTTKY SCAN PICK-UP	33
3.1 Theory and design	33
3.2 Results	34
4. CONCLUDING DETAILS	35
ACKNOWLEDGEMENTS	36
REFERENCES	37
APPENDIX (List of drawings)	
FIGURES	

PART I : THE WIDEBAND PICK-UPS

1. INTRODUCTION

Three different types of wideband pick-up are in use in the SPS; these are an electrostatic pick-up, a wall current pick-up and a directional coupler pick-up.

The first is used to provide signals for a permanent display of the longitudinal structure over one revolution period and to measure such low frequency parameters as the injection frequency and debunching time of the injected beam from the CPS. The second is used a) in the time domain for detailed observation of the bunch shape and length (in particular, either a continuous or gated display of the bunch using a sampling system), and for observation of coherent bunch oscillations (displayed using a 1 GHz real time oscilloscope), and b) in the frequency domain, for instability observation, bunch spectra observation etc. The output of a second of these pick-ups is also used to provide a permanent bunch height signal (peak detected wideband pick-up). The third type of pick-up, although useful for longitudinal measurements, especially in the frequency domain, is used mainly for observation of high frequency transverse movement in both the frequency and time domain.

The following text gives a detailed description of the design of these pick-ups, based on guidelines derived from simple theory, followed by details of their performance.

2. GENERAL REQUIREMENTS FOR THE PICK-UPS

Ideally the wideband pick-up would extend from d.c. to many GHz with a sensitivity sufficient to allow observation of a pencil beam of intensity say 10^{10} ppp. It is difficult to design a single pick-up to fulfil or even approach such specifications and originally it was decided to use two or more pick-ups, combining their outputs onto a single cable with suitable multiplexing networks such that the final result was that desired. Experiments in this direction showed the feasibility of such a system, but also showed that the matching networks required introduced considerable loss and consequent pick-up insensitivity. Furthermore, it became clear that the separate

requirements for the signals matched the expected performances of the individual pick-ups. So finally the pick-ups are used independently, and this allows more flexibility since the signals are all available separately at the surface.

The first, lowest frequency, pick-up is the electrostatic pick-up. The beam current transformer provides signals from d.c. to several MHz. The electrostatic pick-up is designed to extend this range to of the order of 1 GHz. 1 GHz is 5 times the fundamental RF frequency and a cut-off at this frequency will allow correct observation of the beam signal at 200 MHz. (The "ringing frequency" is much higher than 200 MHz.) To observe one complete turn of the machine correctly (23 μ secs) the lower cut-off frequency should be of the order of $f_{\text{revolution}}/10$ for negligible phase shift at the revolution frequency (the "droop" along the signal is negligible). With these two end points fixed (18 octaves frequency range), the RF frequency in the CPS falls conveniently within the band, permitting observation of debunching at 10 GeV, residual CPS structure etc. As for the sensitivity, this is allowed to take second place bearing in mind that, provided a good signal-to-noise ratio can be obtained, amplifiers (including low noise amplifiers) exist which cover the whole range and would permit observation at low beam intensities.

The second longitudinal pick-up (the wall current pick-up) is required to provide information on the shape of the individual RF bunches and their length (for emittance measurements). The lower frequency in this case should be $\leq f_{\text{RF}}/10$, i.e. < 20 MHz for minimum distortion of the bunches. The upper frequency is given by the shortest bunch expected (~ 600 psecs at transition) which implies frequencies > 3 GHz (i.e. 8 octaves bandwidth or more). The second major use for this pick-up, observations in the frequency domain of instabilities etc., implies a bandwidth which is reasonably covered by the previous requirements. The sensitivity is much more important than in the electrostatic pick-up case since this pick-up is expected to be the major research tool. Typically the electrostatic pick-up has a sensitivity of $\sim 2 \Omega$ (voltage in 50Ω /beam current). The sensitivity of the wall current monitor should, if possible, be significantly better over the whole bandwidth.

The third type of pick-up, as mentioned in the introduction, can be used for very high frequency observation in the longitudinal domain. However, this directional coupler pick-up lends itself very well to observation in the transverse plane. Here the requirement is very similar to that for the wall current pick-up, i.e. a low frequency response as far below 200 MHz as possible, a high frequency response up to ~ 3 GHz together with a sensitivity as high as possible. On top of this a difference signal is required a) offering as much discrimination against the sum signal as possible and b) which changes linearly with beam position.

3. THE ELECTROSTATIC PICK-UP

The design of this pick-up follows very closely the pick-up described by Umstätter¹⁾, the detailed geometry being changed to suit the SPS.

3.1 Theory and design

Consider a cylinder inside and coaxial with the vacuum chamber as in Fig. 1. Following Boussard and Burnod²⁾, an equivalent circuit can be drawn as in Fig. 2, where C is the capacitance of the pick-up and R is the measuring impedance. The power abstracted from the beam is infinitesimal compared with that available and the beam can be considered an infinite current source.

$$V_{\text{out}} = \frac{(i(t) - i(t + \Delta t))R}{1 + j\omega CR} \quad \text{and} \quad i(t) - i(t + \Delta t) = \frac{di}{dt} \Delta t = j\omega i \frac{\ell}{v}$$

where

ℓ is the length of the pick up, and

v is the velocity of the beam.

Therefore the transfer impedance of the pick-up is given by

$$Z_{\text{transfer}} = \frac{V_{\text{out}}}{I_{\text{beam}}} = \frac{j\omega \ell}{v} \frac{R}{1 + j\omega CR} \quad (1)$$

The pick-up is essentially high pass unless R is very large when Eq. (1) becomes

$$Z_{\text{transfer}} = \frac{\ell}{cv} \cdot$$

The model is accurate only at low frequencies. When the wavelength becomes comparable to the pick-up dimensions, resonances occur and the response is greatly modified. In particular when the electrode length is one half wavelength there is a null in the response, (assuming the output ports are in the centre of the pick-up); a circumferential mode also exists when the wavelength is equal to the mean circumference of the coaxial line formed by the electrode and the vacuum chamber. (The exact frequencies for resonance depend upon fringing fields, etc.). Which of the two is lowest in frequency depends upon the length/diameter ratio of the pick-up. Thus a typical response is as in Fig. 3. (Other spurious resonances due to, for example, the external vacuum box may be important.)

Thus, to push the second type of resonance as high in frequency as possible, the pick-up is made as small as possible. A place in the SPS machine near a QD quadrupole was made available for the wideband pick-up, the beam at this point being at its smallest. The circumferential resonance can also be damped as shown by Umstätter¹⁾. The electrode is cut longitudinally into four parts (refer to Fig. 4) and damping resistors are inserted in the slots formed. Secondly, the output ports themselves can be used to damp waves propagating around the circumference by a suitable choice of components. The optimization of this damping is done experimentally.

Returning to the low frequency model the transfer impedance for R very large has been shown to be ℓ/cv . The capacitance can be divided into two essential parts: that provided by the loading of any external circuits plus any stray capacitance, C_a , and that of the capacitance of the coaxial cylinder, C_b , which will be proportional to ℓ , $C_b' \ell$. Thus

$$Z_{\text{transfer}} = \frac{\ell}{(C_a + C_b' \ell) v} = \frac{\frac{1}{v}}{\frac{C_a}{\ell} + C_b'}$$

To maximize this impedance C_a/ℓ should be small. C_b' is typically 2 pf/cm and C_a is easily 20 pf, forcing ℓ to be $\gg 10$ cms. Unfortunately the electrode should be much shorter than $\lambda/2$ at the maximum operating frequency and for 1 GHz, $\lambda = 30$ cms. A practical compromise is given when the electrode capacitance equals the stray capacitance and here $\ell = \lambda/3$ at 1 GHz. There is some freedom available with C_b' which can be lowered by increasing the outer vacuum chamber diameter, but this is also undesirable because the circumferential resonances are correspondingly lowered in frequency.

The final dimensions can be found by referring to the scale drawing (Fig. 5).

The high impedance required for a good low frequency response precludes direct cable connection and implies an FET, emitter follower, or cathode follower head amplifier. To keep stray capacitance as low as possible, the head amplifier should be placed on the pick-up, and to avoid radiation problems a tube design was chosen (c.f. Umstätter¹⁾). A by-pass circuit across the valve is provided for the high frequency signals and several damping components for the circumferential resonance are added. In the final design head amplifiers were placed on each output port to provide more signal flexibility. The system circuits were adjusted as an ensemble, the final circuit for each amplifier being given in Fig. 6. The vacuum feedthroughs used were a modified form of a feedthrough developed for the position monitors in the SPS¹⁴⁾. They were used finally on all pick-ups described here and details will be given in the section on the wall current monitor.

3.2 Results

The pick-up was adjusted and measured using a 50 Ω test system, with the vacuum chamber itself forming the outer conductor. Conical sections were used at either end to reduce the coaxial line to normal cable size.

3.2.1 Tests on the bench

i) Without amplifier

	Calculated	Measured
a) 1st circumferential mode (mean radius = 10.5 cm)	900 MHz	920 MHz
b) Low frequency cut-off (50 Ω) Capacitance electrode = 26 pf	122 MHz	80 MHz
c) Transfer impedance Z'	13 Ω	11.6 Ω

Fig. 7 shows the 1st circumferential resonance together with curves showing the effect of various damping elements. The 2 dB ripple in the passband is caused by mismatches on this particular test line. The strip-line formed by the cylinder and the exterior has an impedance of $\sim 30 \Omega$.

ii) With head amplifier (input capacitance ~ 20 pf)

	Calculated	Measured
a) Transfer impedance $Z'' = Z' \left(\frac{20}{26+20} \right)$	6.56 Ω	
b) Loss due to matching network in amplifier	$\div 3$	
c) Final transfer impedance	2.2 Ω	1.81 Ω
d) Low frequency cut-off (amplifier input resistance 560 K Ω)	6 KHz	5-6.4 KHz (depending on amplifier)
e) High frequency cut-off		> 2 GHz from risetime measurements

See Figure 8.

3.2.2 Tests with cable

The pick-up as used is joined by a $\frac{3}{8}$ " flexwell cable of length ~ 120 metres to BA3. The results at this point are:

- a) low frequency cut-off 5 KHz
- b) high frequency cut-off 600 MHz
- c) Impedance $\sim 1.1 \Omega$

(By peaking the response in the head amplifier bypass circuit, the affect of the attenuation due to the cable could be compensated.)

4. THE WALL-CURRENT PICK-UP

Several references are available for the wall current pick-up, for example, Borer³⁾, Gelato⁴⁾ and Schneider⁵⁾.

4.1 Theory and design

Consider a circular vacuum chamber with a proton beam passing along the axis. For relativistic proton beams the charge image in the walls is an accurate representation of the charge distribution in the beam (see Kerns and Large⁶⁾). If the vacuum chamber is cut around the circumference and a resistance inserted across the gap formed, then a voltage proportional to the beam current is developed and can be measured. In deriving an equivalent circuit for this pick-up it is supposed that there will be a closed chamber around the gap (Fig. 9). This chamber fulfils several purposes; it shields

the gap from external fields, it can provide a vacuum joint and it can define clearly a d.c. shunt path. As before, the beam is taken as an infinite current source and the equivalent circuit becomes as in Fig. 10. C represents the capacitance across the gap, R the measuring resistance and Z the impedance of the box measured at the gap.

The voltage developed across the gap is thus

$$V = I / (j\omega C + \frac{1}{R} + \frac{1}{Z}) = \frac{RI}{(1 + j\omega CR + \frac{R}{Z})}.$$

As $Z \rightarrow \infty$ this becomes a low pass network, the gap capacitance providing the high frequency cut-off. In general, at low frequencies Z will appear inductive and provide a low frequency cut-off, whereas at high frequencies resonances will occur in the box and modify the impedance accordingly.

A generally used solution to the problem of the external shunt path is to fill the exterior chamber with ferrites; this increases the inductance at low frequencies, lowering the cut-off frequency and also provides an ill-defined damping at very high frequencies where the ferrites become lossy. The procedure adopted here was to attempt to create a well-defined impedance at the gap (suggested by Zettler⁷). The technique is to regard the inner and outer chambers as forming a coaxial line. This line will present its characteristic impedance at the gap if it behaves as if it were infinitely long, i.e. all the power flowing along it from the gap must be absorbed without reflection. Techniques for producing matched loads in waveguides and coaxial lines with absorptive material are well known, the problem here being aggravated by the wide frequency range required (10 MHz to 4 GHz). Such a solution will provide a resistive impedance at the gap above a few MHz; below this frequency it becomes more inductive and remains of course a short circuit at d.c. Thus the high frequency model can be written

$$V = \frac{R'I}{1 + j\omega CR'} \quad \text{where} \quad \frac{1}{R'} = \frac{1}{R} + \frac{1}{Z_{\text{line}}}$$

and the low frequency model is

$$V = \frac{RI}{1 + \frac{R}{j\omega L}}$$

L being the inductance at low frequencies.

The resistance R is assumed to be distributed around the gap so that the beam is enclosed and the voltage measured is independent of beam position.

The detailed design of the pick-up falls into three parts, the gap design, the shielding chamber or "sump" design and the design of the signal output interconnections.

First, the gap design is described. As for the electrostatic pick-up, the wall current pick-up is as small as possible to push the waveguide mode cut-off frequencies as high as possible. For this reason, the pick-up is also near to the QD quadrupole and the maximum beam diameter determines the minimum inner diameter. The gap in the wall should be short compared to the shortest bunch length so that the beam shape is not integrated by the gap. At transition the bunch length shrinks to ~ 15 cms and hence the gap should be less than ~ 7 mm. At the same time for a good high frequency response the capacitance must be low. Clearly a ceramic vacuum seal at or near the gap provides a satisfactory vacuum solution, but the extra capacitance introduced will lower the upper cut-off frequency. A ceramic at the gap may also require shielding from possible charge deposition; this shielding and the ceramic itself will provide a rather ill-defined path for the wall current. Against these arguments is the fact that a vacuum seal away from the gap may make signal transfer difficult and implies that any damping material used in the sump is good for a vacuum. Finally, the latter disadvantages seemed less important than a clear, well-defined gap and the final layout can be seen in Figs. 11 and 14a.

The gap length is clearly smaller than **specified** by the bunch length requirement. The 2 mm length finally chosen was determined by the system of signal transfer to be described later. The capacitance of the gap is of the order of 7 pf which implies a high frequency cut-off of $23/R$ GHz, where R is the total impedance at the gap. Therefore, for a 5 GHz cut-off, $R = 4.5 \Omega$ ($4 \text{ GHz} \rightarrow 5.75 \Omega$). The gap capacitance could be reduced, to allow a **higher** resistance, by using thinner walls for the vacuum chamber or by increasing the gap length. The values chosen are a compromise between the electrical requirements already specified and the mechanical constraints of the signal transfer system.

The next step concerns the design of the sump or outer coaxial line. To do this a 50 Ω coaxial test line was made with inner dimensions equal to the vacuum chamber, each end being connected via a conical section to the measuring equipment. The system was tested with both conical sections in place to check its reflection properties and then one end was replaced by a short circuit. Measuring the reflection coefficient given by various distributions of materials in the line permitted the design of the sump. As expected, the final design reflects the normal design techniques for matched loads, i.e. a gradual change in line properties compared with the smallest wavelength together with a mass of absorptive material for the lower frequencies. The following materials were tried.

- 1) U60 and U17 Sifferit from Siemens.
- 2) Eccosorb H "hair absorber"; Emerson & Cummings.
- 3) Eccosorb ZN tiles; Emerson & Cummings.

The U60 and U17 ferrites were effective at frequencies higher than several hundred MHz. The same was true for the hair absorber which has the added disadvantage of being very bad in vacuum especially when slightly heated. The best material was undoubtedly the ZN ferrite and the final optimum distribution, bearing in mind the restraints of available space in the machine, is as shown in Figs. 12a and 14a.

With this solution the reflection coefficient was < 0.13 for 300 MHz to > 4 GHz. Below 300 MHz, the reflection coefficient slowly increases as the ferrites become less absorptive and more inductive. An approximate lower 3 dB point is given when the resistance across the gap ($\sim 5 \Omega$, as seen before), is equal to the impedance modulus due to this line. This occurs between 5 and 10 MHz. (By taking up more space and increasing the bulk of ferrite the low frequency response can be pushed much lower).

The outer dimensions of the sump were chosen on the basis of the total resistance required at the gap. This depends on the signal transfer system to be described later; a value of 25 Ω characteristic impedance was found suitable and this gives mechanical dimensions which fit well in the available space.

The ZN tiles were tested for their vacuum properties by the ISR (Bramham⁸), and after suitable conditioning (cleaning, baking, etc.) were found to be good. The conditioning does not affect the RF properties. For security a pumping port was included on the side of the first pick-up, but as this has never been used subsequent pick-ups do not have this facility. The ferrites were cut into segments in order to fit accurately around the vacuum chamber, using ultrasonic machining. This process was also used to form the fixing holes in the other tiles. (Note that the screw heads are sunk below the surface of the ferrite.)

The final problem to solve is that of taking the signal from the gap. Coaxial lines were tried initially and, of the various configurations tried, that in Fig. 13 was best, although the upper frequency response was limited by the series inductance of the inner lead across the gap. To overcome this problem a stripline was used, or more exactly eight striplines distributed about the gap (Fig. 14). By using 50 Ω stripline and matching this through the gap to a feedthrough in the outer cylinder, the frequency response was raised to the value expected from the capacitance of the gap. (The 8 $\times$ 50 Ω lines in parallel with the 25 Ω sump give 5 Ω across the gap.) It is important to take care of the matching at all points along the stripline, in particular at the junction between the feedthrough and the stripline. The feedthrough, as mentioned before, is a modified version of the SPS position monitor feedthroughs. The transmission measurement of two such modified feedthroughs back to back is given in Fig. 15. There is a slight droop in the response at about 4.5 GHz and then a much sharper cut-off at about 5.79 GHz. Rise-time measurements confirm the upper frequency to be 5.6 GHz.

In order that the pick-up is insensitive to the movement of the beam the eight output points must be added together. This can be done by a lossy resistive network which will provide some isolation between the outputs. However, bearing in mind the frequency range of the device, i.e. $\sim$ 5 MHz to $>$ 3 GHz, a more suitable solution, offering far more isolation, is to use a sum and difference hybrid. Such a hybrid, the DS-8, manufactured in semi-lumped component technology, is manufactured by ANZAC. This has a guaranteed bandwidth of 2-2000 MHz and pulse response tests indicate an upper frequency cut-off which is much higher. Thus the whole system is in 50 Ω , from the gap outwards, and as long as a reasonable 50 Ω termination is provided by the final cable, there will be no problems from reflections being re-reflected at the gap.

To calculate the expected transfer impedance for the pick-up the model in Fig. 16 is used. R is the resistance given by the eight $50\ \Omega$ striplines in parallel, R' is the impedance of the sump, $25\ \Omega$.

At a frequency low enough for C to be neglected, the current in each resistor (stripline) is $I/10$. The power developed in each line is $\frac{I^2 50}{10^2}$ and the total power at the output of the hybrid is $\frac{I^2}{2} \cdot \frac{8}{K}$, where K introduces the loss in the hybrid. The voltage developed across a $50\ \Omega$ load at the output of the hybrid will be

$$V_{50} = \sqrt{\frac{I^2 4}{K} \cdot 50} \quad \text{or} \quad Z_{\text{transfer}} = \sqrt{\frac{200}{K}}.$$

The attenuation through the hybrid is measured as $\sim 0.5\ \text{dB}$, i.e. $K = 1.122$ and so finally

$$Z_{\text{transfer}} = 13.4\ \Omega.$$

For precise details of the pick-up it is necessary to refer to Fig. 14 or the detailed drawings: one point to note, however, is the use of RF spiral contacts at the feedthroughs and at the vacuum tube joints, this latter ensuring that the current path is disturbed as little as possible in the vicinity of the pick-up. For the same reason, the resonator formed at the joint of two vacuum flanges is filled with a metal disk when the final assembly of the pick-up with the rest of the machine is done.

4.2 Results

4.2.1 Tests on the bench

As described above, the tests were carried out using a $50\ \Omega$ coaxial transmission system with conical adapting sections. Step waveforms were used for the measurements. Fig. 17 shows the step response as seen at any of the eight ports, the other ports being terminated in $50\ \Omega$. From these photos the upper and lower frequency 3 dB points can be calculated as

$$f_{3\text{dB}} \text{ upper} = 4.4\ \text{GHz}$$

$$f_{3\text{dB}} \text{ lower} = 4.2\ \text{MHz},$$

these figures agreeing fairly well with the limits given by gap capacitance and sump inductance.

Fig. 17c shows an interesting effect. The step incident at the gap divides between the sump and the striplines. The higher frequencies in the sump are absorbed but the low frequencies are "reflected" and thus create the decay. However, the reflected waves take a finite time to return to the gap and this means that the decay start is delayed for approximately twice the transit time of the sump.

The photo in Fig. 18 shows the response from the output of the hybrid. These photos give

$$f_{3dB \text{ upper}} = 3.1 \text{ GHz}$$

$$f_{3dB \text{ lower}} = 4.4 \text{ MHz}$$

$$Z_{\text{transfer}} = 15.5 \Omega$$

Clearly the hybrid is at present the limiting factor for the upper frequency response. If this were improved the next limitation would be the gap capacitance/resistance followed by the feedthrough cut-off. The transfer impedance measured is slightly higher than expected.

4.2.2 Tests with cable

The signal from one of the pick-ups is connected via a splitter to a sampling system in a pit next to the pick-up and here the full bandwidth is available. The other half of the split is taken by 120 m of $1\frac{5}{8}$ " Flexwell cable to the Faraday cage in BA3. Here the following parameters are measured using a step waveform

$$f_{3dB \text{ upper}} = 2 \text{ GHz}$$

$$f_{3dB \text{ lower}} = 4.4 \text{ MHz}$$

$$Z_{\text{transfer}} = 13 \Omega \text{ (with no split to the sampling) .}$$

The upper frequency cut-off agrees very well with the expected attenuation due to the 120 m of cable.

A second pick-up is connected directly to console I in the Main Control room via 163 m of $1\frac{5}{8}$ " Flexwell cable. The signal attenuation due to this cable is given in Fig. 19.

4.2.3 Position sensitivity tests

By replacing the inner conductor of the coaxial test system with a wire it is possible to observe the pick-up response to different equivalent beam positions. The output from ports 2 and 6 (diametrically opposed), with $50\ \Omega$ on all other ports, is given for the wire centred and for the wire 20 mm towards port 6 in Figs. 20a and 20b. Repeating the experiment, but observing the output of the hybrid gives the results in Figs. 20c, d and e.

The summation of the eight signals has made the pick-up insensitive to beam position.

5. THE DIRECTIONAL COUPLER PICK-UP

The directional coupler can discriminate, as its name implies, between two electromagnetic fields travelling in opposite directions. Kerns & Large⁶⁾ have described how such a pick-up can be used to observe the motion of beams of particles. A modification to this pick-up, described below, produces a truly wideband performance.

5.1 Theory

The pick-up consists essentially of an electrode placed the length of the vacuum chamber and which couples to both the electric and magnetic fields produced by the beam. At each end the electrode is connected to a feedthrough passing through the chamber wall so that the signal can be extracted. The electrode should be terminated in its characteristic impedance at both ends, cf. Fig. 21.

Assuming that the beam is travelling at or near the velocity of light, then the electromagnetic fields produced by the beam are equivalent to those produced by a coaxial line⁵⁾ and the theory for design of directional couplers as developed by Oliver⁷⁾ can be used. In general, the whole range of design theory for TEM directional couplers can be directly applied, but the most important general result is as follows.

Let the coupling to the beam fields at a point z on the pick-up, see Fig. 21, be described by $K(z)$, then the step response will be given by

$$s(t) = \frac{1}{2} K \left(\frac{vt}{2} \right)$$

where

$$\frac{vt}{2} = z$$

t = time

v = velocity of wave

That is, the response to a unit step function is equal to half the coupling function with z replaced by $vt/2$.

The response in the frequency domain can be written

$$F(\omega) = i\omega \int_0^{2l/v} \frac{1}{2} K \left(\frac{vt}{2} \right) e^{-i\omega t} dt$$

where l = length of pick-up.

The main assumptions which are made are

- a) $|F(\omega)|^2 \ll 1$, i.e. the reaction of the induced waves back on the beam will be negligible.
- b) The electrode is matched in its characteristic impedance and there are no internal reflections.

If, as well, the coupling to the electric and magnetic fields is equal then the pick-up is truly directional, i.e. the signal from the left-hand port will only be present when stimulated by a beam going from left to right and not by one from right to left. This latter property is obviously of use with systems of two beams travelling in opposite directions.

The result given above is now applied to two particular cases.

5.1.1 Constant coupling

In this case the electrode or stripline is of constant width and is placed at a constant distance from the vacuum chamber wall. The following results are obtained:-

$$i) \quad K(Z) = C \quad \text{for } Z = 0 \text{ to } \ell \quad (\text{N.B. } K \text{ is small})$$

$$s(t) = \text{constant} \quad (t = 0 \text{ to } 2\ell/v).$$

$$ii) \quad |F(\omega)| = |K \sin \left(\frac{\ell\omega}{v} \right)|$$

and

$$\angle f(\omega) = \frac{\pi}{2} - \frac{\omega\ell}{v} \quad (\text{using the integral above}).$$

The response to the step function is therefore a pulse of length $2\ell/v$, see Fig. 22. This can be seen qualitatively; as the fields associated with the step on the beam intersect the leading edge of the stripline two waves are produced, one positive which propagates outwards, and one negative which propagates along the line. Similarly, as the beam passes the end of the stripline a positive wave is created in the outward path which cancels the negative wave from the other end immediately, the wave and beam being in synchronism. The negative wave which is also produced at this point propagates to the left and cancels the output after a time equal to twice the transit time along the electrode. Signals thus only appear at the upstream port.

The pulse response, more easily identifiable with a proton bunch, can be found by summing the responses to two step functions, one positive and one negative, separated in time. This is shown in Fig. 23 where the output is seen to consist of a faithful reproduction of the input pulse with a negative ghost at a time $2\ell/v$ later. The pulse length must therefore be less than twice the transit time of the coupler to be distinguished. Repeating such arguments for a sinusoidal waveform shows clearly that, for certain frequencies, a null in the response is produced. Hence, qualitatively the frequency response given above and plotted in Fig. 24 is again derived.

In conclusion, provided the length of the stripline is chosen carefully, the response of the pick-up to a pulse will be exact (ignoring the negative ghost). However, if the frequency response is of primary interest, for example for instability observation, then the 'holes' in the response are rather embarrassing.

5.1.2 Exponential coupling

If the interest is in a flat frequency response then a coupling that decreases slowly along the length of the stripline can be imagined, the 'cancelling' wave from the downstream end becoming negligible. Anticipating the answer somewhat, a coupling constant varying exponentially with distance is assumed. The stripline will therefore have an exponentially decreasing width and will move progressively nearer the vacuum chamber wall to maintain the characteristic impedance.

Thus

$$K(Z) = K \exp\left(-\frac{Za}{\ell}\right) \quad \begin{array}{l} (z = 0 \text{ to } \ell \\ a = \text{attenuation constant}) \end{array}$$

and the step response is

$$S(t) = \frac{K}{2} \exp\left(-\frac{vta}{2\ell}\right) \quad (t = 0 \text{ to } 2\ell/v).$$

In the frequency domain, the integral above gives

$$F(\omega) = \frac{\frac{K\omega\ell}{v}}{\left[a^2 + \frac{4\omega^2\ell^2}{v^2}\right]^{\frac{1}{2}}} \left(1 + \frac{1}{e^{2a}} - \frac{2}{e^a} \cos \frac{2\omega\ell}{v}\right)^{\frac{1}{2}}$$

and

$$\angle F(\omega) = \tan^{-1} \left[\frac{2 \frac{\omega\ell}{v} \sin \frac{2\omega\ell}{v} + a (e^a - \cos \frac{2\omega\ell}{v})}{2 \frac{\omega\ell}{v} (e^a - \cos \frac{2\omega\ell}{v}) - a \sin \frac{2\omega\ell}{v}} \right].$$

The response to a step function is seen immediately (as it simply follows the exponential shape of the line) and, following the procedure in the previous section, the pulse response is readily found, as shown in Figs. 25 and 26. For values of the decay constant which are not large, the negative ghost is still present but smaller.

The frequency response is rather hidden in the formula this time, but a good qualitative feeling can be obtained as follows. First, imagine the case where the decay constant is very large. Here the frequency response is

$$F(\omega)_{a \rightarrow \text{large}} = \frac{K\omega\ell}{\left(a^2 + \frac{4\omega^2\ell^2}{v^2}\right)^{\frac{1}{2}}} .$$

This is the amplitude response of a 1 pole high pass filter, the 3 dB cut-off point being

$$f_{3\text{dB}} = \frac{va}{4\pi\ell} .$$

Now as the constant 'a' decreases in value, keeping the length, ℓ , of the stripline constant, the size of the reflected wave slowly increases, inducing ripples on the amplitude response (see Fig. 27). In the limit, 'a' becomes zero and the formulae reduces to that for the constant coupling case. The peak-to-valley ratio for the ripple is

$$A_{\text{ripple}} = \frac{\frac{K(0)}{K(\ell)} + 1}{\frac{K(0)}{K(\ell)} - 1} .$$

For a given length the low frequency cut-off is pushed lower in frequency as the ripple size increases and finally the choice of the decay constant is a compromise between these two factors and others introduced by mechanical considerations.

It is worth noting that if the coupler is rotated end for end, the signal still being taken from the upstream port, then the step response and phase response will be reversed, see Fig. 28, but the amplitude versus frequency response will remain the same. Hence, if a pick-up is required to respond to beams in both directions and the pulse response is of interest, then a constant or symmetrical coupling might be preferred. If, on the other hand, the amplitude response is of interest then an exponential coupler is entirely suitable.

If the exponential decay is "complete" (e.g. $K(0)/K(\ell) \approx 100$) and the 1 pole high pass filter response is approached, then the interesting possibility exists of combining this signal with that from a low frequency pick-up. The latter's frequency response should be corrected so that a total system response having a linear phase response is produced, i.e. the exponentially decreasing pulse response is corrected by adding an exponentially increasing pulse with the same time constant (see Fig. 29). To add the two signals, a simple resistive

adding network can be used provided that the output impedance of the two pick-ups is constant for all frequencies. This is inherently true for the directional coupler pick-up which has striplines terminated in their characteristic impedance. These ideas, although tried and proved in the laboratory, have not been installed in the machine since the interest in this pick-up lies in its use in the high frequency domain as a transverse and longitudinal instability measurement device. In either case, it is required that the pick-up should give a sum signal insensitive to beam movement in the transverse plane (as well as the difference signal for the transverse type). Using formulae derived from Kerns et al.⁵⁾ or Cuperus¹⁰⁾, the sum and difference signals can be calculated for different configurations (Figs. 30a,b). The results indicate that for a sum signal reasonably independent of beam position the sum of at least four electrodes is required. These can be added together using matched resistive adders which give the maximum bandwidth at the expense of 3 dB loss per addition. It is not necessary to provide isolation since all the system including the striplines is in 50 Ω and reflections are absorbed by the terminating loads. When higher sensitivity or a difference signal is required, then sum and difference hybrids can be used. The frequency response will then be limited by the hybrid.

Finally, to conclude this section, it is plain that many different shapes for the stripline may be chosen. In particular, the equal ripple Chebyshev or even more complicated forms, could be used to reduce the ripple in the passband. This is a possibility for future development.

5.2 Design

The design follows in a straightforward way from the ideas presented above. The length of the pick-up is determined primarily by space considerations. A possibly equally important factor is the requirement that the electrode itself should be self-supporting; any ceramic or other supports in general introduce reflections and slow down the coupled wave. Standard feedthroughs, as described before, are used, one at each end of each coupler, reducing termination problems and allowing access, if required, to the signal from beams in both directions. Mechanical constraints imply a minimum size for the thin end and also for the thickness of the electrode which in theory should be infinitely thin so that the edges do not disturb the fields and produce an apparent increase in width. The other end is as large as possible, bearing in mind that the larger it is, the larger the outer envelope must be,

since the 50 Ω match must be maintained on the stripline, and the lower the first waveguide mode resonance will be. The width also influences the matching problems at the junction between the stripline and the feedthrough.

The exponential decay constant is thus determined and the electrode can be machined on a numerically-controlled mill to this shape. (Corrections for the finite thickness can be calculated and included in the final design.) To maintain the 50 Ω impedance along the line it must be curved in an exponential form towards the wall. This was accomplished by observation of the time domain reflectometer response, the stripline being formed manually to the correct shape and then clamped by a fixing screw on each feedthrough (see Fig. 31a and the photos Figs. 31b and 31c).

With no support other than at the ends, mechanical vibrations were observable if the pick-up was sharply knocked, but the original shape was quickly regained. The optimum matching at the ends into the feedthroughs was found experimentally again using TDR techniques.

5.3 Results

5.3.1 Transverse wideband pick-up

Two pick-up configurations were designed to be used for measurements in the transverse plane. Identical striplines are used, but the pick-ups differ in their outer dimensions. The larger is placed in the ring at a position approaching β_H max (31799) and is used for horizontal measurements. The other type is used in two positions; one is placed at β_V max (31931) for vertical measurement and the other is used in the horizontal plane at a position where $\alpha_p/\sqrt{\beta_H} \times dV/dx$ is optimum (31102) (dV/dx represents the sensitivity of the pick-up). This position gives some discrimination between the α_p and β_h functions.

The pick-up was tested as a coaxial line as described in the previous sections. The final dimensions for the stripline are given in Fig. 31. From these the decay constant is calculated as $a = 2.485$.

i) TDR response of stripline

A typical response is given in Fig. 32. The ceramic in the feedthrough is clearly visible. All striplines were adjusted so that $\rho < \pm 0.05$.

ii) Step response

The step responses of the test line and of the corresponding output from a single stripline are given in Fig. 33. Note the exponential decay as expected, the finite response from the thin end of the coupler and the superimposed resonance at ~ 4.44 GHz. The characteristics for a single stripline in the smaller pick-up are:-

	Measured	Calculated
f_{3dB} upper	~ 6 GHz	-
f_{3dB} lower	133 MHz	150 MHz
Transfer impedance	4 Ω	-

The signals from the four electrodes in the transverse pick-ups are combined using Anzac H-183 hybrids which have a frequency response from 30 MHz to > 3 GHz. The hybrids are connected as in Fig. 34. The sum step response from one pick-up is shown in Fig. 35 and the following results are obtained:

	Smaller pick-up	Larger pick-up
f_{3dB} upper	4.00 GHz	3.3 GHz
f_{3dB} lower	133 MHz	163 MHz
Transfer impedance	5.73 Ω	3.94 Ω

(Note that the resonance is much less in evidence.)

iii) Directivity

With a step response as given in Fig. 36 found at the upstream port, the response at the downstream port is as in Fig. 36a. The high frequencies are the least discriminated against and the amplitude indicates a directivity of ~ 16.5 dB. Fig. 36b shows the response from this port for a beam travelling in the opposite direction.

iv) Frequency response

The frequency response of the sum signal as measured between 0 and 2 GHz for the larger pick-up can be seen in Fig. 37. The ripple is not constant as expected, but increases slowly. However, an analysis of the electrode as it actually is, i.e. with a largish securing pad for attaching the thin end to the feedthrough, gives the theoretical graphs shown in Fig. 38. These show very good agreement with the measured response.

v) Isolation

The isolation between two pairs of couplers is > 50 dB up to the cut-off frequency of the vacuum chamber. Above this frequency, resonances reduce the isolation to ~ 20 dB at the peaks (as measured to 4 GHz). However, this isolation can be improved considerably at high frequencies by placing ferrite beads between the couplers (see Fig. 39). The pick-ups as installed do not contain these ferrites and their usefulness for difference measurements is limited at high frequencies by resonances. For the larger pick-up the upper useful frequency is ~ 1.1 GHz and for the smaller ~ 1.7 GHz.

vi) Linearity of difference signal

This was measured by displacing a thin wire in the chamber at 45° to the electrodes. (The pick-up is mounted at 45° to the horizontal.) The wire carries a pulse and although the wire is not matched the pulse is short enough to be readily distinguished from reflections. The change of impedance of this line with eccentricity is of the order of 5% maximum for the displacements used and neglected. The results for the smaller pick-up are given in Fig. 40. The general response agrees very well with that predicted in Fig. 30b. The difference transfer impedance Z_D is calculated as:-

	Smaller pick-up	Larger pick-up
Z_D	$0.11 \Omega/\text{mm}$	$0.065 \Omega/\text{mm}$

5.3.2 Response of the longitudinal pick-up

One of the directional coupler pick-ups as used in the SPS is connected specifically as a longitudinal pick-up and is placed next to the wall current and electrostatic pick-ups. Instead of adding the signals with hybrids, which limits the frequency response, resistive adders are used (see Fig. 4), these having a bandwidth far in excess of the bandwidth of the pick-up.

The results for this pick-up, which has a modified stripline (larger and with a smaller pad for attaching the thin end) are as follows:-

$$f_{3dB \text{ upper}} = 5 \text{ GHz}$$

$$f_{3dB \text{ lower}} = 187 \text{ MHz}$$

$$\text{Transfer impedance} = 3.5 \Omega$$

It should be noted that this high frequency pick-up is protected from waveguide resonances by ferrite traps which will be described later.

5.3.3 Connections for the directional coupler pick-ups

The difference signals from the pick-ups 31799 and 31931 are routed through to console No. I in the Main Control room. The sum signals are available in the computer room. The signals from 31102 go directly to the Faraday Cage from where, if required, they can be routed to the Control Room via the high frequency multiplexer. Figs. 42a and b give details of cable numbers, types and lengths.

6. WAVEGUIDE MODE TRAPS

In the previous section describing the pick-ups, mention has been made of the need for the high frequency pick-ups to be as small as possible to raise the frequency at which spurious resonances become possible. These resonances can occur within the pick-up itself or can exist elsewhere in the machine and couple to the pick-up via the vacuum chamber, since for any given piece of vacuum chamber there is a frequency above which energy can propagate. This waveguide cut-off frequency depends upon the shape and dimensions of the vacuum chamber, but in principle the smaller the tube the higher the frequency. Any discontinuity in the vacuum chamber can excite electromagnetic waves when the beam passes and these will propagate in both directions away from the discontinuity. Above a certain frequency, the pick-ups are thus sensitive not only to the beam fields, but also to fields propagating in these waveguide modes.

To try and alleviate this problem, "waveguide mode traps" have been built. Effectively they consist of two sections of vacuum chamber which sit on either side of a pick-up and ideally absorb all energy above the cut-off frequency.

It is clear that they should not couple strongly to the 200 MHz fundamental accelerating frequency or its harmonics so that they do not absorb beam energy and heat-up. Therefore this trap should preferably start to work only near the cut-off frequency of the pick-up vacuum chamber. A further design criterion is that they should not only absorb energy coming from outside the pick-up, but they should also not reflect any waves generated within the pick-up itself. This is not such a serious problem since the pick-up, in particular the wall current monitor, is designed to look as "smooth" as possible to the beam.

The waveguide mode traps, the design of which follows, are used in the SPS at present only with the longitudinal pick-ups. As already mentioned in the section on transverse pick-ups, it is probable that they would also benefit from the damping of resonances caused by the pick-up itself and by the adjoining vacuum chambers.

6.1 Theory and design

6.1.1 Modes in the vacuum chamber

All the pick-ups described so far are circular in cross-section. From the outset it is assumed that the trap will take the form of a cylinder and consequently only modes propagating in circular waveguides are considered. The following table gives the first few modes that will exist together with their cut-off frequencies for two particular values of b , the radius of the chamber. First 50 mm, which will be of the right order of magnitude for the trap radius, and secondly 41.5 mm, which is the internal radius of the wall current monitor.

Mode	TE ₁₁	TM ₀₁	TE ₂₁	TE ₀₁ , TM ₁₁
b/λ_c (λ_c = cut-off wavelength)	0.293	0.383	0.486	0.610
Cut-off frequency GHz (b=50 mm)	1.798	2.298	2.917	3.66
(b=41.5 mm)	2.118	2.769	3.514	4.41
Cut-off frequency normalized to TE ₁₁ mode cut-off	1	1.307	1.659	2.08

For the pick-up alone, it can be seen that it is protected to about 2 GHz, remembering that energy can penetrate in an evanescent mode even below the cut-off frequency. The first mode that can be present is the TE₁₁ mode which

has no longitudinal electric field and which will not be seen by a perfect longitudinal sum pick-up. However, imperfections in the pick-up may make the presence of this mode felt. The first mode with longitudinal electric field is the TM_{01} which is present above 2.7 GHz. After that the TE_{21} is followed by the second mode with longitudinal electric field, the TM_{11} . This latter will only be present above ~ 4.4 GHz. Thus the two modes which should really be damped are the TE_{11} and the TM_{01} and it is on these that emphasis is placed. (Even so the trap will also couple to fields of TE_{21} , TM_{11} , etc. modes.) With the damping of the first two modes the pick-up will be protected to 3.5 GHz and, since the TE_{21} is similar to the TE_{11} , probably to 4.4 GHz.

6.1.2 Possible damping elements and materials

a) Probes and antennae

It is possible to make probes or antennae which are broadband and which can couple strongly to certain field configurations. For example, the standard waveguide to coax transition can be considered as such a probe and a shaped slot in a waveguide wall can radiate energy like an antenna. In general, however, a probe or antenna which couples strongly to one mode will not couple **efficiently** to another. This implies at least one probe per mode per trap. The traps are to be used to protect the two high frequency pick-ups, the wall-current and the directional coupler. These two sit with the electrostatic pick-up in a space of ~ 2 m and there is not much room for the traps. This excluded the use of antennae almost immediately. Experiments with probes indicated that for strong coupling they should penetrate further into the chamber than could be allowed and so this approach was abandoned in favour of a dissipative trap.

b) Absorbing materials

A dissipative trap is simple to conceive. There is simply a layer of material surrounding the beam which absorbs microwave energy flowing in the waveguide. Experience in the design of the pick-ups shows how such material can be used. The following were tried:-

i) Eccosorb Hair Absorber	) Emerson & Cumming
ii) ZN ferrite (tiles)	
iii) U60 ferrite (beads)	) Siemens
iv) U17 ferrite (beads)	

- i) Eccosorb This was quickly abandoned because its poor vacuum qualities imply ceramic windows which would create matching problems in the trap.
- ii) ZN, U60, UI7 These three ferrite materials can be most easily compared
- iii) by reference to the following table which gives the attenuation length
- iv) (i.e. the length at which the fields travelling in the material have dropped to $1/e$ of their initial value), for various frequencies:

Frequency	attenuation length (mm)			
	200 MHz	600 MHz	1000 MHz	3000 MHz
ZN	5.047	-	3.748	-
U60	1661	76.25	9.1	3
UI7	5580	16.67	8.63	-

ZN material, as noted before, is very broadband and will absorb as strongly at 200 MHz as at 1000 MHz. The U60 and UI7 materials are far more attractive. At 200 MHz the U60 is more lossy than the UI7, but even so still has an attenuation length of 1.6 metres. By 600 MHz the two have changed over, the UI7 already approaching the losses of the ZN while the U60 still has an attenuation length of 8 cm. At 1 GHz and above they have very similar attenuation characteristics.

The power in the beam is concentrated at the harmonics of 200 MHz, the accelerating frequency. Taking a cosine squared distribution for the proton bunch intensity, graphs as in Fig. 43 can be plotted. As the bunching factor increases the current in each harmonic component increases and approaches twice the d.c. value of the beam. (The cosine squared distribution is a more reasonable distribution to take than either the cosine or parabolic distributions.) What is of interest is the mean power dissipated during one machine cycle where the bunching factor is continually changing from a minimum of ~ 1 at injection to a maximum of ~ 8 for a brief moment at transition energy. This mean power is difficult to estimate; however, it would seem that at least the harmonics to 600 MHz should be considered. With this in mind, the U60 material is chosen so that large attenuation of the microwave frequencies can be expected with minimum coupling to the beam.

6.1.3 Distribution of ferrite beads in the trap

a) The test set-up

To determine the optimum distribution of U60 ferrite beads, two test systems were made. These consisted of silver-plated brass cylinders of the required diameter, (pick-up diameter plus twice the bead height), short-circuited at either end. Probes were inserted in these waveguides to excite the required TE_{11} or TM_{01} mode (Fig. 44). By varying the probe shape and its dimensions and position in the cylinder, a good match to the waveguide can be obtained over a fairly wide frequency range, as shown in the following table:-

Mode	Cut-off frequency for 104 mm diameter waveguide (GHz)	Operating frequency range (GHz)
TE_{11}	1.7	1.7 $\rightarrow$ 2.25
TM_{01}	2.2	2.25 $\rightarrow$ 3.625

Resonances occurred just outside the passband at 2.35 and 2.45 GHz for the TE_{11} mode, probably caused by excitation of the next mode. There was one sharp resonance in the passband at 2.725 GHz for the TM_{01} mode.

b) Results with ferrite beads

The graphs in Figs. 45a and 45b show the transmission characteristics for several variations of the final type of distribution of beads chosen. The usual gradual change in properties is required for low reflection, together with a mass of material for good absorption. The final layout is given in Figs. 46a and 46b. Two versions are shown, one for the trap used at either end of the pick-ups and one for the trap used between the two pick-ups.

For the TE_{11} mode, rotation of the ferrites relative to the probes to give various polarizations of the fields showed no effects. For the TM_{01} mode, a comparison was made between the U60 and the U17 material; here again there was no effective difference.

The results for the final distribution are summarized below:-

	Transmission loss	Reflection loss
TE_{11}	≥ 12 dB	≥ 16 dB (decreasing slightly towards the higher frequencies)
TM_{01}	≥ 14 dB	≥ 10 dB

6.1.4 The power test

Once a final distribution for the ferrites had been determined, a test was made to estimate the effect of a high intensity beam on the ferrites. A "worst case" was taken where a cosine square proton pulse with a bunching factor of 10 was constantly present. Since there was no facility available for producing such a pulse it was decided to refer all frequencies to 200 MHz. Measurements with a coaxial line and the ferrites gave the attenuation of the ferrite bead system at all frequencies to 2 GHz. The current flowing in the walls for a given beam intensity can be calculated for the 200 MHz component. For each higher harmonic, extra power is absorbed by the ferrites, but there is a weighting factor due to the Fourier distribution. Adding all components to 2 GHz gives finally the power required at 200 MHz to simulate this beam using a normal coaxial line. Such a coaxial line with the ferrites inside and suitable adapters at either end was made and connected to a power amplifier at 200 MHz. Heat sensitive paints were used to determine the temperature change and power was applied up to 1 KW (three times the calculated value). The temperature of all ferrites remained below 60°C and with all the safety factors included (three times calculated power, continuous operation, equivalent bunching factor 10) it was concluded that no problems would arise.

6.1.5 Other design details

The waveguide mode traps are made in two forms. One consists of four lines of ten beads at 90° , followed by three rings of ferrites and this is used at the upstream end of the wall current pick-up and the downstream end of the directional coupler pick-up. Between the two pick-ups is the second form of trap which has three rings of ferrites with four lines of five beads, at 90° , on either side. The beads are held by beryllium copper clips which are spot-welded onto the support. The trap at the downstream end is actually placed inside the directional coupler pick-up to gain space and this allows the 2×210 mm required for the other two traps. The fingers and rings are held in place by conical pieces at each end (see Fig. 47), which also serve to fill the gap present in the vacuum flange (a high frequency resonator). Note that the ferrites are set back with respect to the 83 mm wall current pick-up and hence it is expected that the reflection is now much lower. The diameter of the trap is given by the 83 mm of the pick-up plus 2×8.5 mm for the ferrite beads, plus 4 mm safety factor.

The ferrites were baked and cleaned before final installation.

6.2 Results

Measurements of the harmonic distribution in the beam during a normal cycle (Fig. 48) show that the power test was very conservative and the traps should be safe to very much higher intensities. As to their behaviour as traps, this has been impossible to estimate. Certainly they have caused no problems and hopefully they are eliminating some problems. Operational experience with the transverse pick-ups indicates that they might benefit greatly from the addition of such traps.

7. CONCLUSIONS AND FINAL DETAILS

The final complete layout of the longitudinal pick-up is given in Figs. 47a and 47b. The longitudinal and transverse pick-ups are all isolated from their supports by kapton film and from the adjacent vacuum chambers by ceramic coated flanges. In this way the earth point for each pick-up exists at one point only, i.e. either the Faraday cage or the Main Control room. The cabling diagram for all the pick-ups is given in Fig. 42, and reference should be made to this for details of signal outlet points, etc.

PART II : THE NARROWBAND PICK-UPS

1. INTRODUCTION

The two narrowband pick-ups to be described here are the phase pick-up and the Schottky scan pick-up.

The first provides information about the phase of the main RF accelerating frequency component on the beam, information which is used in the phase correcting loops of the low-level RF system. The second is a tunable pick-up which is designed to be at least an order of magnitude more sensitive than the wideband pick-ups previously described. It is used for observation of high frequency noise on the beam with a view to obtaining information about the momentum distribution of protons in the beam.

2. THE PHASE PICK-UP

Where the frequency change of the accelerating signal during acceleration is large, then a pick-up designed to observe the phase of the RF component on the beam must either be wideband, with a linear phase versus frequency response, or must be narrowband and tuned or narrowband with phase correcting networks. If, as in the SPS, the frequency change is small (0.5%), then the possibility exists of using a fixed tuned cavity resonator of moderate Q . This will have a linear phase response over the frequency range of interest and at the same time a high sensitivity. The latter property is particularly useful for certain modes of operation such as very low intensity or coasting beam (low phase noise).

2.1 Theory and design

This is treated very briefly. The phase pick-up is designed as a fixed tuned low Q resonator. An inner diameter for the vacuum chamber of 156 mm was chosen so as not to restrict the choice of position in the machine. A suitable ceramic seal was available from the ISR, (drawing No. 214.157.2A) and the pick-up was designed around this. A re-entrant cavity was chosen (Fig. 49); this allows the cavity to be tuned by adjusting the length and provides a good R/Q value. Published curves, e.g. Ginzton & Nalos¹²⁾, indicate that the R/Q has a rough maximum for a square toroidal cross-section.

Curves are also available for calculating the resonant frequency, e.g. Moreno¹¹⁾, but with a large internal diameter for the vacuum chamber these become inaccurate and it is better to determine the approximate length using a model. The tolerances on the construction of the ceramic are an important factor in determining the resonant frequency. Using simple reasoning the ceramic seal can be taken as a parallel plate capacitor, hence

$$\text{capacitance } C = \frac{K2\pi rx}{t}$$

K = constant
x = thickness
r = radius
t = length

therefore

$$\frac{\Delta C}{C} = \frac{\Delta r}{r} + \frac{\Delta x}{x} - \frac{\Delta t}{t} .$$

If this capacitance resonates with the external cavity as an inductance then

$$\frac{\Delta \omega}{\omega} = \frac{1}{2} \frac{\Delta C}{C} .$$

For a tolerance of 0.1 mm in the thickness of 6 mm, $\Delta x/x = 1.7\%$ and hence $\Delta \omega/\omega = 0.85\%$. This value of $\Delta \omega/\omega$ is greater than the frequency swing and indicates why each pick-up must be tuned with its own ceramic. The tuning is done by machining the edges of the end plate, thus altering the length of the cavity.

The Q must be fairly low to give the required phase variation with frequency. For a simple resonant circuit the phase change with frequency is given by

$$\tan \theta = - \left(\frac{\omega}{\omega_0} - \frac{\omega_0}{\omega} \right) Q$$

$\omega_0 = 2\pi \times \text{resonant frequency}$
Q = loaded Q of cavity

differentiating and letting ω tend to ω_0 gives

$$\frac{d\theta}{d\omega} = - \frac{2Q}{\omega_0} = \tau, \text{ the delay .}$$

The signal from the pick-up will be compared with the signal from the main cavity. This latter signal can be delayed by $2Q/\omega_0$ so that only the non-linear part of the phase response is of importance when the phase comparison is made.

Then

$$\theta - \theta_{lin} = \tan^{-1} \left(\frac{\omega_0}{\omega} - \frac{\omega}{\omega_0} \right) Q - \frac{2Q}{\omega_0} (\omega - \omega_0) .$$

If $\theta - \theta_{lin}$ is limited now to 1° maximum for the total frequency change of 0.5%, then Q_{maximum} is found to be ~ 59 . In fact the delay can be under-compensated slightly to distribute the error (see Fig. 50). In this way, the Q can be allowed to rise to ~ 100 .

To obtain this low Q a large coupling is required. The cavity could also be damped with ferrites or with the use of lossy material in the construction, but in this case the cavity will heat as a function of the beam intensity, i.e. the resonant frequency and thus the phase will change. It is better to take the power out of the cavity. Large coupling can be obtained using large loops whose inductance may have to be tuned out by series capacitors; this would introduce more coupled resonant circuits. The final solution was four untuned loops.

The loops should be terminated in 50Ω . The signal can be taken from any one and the other three can be loaded with 50Ω , or for maximum transfer impedance the four signals can be added. A 4-input, radiation resistant, hybrid, the DMS115 is available from TRM Inc. The hybrid is narrow-band, but over the frequency range of interest the phase change is less than $\pm 0.35^\circ$.

The final mechanical design is given in Fig. 51.

2.2 Results

The measurements and calculations are summarized in the following table:

Table I

	Phase pick-up 1		Phase pick-up 2	
	Calculated	Measured	Calculated	Measured
Resonant frequency (20°C) MHz		199.950		199.972
Loaded $Q = Q_L$		63.5		64.7
Unloaded $Q = Q_O$		2576		2621
R/Q corrected for transit time factor ¹⁾ Ω/m	25 ²⁾	37.17		
Transit time factor	0.973 ³⁾	0.9737		
Transfer impedance Ω				
i) Normal operation	321		323	
ii) Single bunch operation	11		11	
Cavity delay at $\omega = \omega_0$ nsecs	101.1	98.3	103	
Non-linear variation of phase with frequency $\left\{ \begin{array}{l} \text{i) no hybrid} \\ \text{ii) phase hybrid} \end{array} \right.$	< 1°	< $\pm 0.5^\circ$ $\leq \pm 0.5^\circ$		$\leq \pm 0.5^\circ$
Maximum variation in signal amplitude across frequency band		0.5 dB		0.5 dB
For a beam of 10^{13} particles: (max. RF component)				
i) Power dissipated in cavity	0.6 W			
ii) Power coupled out by each loop	5.77 W			
iii) Power dissipated in hybrid	2.52 W			
Change of phase with beam position °/mm		≤ 0.025		
Change of frequency/phase with temperature		7 kHz/°C $\equiv 0.3^\circ/\text{°C}$		

- 1) The R/Q and transit time factor are measured in the normal way by passing a bead through the cavity and measuring the phase change at constant frequency as a function of the bead position.
- 2) Estimated from the curves of Ginzton and Nalos (Ref. 12).
- 3) Calculated from formulae given by Beck (Ref. 13).

3. THE SCHOTTKY SCAN PICK-UP

The determination of the momentum distribution in a proton beam by observation of the frequency spectrum is well known. Since the start-up of the SPS, the wall current pick-up, previously described, has been used with some success to observe the width of spectral lines of unbunched beams and hence to calculate the $\Delta p/p$. A spectrum analyzer is used to make the analysis, and the optimum frequency has been found to be between 500 and 1500 MHz. It became evident that the measurement would benefit greatly from an increase in pick-up sensitivity and hence the Schottky scan pick-up was designed.

3.1 Theory and design

The operating frequency of the pick-up should be within the range 500 → 1500 MHz. To obtain the high frequency response, it is necessary to keep the pick-up small. It is therefore designed to be used near a QD quadrupole. To alleviate vacuum problems, it was decided to build the pick-up around a ceramic vacuum seal in the vacuum chamber. Mechanical constraints determined the design of this seal, though it was kept reasonably small.

The need to obtain the required frequency range and yet maintain a good sensitivity implies a tunable resonating cavity. An elongated re-entrant cavity can be tuned by varying its length, e.g. by using a movable piston (see Fig. 52). With the piston at its furthest from the gap, the cavity can be considered as a lumped capacitance at the gap tuned by the inductance of the short circuited line. At the other extreme the cavity approaches a TM₀₁₀ type cavity for the highest frequency. These two factors, together with the diameter of the vacuum chamber, determine the main cavity dimensions. The piston should provide a low impedance current path between the walls of the pick-up and hence sliding RF contacts are used around the piston.

The ceramic itself is too long to be considered as the measuring gap. For high frequencies the transit time would be too great and the effective R/Q would drop rapidly. Hence the inner wall of the cavity is extended along the ceramic to provide a gap of 10 mm ($\lambda/20$ at 1500 MHz). The ceramic will still affect the field distribution but this will be included in the measurements.

To extract the signal from the cavity a loop coupling to the circumferential magnetic field is used. The loop serves not only to extract the signal, but also to define the loaded Q . This latter is determined by a compromise between several factors.

- 1) Usable bandwidth at the resonating frequency.
- 2) Transfer impedance.
- 3) Maximum allowable gap voltage.
- 4) Power dissipation in the cavity.

The compromise value is ~ 400 which gives good sensitivity whilst presenting little risk of breakdown should the cavity be tuned to a harmonic of the RF accelerating frequency. (It is wise, nonetheless, to avoid these frequencies.)

The loop and its rigid supporting line can be seen in Fig. 53. The whole line has an impedance of 50Ω and is terminated in an N-type connector.

The cavity is attached to one side of the ceramic seal using pins. The electrical contact is made on both sides using spiral spring contacts.

To tune the cavity, the piston is moved by pushing/pulling at three points on the circumference to avoid misalignment and jamming. A motor is used via a pre-set clutch and chain drive. The slider of a linear potentiometer is moved in parallel to the piston and its varying resistance gives an indication of the resonant frequency.

3.2 Results

The measurements are summarized, for a particular frequency, in the table below. For results at other frequencies the graphs in Figs. 54 to 58 should be consulted. Fig. 54 shows, as a function of frequency, the R/Q uncorrected and corrected for the phase slip τ which is also given. Note how the R/Q rises by a factor 2 as the cavity becomes shorter. At the same time, the transit time factor decreases (finite gap length) and the result is a corrected R/Q which decreases with frequency. Fig. 55 shows the Q 's measured. The unloaded Q_u of the pick-up is fairly constant at 1250 ± 150 (the cavity is made of ANTICO). The coupling factor for the loop varies considerably passing through a broad maximum at 1200 MHz. The loaded Q_L variation is thus dominated by the coupling factor.

Fig. 56 shows the transfer impedance

$$\left(Z_{50 \Omega} = \sqrt{\frac{50 Q_L \cdot (Q_U - Q_L)}{Q_U} \cdot \frac{R}{Q}} \right),$$

the shunt impedance ($R_{sh} = R/Q \cdot Q_L$) and the power dissipated in the cavity

$$\left(\frac{P_c}{I_b^2} = \frac{Q_L^2}{Q_U} \cdot \frac{R}{Q} \right).$$

Fig. 57 gives the resonant frequency as a function of the resistance measured on the potentiometer, and Fig. 58 plots the higher order modes found as a function of the fundamental frequency.

Table II

Tuning range 520 MHz $\rightarrow$ 1640 MHz

For a fundamental frequency f_0	1490 MHz
the following values are found:	
potentiometer resistance	280 Ω
1st harmonic (dipole)	1700 MHz
2nd harmonic (quadrupole)	2050 MHz
unloaded Q	1250
loaded Q	340
bandwidth (3 dB)	4.4 MHz
R/Q corrected	12.5
transit time factor t	0.58
transfer impedance	385 Ω
P_{cavity}/I_b^2 (I_b = beam current at f_0)	950 W/A ²
(Power output into 50 Ω)/ I_b^2	2964 W/A ²

4. CONCLUDING DETAILS

The signals from the two phase pick-ups and the Schottky scan pick-up arrive in the Faraday cage from where the latter can also be tuned. The cables for the phase pick-ups are compensated $7/8$ " Flexwell (phase compensated for temperature changes) and for the other normal $7/8$ " Flexwell. For more details refer to the cabling diagram (see Fig. 59).

ACKNOWLEDGEMENTS

The design of the pick-ups has benefited greatly from many fruitful discussions with C. Zettler and D. Boussard. For the mechanical design R. Gueïssaz and P. Griessen have given invaluable help.

REFERENCES

- 1) H. Umstätter, The new wide-band pick-up station of the PS, CERN/MPS/SR.70-1.
- 2) D. Boussard and L. Burnod, Choix du type de détecteurs de position pour le SPS, Lab. 11-CO/BM/72-6.
- 3) J. Borer, private communication.
- 4) G. Gelato, PSB wideband observation system - survey of options and proposed solution, SI/Note EL/70-5.
- 5) G.C. Schneider, Signal transmission theory of the low-energy UHF wideband pick-up station for the new Linac, MPS/AE/Note 74-6.
- 6) Q. Kerns and D. Large, Analysis of a travelling wave beam electrode, July 7th, 1964, UCRL-11551.
- 7) C. Zettler, Private communication.
- 8) P. Bramham, RF tests on Eccosorb ZN ferrite tiles for damping cavities, BEIC-133/PB/ps.
- 9) B.M. Oliver, Directional electromagnetic couplers, Proc.I.R.E., Vol. 42, No. 11, pp.1686-1692.
- 10) J. Cuperus, Monitoring of particle beams at high frequencies, CERN/PS/LIN 76-7.
- 11) T. Moreno, Microwave transmission design data, Dover Publications Inc.
- 12) E. Ginzton and E. Nalos, Shunt impedance of klystron cavities, IRE transactions, Microwave Theory and Techniques, October 1955, pp.4-7.
- 13) A.H.W. Beck, Velocity modulated thermionic tubes, Cambridge University Press, 1948.
- 14) R. Bossart and J-P. Papis, Lab. 11-CO/Spec./73-12.

APPENDIX

LIST OF DRAWINGS

(These drawings can be referred to for numbers of more detailed drawings.)

1. Electrostatic pick-up	8022.0052.1B
2. Wall-current pick-up	8022.0014.0C
3. Directional coupler pick-up - small transverse	8022.0067.0B
- large transverse	8022.0045.0
- longitudinal	8022.0114.0
4. Waveguide mode traps	8022.0065.1
	8022.0064.1
5. Phase pick-up	8022.1012.1
	8022.1023.0
6. Schottky scan pick-up	8022.3027.0
7. AEW longitudinal pick-up station	8022.0119.0

Fig. 1 - Sketch of electrostatic pick-up

Fig. 2 - Equivalent circuit

Fig. 3 - Typical response

Fig. 4 - Interior view of electrostatic pick-up

Fig. 5 - The electrostatic pick-up

FIG 6 - Circuit of head amplifier

Fig. 7 - Damping of transverse resonance

200 ps/div

Pulse output from test line

2 ns/div

200 ps/div

Pulse output from head amplifier

2 ns/div

Pulse output from head amplifier

Fig. 8 - Pulse response of electrostatic pick-up plus head amplifier

Fig. 9 - Sketch of wall current pick-up

Fig. 10 - Equivalent circuit

Fig. II - Gap dimensions - wall current pick-up

Fig. 12a - Distribution of ferrites in the wall current pick-up

Fig. 12b - Wall current pick-up - end plate removed

Fig. 13 - Signal output using coaxial lines

Fig. 14a - The wall current pick-up

Fig. 14a - The wall current pick-up

Modification
A Ajouter l'axe et le point de vue
B Ajouter l'axe et le point de vue
C Ajouter une correction rapide

Fig. 14b - Wall-current pick-up

Fig. 15 - Response of two feedthroughs back to back

Fig. 16 - Equivalent circuit high frequencies

- a) Output from test line
50 mV/div
100 ps/div

- b) Output from port No. 2:-
5 mV/div
100 ps/div

- c) 5 mV/div
1 ns/div

- d) 5 mV/div
20 ns/div

Fig. 17 - Pulse response from one port of wall current pick-up

a) 10 mV/div
100 ps/div

b) 20 mV/div
2 ns/div

c) 10 mV/div
20 ns/div

Fig. 18 - Output from hybrid - wall current pick-up

Fig. 19 - Attenuation of Flexwell cables

a) Output from ports 2 and 6 with the wire centred.

5 mV/div 500 ps/div

b) Output from ports 2 and 6 with the wire 20 mm towards port 2

10 mV/div 500 ps/div

c) Sum output - wire centred

5 mV/div 500 ps/div

d) Sum output - wire 20 mm off centre

5 mV 500 ps/div

e) Sum output - wire 30 mm off centre

5 mV 500 ps/div

Fig. 20 - Pulse response of wall current pick-up to off-centre beams

Fig. 21 - Sketch of directional coupler pick-up

Fig. 22 - Response to step input

Fig. 23 - Response to pulse input

Fig. 24 - Frequency amplitude/phase response

Fig. 25 - Response to step input

Fig. 26 - Response to pulse input

Fig. 27 - Response of couplers with different decay constants

Fig. 28 - Response of reversed coupler

Fig. 29 - Addition of pick-up signals

Fig. 30a - Difference pick-up - two striplines

Fig. 30b - Difference pick-up - four striplines

Fig. 31a - The directional coupler pick-up

Fig. 3lb - Interior of directional coupler pick-up

Fig. 31c - Directional coupler pick-up

Fig. 32 - Typical TDR response of stripline
50 mp/div 500 ps/div

a) Test line output
50 mV/div 50 ps/div

b) Stripline output
5 mV/div 50 ps/div

c) Stripline output
5 mV/div 500 ps/div

Fig. 33 - Response of single stripline to test pulse

Fig. 34 - Addition of signals using hybrids

a) 5 mV/div 50 ps/div

b) 5 mV/div 500 ps/div

Fig. 35 - Sum response of directional coupler pick-up

Fig. 36a - Directivity of single stripline

Fig. 36b - Response of reversed stripline

Fig. 37 - Frequency response of sum signal from directional coupler pick-up
200 MHz/div 2.5 dB/div

Fig. 38 - Effect of fixing pad on coupler response

Fig. 39 - Damping of resonances in transverse pick-ups

Fig. 40 - Position sensitivity transverse pick-up

Fig. 41 - Addition of signals using resistors

Fig. 42b - Cabling diagram - transverse pick-ups

Fig. 43 - Harmonic component in bunch for various bunching factors

Fig. 44 - Sketch of waveguide test set

Fig. 45a - TELL transmission

Fig. 45b - TM01 transmission

Fig. 46a - Ferrite distribution, end trap

Fig. 46b - Ferrite distribution, centre trap

Fig. 47b - Final assembly - longitudinal pick-up

Fig. 47a - The complete longitudinal pick-up

Fig. 48 - Harmonic components observed during standard machine cycle
100 ms/div 10 dB/div

Fig. 49 - Sketch of re-entrant cavity

Fig. 50 - Compensation of phase shift in phase pick-up

Fig. 51 - Phase pick-up

Fig. 52 - The Schottky scan pick-up

Fig. 53 - Schottky scan pick-up - detail of coupling loop

Fig. 54 - R/Q and phase slip as a function of frequency

Fig. 55 - Q's and coupling coefficient
versus frequency

Fig. 56 - Transfer impedance, shunt impedance and dissipated power versus frequency

Fig. 58 - Higher order modes

Fig. 59 - Cabling diagram - Schottky and phase pick-ups